

cuRAND Library Programming Guide

Release 13.5

NVIDIA Corporation

Nov 02, 2026

Contents

1 Introduction **1**

2 Compatibility and Versioning **3**

3 Host API Overview **5**
3.1 Generator Types . . . 6
3.2 Generator Options . . . 6
3.2.1 Seed . . . 6
3.2.2 Offset . . . 6
3.2.3 Order . . . 7
3.3 Return Values . . . 10
3.4 Generation Functions . . . 10
3.5 Host API Example . . . 12
3.6 Static Library support . . . 13
3.7 Performance Notes . . . 13
3.8 Thread Safety . . . 14

4 Device API Overview **15**
4.1 Pseudorandom Sequences . . . 15
4.1.1 Bit Generation with XORWOW and MRG32k3a generators . . . 15
4.1.2 Bit Generation with the MTGP32 generator . . . 16
4.1.3 Bit Generation with Philox_4x32_10 generator . . . 18
4.1.4 Distributions . . . 19
4.2 Quasirandom Sequences . . . 20
4.3 Skip-Ahead . . . 22
4.4 Device API for discrete distributions . . . 22
4.5 Performance Notes . . . 23
4.6 Device API Examples . . . 24
4.7 Thrust and cuRAND Example . . . 37
4.8 Poisson API Example . . . 38

5 Testing **47**

6 APIs **55**
6.1 Device API . . . 55
6.1.1 Macros . . . 66
6.1.2 Functions . . . 67
6.1.3 Variables . . . 101
6.2 Host API . . . 102
6.2.1 Macros . . . 104
6.2.2 Enumerations . . . 104
6.2.3 Functions . . . 107

7 Structs **125**

7.1 curandStateMRG32k3a . . . 125
7.2 curandStateMtgp32 . . . 125
7.3 curandStateScrambledSobol32 . . . 126
7.4 curandStateScrambledSobol64 . . . 126
7.5 curandStateSobol32 . . . 127
7.6 curandStateSobol64 . . . 127
7.7 curandStateTest . . . 128
7.8 curandStateXORWOW . . . 128
7.9 mtgp32_kernel_params . . . 129
7.10 mtgp32_params_fast . . . 129

8 Bibliography **131**

9 Acknowledgements **133**

10 Notices **135**
10.1 Notice . . . 135
10.2 OpenCL . . . 136
10.3 Trademarks . . . 136

Chapter 1. Introduction

The cuRAND library provides facilities that focus on the simple and efficient generation of high-quality pseudorandom and quasirandom numbers. A *pseudorandom* sequence of numbers satisfies most of the statistical properties of a truly random sequence but is generated by a deterministic algorithm. A *quasirandom* sequence of n -dimensional points is generated by a deterministic algorithm designed to fill an n -dimensional space evenly.

cuRAND consists of two pieces: a library on the host (CPU) side and a device (GPU) header file. The host-side library is treated like any other CPU library: users include the header file, `/include/curand.h`, to get function declarations and then link against the library. Random numbers can be generated on the device or on the host CPU. For device generation, calls to the library happen on the host, but the actual work of random number generation occurs on the device. The resulting random numbers are stored in global memory on the device. Users can then call their own kernels to use the random numbers, or they can copy the random numbers back to the host for further processing. For host CPU generation, all of the work is done on the host, and the random numbers are stored in host memory.

The second piece of cuRAND is the device header file, `/include/curand_kernel.h`. This file defines device functions for setting up random number generator states and generating sequences of random numbers. User code may include this header file, and user-written kernels may then call the device functions defined in the header file. This allows random numbers to be generated and immediately consumed by user kernels without requiring the random numbers to be written to and then read from global memory.

Chapter 2. Compatibility and Versioning

The host API of cuRAND is intended to be backward compatible at the source level with future releases (unless stated otherwise in the release notes of a specific future release). In other words, if a program uses cuRAND, it should continue to compile and work correctly with newer versions of cuRAND without source code changes.

cuRAND is not guaranteed to be backward compatible at the binary level. Using different versions of the `curand.h` header file and the shared library is not supported. Using different versions of cuRAND and the CUDA runtime is not supported.

The device API should be backward compatible at the source level for public functions in most cases.

Chapter 3. Host API Overview

To use the host API, user code should include the library header file `curand.h` and dynamically link against the cuRAND library. The library uses the CUDA runtime, thus when using the static cuRAND library user needs to link against CUDA Runtime too.

Random numbers are produced by generators. A generator in cuRAND encapsulates all the internal state necessary to produce a sequence of pseudorandom or quasirandom numbers. The normal sequence of operations is as follows:

1. Create a new generator of the desired type (see Generator Types) with `curandCreateGenerator()`.

2. Set the generator options (see Generator Options); for example, use `curandSetPseudoRandomGeneratorSeed()` to set the seed.

3. Allocate memory on the device with `cudaMalloc()`.

4. Generate random numbers with `curandGenerate()` or another generation function.

5. Use the results.

6. If desired, generate more random numbers with more calls to `curandGenerate()`.

7. Clean up with `curandDestroyGenerator()`.

To generate random numbers on the host CPU, in step one above call `curandCreateGeneratorHost()`, and in step three, allocate a host memory buffer to receive the results. All other calls work identically whether you are generating random numbers on the device or on the host CPU.

It is legal to create several generators at the same time. Each generator encapsulates a separate state and is independent of all other generators. The sequence of numbers produced by each generator is deterministic. Given the same set-up parameters, the same sequence will be generated with every run of the program. Generating random numbers on the device will result in the same sequence as generating them on the host CPU.

Note that `curandGenerate()` in step 4 above launches a kernel and returns asynchronously. If you launch another kernel in a different stream, and that kernel needs to use the results of curandGenerate(), you must either call `cudaDeviceSynchronize()` or use the stream management/event management routines, to ensure that the random generation kernel has finished execution before the new kernel is launched.

Note that it is not valid to pass a host memory pointer to a generator that is running on the device, and it is not valid to pass a device memory pointer to a generator that is running on the CPU. Behavior in these cases is undefined.

3.1. Generator Types

Random number generators are created by passing a type to `curandCreateGenerator()`. There are nine types of random number generators in cuRAND, that fall into two categories. `CURAND_RNG_PSEUDO_XORWOW`, `CURAND_RNG_PSEUDO_MRG32K3A`, `CURAND_RNG_PSEUDO_MTGP32`, `CURAND_RNG_PSEUDO_PHILOX4_32_10` and `CURAND_RNG_PSEUDO_MT19937` are pseudorandom number generators. `CURAND_RNG_PSEUDO_XORWOW` is implemented using the XORWOW algorithm, a member of the xor-shift family of pseudorandom number generators. `CURAND_RNG_PSEUDO_MRG32K3A` is a member of the Combined Multiple Recursive family of pseudorandom number generators. `CURAND_RNG_PSEUDO_MT19937` and `CURAND_RNG_PSEUDO_MTGP32` are members of the Mersenne Twister family of pseudorandom number generators. `CURAND_RNG_PSEUDO_MTGP32` has parameters customized for operation on the GPU. `CURAND_RNG_PSEUDO_MT19937` has the same parameters as CPU version, but ordering is different. `CURAND_RNG_PSEUDO_MT19937` supports only HOST API and can be used only on architecture sm_35 or higher. `CURAND_RNG_PHILOX4_32_10` is a member of Philox family, which is one of the three non-cryptographic Counter Based Random Number Generators presented on SC11 conference by D E Shaw Research. There are 4 variants of the basic SOBOL' quasi random number generator. All of the variants generate sequences in up to 20,000 dimensions. `CURAND_RNG_QUASI_SOBOL32`, `CURAND_RNG_QUASI_SCRAMBLED_SOBOL32`, `CURAND_RNG_QUASI_SOBOL64`, and `CURAND_RNG_QUASI_SCRAMBLED_SOBOL64` are quasirandom number generator types. `CURAND_RNG_QUASI_SOBOL32` is a Sobol' generator of 32-bit sequences. `CURAND_RNG_QUASI_SCRAMBLED_SOBOL32` is a scrambled Sobol' generator of 32-bit sequences. `CURAND_RNG_QUASI_SOBOL64` is a Sobol' generator of 64-bit sequences. `CURAND_RNG_QUASI_SCRAMBLED_SOBOL64` is a scrambled Sobol' generator of 64-bit sequences.

3.2. Generator Options

Once created, random number generators can be defined using the general options seed, offset, and order.

3.2.1. Seed

The seed parameter is a 64-bit integer that initializes the starting state of a pseudorandom number generator. The same seed always produces the same sequence of results.

3.2.2. Offset

The offset parameter is used to skip ahead in the sequence. If offset = 100, the first random number generated will be the 100th in the sequence. This allows multiple runs of the same program to continue generating results from the same sequence without overlap. Note that the skip ahead function is not available for the `CURAND_RNG_PSEUDO_MTGP32` and `CURAND_RNG_PSEUDO_MT19937` generators.

3.2.3. Order

The order parameter is used to choose how the results are ordered in global memory. It also has direct influence on performance of cuRAND generation functions.

There are five ordering choices for pseudorandom sequences: CURAND_ORDERING_PSEUDO_DEFAULT, CURAND_ORDERING_PSEUDO_LEGACY, CURAND_ORDERING_PSEUDO_BEST, CURAND_ORDERING_PSEUDO_SEEDED, and CURAND_ORDERING_PSEUDO_DYNAMIC. There is one ordering choice for quasirandom numbers, CURAND_ORDERING_QUASI_DEFAULT. The default ordering for pseudorandom number generators is CURAND_ORDERING_PSEUDO_DEFAULT, while the default ordering for quasirandom number generators is CURAND_ORDERING_QUASI_DEFAULT.

The two pseudorandom orderings CURAND_ORDERING_PSEUDO_DEFAULT and CURAND_ORDERING_PSEUDO_BEST produce the same output ordering for all pseudo-random generators, except MT19937 for which CURAND_ORDERING_PSEUDO_DEFAULT is the same as CURAND_ORDERING_PSEUDO_LEGACY. For MT19937 CURAND_ORDERING_PSEUDO_BEST may generate different output on different models of GPUs, and it can't be used with a host generator created using `curandCreateGeneratorHost()`. Future releases of cuRAND may change the ordering associated with CURAND_ORDERING_PSEUDO_BEST to improve either performance or the quality of the results. It will always be the case that the ordering obtained with CURAND_ORDERING_PSEUDO_BEST is deterministic and is the same for each run of the program. The ordering obtained with CURAND_ORDERING_PSEUDO_LEGACY is guaranteed to remain the same for all cuRAND releases.

The CURAND_ORDERING_PSEUDO_DYNAMIC ordering can't be used with a host generator created using `curandCreateGeneratorHost()`, and it is currently only supported with the following pseudo-random generators: CURAND_RNG_PSEUDO_XORWOW, CURAND_RNG_PSEUDO_PHILOX4_32_10, CURAND_RNG_PSEUDO_MRG32K3A, and CURAND_RNG_PSEUDO_MTGP32. When CURAND_ORDERING_PSEUDO_DYNAMIC ordering is selected cuRAND tries to maximize GPU utilization to deliver the best performance. The ordering obtained with CURAND_ORDERING_PSEUDO_DYNAMIC can be different on different GPUs. It is not guaranteed to: remain the same for all cuRAND releases, and be the same for all distributions. It is guaranteed to be deterministic.

The differences in behavior of the ordering parameters for each generator type are outlined below:

- XORWOW pseudorandom generator
  - CURAND_ORDERING_PSEUDO_DEFAULT

    The output ordering of CURAND_ORDERING_PSEUDO_DEFAULT is the same as CURAND_ORDERING_PSEUDO_BEST in the current release.
  - CURAND_ORDERING_PSEUDO_BEST

    The output ordering of CURAND_ORDERING_PSEUDO_BEST is the same as CURAND_ORDERING_PSEUDO_LEGACY in the current release.
  - CURAND_ORDERING_PSEUDO_LEGACY

    The result at offset n in global memory is from position

    $$(n \bmod 4096) \cdot 2^{67} + \lfloor n/4096 \rfloor$$

    in the original XORWOW sequence.
  - CURAND_ORDERING_PSEUDO_DYNAMIC

    The output ordering of CURAND_ORDERING_PSEUDO_DYNAMIC can be different on different GPUs.
  - CURAND_ORDERING_PSEUDO_SEEDED

The result at offset n in global memory is from position $n/4096\rfloor$ in the XORWOW sequence seeded with a combination of the user seed and the number $n \bmod 4096$. In other words, each of 4096 threads uses a different seed. This seeding method reduces state setup time but may result in statistical weaknesses of the pseudorandom output for some user seed values.

- MRG32k3a pseudorandom generator
  - `CURAND_ORDERING_PSEUDO_DEFAULT`

    The output ordering of `CURAND_ORDERING_PSEUDO_DEFAULT` is the same as `CURAND_ORDERING_PSEUDO_BEST` in the current release.
  - `CURAND_ORDERING_PSEUDO_BEST`

    The result at offset n in global memory is from position

    $(n \bmod 81920) \cdot 2^{76} + \lfloor n/81920 \rfloor$

    in the original MRG32k3a sequence. (Note that the stride between subsequent samples for MRG32k3a is not the same as for XORWOW)
  - `CURAND_ORDERING_PSEUDO_LEGACY`

    The result at offset n in global memory is from position

    $(n \bmod 4096) \cdot 2^{76} + \lfloor n/4096 \rfloor$

    in the original MRG32k3a sequence. (Note that the stride between subsequent samples for MRG32k3a is not the same as for XORWOW)
  - `CURAND_ORDERING_PSEUDO_DYNAMIC`

    The output ordering of `CURAND_ORDERING_PSEUDO_DYNAMIC` can be different on different GPUs.
- MTGP32 pseudorandom generator
  - `CURAND_ORDERING_PSEUDO_DEFAULT`

    The output ordering of `CURAND_ORDERING_PSEUDO_DEFAULT` is the same as `CURAND_ORDERING_PSEUDO_BEST` in the current release.
  - `CURAND_ORDERING_PSEUDO_BEST`

    The MTGP32 generator actually generates 192 distinct sequences based on different parameter sets for the basic algorithm. Let $S(p)$ be the sequence for parameter set p.

    The result at offset n in global memory is from position $n \bmod 256$ from the sequence

    $S(\lfloor n/256 \rfloor \bmod 192)$

    In other words 256 samples from $S(0)$ are followed by 256 samples from $S(1)$ and so-on, up to $S(191)$. This pattern repeats, so the subsequent 256 samples are from $S(0)$, followed by 256 samples from $S(1)$, ands so on.
  - `CURAND_ORDERING_PSEUDO_LEGACY`

    The MTGP32 generator actually generates 64 distinct sequences based on different parameter sets for the basic algorithm. Let $S(p)$ be the sequence for parameter set p.

    The result at offset n in global memory is from position $n \bmod 256$ from the sequence

    $S(\lfloor n/256 \rfloor \bmod 64)$

In other words 256 samples from $S(0)$ are followed by 256 samples from $S(1)$ and so-on, up to $S(63)$. This pattern repeats, so the subsequent 256 samples are from $S(0)$, followed by 256 samples from $S(1)$, ands so on.

- `CURAND_ORDERING_PSEUDO_DYNAMIC`

  The output ordering of `CURAND_ORDERING_PSEUDO_DYNAMIC` can be different on different GPUs. In this ordering MTGP32 can use different precalculated parameters than original MTGP32 implementation.

- MT19937 pseudorandom generator
  - `CURAND_ORDERING_PSEUDO_DEFAULT`

    The output ordering of `CURAND_ORDERING_PSEUDO_DEFAULT` is the same as `CURAND_ORDERING_PSEUDO_LEGACY` in the current release.

  - `CURAND_ORDERING_PSEUDO_LEGACY`

    Ordering is based heavily on the standard MT19937 CPU implementation. Output is generated by 8192 independent generators. Each generator generates consecutive subsequence of the original sequence. Length of each subsequence is 2^{1000}. Random numbers are generated by eights thus first 8 elements come from first subsequence, next 8 elements come form second subsequence and so on. Results are permuted differently than originally to achieve higher performance. Ordering is independent of the hardware that you are using. For more information please see [18].

  - `CURAND_ORDERING_PSEUDO_BEST`

    The output ordering of `CURAND_ORDERING_PSEUDO_BEST` to achieve better performance depends on number of SMs that composed your GPU. Random numbers are generated in the same way as with `CURAND_ORDERING_PSEUDO_LEGACY` but the number of generators may be different to achieve better performance. Generating seeds is much faster using this ordering.

    The ordering `CURAND_ORDERING_PSEUDO_BEST` is only supported with GPU cuRAND random number generators and can't be used with a host generator created using `curandCreateGeneratorHost()`.

- Philox_4x32_10 pseudorandom generator
  - `CURAND_ORDERING_PSEUDO_DEFAULT`

    The output ordering of `CURAND_ORDERING_PSEUDO_DEFAULT` is the same as `CURAND_ORDERING_PSEUDO_BEST` in the current release.

  - `CURAND_ORDERING_PSEUDO_BEST`

    The output ordering of `CURAND_ORDERING_PSEUDO_BEST` is the same as `CURAND_ORDERING_PSEUDO_LEGACY` in the current release.

  - `CURAND_ORDERING_PSEUDO_LEGACY`

    Each thread in Philox_4x32_10 generator generates distinct sequences based on different parameter sets for the basic algorithm. In host API there are 65536 different sequences. Each four values from one sequence are followed by four values from next sequence.

  - `CURAND_ORDERING_PSEUDO_DYNAMIC`

    The output ordering of `CURAND_ORDERING_PSEUDO_DYNAMIC` can be different on different GPUs.

- 32 and 64 bit SOBOL and Scrambled SOBOL quasirandom generators

- `CURAND_ORDERING_QUASI_DEFAULT`

  When generating n results in d dimensions, the output will consist of n/d results from dimension 1, followed by n/d results from dimension 2, and so on up to dimension d. Only exact multiples of the dimension size may be generated. The dimension parameter d is set with `curandSetQuasiRandomGeneratorDimensions()` and defaults to 1.

3.3. Return Values

All cuRAND host library calls have a return value of `curandStatus_t`. Calls that succeed without errors return `CURAND_STATUS_SUCCESS`. If errors occur, other values are returned depending on the error. Because CUDA allows kernels to execute asynchronously from CPU code, it is possible that errors in a non-cuRAND kernel will be detected during a call to a library function. In this case, `CURAND_STATUS_PREEXISTING_ERROR` is returned.

3.4. Generation Functions

```
curandStatus_t
curandGenerate(
    curandGenerator_t generator,
    unsigned int *outputPtr, size_t num)

curandStatus_t
curandGenerateLongLong(
    curandGenerator_t generator,
    unsigned long long *outputPtr, size_t num)
```

The `curandGenerate()` function is used to generate pseudo- or quasirandom bits of output for XORWOW, MRG32k3a, MTGP32, MT19937, Philox_4x32_10 and SOBOL32 generators. Each output element is a 32-bit unsigned int where all bits are random. For SOBOL64 generators, each output element is a 64-bit unsigned long long where all bits are random. `curandGenerate()` returns an error for SOBOL64 generators. Use `curandGenerateLongLong()` to generate 64 bit integers with the SOBOL64 generators.

```
curandStatus_t
curandGenerateUniform(
    curandGenerator_t generator,
    float *outputPtr, size_t num)
```

The `curandGenerateUniform()` function is used to generate uniformly distributed floating point values between 0.0 and 1.0, where 0.0 is excluded and 1.0 is included.

```
curandStatus_t
curandGenerateNormal(
    curandGenerator_t generator,
    float *outputPtr, size_t n,
    float mean, float stddev)
```

The `curandGenerateNormal()` function is used to generate normally distributed floating point values with the given mean and standard deviation.

```
curandStatus_t
curandGenerateLogNormal(
    curandGenerator_t generator,
    float *outputPtr, size_t n,
    float mean, float stddev)
```

The `curandGenerateLogNormal()` function is used to generate log-normally distributed floating point values based on a normal distribution with the given mean and standard deviation.

```
curandStatus_t
curandGeneratePoisson(
    curandGenerator_t generator,
    unsigned int *outputPtr, size_t n,
    double lambda)
```

The `curandGeneratePoisson()` function is used to generate Poisson-distributed integer values based on a Poisson distribution with the given lambda.

```
curandStatus_t
curandGenerateUniformDouble(
    curandGenerator_t generator,
    double *outputPtr, size_t num)
```

The `curandGenerateUniformDouble()` function generates uniformly distributed random numbers in double precision.

```
curandStatus_t
curandGenerateNormalDouble(
    curandGenerator_t generator,
    double *outputPtr, size_t n,
    double mean, double stddev)
```

`curandGenerateNormalDouble()` generates normally distributed results in double precision with the given mean and standard deviation. Double precision results can only be generated on devices of compute capability 1.3 or above, and the host.

```
curandStatus_t
curandGenerateLogNormalDouble(
    curandGenerator_t generator,
    double *outputPtr, size_t n,
    double mean, double stddev)
```

`curandGenerateLogNormalDouble()` generates log-normally distributed results in double precision, based on a normal distribution with the given mean and standard deviation.

For quasirandom generation, the number of results returned must be a multiple of the dimension of the generator.

Generation functions can be called multiple times on the same generator to generate successive blocks of results. For pseudorandom generators, multiple calls to generation functions will yield the same result as a single call with a large size. For quasirandom generators, because of the ordering of dimensions in memory, many shorter calls will not produce the same results in memory as one larger call; however the generated n-dimensional vectors will be the same.

Double precision results can only be generated on devices of compute capability 1.3 or above, and the host.

3.5. Host API Example

```
/*
 * This program uses the host CURAND API to generate 100
 * pseudorandom floats.
 */
#include <stdio.h>
#include <stdlib.h>
#include <cuda_runtime.h>
#include <curand.h>

#define CUDA_CALL(x) do { if((x)!=cudaSuccess) { \
    printf("Error at %s:%d\n",__FILE__,__LINE__);\
    return EXIT_FAILURE;}} while(0)
#define CURAND_CALL(x) do { if((x)!=CURAND_STATUS_SUCCESS) { \
    printf("Error at %s:%d\n",__FILE__,__LINE__);\
    return EXIT_FAILURE;}} while(0)

int main(int argc, char *argv[])
{
    size_t n = 100;
    size_t i;
    curandGenerator_t gen;
    float *devData, *hostData;

    /* Allocate n floats on host */
    hostData = (float *)calloc(n, sizeof(float));

    /* Allocate n floats on device */
    CUDA_CALL(cudaMalloc((void **)&devData, n*sizeof(float)));

    /* Create pseudo-random number generator */
    CURAND_CALL(curandCreateGenerator(&gen,
                CURAND_RNG_PSEUDO_DEFAULT));

    /* Set seed */
    CURAND_CALL(curandSetPseudoRandomGeneratorSeed(gen,
                1234ULL));

    /* Generate n floats on device */
    CURAND_CALL(curandGenerateUniform(gen, devData, n));

    /* Copy device memory to host */
    CUDA_CALL(cudaMemcpy(hostData, devData, n * sizeof(float),
        cudaMemcpyDeviceToHost));

    /* Show result */
    for(i = 0; i < n; i++) {
        printf("%1.4f ", hostData[i]);
    }
    printf("\n");

    /* Cleanup */
    CURAND_CALL(curandDestroyGenerator(gen));
    CUDA_CALL(cudaFree(devData));
    free(hostData);
```

(continues on next page)

(continued from previous page)

```
    return EXIT_SUCCESS;
}
```

3.6. Static Library support

Starting with release 6.5, the cuRAND Library is also delivered in a static form as libcurand_static.a on Linux and Mac. Static libraries are not supported on Windows. The static cuRAND library depends on a common thread abstraction layer library called libcuos.a on Linux and Mac and cuos.lib on Windows.

For example, on linux, to compile a small application using cuRAND against the dynamic library, the following command can be used:

```
nvcc myCurandApp.c  -lcurand  -o myCurandApp
```

Whereas to compile against the static cuRAND library, the following command has to be used:

```
nvcc myCurandApp.c  -lcurand_static   -lculibos -o myCurandApp
```

It is also possible to use the native Host C++ compiler. Depending on the Host Operating system, some additional libraries like `pthread` or `dl` might be needed on the linking line. The following command on Linux is suggested :

```
g++ myCurandApp.c  -lcurand_static   -lculibos -lcudart_static -lpthread -ldl -I
↪<cuda-toolkit-path>/include -L <cuda-toolkit-path>/lib64 -o myCurandApp
```

Note that in the latter case, the library `cuda` is not needed. The CUDA Runtime will try to open explicitly the `cuda` library if needed. In the case of a system which does not have the CUDA driver installed, this allows the application to gracefully manage this issue and potentially run if a CPU-only path is available.

3.7. Performance Notes

In general you will get the best performance from the cuRAND library by generating blocks of random numbers that are as large as possible. Fewer calls to generate many random numbers is more efficient than many calls generating only a few random numbers. The default pseudorandom generator, XORWOW, with the default ordering takes some time to setup the first time it is called. Subsequent generation calls do not require this setup. To avoid this setup time, use the `CURAND_ORDERING_PSEUDO_SEEDED` ordering.

The MTGP32 Mersenne Twister algorithm is closely tied to the thread and block count. The state structure for MTGP32 actually contains the state for 256 consecutive samples from a given sequence, as determined by a specific parameter set. Each of 64 blocks uses a different parameter set and each of 256 threads generates one sample from the state, and updates the state. Hence the most efficient use of MTGP32 is to generate a multiple of 16384 samples.

The MT19937 algorithm performance depends on number of samples generated during the single call. Peak performance can be achieved while generating more than 2GB of data, but 80% of peak performance can be achieved while generating only 80MB. Please see [18] for reference.

The Philox_4x32_10 algorithm is closely tied to the thread and block count. Each thread computes 4 random numbers in the same time thus the most efficient use of Philox_4x32_10 is to generate a multiple of 4 times number of threads.

To get the best performance for cuRAND host APIs users are encouraged to use `CURAND_ORDERING_PSEUDO_BEST` or `CURAND_ORDERING_PSEUDO_DYNAMIC` orderings.

3.8. Thread Safety

cuRAND host APIs are thread safe as long as different host threads use different generators, generators are not MT19937 (`CURAND_RNG_PSEUDO_MT19937`), and the outputs are disjoint.

Please note that cuRAND host APIs are not thread safe when used with MT19937 generators (`CURAND_RNG_PSEUDO_MT19937`).

Chapter 4. Device API Overview

To use the device API, include the file `curand_kernel.h` in files that define kernels that use cuRAND device functions. The device API includes functions pseudorandom generation for and quasirandom generation.

4.1. Pseudorandom Sequences

The functions for pseudorandom sequences support bit generation and generation from distributions.

4.1.1. Bit Generation with XORWOW and MRG32k3a generators

```
__device__ unsigned int
curand(curandStateXORWOW_t *state)

__device__ unsigned int
curand(curandStateMRG32k3a_t *state)
```

Following a call to `curand_init()`, `curand()` returns a sequence of pseudorandom numbers with a period greater than 2^{190}. If `curand()` is called with the same initial state each time, and the state is not modified between the calls to `curand()`, the same sequence is always generated.

```
__device__ void
curand_init(unsigned long long seed,
            unsigned long long sequence,
            unsigned long long offset,
            curandStateXORWOW_t *state)

__device__ void
curand_init(unsigned long long seed,
            unsigned long long sequence,
            unsigned long long offset,
            curandStateMRG32k3a_t  *state)
```

The `curand_init()` function sets up an initial state allocated by the caller using the given seed, sequence number, and offset within the sequence. Different seeds are guaranteed to produce different starting states and different sequences. The same seed always produces the same state and the same

sequence. The state set up will be the state after 2^{67} □ `sequence` + `offset` calls to `curand()` from the seed state.

Sequences generated with different seeds usually do not have statistically correlated values, but some choices of seeds may give statistically correlated sequences. Sequences generated with the same seed and different sequence numbers will not have statistically correlated values.

For the highest quality parallel pseudorandom number generation, each experiment should be assigned a unique seed. Within an experiment, each thread of computation should be assigned a unique sequence number. If an experiment spans multiple kernel launches, it is recommended that threads between kernel launches be given the same seed, and sequence numbers be assigned in a monotonically increasing way. If the same configuration of threads is launched, random state can be preserved in global memory between launches to avoid state setup time.

4.1.2. Bit Generation with the MTGP32 generator

The MTGP32 generator is an adaptation of code developed at Hiroshima University (see [1]). In this algorithm, samples are generated for multiple sequences, each sequence based on a set of computed parameters. cuRAND uses the 200 parameter sets that have been pre-generated for the 32-bit generator with period 2^{11214}. It would be possible to generate other parameter sets, as described in [1], and use those instead. There is one state structure for each parameter set (sequence), and the algorithm allows thread-safe generation and state update for up to 256 concurrent threads (within a single block) for each of the 200 sequences.

Note that two different blocks can not operate on the same state safely. Also note that, within a block, at most 256 threads may operate on a given state.

For the MTGP32 generator, two host functions are provided to help set up parameters for the different sequences in device memory, and to set up the initial state.

```
__host__ curandStatust curandMakeMTGP32Constants(mtgp32paramsfastt params[],
                                                 mtgp32kernelparamst *p)
```

This function reorganizes the parameter set data from the pre-generated format (`mtgp32_params_fast_t`) into the format used by the kernel functions (`mtgp32_kernel_params_t`), and copies them to device memory.

```
__host__ curandStatus_t
curandMakeMTGP32KernelState(curandStateMtgp32_t *s,
                            mtgp32_params_fast_t params[],
                            mtgp32_kernel_params_t *k,
                            int n,
                            unsigned long long seed)
```

This function initializes `n` states, based on the specified parameter set and seed, and copies them to device memory indicated by `s`. Note that if you are using the pre-generated states, the maximum value of `n` is 200.

The cuRAND MTGP32 generator provides two kernel functions to generate random bits.

```
__device__ unsigned int
curand(curandStateMtgp32_t *state)
```

This function computes a thread index, and for that index generates a result and updates state. The thread index `t` is computed as:

```
t = (blockDim.x * blockDim.y * threadIdx.z) + (blockDim.x * threadIdx.y) +
threadIdx.x
```

This function may be called repeatedly from a single kernel launch, with the following constraints:

- It may only be called safely from a block that has 256 or fewer threads.
- A given state may not be used by more than one block.
- A given block may generate randoms using multiple states.
- At a given point in the code, all threads in the block, or none of them, must call this function.

```
__device__ unsigned int
curandmtgp32specific(curandStateMtgp32_t *state, unsigned char index,
                     unsigned char n)
```

This function generates a result and updates state for the position specified by a thread-specific `index`, and advances the offset in the state by `n` positions.`curand_mtgp32_specific` may be called multiple times within a kernel launch, with the following constraints:

- At most 256 threads may call this function for a given state.
- Within a block, for a given state, if `n` threads are calling the function, the indices must run from `0...n-1`. The indices do not have to match the thread numbers, and may be distributed among the threads as required by the calling program. At a given point in the code, all of the indices from `0...n-1`, or none of them, must be used.
- A given state may not be used by more than one block.
- A given block may generate randoms using multiple states.



Figure 1. MTGP32 Block and Thread Operation

Figure 1 is an illustration of how blocks and threads in MTGP32 operate on the generator states. Each row represents a circular state array of 32-bit integers `s(n)`. Threads operating on the array are identified as `T(m)`. The specific case shown matches the internal implementation of the host API, which launches 64 blocks of 256 threads. Each block operates on a different sequence, determined by a unique set of parameters, `P(n)`. One complete state of an MTGP32 sequence is defined by 351 32-bit integers. Each thread `T(m)` operates on one of these integers, `s(n+m)` combining it with `s(n+m+1)` and a pickup element `s(n+m+p)`, where `p <= 95`. It stores the new state at position `s(n+m+351)` in the state array. After thread synchronization, the base index `n` is advanced by the number of threads that have updated the state. To avoid being overwritten, the array itself must be at least 256 + 351 integers in length. In fact it is sized at 1024 integers for efficiency of indexing.

The limitation on the number of threads in a block, which can operate on a given state array, arises from the need to ensure that state `s(n+351)` has been updated before it is needed as a pickup state. If there were a thread `T(256)`, it could use `s(n+256+95)` i.e. `s(n+351)` before thread zero has updated `s(n+351)`. If an application requires that more than 256 threads in a block invoke an MTGP32 generator function, it must use multiple MTGP32 states, either by using multiple parameter sets, or by using multiple generators with different seeds. Also note that the generator functions synchronize threads at the end of each call, so it is most efficient for 256 threads in a block to invoke the generator.

4.1.3. Bit Generation with Philox_4x32_10 generator

```
__device__ unsigned int
curand(curandStatePhilox4_32_10_t *state)
```

Following a call to `curand_init()`, `curand()` returns a sequence of pseudorandom numbers with a period 2^{128}. If `curand()` is called with the same initial state each time, and the state is not modified between the calls to `curand()`, the same sequence is always generated.

```
__device__ void
curand_init(unsigned long long seed,
            unsigned long long subsequence,
            unsigned long long offset,
            curandStatePhilox4_32_10_t *state)
```

The `curand_init()` function sets up an initial state allocated by the caller using the given seed, subsequence and offset. Different seed is guaranteed to produce different starting states and different sequences. Subsequence and offset together define offset in a sequence with period 2^{128}. Offset defines offset in subsequence of length 2^{64}. When last element from subsequence was generated, then the next random number is first element from consecutive subsequence. The same seed always produces the same state and the same sequence.

Sequences generated with different seeds usually do not have statistically correlated values, but some choices of seeds may give statistically correlated sequences.

For the highest quality parallel pseudorandom number generation, each experiment should be assigned a unique seed value. Within an experiment, each thread of computation should be assigned a unique id number. If an experiment spans multiple kernel launches, it is recommended that threads between kernel launches be given the same seed, and id numbers be assigned in a monotonically increasing way. If the same configuration of threads is launched, random state can be preserved in global memory between launches to avoid state setup time.

4.1.4. Distributions

```
__device__ float
curand_uniform (curandState_t *state)
```

This function returns a sequence of pseudorandom floats uniformly distributed between 0.0 and 1.0. It may return from 0.0 to 1.0, where 1.0 is included and 0.0 is excluded. Distribution functions may use any number of unsigned integer values from a basic generator. The number of values consumed is not guaranteed to be fixed.

```
__device__ float
curand_normal (curandState_t *state)
```

This function returns a single normally distributed float with mean 0.0 and standard deviation 1.0. This result can be scaled and shifted to produce normally distributed values with any mean and standard deviation.

```
__device__ float
curand_log_normal (curandState_t *state, float mean, float stddev)
```

This function returns a single log-normally distributed float based on a normal distribution with the given mean and standard deviation.

```
__device__ unsigned int
curand_poisson (curandState_t *state, double lambda)
```

This function returns a single Poisson-distributed unsigned int based on a Poisson distribution with the given lambda. The algorithm used to derive a Poisson result from a uniformly distributed result varies depending on the value of lambda and the type of generator. Some algorithms draw more than one sample for a single output.

```
__device__ double
curand_uniform_double (curandState_t *state)
```

```
__device__ double
curand_normal_double (curandState_t *state)
```

```
__device__ double
curand_log_normal_double (curandState_t *state, double mean, double stddev)
```

The three functions above are the double precision versions of `curand_uniform()`, `curand_normal()`, and `curand_log_normal()`.

For pseudorandom generators, the double precision functions use multiple calls to `curand()` to generate 53 random bits.

```
__device__ float2
curand_normal2 (curandState_t *state)
```

```
__device__ float2
curand_log_normal2 (curandState_t *state)
```

```
__device__ double2
curand_normal2_double (curandState_t *state)
```

```
__device__ double2
curand_log_normal2_double (curandState_t *state)
```

The above functions generate two normally or log normally distributed pseudorandom results with each call. Because the underlying implementation uses the Box-Muller transform, this is generally more efficient than generating a single result with each call.

```
__device__ uint4
curand4 (curandStatePhilox4_32_10_t *state)
```

```
__device__ float4
curand_uniform4 (curandStatePhilox4_32_10_t *state)
```

```
__device__ float4
curand_normal4 (curandStatePhilox4_32_10_t *state)
```

```
__device__ float4
curand_log_normal4 (curandStatePhilox4_32_10_t *state, float mean, float stddev)
```

```
__device__ uint4
curand_poisson4 (curandStatePhilox4_32_10_t *state, double lambda)
```

```
__device__ uint4
curand_discrete4 (curandStatePhilox4_32_10_t *state, curandDiscreteDistribution_t
↪discrete_distribution)
```

```
__device__ double2
curand_uniform2_double (curandStatePhilox4_32_10_t *state)
```

```
__device__ double2
curand_normal2_double (curandStatePhilox4_32_10_t *state)
```

```
__device__ double2
curand_log_normal2_double (curandStatePhilox4_32_10_t *state, double mean, double
↪stddev)
```

The above functions generate four single precision or two double precision results with each call. Because the underlying implementation uses the Philox generator, this is generally more efficient than generating a single result with each call.

4.2. Quasirandom Sequences

Although the default generator type is pseudorandom numbers from XORWOW, Sobol' sequences based on Sobol' 32-bit integers can be generated using the following functions:

```
__device__ void
curand_init (
    unsigned int *direction_vectors,
    unsigned int offset,
    curandStateSobol32_t *state)
```

```
__device__ void
curand_init (
    unsigned int *direction_vectors,
    unsigned int scramble_c,
    unsigned int offset,
    curandStateScrambledSobol32_t *state)
```

```
__device__ unsigned int
curand (curandStateSobol32_t *state)
```

```
__device__ float
curand_uniform (curandStateSobol32_t *state)
```

```
__device__ float
curand_normal (curandStateSobol32_t *state)
```

```
__device__ float
curand_log_normal (
    curandStateSobol32_t *state,
    float mean,
    float stddev)
```

```
__device__ unsigned int
curand_poisson (curandStateSobol32_t *state, double lambda)
```

```
__device__ double
curand_uniform_double (curandStateSobol32_t *state)
```

```
__device__ double
curand_normal_double (curandStateSobol32_t *state)
```

```
__device__ double
curand_log_normal_double (
    curandStateSobol32_t *state,
    double mean,
    double stddev)
```

The `curand_init()` function initializes the quasirandom number generator state. There is no seed parameter, only direction vectors and offset. For scrambled Sobol' generators, there is an additional parameter `scramble_c`, which is the initial value of the scrambled sequence. For the `curandStateSobol32_t` type and the `curandStateScrambledSobol32_t` type the direction vectors are an array of 32 unsigned integer values. For the `curandStateSobol64_t` type and the `curandStateScrambledSobol64_t` type the direction vectors are an array of 64 unsigned long long values. Offsets and initial constants for the scrambled sequence are of type unsigned int for 32-bit Sobol' generators. These parameters are of type unsigned long long for 64-bit Sobol' generators. For the `curandStateSobol32_t` type and the `curandStateScrambledSobol32_t` type the sequence is exactly 2^{32} elements long where each element is 32 bits. For the `curandStateSobol64_t` type and the `curandStateScrambledSobol64_t` type the sequence is exactly 2^{64} elements long where each element is 64 bits. Each call to `curand()` returns the next quasirandom element. Calls to `curand_uniform()` return quasirandom floats or doubles from 0.0 to 1.0, where 1.0 is included and 0.0 is excluded. Similarly, calls to `curand_normal()` return normally distributed floats or doubles with mean 0.0 and standard deviation 1.0. Calls to `curand_log_normal()` return log-normally distributed floats or doubles, derived from the normal distribution with the specified mean and standard deviation. All of the generation functions may be called with any type of Sobol' generator.

As an example, generating quasirandom coordinates that fill a unit cube requires keeping track of three quasirandom generators. All three would start at `offset` = 0 and would have dimensions 0, 1, and 2, respectively. A single call to `curand_uniform()` for each generator state would generate the x, y, and z coordinates. Tables of direction vectors are accessible on the host through the `curandGetDirectionVectors32()` and `curandGetDirectionVectors64()` functions. The direction vectors needed should be copied into device memory before use.

The normal distribution functions for quasirandom generation use the inverse cumulative density function to preserve the dimensionality of the quasirandom sequence. Therefore there are no functions that generate more than one result at a time as there are with the pseudorandom generators.

The double precision Sobol32 functions return results in double precision that use 32 bits of internal precision from the underlying generator.

The double precision Sobol64 functions return results in double precision that use 53 bits of internal precision from the underlying generator. These bits are taken from the high order 53 bits of the 64 bit samples.

4.3. Skip-Ahead

There are several functions to skip ahead from a generator state.

```
__device__ void
skipahead(unsigned long long n, curandState_t *state)
```

```
__device__ void
skipahead(unsigned int n, curandStateSobol32_t *state)
```

Using this function is equivalent to calling `curand()` n times without using the return value, but it is much faster.

```
__device__ void
skipahead_sequence(unsigned long long n, curandState_t *state)
```

This function is the equivalent of calling `curand()` $n \cdot 2^{67}$ times without using the return value and is much faster.

4.4. Device API for discrete distributions

Discrete distributions, such as the Poisson distribution, require additional API's that perform preprocessing on HOST side to generate a histogram for the specific distribution. In the case of the Poisson distribution this histogram is different for different values of lambda. Best performance for these distributions will be seen on GPUs with at least 48KB of L1 cache.

```
curandStatus_t
curandCreatePoissonDistribution(
    double lambda,
    curandDiscreteDistribution_t *discrete_distribution)
```

The `curandCreatePoissonDistribution()` function is used to create a histogram for the Poisson distribution with the given lambda.

```
__device__ unsigned int
curand_discrete (
    curandState_t *state,
    curandDiscreteDistribution_t discrete_distribution)
```

This function returns a single discrete distributed unsigned int based on a distribution for the given discrete distribution histogram.

```
curandStatus_t
curandDestroyDistribution(
    curandDiscreteDistribution_t discrete_distribution)
```

The `curandDestroyDistribution()` function is used to clean up structures related to the histogram.

4.5. Performance Notes

Calls to `curand_init()` are slower than calls to `curand()` or `curand_uniform()`. Large offsets to `curand_init()` take more time than smaller offsets. It is much faster to save and restore random generator state than to recalculate the starting state repeatedly.

As shown below, generator state can be stored in global memory between kernel launches, used in local memory for fast generation, and then stored back into global memory.

```
__global__ void example(curandState *global_state)
{
    curandState local_state;
    local_state = global_state[threadIdx.x];
    for(int i = 0; i < 10000; i++) {
        unsigned int x = curand(&local_state);
        ...
    }
    global_state[threadIdx.x] = local_state;
}
```

Initialization of the random generator state generally requires more registers and local memory than random number generation. It may be beneficial to separate calls to `curand_init()` and `curand()` into separate kernels for maximum performance.

State setup can be an expensive operation. One way to speed up the setup is to use different seeds for each thread and a constant sequence number of 0. This can be especially helpful if many generators need to be created. While faster to set up, this method provides less guarantees about the mathematical properties of the generated sequences. If there happens to be a bad interaction between the hash function that initializes the generator state from the seed and the periodicity of the generators, there might be threads with highly correlated outputs for some seed values. We do not know of any problem values; if they do exist they are likely to be rare.

4.6. Device API Examples

This example uses the cuRAND device API to generate pseudorandom numbers using either the XOR-WOW or MRG32k3a generators. For integers, it calculates the proportion that have the low bit set. For uniformly distributed real numbers, it calculates the proportion that are greater than 0.5. For normally distributed real numbers, it calculates the proportion that are within one standard deviation of the mean.

```
/*
 * This program uses the device CURAND API to calculate what
 * proportion of pseudo-random ints have low bit set.
 * It then generates uniform results to calculate how many
 * are greater than .5.
 * It then generates  normal results to calculate how many
 * are within one standard deviation of the mean.
 */
#include <stdio.h>
#include <stdlib.h>

#include <cuda_runtime.h>
#include <curand_kernel.h>

#define CUDA_CALL(x) do { if((x) != cudaSuccess) { \
    printf("Error at %s:%d\n",__FILE__,__LINE__); \
    return EXIT_FAILURE;}} while(0)

__global__ void setup_kernel(curandState *state)
{
    int id = threadIdx.x + blockIdx.x * blockDim.x;
    /* Each thread gets same seed, a different sequence
       number, no offset */
    curand_init(1234, id, 0, &state[id]);
}

__global__ void setup_kernel(curandStatePhilox4_32_10_t *state)
{
    int id = threadIdx.x + blockIdx.x * blockDim.x;
    /* Each thread gets same seed, a different sequence
       number, no offset */
    curand_init(1234, id, 0, &state[id]);
}

__global__ void setup_kernel(curandStateMRG32k3a *state)
{
    int id = threadIdx.x + blockIdx.x * blockDim.x;
    /* Each thread gets same seed, a different sequence
       number, no offset */
    curand_init(0, id, 0, &state[id]);
}

__global__ void generate_kernel(curandState *state,
                                int n,
                                unsigned int *result)
{
    int id = threadIdx.x + blockIdx.x * blockDim.x;
    int count = 0;
```

(continues on next page)

(continued from previous page)

```
    unsigned int x;
    /* Copy state to local memory for efficiency */
    curandState localState = state[id];
    /* Generate pseudo-random unsigned ints */
    for(int i = 0; i < n; i++) {
        x = curand(&localState);
        /* Check if low bit set */
        if(x & 1) {
            count++;
        }
    }
    /* Copy state back to global memory */
    state[id] = localState;
    /* Store results */
    result[id] += count;
}

__global__ void generate_kernel(curandStatePhilox4_32_10_t *state,
                                int n,
                                unsigned int *result)
{
    int id = threadIdx.x + blockIdx.x * blockDim.x;
    int count = 0;
    unsigned int x;
    /* Copy state to local memory for efficiency */
    curandStatePhilox4_32_10_t localState = state[id];
    /* Generate pseudo-random unsigned ints */
    for(int i = 0; i < n; i++) {
        x = curand(&localState);
        /* Check if low bit set */
        if(x & 1) {
            count++;
        }
    }
    /* Copy state back to global memory */
    state[id] = localState;
    /* Store results */
    result[id] += count;
}

__global__ void generate_uniform_kernel(curandState *state,
                                int n,
                                unsigned int *result)
{
    int id = threadIdx.x + blockIdx.x * blockDim.x;
    unsigned int count = 0;
    float x;
    /* Copy state to local memory for efficiency */
    curandState localState = state[id];
    /* Generate pseudo-random uniforms */
    for(int i = 0; i < n; i++) {
        x = curand_uniform(&localState);
        /* Check if > .5 */
        if(x > .5) {
            count++;
        }
```

(continues on next page)

(continued from previous page)

```
    }
    /* Copy state back to global memory */
    state[id] = localState;
    /* Store results */
    result[id] += count;
}

__global__ void generate_uniform_kernel(curandStatePhilox4_32_10_t *state,
                                int n,
                                unsigned int *result)
{
    int id = threadIdx.x + blockIdx.x * blockDim.x;
    unsigned int count = 0;
    float x;
    /* Copy state to local memory for efficiency */
    curandStatePhilox4_32_10_t localState = state[id];
    /* Generate pseudo-random uniforms */
    for(int i = 0; i < n; i++) {
        x = curand_uniform(&localState);
        /* Check if > .5 */
        if(x > .5) {
            count++;
        }
    }
    /* Copy state back to global memory */
    state[id] = localState;
    /* Store results */
    result[id] += count;
}

__global__ void generate_normal_kernel(curandState *state,
                                int n,
                                unsigned int *result)
{
    int id = threadIdx.x + blockIdx.x * blockDim.x;
    unsigned int count = 0;
    float2 x;
    /* Copy state to local memory for efficiency */
    curandState localState = state[id];
    /* Generate pseudo-random normals */
    for(int i = 0; i < n/2; i++) {
        x = curand_normal2(&localState);
        /* Check if within one standard deviaton */
        if((x.x > -1.0) && (x.x < 1.0)) {
            count++;
        }
        if((x.y > -1.0) && (x.y < 1.0)) {
            count++;
        }
    }
    /* Copy state back to global memory */
    state[id] = localState;
    /* Store results */
    result[id] += count;
}
```

(continues on next page)

(continued from previous page)

```
__global__ void generate_normal_kernel(curandStatePhilox4_32_10_t *state,
                                       int n,
                                       unsigned int *result)
{
    int id = threadIdx.x + blockIdx.x * blockDim.x;
    unsigned int count = 0;
    float2 x;
    /* Copy state to local memory for efficiency */
    curandStatePhilox4_32_10_t localState = state[id];
    /* Generate pseudo-random normals */
    for(int i = 0; i < n/2; i++) {
        x = curand_normal2(&localState);
        /* Check if within one standard deviaton */
        if((x.x > -1.0) && (x.x < 1.0)) {
            count++;
        }
        if((x.y > -1.0) && (x.y < 1.0)) {
            count++;
        }
    }
    /* Copy state back to global memory */
    state[id] = localState;
    /* Store results */
    result[id] += count;
}

__global__ void generate_kernel(curandStateMRG32k3a *state,
                                int n,
                                unsigned int *result)
{
    int id = threadIdx.x + blockIdx.x * blockDim.x;
    unsigned int count = 0;
    unsigned int x;
    /* Copy state to local memory for efficiency */
    curandStateMRG32k3a localState = state[id];
    /* Generate pseudo-random unsigned ints */
    for(int i = 0; i < n; i++) {
        x = curand(&localState);
        /* Check if low bit set */
        if(x & 1) {
            count++;
        }
    }
    /* Copy state back to global memory */
    state[id] = localState;
    /* Store results */
    result[id] += count;
}

__global__ void generate_uniform_kernel(curandStateMRG32k3a *state,
                                        int n,
                                        unsigned int *result)
{
    int id = threadIdx.x + blockIdx.x * blockDim.x;
    unsigned int count = 0;
    double x;
```

(continues on next page)

(continued from previous page)

```
    /* Copy state to local memory for efficiency */
    curandStateMRG32k3a localState = state[id];
    /* Generate pseudo-random uniforms */
    for(int i = 0; i < n; i++) {
        x = curand_uniform_double(&localState);
        /* Check if > .5 */
        if(x > .5) {
            count++;
        }
    }
    /* Copy state back to global memory */
    state[id] = localState;
    /* Store results */
    result[id] += count;
}

__global__ void generate_normal_kernel(curandStateMRG32k3a *state,
                                       int n,
                                       unsigned int *result)
{
    int id = threadIdx.x + blockIdx.x * blockDim.x;
    unsigned int count = 0;
    double2 x;
    /* Copy state to local memory for efficiency */
    curandStateMRG32k3a localState = state[id];
    /* Generate pseudo-random normals */
    for(int i = 0; i < n/2; i++) {
        x = curand_normal2_double(&localState);
        /* Check if within one standard deviaton */
        if((x.x > -1.0) && (x.x < 1.0)) {
            count++;
        }
        if((x.y > -1.0) && (x.y < 1.0)) {
            count++;
        }
    }
    /* Copy state back to global memory */
    state[id] = localState;
    /* Store results */
    result[id] += count;
}

int main(int argc, char *argv[])
{
    const unsigned int threadsPerBlock = 64;
    const unsigned int blockCount = 64;
    const unsigned int totalThreads = threadsPerBlock * blockCount;

    unsigned int i;
    unsigned int total;
    curandState *devStates;
    curandStateMRG32k3a *devMRGStates;
    curandStatePhilox4_32_10_t *devPHILOXStates;
    unsigned int *devResults, *hostResults;
    bool useMRG = 0;
    bool usePHILOX = 0;
```

(continues on next page)

(continued from previous page)

```
    int sampleCount = 10000;
    bool doubleSupported = 0;
    int device;
    struct cudaDeviceProp properties;

    /* check for double precision support */
    CUDA_CALL(cudaGetDevice(&device));
    CUDA_CALL(cudaGetDeviceProperties(&properties,device));
    if ( properties.major >= 2 || (properties.major == 1 && properties.minor >= 3) ) {
        doubleSupported = 1;
    }

    /* Check for MRG32k3a option (default is XORWOW) */
    if (argc >= 2)  {
        if (strcmp(argv[1],"-m") == 0) {
            useMRG = 1;
            if (!doubleSupported){
                printf("MRG32k3a requires double precision\n");
                printf("^^^^ test WAIVED due to lack of double precision\n");
                return EXIT_SUCCESS;
            }
        }else if (strcmp(argv[1],"-p") == 0) {
        usePHILOX = 1;
    }
        /* Allow over-ride of sample count */
        sscanf(argv[argc-1],"%d",&sampleCount);
    }

    /* Allocate space for results on host */
    hostResults = (unsigned int *)calloc(totalThreads, sizeof(int));

    /* Allocate space for results on device */
    CUDA_CALL(cudaMalloc((void **)&devResults, totalThreads *
              sizeof(unsigned int)));

    /* Set results to 0 */
    CUDA_CALL(cudaMemset(devResults, 0, totalThreads *
              sizeof(unsigned int)));

    /* Allocate space for prng states on device */
    if (useMRG) {
        CUDA_CALL(cudaMalloc((void **)&devMRGStates, totalThreads *
                  sizeof(curandStateMRG32k3a)));
    }else if(usePHILOX) {
        CUDA_CALL(cudaMalloc((void **)&devPHILOXStates, totalThreads *
                  sizeof(curandStatePhilox4_32_10_t)));
    }else {
        CUDA_CALL(cudaMalloc((void **)&devStates, totalThreads *
                  sizeof(curandState)));
    }

    /* Setup prng states */
    if (useMRG) {
        setup_kernel<<<64, 64>>>(devMRGStates);
    }else if(usePHILOX)
    {
```

(continues on next page)

(continued from previous page)

```
        setup_kernel<<<64, 64>>>(devPHILOXStates);
    }else {
        setup_kernel<<<64, 64>>>(devStates);
    }

    /* Generate and use pseudo-random  */
    for(i = 0; i < 50; i++) {
        if (useMRG) {
            generate_kernel<<<64, 64>>>(devMRGStates, sampleCount, devResults);
        }else if (usePHILOX){
            generate_kernel<<<64, 64>>>(devPHILOXStates, sampleCount, devResults);
    }else {
            generate_kernel<<<64, 64>>>(devStates, sampleCount, devResults);
        }
    }

    /* Copy device memory to host */
    CUDA_CALL(cudaMemcpy(hostResults, devResults, totalThreads *
        sizeof(unsigned int), cudaMemcpyDeviceToHost));

    /* Show result */
    total = 0;
    for(i = 0; i < totalThreads; i++) {
        total += hostResults[i];
    }
    printf("Fraction with low bit set was %10.13f\n",
        (float)total / (totalThreads * sampleCount * 50.0f));

    /* Set results to 0 */
    CUDA_CALL(cudaMemset(devResults, 0, totalThreads *
              sizeof(unsigned int)));

    /* Generate and use uniform pseudo-random  */
    for(i = 0; i < 50; i++) {
        if (useMRG) {
            generate_uniform_kernel<<<64, 64>>>(devMRGStates, sampleCount,
↪devResults);
        }else if(usePHILOX) {
            generate_uniform_kernel<<<64, 64>>>(devPHILOXStates, sampleCount,
↪devResults);
    }else {
            generate_uniform_kernel<<<64, 64>>>(devStates, sampleCount, devResults);
        }
    }

    /* Copy device memory to host */
    CUDA_CALL(cudaMemcpy(hostResults, devResults, totalThreads *
        sizeof(unsigned int), cudaMemcpyDeviceToHost));

    /* Show result */
    total = 0;
    for(i = 0; i < totalThreads; i++) {
        total += hostResults[i];
    }
    printf("Fraction of uniforms > 0.5 was %10.13f\n",
        (float)total / (totalThreads * sampleCount * 50.0f));
```

(continues on next page)

(continued from previous page)

```
    /* Set results to 0 */
    CUDA_CALL(cudaMemset(devResults, 0, totalThreads *
              sizeof(unsigned int)));

    /* Generate and use normal pseudo-random  */
    for(i = 0; i < 50; i++) {
        if (useMRG) {
            generate_normal_kernel<<<64, 64>>>(devMRGStates, sampleCount, devResults);
        }else if(usePHILOX) {
            generate_normal_kernel<<<64, 64>>>(devPHILOXStates, sampleCount,
↪devResults);
    }else {
            generate_normal_kernel<<<64, 64>>>(devStates, sampleCount, devResults);
        }
    }

    /* Copy device memory to host */
    CUDA_CALL(cudaMemcpy(hostResults, devResults, totalThreads *
        sizeof(unsigned int), cudaMemcpyDeviceToHost));

    /* Show result */
    total = 0;
    for(i = 0; i < totalThreads; i++) {
        total += hostResults[i];
    }
    printf("Fraction of normals within 1 standard deviation was %10.13f\n",
        (float)total / (totalThreads * sampleCount * 50.0f));

    /* Cleanup */
    if (useMRG) {
        CUDA_CALL(cudaFree(devMRGStates));
    }else if(usePHILOX)
    {
        CUDA_CALL(cudaFree(devPHILOXStates));
    }else {
        CUDA_CALL(cudaFree(devStates));
    }
    CUDA_CALL(cudaFree(devResults));
    free(hostResults);
    printf("^^^^ kernel_example PASSED\n");
    return EXIT_SUCCESS;
}
```

The following example uses the cuRAND host MTGP setup API, and the cuRAND device API, to generate integers using the MTGP32 generator, and calculates the proportion that have the low bit set.

```
/*
 * This program uses the device CURAND API to calculate what
 * proportion of pseudo-random ints have low bit set.
 */
#include <stdio.h>
#include <stdlib.h>
#include <cuda_runtime.h>
#include <curand_kernel.h>
/* include MTGP host helper functions */
#include <curand_mtgp32_host.h>
```

(continues on next page)

(continued from previous page)

```
/* include MTGP pre-computed parameter sets */
#include <curand_mtgp32dc_p_11213.h>


#define CUDA_CALL(x) do { if((x) != cudaSuccess) { \
    printf("Error at %s:%d\n",__FILE__,__LINE__); \
    return EXIT_FAILURE;}} while(0)

#define CURAND_CALL(x) do { if((x) != CURAND_STATUS_SUCCESS) { \
    printf("Error at %s:%d\n",__FILE__,__LINE__); \
    return EXIT_FAILURE;}} while(0)

__global__ void generate_kernel(curandStateMtgp32 *state,
                                int n,
                                int *result)
{
    int id = threadIdx.x + blockIdx.x * 256;
    int count = 0;
    unsigned int x;
    /* Generate pseudo-random unsigned ints */
    for(int i = 0; i < n; i++) {
        x = curand(&state[blockIdx.x]);
        /* Check if low bit set */
        if(x & 1) {
            count++;
        }
    }
    /* Store results */
    result[id] += count;
}

int main(int argc, char *argv[])
{
    int i;
    long long total;
    curandStateMtgp32 *devMTGPStates;
    mtgp32_kernel_params *devKernelParams;
    int *devResults, *hostResults;
    int sampleCount = 10000;

    /* Allow over-ride of sample count */
    if (argc == 2) {
        sscanf(argv[1],"%d",&sampleCount);
    }

    /* Allocate space for results on host */
    hostResults = (int *)calloc(64 * 256, sizeof(int));

    /* Allocate space for results on device */
    CUDA_CALL(cudaMalloc((void **)&devResults, 64 * 256 *
              sizeof(int)));

    /* Set results to 0 */
    CUDA_CALL(cudaMemset(devResults, 0, 64 * 256 *
              sizeof(int)));
```

(continues on next page)

(continued from previous page)

```
    /* Allocate space for prng states on device */
    CUDA_CALL(cudaMalloc((void **)&devMTGPStates, 64 *
              sizeof(curandStateMtgp32)));

    /* Setup MTGP prng states */

    /* Allocate space for MTGP kernel parameters */
    CUDA_CALL(cudaMalloc((void**)&devKernelParams, sizeof(mtgp32_kernel_params)));

    /* Reformat from predefined parameter sets to kernel format, */
    /* and copy kernel parameters to device memory               */
    CURAND_CALL(curandMakeMTGP32Constants(mtgp32dc_params_fast_11213,
↪devKernelParams));

    /* Initialize one state per thread block */
    CURAND_CALL(curandMakeMTGP32KernelState(devMTGPStates,
                mtgp32dc_params_fast_11213, devKernelParams, 64, 1234));

    /* State setup is complete */

    /* Generate and use pseudo-random  */
    for(i = 0; i < 10; i++) {
        generate_kernel<<<64, 256>>>(devMTGPStates, sampleCount, devResults);
    }

    /* Copy device memory to host */
    CUDA_CALL(cudaMemcpy(hostResults, devResults, 64 * 256 *
        sizeof(int), cudaMemcpyDeviceToHost));

    /* Show result */
    total = 0;
    for(i = 0; i < 64 * 256; i++) {
        total += hostResults[i];
    }


    printf("Fraction with low bit set was %10.13g\n",
        (double)total / (64.0f * 256.0f * sampleCount * 10.0f));

    /* Cleanup */
    CUDA_CALL(cudaFree(devKernelParams));
    CUDA_CALL(cudaFree(devMTGPStates));
    CUDA_CALL(cudaFree(devResults));
    free(hostResults);
    printf("^^^^ kernel_mtgp_example PASSED\n");
    return EXIT_SUCCESS;
}
```

The following example uses the cuRAND device API to generate uniform double precision numbers with the 64 bit scrambled Sobol generator. It uses the results to derive an approximation of the volume of a sphere.

```
/*
 * This program uses the device CURAND API to calculate what
 * proportion of quasi-random 3D points fall within a sphere
 * of radius 1, and to derive the volume of the sphere.
```

(continues on next page)

(continued from previous page)

```
 *
 * In particular it uses 64 bit scrambled Sobol direction
 * vectors returned by curandGetDirectionVectors64, to
 * generate double precision uniform samples.
 *
 */

#include <stdio.h>
#include <stdlib.h>
#include <cuda_runtime.h>
#include <curand_kernel.h>
#include <curand.h>

#define THREADS_PER_BLOCK 64
#define BLOCK_COUNT 64
#define TOTAL_THREADS (THREADS_PER_BLOCK * BLOCK_COUNT)

/* Number of 64-bit vectors per dimension */
#define VECTOR_SIZE 64


#define CUDA_CALL(x) do { if((x) != cudaSuccess) { \
    printf("Error at %s:%d\n",__FILE__,__LINE__); \
    return EXIT_FAILURE;}} while(0)

#define CURAND_CALL(x) do { if((x) != CURAND_STATUS_SUCCESS) { \
    printf("Error at %s:%d\n",__FILE__,__LINE__); \
    return EXIT_FAILURE;}} while(0)

/* This kernel initializes state per thread for each of x, y, and z */

__global__ void setup_kernel(unsigned long long * sobolDirectionVectors,
                             unsigned long long *sobolScrambleConstants,
                             curandStateScrambledSobol64 *state)
{
    int id = threadIdx.x + blockIdx.x * THREADS_PER_BLOCK;
    int dim = 3*id;
    /* Each thread uses 3 different dimensions */
    curand_init(sobolDirectionVectors + VECTOR_SIZE*dim,
                sobolScrambleConstants[dim],
                1234,
                &state[dim]);

    curand_init(sobolDirectionVectors + VECTOR_SIZE*(dim + 1),
                sobolScrambleConstants[dim + 1],
                1234,
                &state[dim + 1]);

    curand_init(sobolDirectionVectors + VECTOR_SIZE*(dim + 2),
                sobolScrambleConstants[dim + 2],
                1234,
                &state[dim + 2]);
}

/* This kernel generates random 3D points and increments a counter if
 * a point is within a unit sphere
```

(continues on next page)

(continued from previous page)

```
 */
__global__ void generate_kernel(curandStateScrambledSobol64 *state,
                                int n,
                                long long int *result)
{
    int id = threadIdx.x + blockIdx.x * THREADS_PER_BLOCK;
    int baseDim = 3 * id;
    long long int count = 0;
    double x, y, z;

    /* Generate quasi-random double precision coordinates */
    for(int i = 0; i < n; i++) {
        x = curand_uniform_double(&state[baseDim]);
        y = curand_uniform_double(&state[baseDim + 1]);
        z = curand_uniform_double(&state[baseDim + 2]);

        /* Check if within sphere of radius 1 */
        if( (x*x + y*y + z*z) < 1.0) {
            count++;
        }
    }
    /* Store results */
    result[id] += count;
}

int main(int argc, char *argv[])
{
    int i;
    long long total;
    curandStateScrambledSobol64 *devSobol64States;
    curandDirectionVectors64_t *hostVectors64;
    unsigned long long int * hostScrambleConstants64;
    unsigned long long int * devDirectionVectors64;
    unsigned long long int * devScrambleConstants64;
    long long int *devResults, *hostResults;
    int sampleCount = 10000;
    int iterations = 100;
    double fraction;
    double pi = 3.1415926535897932;

    /* Allow over-ride of sample count */
    if (argc == 2) {
        sscanf(argv[1],"%d",&sampleCount);
    }

    /* Allocate space for results on host */
    hostResults = (long long int*)calloc(TOTAL_THREADS,
                                         sizeof(long long int));

    /* Allocate space for results on device */
    CUDA_CALL(cudaMalloc((void **)&devResults,
                         TOTAL_THREADS * sizeof(long long int)));

    /* Set results to 0 */
    CUDA_CALL(cudaMemset(devResults, 0,
                         TOTAL_THREADS * sizeof(long long int)));
```

(continues on next page)

(continued from previous page)

```
    /* Get pointers to the 64 bit scrambled direction vectors and constants*/
    CURAND_CALL(curandGetDirectionVectors64( &hostVectors64,
                                             CURAND_SCRAMBLED_DIRECTION_VECTORS_64_
↪JOEKUO6));

    CURAND_CALL(curandGetScrambleConstants64( &hostScrambleConstants64));


    /* Allocate memory for 3 states per thread (x, y, z), each state to get a unique
↪dimension */
    CUDA_CALL(cudaMalloc((void **)&devSobol64States,
              TOTAL_THREADS * 3 * sizeof(curandStateScrambledSobol64)));

    /* Allocate memory and copy 3 sets of vectors per thread to the device */

    CUDA_CALL(cudaMalloc((void **)&(devDirectionVectors64),
                         3 * TOTAL_THREADS * VECTOR_SIZE * sizeof(long long int)));

    CUDA_CALL(cudaMemcpy(devDirectionVectors64, hostVectors64,
                         3 * TOTAL_THREADS * VECTOR_SIZE * sizeof(long long int),
                         cudaMemcpyHostToDevice));

    /* Allocate memory and copy 3 scramble constants (one costant per dimension)
       per thread to the device */

    CUDA_CALL(cudaMalloc((void **)&(devScrambleConstants64),
                         3 * TOTAL_THREADS * sizeof(long long int)));

    CUDA_CALL(cudaMemcpy(devScrambleConstants64, hostScrambleConstants64,
                         3 * TOTAL_THREADS * sizeof(long long int),
                         cudaMemcpyHostToDevice));

    /* Initialize the states */

    setup_kernel<<<BLOCK_COUNT, THREADS_PER_BLOCK>>>(devDirectionVectors64,
                                                     devScrambleConstants64,
                                                     devSobol64States);

    /* Generate and count quasi-random points  */

    for(i = 0; i < iterations; i++) {
        generate_kernel<<<BLOCK_COUNT, THREADS_PER_BLOCK>>>(devSobol64States,
↪sampleCount, devResults);
    }

    /* Copy device memory to host */

    CUDA_CALL(cudaMemcpy(hostResults,
              devResults,
              TOTAL_THREADS * sizeof(long long int),
              cudaMemcpyDeviceToHost));

    /* Tally and show result */

    total = 0;
```

(continues on next page)

(continued from previous page)

```
    for(i = 0; i < TOTAL_THREADS; i++) {
        total += hostResults[i];
    }

    fraction = (double)total / ((double)TOTAL_THREADS * (double)sampleCount *
↪(double)iterations);
    printf("Fraction inside sphere was %g\n", fraction);
    printf("(4/3) pi = %g, sampled volume = %g\n",(4.0*pi/3.0),8.0 * fraction);

    /* Cleanup */

    CUDA_CALL(cudaFree(devSobol64States));
    CUDA_CALL(cudaFree(devDirectionVectors64));
    CUDA_CALL(cudaFree(devScrambleConstants64));
    CUDA_CALL(cudaFree(devResults));
    free(hostResults);
    printf("^^^^ kernel_sobol_example PASSED\n");


    return EXIT_SUCCESS;
}
```

4.7. Thrust and cuRAND Example

The following example demonstrates mixing cuRAND and Thrust. It is a minimally modified version of `monte_carlo.cu`, one of the standard Thrust examples. The example estimates π by randomly picking points in the unit square and calculating the distance to the origin to see if the points are in the quarter unit circle.

```
#include <thrust/iterator/counting_iterator.h>
#include <thrust/functional.h>
#include <thrust/transform_reduce.h>
#include <curand_kernel.h>

#include <iostream>
#include <iomanip>

// we could vary M & N to find the perf sweet spot

struct estimate_pi :
    public thrust::unary_function<unsigned int, float>
{
  __device__
  float operator()(unsigned int thread_id)
  {
    float sum = 0;
    unsigned int N = 10000; // samples per thread

    unsigned int seed = thread_id;

    curandState s;

    // seed a random number generator
```

(continues on next page)

(continued from previous page)

```
    curand_init(seed, 0, 0, &s);

    // take N samples in a quarter circle
    for(unsigned int i = 0; i < N; ++i)
    {
      // draw a sample from the unit square
      float x = curand_uniform(&s);
      float y = curand_uniform(&s);

      // measure distance from the origin
      float dist = sqrtf(x*x + y*y);

      // add 1.0f if (u0,u1) is inside the quarter circle
      if(dist <= 1.0f)
        sum += 1.0f;
    }

    // multiply by 4 to get the area of the whole circle
    sum *= 4.0f;

    // divide by N
    return sum / N;
  }
};

int main(void)
{
  // use 30K independent seeds
  int M = 30000;

  float estimate = thrust::transform_reduce(
        thrust::counting_iterator<int>(0),
        thrust::counting_iterator<int>(M),
        estimate_pi(),
        0.0f,
        thrust::plus<float>());
  estimate /= M;

  std::cout << std::setprecision(3);
  std::cout << "pi is approximately ";
  std::cout << estimate << std::endl;
  return 0;
}
```

4.8. Poisson API Example

This example shows the differences between the 3 API types for the Poisson distribution. It is a simulation of queues in a store. The host API is the most robust for generating large vectors of Poisson-distributed random numbers. (i.e. it has the best statistical properties across the full range of lambda values) The discrete Device API is almost as robust as the HOST API and allows Poisson-distributed random numbers to be generated inside a kernel. The simple Device API is the least robust but is more efficient when generating Poisson-distributed random numbers for many different lambdas.

```
/*
 * This program uses CURAND library for Poisson distribution
 * to simulate queues in store for 16 hours. It shows the
 * difference of using 3 different APIs:
 * - HOST API -arrival of customers is described by Poisson(4)
 * - SIMPLE DEVICE API -arrival of customers is described by
 *     Poisson(4*(sin(x/100)+1)), where x is number of minutes
 *     from store opening time.
 * - ROBUST DEVICE API -arrival of customers is described by:
 *     - Poisson(2) for first 3 hours.
 *     - Poisson(1) for second 3 hours.
 *     - Poisson(3) after 6 hours.
 */

#include <stdio.h>
#include <stdlib.h>
#include <cuda_runtime.h>
#include <curand_kernel.h>
#include <curand.h>

#define CUDA_CALL(x) do { if((x) != cudaSuccess) { \
    printf("Error at %s:%d\n",__FILE__,__LINE__); \
    return EXIT_FAILURE;}} while(0)
#define CURAND_CALL(x) do { if((x)!=CURAND_STATUS_SUCCESS) { \
    printf("Error at %s:%d\n",__FILE__,__LINE__);\
    return EXIT_FAILURE;}} while(0)


#define HOURS 16
#define OPENING_HOUR 7
#define CLOSING_HOUR (OPENING_HOUR + HOURS)

#define access_2D(type, ptr, row, column, pitch)\
    *((type*)((char*)ptr + (row) * pitch) + column)

enum API_TYPE {
    HOST_API = 0,
    SIMPLE_DEVICE_API = 1,
    ROBUST_DEVICE_API = 2,
};

/* global variables */
API_TYPE api;
int report_break;
int cashiers_load_h[HOURS];
__constant__ int cashiers_load[HOURS];

__global__ void setup_kernel(curandState *state)
{
    int id = threadIdx.x + blockIdx.x * blockDim.x;
    /* Each thread gets same seed, a different sequence
       number, no offset */
    curand_init(1234, id, 0, &state[id]);
}

__inline__ __device__
void update_queue(int id, int min, unsigned int new_customers,
```

(continues on next page)

(continued from previous page)

```
                  unsigned int &queue_length,
                  unsigned int *queue_lengths, size_t pitch)
{
    int balance;
    balance = new_customers - 2 * cashiers_load[(min-1)/60];
    if (balance + (int)queue_length <= 0){
        queue_length = 0;
    }else{
        queue_length += balance;
    }
    /* Store results */
    access_2D(unsigned int, queue_lengths, min-1, id, pitch)
        = queue_length;
}


__global__ void simple_device_API_kernel(curandState *state,
                    unsigned int *queue_lengths, size_t pitch)
{
    int id = threadIdx.x + blockIdx.x * blockDim.x;
    unsigned int new_customers;
    unsigned int queue_length = 0;
    /* Copy state to local memory for efficiency */
    curandState localState = state[id];
    /* Simulate queue in time */
    for(int min = 1; min <= 60 * HOURS; min++) {
        /* Draw number of new customers depending on API */
        new_customers = curand_poisson(&localState,
                                4*(sin((float)min/100.0)+1));
        /* Update queue */
        update_queue(id, min, new_customers, queue_length,
                     queue_lengths, pitch);
    }
    /* Copy state back to global memory */
    state[id] = localState;
}


__global__ void host_API_kernel(unsigned int *poisson_numbers,
                    unsigned int *queue_lengths, size_t pitch)
{
    int id = threadIdx.x + blockIdx.x * blockDim.x;
    unsigned int new_customers;
    unsigned int queue_length = 0;
    /* Simulate queue in time */
    for(int min = 1; min <= 60 * HOURS; min++) {
        /* Get random number from global memory */
        new_customers = poisson_numbers
                    [blockDim.x * gridDim.x * (min -1) + id];
        /* Update queue */
        update_queue(id, min, new_customers, queue_length,
                     queue_lengths, pitch);
    }
}

__global__ void robust_device_API_kernel(curandState *state,
```

(continues on next page)

(continued from previous page)

```
                    curandDiscreteDistribution_t poisson_1,
                    curandDiscreteDistribution_t poisson_2,
                    curandDiscreteDistribution_t poisson_3,
                    unsigned int *queue_lengths, size_t pitch)
{
    int id = threadIdx.x + blockIdx.x * 64;
    unsigned int new_customers;
    unsigned int queue_length = 0;
    /* Copy state to local memory for efficiency */
    curandState localState = state[id];
    /* Simulate queue in time */
    /* first 3 hours */
    for(int min = 1; min <= 60 * 3; min++) {
        /* draw number of new customers depending on API */
        new_customers =
                    curand_discrete(&localState, poisson_2);
        /* Update queue */
        update_queue(id, min, new_customers, queue_length,
                                    queue_lengths, pitch);
    }
    /* second 3 hours */
    for(int min = 60 * 3 + 1; min <= 60 * 6; min++) {
        /* draw number of new customers depending on API */
        new_customers =
                    curand_discrete(&localState, poisson_1);
        /* Update queue */
        update_queue(id, min, new_customers, queue_length,
                                    queue_lengths, pitch);
    }
    /* after 6 hours */
    for(int min = 60 * 6 + 1; min <= 60 * HOURS; min++) {
        /* draw number of new customers depending on API */
        new_customers =
                    curand_discrete(&localState, poisson_3);
        /* Update queue */
        update_queue(id, min, new_customers, queue_length,
                                    queue_lengths, pitch);
    }
    /* Copy state back to global memory */
    state[id] = localState;
}

/* Set time intervals between reports */
void report_settings()
{
    do{
        printf("Set time intervals between queue reports");
        printf("(in minutes > 0)\n");
        if (scanf("%d", &report_break) == 0) continue;
    }while(report_break <= 0);
}


/* Set number of cashiers each hour */
void add_cachiers(int *cashiers_load)
{
```

(continues on next page)

(continued from previous page)

```
    int i, min, max, begin, end;
    printf("Cashier serves 2 customers per minute...\n");
    for (i = 0; i < HOURS; i++){
        cashiers_load_h[i] = 0;
    }
    while (true){
        printf("Adding cashier...\n");
        min = OPENING_HOUR;
        max = CLOSING_HOUR-1;
        do{
            printf("Set hour that cahier comes (%d-%d)",
                                                min, max);
            printf(" [type 0 to finish adding cashiers]\n");
            if (scanf("%d", &begin) == 0) continue;
        }while (begin > max || (begin < min && begin != 0));
        if (begin == 0) break;
        min = begin+1;
        max = CLOSING_HOUR;
        do{
            printf("Set hour that cahier leaves (%d-%d)",
                                                min, max);
            printf(" [type 0 to finish adding cashiers]\n");
            if (scanf("%d", &end) == 0) continue;
        }while (end > max || (end < min && end != 0));
        if (end == 0) break;
        for (i = begin - OPENING_HOUR;
             i < end   - OPENING_HOUR; i++){
            cashiers_load_h[i]++;
        }
    }
    for (i = OPENING_HOUR; i < CLOSING_HOUR; i++){
        printf("\n%2d:00 - %2d:00     %d cashier",
                i, i+1, cashiers_load_h[i-OPENING_HOUR]);
        if (cashiers_load[i-OPENING_HOUR] != 1) printf("s");
    }
    printf("\n");
}

/* Set API type */
API_TYPE set_API_type()
{
    printf("Choose API type:\n");
    int choose;
    do{
        printf("type 1 for HOST API\n");
        printf("type 2 for SIMPLE DEVICE API\n");
        printf("type 3 for ROBUST DEVICE API\n");
        if (scanf("%d", &choose) == 0) continue;
    }while( choose < 1 || choose > 3);
    switch(choose){
        case 1: return HOST_API;
        case 2: return SIMPLE_DEVICE_API;
        case 3: return ROBUST_DEVICE_API;
        default:
            fprintf(stderr, "wrong API\n");
            return HOST_API;
```

(continues on next page)

(continued from previous page)

```
    }
}

void settings()
{
    add_cachiers(cashiers_load);
    cudaMemcpyToSymbol("cashiers_load", cashiers_load_h,
            HOURS * sizeof(int), 0, cudaMemcpyHostToDevice);
    report_settings();
    api = set_API_type();
}

void print_statistics(unsigned int *hostResults, size_t pitch)
{
    int min, i, hour, minute;
    unsigned int sum;
    for(min = report_break; min <= 60 * HOURS;
                            min += report_break) {
        sum = 0;
        for(i = 0; i < 64 * 64; i++) {
            sum += access_2D(unsigned int, hostResults,
                                       min-1, i, pitch);
        }
        hour = OPENING_HOUR + min/60;
        minute = min%60;
        printf("%2d:%02d   # of waiting customers = %10.4g |",
                    hour, minute, (float)sum/(64.0 * 64.0));
        printf("  # of cashiers = %d  |  ",
                    cashiers_load_h[(min-1)/60]);
        printf("# of new customers/min ~= ");
        switch (api){
            case HOST_API:
                printf("%2.2f\n", 4.0);
                break;
            case SIMPLE_DEVICE_API:
                printf("%2.2f\n",
                            4*(sin((float)min/100.0)+1));
                break;
            case ROBUST_DEVICE_API:
                if (min <= 3 * 60){
                    printf("%2.2f\n", 2.0);
                }else{
                    if (min <= 6 * 60){
                        printf("%2.2f\n", 1.0);
                    }else{
                        printf("%2.2f\n", 3.0);
                    }
                }
                break;
            default:
                fprintf(stderr, "Wrong API\n");
        }
    }
}
```

(continues on next page)

(continued from previous page)

```
int main(int argc, char *argv[])
{
    int n;
    size_t pitch;
    curandState *devStates;
    unsigned int *devResults, *hostResults;
    unsigned int *poisson_numbers_d;
    curandDiscreteDistribution_t poisson_1, poisson_2;
    curandDiscreteDistribution_t poisson_3;
    curandGenerator_t gen;

    /* Setting cashiers, report and API */
    settings();

    /* Allocate space for results on device */
    CUDA_CALL(cudaMallocPitch((void **)&devResults, &pitch,
              64 * 64 * sizeof(unsigned int), 60 * HOURS));

    /* Allocate space for results on host */
    hostResults = (unsigned int *)calloc(pitch * 60 * HOURS,
              sizeof(unsigned int));

    /* Allocate space for prng states on device */
    CUDA_CALL(cudaMalloc((void **)&devStates, 64 * 64 *
             sizeof(curandState)));

    /* Setup prng states */
    if (api != HOST_API){
        setup_kernel<<<64, 64>>>(devStates);
    }
    /* Simulate queue  */
    switch (api){
        case HOST_API:
            /* Create pseudo-random number generator */
            CURAND_CALL(curandCreateGenerator(&gen,
                                CURAND_RNG_PSEUDO_DEFAULT));
            /* Set seed */
            CURAND_CALL(curandSetPseudoRandomGeneratorSeed(
                                        gen, 1234ULL));
            /* compute n */
            n = 64 * 64 * HOURS * 60;
            /* Allocate n unsigned ints on device */
            CUDA_CALL(cudaMalloc((void **)&poisson_numbers_d,
                                n * sizeof(unsigned int)));
            /* Generate n unsigned ints on device */
            CURAND_CALL(curandGeneratePoisson(gen,
                                poisson_numbers_d, n, 4.0));
            host_API_kernel<<<64, 64>>>(poisson_numbers_d,
                                        devResults, pitch);
            /* Cleanup */
            CURAND_CALL(curandDestroyGenerator(gen));
            break;
        case SIMPLE_DEVICE_API:
            simple_device_API_kernel<<<64, 64>>>(devStates,
                                        devResults, pitch);
            break;
```

(continues on next page)

(continued from previous page)

```
        case ROBUST_DEVICE_API:
            /* Create histograms for Poisson(1) */
            CURAND_CALL(curandCreatePoissonDistribution(1.0,
                                                &poisson_1));
            /* Create histograms for Poisson(2) */
            CURAND_CALL(curandCreatePoissonDistribution(2.0,
                                                &poisson_2));
            /* Create histograms for Poisson(3) */
            CURAND_CALL(curandCreatePoissonDistribution(3.0,
                                                &poisson_3));
            robust_device_API_kernel<<<64, 64>>>(devStates,
                            poisson_1, poisson_2, poisson_3,
                            devResults, pitch);
            /* Cleanup */
            CURAND_CALL(curandDestroyDistribution(poisson_1));
            CURAND_CALL(curandDestroyDistribution(poisson_2));
            CURAND_CALL(curandDestroyDistribution(poisson_3));
            break;
        default:
            fprintf(stderr, "Wrong API\n");
    }
    /* Copy device memory to host */
    CUDA_CALL(cudaMemcpy2D(hostResults, pitch, devResults,
                pitch, 64 * 64 * sizeof(unsigned int),
                60 * HOURS, cudaMemcpyDeviceToHost));
    /* Show result */
    print_statistics(hostResults, pitch);
    /* Cleanup */
    CUDA_CALL(cudaFree(devStates));
    CUDA_CALL(cudaFree(devResults));
    free(hostResults);
    return EXIT_SUCCESS;
}
```

Chapter 5. Testing

The XORWOW generator was proposed by Marsaglia [5] and has been tested using the TestU01 "Crush" framework of tests [6]. The full suite of NIST pseudorandomness tests [7] has also been run, though the focus has been on TestU01. The most rigorous of the TestU01 batteries is "BigCrush", which executes 106 statistical tests over the course of approximately 5 hours on a high-end CPU/GPU. The XORWOW generator passes all of the tests on most runs, but does produce occasional suspect statistics. Below is an example of the summary output from a run that did not pass all tests, with the detail of the specific failure.

```
========= Summary results of BigCrush =========

 Version:          TestU01 1.2.3
 Generator:        curandXORWOW
 Number of statistics:  160
 Total CPU time:   05:17:59.63
 The following tests gave p-values outside [0.001, 0.9990]:
 (eps  means a value < 1.0e-300):
 (eps1 means a value < 1.0e-15):

       Test                          p-value
 ----------------------------------------------
 81  LinearComp, r = 29            1 - 7.1e-11
 ----------------------------------------------
 All other tests were passed

Detail from test 81:

scomp_LinearComp test:
-----------------------------------------------
   N =  1,  n = 400020,  r = 29,    s = 1



-----------------------------------------------
Number of degrees of freedom          :   12
Chi2 statistic for size of jumps      :    7.11
p-value of test                       :    0.85


-----------------------------------------------
Normal statistic for number of jumps  :   -6.41
p-value of test                       : 1 - 7.1e-11    *****
```

To put this into perspective, there is a table in [6] that gives the results of running various levels of the "Crush" tests on a broad selection of generators. Only a small number of generators pass all of the

BigCrush tests. For example the widely-respected Mersenne twister [8] consistently fails two of the linear complexity tests.

The MRG32k3a generator was proposed in [9], with a specific implementation suggested in [10]. This generator passes all "BigCrush" tests frequently, with occasional marginal results similar to those shown below.

```
========= Summary results of BigCrush =========

 Version:          TestU01 1.2.3
 Generator:        curandMRG32k3a
 Number of statistics:  160
 Total CPU time:   07:14:55.41
 The following tests gave p-values outside [0.001, 0.9990]:
 (eps  means a value < 1.0e-300):
 (eps1 means a value < 1.0e-15):

       Test                          p-value
 ----------------------------------------------
 59  WeightDistrib, r = 0            5.2e-4
 ----------------------------------------------
 All other tests were passed

Detail from test 59:

svaria_WeightDistrib test:
-----------------------------------------------
   N =  1,  n = 20000000,  r =  0,  k = 256,  Alpha =      0,  Beta =   0.25


-----------------------------------------------
Number of degrees of freedom          :   67
Chi-square statistic                  :  111.55
p-value of test                       :  5.2e-4    *****

-----------------------------------------------
CPU time used                    :  00:02:56.25
```

The MTGP32 generator is an adaptation of the work outlined in [1]. The MTGP32 generator exhibits some marginal results on "BigCrush". Below is an example.

```
========= Summary results of BigCrush =========

 Version:          TestU01 1.2.3
 Generator:        curandMtgp32Int
 Number of statistics:  160
 Total CPU time:   05:45:29.49
 The following tests gave p-values outside [0.001, 0.9990]:
 (eps  means a value < 1.0e-300):
 (eps1 means a value < 1.0e-15):

       Test                          p-value
 ----------------------------------------------
 12  CollisionOver, t = 21           0.9993
 ----------------------------------------------
 All other tests were passed

Detail from test 12:
```

(continues on next page)

(continued from previous page)

```
smultin_MultinomialOver test:
-----------------------------------------------
   N = 30,  n = 20000000,  r = 28,   d =    4,   t = 21,
       Sparse =   TRUE

       GenerCell = smultin_GenerCellSerial
       Number of cells = d^t =      4398046511104
       Expected number per cell =  1 /  219902.33
       EColl = n^2 / (2k) =  45.47473509
       Hashing =   TRUE

       Collision test

       CollisionOver:   density = n / k =  1 /  219902.33
       Expected number of collisions = Mu =      45.47


-----------------------------------------------
Results of CollisionOver test:

POISSON approximation                :
Expected number of collisions = N*Mu  :     1364.24
Observed number of collisions         :     1248
p-value of test                       :    0.9993    *****

------------------------------
Total number of cells containing j balls

  j =  0                             :  131940795334368
  j =  1                             :        599997504
  j =  2                             :             1248
  j =  3                             :                0
  j =  4                             :                0
  j =  5                             :                0

-----------------------------------------------
CPU time used                    :  00:04:32.52
```

The MT19937 generator is, by far, the most widely used PRNG

```
========= Summary results of BigCrush =========

 Version:          TestU01 1.2.3
 Generator:        curandMT19937Int
 Number of statistics:  160
 Total CPU time:   03:12:59.34

 All tests were passed
```

The Philox4_32_10 generator is one of the counter-based RNGs described in [17].

```
========= Summary results of BigCrush =========

 Version:          TestU01 1.2.3
 Generator:        curandPHILOXInt
 Number of statistics:  160
```

(continues on next page)

(continued from previous page)

```
Total CPU time:   03:18:50.30

All tests were passed
```

Sobol' sequences are generated using the direction vectors recommended by Joe and Kuo [2]. The scrambled Sobol' method is described in [3] and [4].

Testing of the normal distribution, with the each of the generators, has been done using the Pearson chi-squared test [11], [12], the Jarque-Bera test [13], the Kolmogorov-Smirnov test [14], [15], and the Anderson-Darling test [16].

Tests are run over the range +/- 6 standard deviations. Three Pearson tests are run, with cell counts 1000, 100, and 25. The test output has columns labeled PK for Pearson with 1000 cells, PC for Pearson with 100 cells, P25 for Pearson with 25 cells, JB for Jarque-Bera, KS for Kolmogorov-Smirnov, and AD for Anderson-Darling. The rejection criterion for each test is printed below the label.

The following tables are representative of the test output for statistical testing of the normal distribution for XORWOW, MRG32k3a, MTGP32, MT19937, Philox, Sobol' 32-bit, and scrambled Sobol' 32-bit generators. The rows of each table represent the statistical results computed over successive sequences of 10000 samples.

XORWOW Generator:

```
    PK          PC          P25          JB          KS          AD
   <1058       <118         <33         <4.6       <0.0122      <.632
-------------------------------------------------------------------------
 684.48120    58.97784    20.44693     2.84152     0.00540     0.32829
 686.37925    54.84938     7.79583     0.55109     0.00900     0.25832
 673.21437    69.15825    15.46540     0.30335     0.00872     0.26772
 568.26999    49.99519     8.85046     0.66624     0.00870     0.22939
 639.10690    84.23040    10.19753     0.19844     0.00542     0.27939
```

MRg32k3a Generator:

```
    PK          PC          P25          JB          KS          AD
   <1058       <118         <33         <4.6       <0.0122      <.632
-------------------------------------------------------------------------

 764.38500    74.48157    19.32716     1.50118     0.01103     0.60351
 795.31006    74.15086    11.78414     1.15159     0.00821     0.35343
 741.85426    91.88692    20.67103     2.34232     0.00900     0.61787
 644.62093    70.68369    17.18277     0.32870     0.01243*    0.34630
 806.02693    93.50691    23.10548     2.67340     0.00978     0.51466
```

MTGP32 Generator:

```
    PK          PC          P25          JB          KS          AD
   <1058       <118         <33         <4.6       <0.0122      <.632
-------------------------------------------------------------------------

 924.62604   110.19868    23.45811     0.86919     0.00519     0.33411
 708.76047    79.42919    20.67913     1.13427     0.01142     0.54632
 674.17713    65.80415    13.09834     1.07799     0.01040     0.23860
 733.35915    57.13829    17.66337     3.17017     0.01188     0.30864
 620.17297    50.39043    14.75682     0.57970     0.00845     0.28916
```

MT19937 Generator:

```
    PK           PC           P25           JB           KS           AD
   <1058        <118         <33           <4.6         <0.0077      <.632
-------------------------------------------------------------------------

 663.51515     67.53027      9.70908      0.70428      0.00482      0.22643
 758.11526     65.27417     10.81213      0.16740      0.00541      0.24615
 678.79743     60.92754     27.50102      1.33330      0.00546      0.42693
 741.21087     82.42319     24.10450      1.84422      0.00570      0.41724
 644.92464     71.74918     18.32281      1.01582      0.00546      0.30622
```

Philox_4x32_10 Generator:

```
    PK           PC           P25           JB           KS           AD
   <1058        <118         <33           <4.6         <0.0122      <.632
-------------------------------------------------------------------------

 688.73231     78.60241     18.28300      0.23786      0.00520      0.24052
 600.66650     59.78966     21.59090      4.24401      0.00464      0.49806
 916.60146     78.16294     10.01345      1.53526      0.00660      0.25025
 713.67544     61.20329     15.82239      0.79568      0.00614      0.26091
 699.84498     80.73224     16.07304      1.37786      0.00464      0.29227
```

Sobol' 32-bit generator:

```
    PK           PC           P25           JB           KS           AD
   <1058        <118         <33           <4.6         <0.0122      <.632
-------------------------------------------------------------------------

 157.04578      6.47398      1.45802      0.19007      0.00024      0.00188
 243.82767     11.98164      1.34982      0.00668      0.00030      0.00086
 229.87234     10.40206      2.73912      0.04165      0.00036      0.00137
 290.29451     17.09013      3.25717      0.02583      0.00042      0.00172
 327.32072     19.22832      5.09510      0.00335      0.00036      0.00127
```

Scrambled Sobol' 32-bit generator:

```
    PK           PC           P25           JB           KS           AD
   <1058        <118         <33           <4.6         <0.0122      <.632
-------------------------------------------------------------------------
 255.80606     10.93180      1.33766      0.01226      0.00036      0.00112
 258.84244      8.45589      1.56766      0.04164      0.00036      0.00170
 585.34346     49.33610      5.32037      0.04069      0.00043      0.00208
 337.50312     27.64720      3.38925      0.01953      0.00041      0.00211
 729.56687     56.89682     32.89772      0.00911      0.00040      0.00204
```

Even though the log-normal distribution is closely derived from the normal distribution, it has also been tested using the Pearson chi-squared test and the Kolmogorov-Smirnov test.

The following tables are representative of the test output for statistical testing of the log normal distribution for XORWOW, MRG32k3a, MTGP32, MT19937, Philox, Sobol' 32-bit, and scrambled Sobol' 32-bit generators.

XORWOW generator:

```
   PK           PC           P25           KS
   <1058        <118         <33           <0.0122
-------------------------------------------------
```

(continues on next page)

(continued from previous page)

```
1019.57936    105.63667     13.15820      0.00540
 991.93663     91.95369     20.46549      0.00900
 983.09678    115.34978     20.50434      0.00872
 966.45604    113.30013     24.54060      0.00870
 996.35262    111.50026     21.01332      0.00542
```

MRG32k3a generator:

```
    PK           PC           P25           KS
   <1058        <118         <33           <0.0122
-----------------------------------------------------

1000.00359     90.12428     22.82709      0.00826
 942.17843     81.16259     16.13670      0.00739
1005.62148    102.29924     23.62705      0.00697
1053.68391     98.75565     28.65422      0.01107
 998.38936    103.43649     19.26568      0.00803
```

MTGP32 generator:

```
    PK           PC           P25           KS
   <1058        <118         <33           <0.0122
-----------------------------------------------------

1010.18903     94.51850     17.98126      0.00771
 993.78319     76.86543     12.48859      0.00831
1010.22068     63.76027     11.65743      0.00677
 963.33103     89.44369     17.96636      0.01200
 927.15616     75.85515     13.64221      0.00566
```

MT19937 generator:

```
    PK           PC           P25           KS
   <1058        <118         <33           <0.0122
-----------------------------------------------------

 929.15309     83.63208     16.91037      0.00482
1058.79511    114.19971     27.28300      0.00541
 963.35338    103.52657     26.68634      0.00546
1009.21512    114.36706     38.44470      0.00570
 976.91303     84.83272     14.78584      0.00546
```

Philox_4x32_10 generator:

```
    PK           PC           P25           KS
   <1058        <118         <33           <0.0122
-----------------------------------------------------

 992.19843    100.39826     14.91235      0.00357
 962.03714    115.40663     18.03086      0.00595
1006.41781     92.84903     27.33686      0.00385
1009.75491     96.93654     11.99484      0.00520
1003.85449     89.00801     15.64060      0.00464
```

Sobol' 32-bit generator:

```
    PK           PC           P25           KS
   <1058        <118         <33           <0.0122
-----------------------------------------------------

 289.42589      5.03327      0.48858      0.00024
 386.79860      6.57783      0.76902      0.00030
 355.04631      8.54472      1.12228      0.00036
 434.19211      9.54021      2.07006      0.00042
 343.57507     10.71571      0.42503      0.00036
```

Scrambled Sobol- 32-bit generator:

```
   PK           PC           P25           KS
   <1058        <118         <33           <0.0122
-----------------------------------------------------

 354.55037      8.20727      0.24592      0.00036
 506.45280     12.93848      0.73323      0.00036
 451.96949     18.18903      0.69465      0.00043
 593.25666     16.55782      0.54769      0.00041
 423.05263     12.06600      0.53472      0.00040
```

Testing of the Poisson-distribution, with the each of the generators, has been done using the Pearson chi-squared test [11].

Tests are run over a broad range of lambda values, and the statistics are compared to those for Poisson distribution results using MKL.

Chapter 6. APIs

6.1. Device API

Macros

CR_CUDART_PI

CR_CUDART_TWO_TO_52

CURAND_STD

GCC_UNUSED_PARAMETER

KNUTH_FLOAT_CONST

MAGIC_DOUBLE_CONST

QUALIFIERS

Functions

__device__ float *__cr_exp*(float a)

__device__ double *__cr_lgamma_integer*(int a)

__device__ float *__cr_log*(float a)

__device__ float *__cr_pgammainc*(float a, float x)

__device__ float *__cr_pgammaincinv*(float a, float y)

__device__ float *__cr_rcp*(float a)

__device__ float *__cr_rsqrt*(float a)

__device__ int *__curand_find_trailing_zero*(unsigned long long x)

__device__ int *__curand_find_trailing_zero*(unsigned int x)

__device__ void *__curand_generate_skipahead_matrix_xor*(unsigned int matrix[])

__host__ __device__ double *__curand_ldg_war*(const double *ptr)

__host__ __device__ unsigned int *__curand_ldg_war*(const unsigned int *ptr)

__device__ unsigned long long *__curand_umad*(unsigned int a, unsigned int b, unsigned long long c)

__device__ unsigned long long *__curand_umul*(unsigned int a, unsigned int b)

__host__ double * *__get__cr_lgamma_table_host*(void)

__device__ unsigned int * *__get_mrg32k3a_matrix*(int n)

__host__ unsigned int * *__get_mrg32k3a_matrix_host*(int n)

__device__ unsigned int * *__get_precalculated_matrix*(int n)

__host__ unsigned int * *__get_precalculated_matrix_host*(int n)

__device__ unsigned int *_curand_M2_double*(T x, curandDistributionM2Shift_t distributionM2)

__device__ uint4 *_curand_M2_double4*(T x, curandDistributionM2Shift_t distributionM2)

__device__ unsigned int *_curand_binary_search_double*(T x, curandDistributionShift_t distribution)

__device__ float2 *_curand_box_muller*(unsigned int x, unsigned int y)

__device__ double2 *_curand_box_muller_double*(unsigned int x0, unsigned int x1, unsigned int y0, unsigned int y1)

__device__ unsigned int *_curand_discrete*(T x, curandDiscreteDistribution_t discrete_distribution)

__device__ void *_curand_init_inplace*(unsigned long long seed, unsigned long long subsequence, unsigned long long offset, curandStateXORWOW_t *state)

__device__ void _curand_init_scratch(unsigned long long seed, unsigned long long subsequence, unsigned long long offset, curandStateXORWOW_t *state, unsigned int *scratch)

__device__ unsigned int _curand_poisson(T x, double lambda)

__device__ unsigned int _curand_poisson_ITR_double(T x, double lambda)

__device__ unsigned int _curand_poisson_from_normal(T x, double lambda)

__device__ float _curand_uniform(unsigned long long x)

__device__ float _curand_uniform(unsigned int x)

__device__ float4 _curand_uniform4(uint4 x)

__device__ double _curand_uniform_double(unsigned int x)

__device__ double _curand_uniform_double(unsigned long long x)

__device__ double _curand_uniform_double_excluding_one(unsigned long long x)

__device__ double _curand_uniform_double_excluding_one(unsigned int x)

__device__ double _curand_uniform_double_hq(unsigned int x, unsigned int y)

__device__ void _skipahead_inplace(const unsigned long long x, T *state)

__device__ void _skipahead_scratch(unsigned long long x, T *state, unsigned int *scratch)

__device__ void _skipahead_sequence_inplace(unsigned long long x, T *state)

__device__ void _skipahead_sequence_scratch(unsigned long long x, T *state, unsigned int *scratch)

__device__ unsigned int curand(curandStateXORWOW_t *state)
Return 32-bits of pseudorandomness from an XORWOW generator.

__device__ unsigned long long curand(curandStateSobol64_t *state)
Return 64-bits of quasirandomness from a Sobol64 generator.

__device__ unsigned long long curand(curandStateScrambledSobol64_t *state)
Return 64-bits of quasirandomness from a scrambled Sobol64 generator.

__device__ unsigned int curand(curandStateTest_t *state)

__device__ unsigned int curand(curandStatePhilox4_32_10_t *state)
Return 32-bits of pseudorandomness from an Philox4_32_10 generator.

__device__ unsigned int *curand*(curandStateMRG32k3a_t *state)
Return 32-bits of pseudorandomness from an MRG32k3a generator.

__device__ unsigned int *curand*(curandStateSobol32_t *state)
Return 32-bits of quasirandomness from a Sobol32 generator.

__device__ unsigned int *curand*(curandStateScrambledSobol32_t *state)
Return 32-bits of quasirandomness from a scrambled Sobol32 generator.

__device__ unsigned int *curand*(curandStateMtgp32_t *state)
Return 32-bits of pseudorandomness from a mtgp32 generator.

__device__ uint4 *curand4*(curandStatePhilox4_32_10_t *state)
Return tuple of 4 32-bit pseudorandoms from a Philox4_32_10 generator.

__host__ curandStatus_t *curandMakeMTGP32Constants*(const mtgp32_params_fast_t params[], mtgp32_kernel_params_t *p)
Set up constant parameters for the mtgp32 generator.

__host__ curandStatus_t *curandMakeMTGP32ConstantsImpl*(const mtgp32_params_fast_t params[], ParamsType *p, const int block_num)

__host__ curandStatus_t *curandMakeMTGP32KernelState*(curandStateMtgp32_t *s, mtgp32_params_fast_t params[], mtgp32_kernel_params_t *k, int n, unsigned long long seed)
Set up initial states for the mtgp32 generator.

__device__ unsigned int *curand_M2_double*(STATE *state, curandDistributionM2Shift_t distributionM2)

__device__ uint4 *curand_M2_double4*(STATE *state, curandDistributionM2Shift_t distributionM2)

__device__ double *curand_MRG32k3a*(curandStateMRG32k3a_t *state)

__device__ unsigned int *curand__discrete*(STATE state, curandDiscreteDistribution_t discrete_distribution)

__NV_SILENCE_DEPRECATION_BEGIN __device__ uint4 *curand__discrete4*(STATE state, curandDiscreteDistribution_t discrete_distribution)

__device__ unsigned int *curand_binary_search_double*(STATE *state, curandDistributionShift_t distribution)

__device__ float2 *curand_box_muller*(R *state)

__device__ double2 *curand_box_muller2_double*(R *state)

__device__ float4 *curand_box_muller4*(R *state)

__NV_SILENCE_DEPRECATION_BEGIN __device__ double4 *curand_box_muller4_double*(R *state)

__device__ double2 *curand_box_muller_double*(R *state)

__device__ float2 *curand_box_muller_mrg*(curandStateMRG32k3a_t *state)

__device__ double2 *curand_box_muller_mrg_double*(curandStateMRG32k3a_t *state)

__device__ unsigned int *curand_discrete*(curandStatePhilox4_32_10_t *state, curandDiscreteDistribution_t discrete_distribution)

__device__ unsigned int *curand_discrete*(curandStateSobol32_t *state, curandDiscreteDistribution_t discrete_distribution)

__device__ unsigned int *curand_discrete*(curandStateMRG32k3a_t *state, curandDiscreteDistribution_t discrete_distribution)

__NV_SILENCE_DEPRECATION_END __device__ unsigned int *curand_discrete*(curandStateXORWOW_t *state, curandDiscreteDistribution_t discrete_distribution)

__device__ unsigned int *curand_discrete*(curandStateScrambledSobol64_t *state, curandDiscreteDistribution_t discrete_distribution)

__device__ unsigned int *curand_discrete*(curandStateScrambledSobol32_t *state, curandDiscreteDistribution_t discrete_distribution)

__device__ unsigned int *curand_discrete*(curandStateSobol64_t *state, curandDiscreteDistribution_t discrete_distribution)

__device__ unsigned int *curand_discrete*(curandStateMtgp32_t *state, curandDiscreteDistribution_t discrete_distribution)

__device__ uint4 *curand_discrete4*(curandStatePhilox4_32_10_t *state, curandDiscreteDistribution_t discrete_distribution)

__device__ void *curand_init*(unsigned long long seed, unsigned long long subsequence, unsigned long long offset, curandStateTest_t *state)

__device__ void *curand_init*(curandDirectionVectors64_t direction_vectors, unsigned long long scramble_c, unsigned long long offset, curandStateScrambledSobol64_t *state)
Initialize Scrambled Sobol64 state.

__device__ void *curand_init*(curandDirectionVectors64_t direction_vectors, unsigned long long offset, curandStateSobol64_t *state)
Initialize Sobol64 state.

__device__ void *curand_init*(curandDirectionVectors32_t direction_vectors, unsigned int offset, curandStateSobol32_t *state)
Initialize Sobol32 state.

__device__ void *curand_init*(unsigned long long seed, unsigned long long subsequence, unsigned long long offset, curandStateXORWOW_t *state)
Initialize XORWOW state.

__device__ void *curand_init*(unsigned long long seed, unsigned long long subsequence, unsigned long long offset, curandStatePhilox4_32_10_t *state)
Initialize Philox4_32_10 state.

__device__ void *curand_init*(unsigned long long seed, unsigned long long subsequence, unsigned long long offset, curandStateMRG32k3a_t *state)
Initialize MRG32k3a state.

__device__ void *curand_init*(curandDirectionVectors32_t direction_vectors, unsigned int scramble_c, unsigned int offset, curandStateScrambledSobol32_t *state)
Initialize Scrambled Sobol32 state.

__device__ float *curand_log_normal*(curandStateXORWOW_t *state, float mean, float stddev)
Return a log-normally distributed float from an XORWOW generator.

__device__ float *curand_log_normal*(curandStateScrambledSobol32_t *state, float mean, float stddev)
Return a log-normally distributed float from a scrambled Sobol32 generator.

__device__ float *curand_log_normal*(curandStatePhilox4_32_10_t *state, float mean, float stddev)
Return a log-normally distributed float from an Philox4_32_10 generator.

__device__ float *curand_log_normal*(curandStateScrambledSobol64_t *state, float mean, float stddev)
Return a log-normally distributed float from a scrambled Sobol64 generator.

__device__ float *curand_log_normal*(curandStateMtgp32_t *state, float mean, float stddev)
Return a log-normally distributed float from an MTGP32 generator.

__device__ float *curand_log_normal*(curandStateSobol64_t *state, float mean, float stddev)
Return a log-normally distributed float from a Sobol64 generator.

__device__ float *curand_log_normal*(curandStateSobol32_t *state, float mean, float stddev)
Return a log-normally distributed float from a Sobol32 generator.

__device__ float *curand_log_normal*(curandStateMRG32k3a_t *state, float mean, float stddev)
Return a log-normally distributed float from an MRG32k3a generator.

__device__ float2 *curand_log_normal2*(curandStateMRG32k3a_t *state, float mean, float stddev)
Return two normally distributed floats from an MRG32k3a generator.

__device__ float2 *curand_log_normal2*(curandStatePhilox4_32_10_t *state, float mean, float stddev)
Return two normally distributed floats from an Philox4_32_10 generator.

__device__ float2 *curand_log_normal2*(curandStateXORWOW_t *state, float mean, float stddev)
Return two normally distributed floats from an XORWOW generator.

__device__ double2 *curand_log_normal2_double*(curandStateMRG32k3a_t *state, double mean, double stddev)
Return two log-normally distributed doubles from an MRG32k3a generator.

__device__ double2 *curand_log_normal2_double*(curandStateXORWOW_t *state, double mean, double stddev)
Return two log-normally distributed doubles from an XORWOW generator.

__device__ double2 *curand_log_normal2_double*(curandStatePhilox4_32_10_t *state, double mean, double stddev)
Return two log-normally distributed doubles from an Philox4_32_10 generator.

__device__ float4 *curand_log_normal4*(curandStatePhilox4_32_10_t *state, float mean, float stddev)
Return four normally distributed floats from an Philox4_32_10 generator.

__NV_SILENCE_DEPRECATION_BEGIN __device__ double4 *curand_log_normal4_double*(curandStatePhilox4_32_10_ *state, double mean, double stddev)

__device__ double *curand_log_normal_double*(curandStateXORWOW_t *state, double mean, double stddev)
Return a log-normally distributed double from an XORWOW generator.

__NV_SILENCE_DEPRECATION_END __device__ double *curand_log_normal_double*(curandStateMRG32k3a_t *state, double mean, double stddev)
Return a log-normally distributed double from an MRG32k3a generator.

__device__ double *curand_log_normal_double*(curandStateMtgp32_t *state, double mean, double stddev)
Return a log-normally distributed double from an MTGP32 generator.

__device__ double *curand_log_normal_double*(curandStateSobol32_t *state, double mean, double stddev)
Return a log-normally distributed double from a Sobol32 generator.

__device__ double *curand_log_normal_double*(curandStateScrambledSobol64_t *state, double mean, double stddev)
Return a log-normally distributed double from a scrambled Sobol64 generator.

__device__ double *curand_log_normal_double*(curandStateSobol64_t *state, double mean, double stddev)
Return a log-normally distributed double from a Sobol64 generator.

__device__ double *curand_log_normal_double*(curandStateScrambledSobol32_t *state, double mean, double stddev)
Return a log-normally distributed double from a scrambled Sobol32 generator.

__device__ double *curand_log_normal_double*(curandStatePhilox4_32_10_t *state, double mean, double stddev)
Return a log-normally distributed double from an Philox4_32_10 generator.

__device__ float *curand_mtgp32_single*(curandStateMtgp32_t *state)
Return a uniformly distributed float from a mtgp32 generator.

__device__ float *curand_mtgp32_single_specific*(curandStateMtgp32_t *state, unsigned char index, unsigned char n)
Return a uniformly distributed float from a specific position in a mtgp32 generator.

__device__ unsigned int *curand_mtgp32_specific*(curandStateMtgp32_t *state, unsigned char index, unsigned char n)
Return 32-bits of pseudorandomness from a specific position in a mtgp32 generator.

__device__ float *curand_normal*(curandStateScrambledSobol32_t *state)
Return a normally distributed float from a scrambled Sobol32 generator.

__device__ float *curand_normal*(curandStateScrambledSobol64_t *state)
Return a normally distributed float from a scrambled Sobol64 generator.

__device__ float *curand_normal*(curandStateMRG32k3a_t *state)
Return a normally distributed float from an MRG32k3a generator.

__NV_SILENCE_DEPRECATION_END __device__ float *curand_normal*(curandStateXORWOW_t *state)
Return a normally distributed float from an XORWOW generator.

__device__ float *curand_normal*(curandStateSobol64_t *state)
Return a normally distributed float from a Sobol64 generator.

__device__ float *curand_normal*(curandStateMtgp32_t *state)
Return a normally distributed float from a MTGP32 generator.

__device__ float *curand_normal*(curandStatePhilox4_32_10_t *state)
Return a normally distributed float from an Philox4_32_10 generator.

__device__ float *curand_normal*(curandStateSobol32_t *state)
Return a normally distributed float from a Sobol32 generator.

__device__ float2 *curand_normal2*(curandStatePhilox4_32_10_t *state)
Return two normally distributed floats from an Philox4_32_10 generator.

__device__ float2 *curand_normal2*(curandStateXORWOW_t *state)
Return two normally distributed floats from an XORWOW generator.

__device__ float2 *curand_normal2*(curandStateMRG32k3a_t *state)
Return two normally distributed floats from an MRG32k3a generator.

__NV_SILENCE_DEPRECATION_END __device__ double2 *curand_normal2_double*(curandStateMRG32k3a_t *state)
Return two normally distributed doubles from an MRG32k3a generator.

__device__ double2 *curand_normal2_double*(curandStateXORWOW_t *state)
Return two normally distributed doubles from an XORWOW generator.

__device__ double2 *curand_normal2_double*(curandStatePhilox4_32_10_t *state)
Return two normally distributed doubles from an Philox4_32_10 generator.

__device__ float4 *curand_normal4*(curandStatePhilox4_32_10_t *state)
Return four normally distributed floats from an Philox4_32_10 generator.

__NV_SILENCE_DEPRECATION_BEGIN __device__ double4 *curand_normal4_double*(curandStatePhilox4_32_10_t *state)

__device__ double *curand_normal_double*(curandStateSobol64_t *state)
Return a normally distributed double from a Sobol64 generator.

__device__ double *curand_normal_double*(curandStateMRG32k3a_t *state)
Return a normally distributed double from an MRG32k3a generator.

__device__ double *curand_normal_double*(curandStateMtgp32_t *state)
Return a normally distributed double from an MTGP32 generator.

__device__ double *curand_normal_double*(curandStateScrambledSobol64_t *state)
Return a normally distributed double from a scrambled Sobol64 generator.

__device__ double *curand_normal_double*(curandStatePhilox4_32_10_t *state)
Return a normally distributed double from an Philox4_32_10 generator.

__device__ double *curand_normal_double*(curandStateScrambledSobol32_t *state)
Return a normally distributed double from a scrambled Sobol32 generator.

__device__ double *curand_normal_double*(curandStateXORWOW_t *state)
Return a normally distributed double from an XORWOW generator.

__device__ double *curand_normal_double*(curandStateSobol32_t *state)
Return a normally distributed double from an Sobol32 generator.

__device__ unsigned int *curand_poisson*(curandStateSobol64_t *state, double lambda)
Return a Poisson-distributed unsigned int from a Sobol64 generator.

__device__ unsigned int *curand_poisson*(curandStateScrambledSobol32_t *state, double lambda)
Return a Poisson-distributed unsigned int from a scrambled Sobol32 generator.

__device__ unsigned int *curand_poisson*(curandStateMtgp32_t *state, double lambda)
Return a Poisson-distributed unsigned int from a MTGP32 generator.

__device__ unsigned int *curand_poisson*(curandStateScrambledSobol64_t *state, double lambda)
Return a Poisson-distributed unsigned int from a scrambled Sobol64 generator.

__device__ unsigned int *curand_poisson*(curandStateSobol32_t *state, double lambda)
Return a Poisson-distributed unsigned int from a Sobol32 generator.

__device__ unsigned int *curand_poisson*(curandStatePhilox4_32_10_t *state, double lambda)
Return a Poisson-distributed unsigned int from a Philox4_32_10 generator.

__device__ unsigned int *curand_poisson*(curandStateXORWOW_t *state, double lambda)
Return a Poisson-distributed unsigned int from a XORWOW generator.

__device__ unsigned int *curand_poisson*(curandStateMRG32k3a_t *state, double lambda)
Return a Poisson-distributed unsigned int from a MRG32k3A generator.

__device__ uint4 *curand_poisson4*(curandStatePhilox4_32_10_t *state, double lambda)
Return four Poisson-distributed unsigned ints from a Philox4_32_10 generator.

__device__ unsigned int *curand_poisson_from_normal*(STATE state, double lambda)

__device__ uint4 *curand_poisson_from_normal4*(STATE state, double lambda)

__device__ unsigned int *curand_poisson_gammainc*(T state, float lambda)

__device__ uint4 *curand_poisson_gammainc4*(T state, float lambda)

__device__ unsigned int *curand_poisson_knuth*(T *state, float lambda)

__device__ uint4 *curand_poisson_knuth4*(T *state, float lambda)

__device__ float *curand_uniform*(curandStateMtgp32_t *state)
Return a uniformly distributed float from a MTGP32 generator.

__device__ float *curand_uniform*(curandStateTest_t *state)

__device__ float *curand_uniform*(curandStateSobol32_t *state)
Return a uniformly distributed float from a Sobol32 generator.

__device__ float *curand_uniform*(curandStateScrambledSobol64_t *state)
Return a uniformly distributed float from a scrambled Sobol64 generator.

__NV_SILENCE_DEPRECATION_END __device__ float *curand_uniform*(curandStatePhilox4_32_10_t *state)
Return a uniformly distributed float from a Philox4_32_10 generator.

__device__ float *curand_uniform*(curandStateScrambledSobol32_t *state)
Return a uniformly distributed float from a scrambled Sobol32 generator.

__device__ float *curand_uniform*(curandStateSobol64_t *state)
Return a uniformly distributed float from a Sobol64 generator.

__device__ float *curand_uniform*(curandStateMRG32k3a_t *state)
Return a uniformly distributed float from an MRG32k3a generator.

__device__ float *curand_uniform*(curandStateXORWOW_t *state)
Return a uniformly distributed float from an XORWOW generator.

__device__ double2 *curand_uniform2_double*(curandStatePhilox4_32_10_t *state)
Return a uniformly distributed tuple of 2 doubles from an Philox4_32_10 generator.

__device__ float4 *curand_uniform4*(curandStatePhilox4_32_10_t *state)
Return a uniformly distributed tuple of 4 floats from a Philox4_32_10 generator.

__NV_SILENCE_DEPRECATION_BEGIN __device__ double4 *curand_uniform4_double*(curandStatePhilox4_32_10_t *state)

__device__ double *curand_uniform_double*(curandStateScrambledSobol32_t *state)
Return a uniformly distributed double from a scrambled Sobol32 generator.

__device__ double *curand_uniform_double*(curandStateScrambledSobol64_t *state)
Return a uniformly distributed double from a scrambled Sobol64 generator.

__device__ double *curand_uniform_double*(curandStateMtgp32_t *state)
Return a uniformly distributed double from a MTGP32 generator.

__device__ double *curand_uniform_double*(curandStatePhilox4_32_10_t *state)
Return a uniformly distributed double from a Philox4_32_10 generator.

__device__ double *curand_uniform_double*(curandStateMRG32k3a_t *state)
Return a uniformly distributed double from an MRG32k3a generator.

__device__ double *curand_uniform_double*(curandStateTest_t *state)

__device__ double *curand_uniform_double*(curandStateSobol32_t *state)
Return a uniformly distributed double from a Sobol32 generator.

__device__ double *curand_uniform_double*(curandStateSobol64_t *state)
Return a uniformly distributed double from a Sobol64 generator.

__device__ double *curand_uniform_double*(curandStateXORWOW_t *state)
Return a uniformly distributed double from an XORWOW generator.

unsigned int *ini_func1*(unsigned int x)

unsigned int *ini_func2*(unsigned int x)

__host__ int *mtgp32_init_by_array*(unsigned int state[], const mtgp32_params_fast_t *para, unsigned int *array, int length)

__host__ int *mtgp32_init_by_str*(unsigned int state[], const mtgp32_params_fast_t *para, unsigned char *array)

__host__ void *mtgp32_init_state*(unsigned int state[], const mtgp32_params_fast_t *para, unsigned int seed)

__device__ unsigned int *para_rec*(mtgp32_kernel_params_t *k, unsigned int X1, unsigned int X2, unsigned int Y, int bid)

__device__ void *skipahead*(unsigned long long n, curandStateMRG32k3a_t *state)
Update MRG32k3a state to skip n elements.

__device__ curand_detail::enable_if< curand_detail::is_same< curandStateSobol64_t *, T >::value||curand_detail::is_same< curandStateScrambledSobol64_t *, T >::value >::type *skipahead*(unsigned long long n, T state)
Update Sobol64 state to skip n elements.

__device__ void *skipahead*(unsigned long long n, curandStateXORWOW_t *state)
Update XORWOW state to skip n elements.

__device__ void *skipahead*(unsigned long long n, curandStateTest_t *state)

__device__ curand_detail::enable_if< curand_detail::is_same< curandStateSobol32_t *, T >::value||curand_detail::is_same< curandStateScrambledSobol32_t *, T >::value >::type *skipahead*(unsigned int n, T state)
Update Sobol32 state to skip n elements.

__device__ void *skipahead*(unsigned long long n, curandStatePhilox4_32_10_t *state)
Update Philox4_32_10 state to skip n elements.

__device__ void *skipahead_sequence*(unsigned long long n, curandStateMRG32k3a_t *state)
Update MRG32k3a state to skip ahead n sequences.

__device__ void *skipahead_sequence*(unsigned long long n, curandStatePhilox4_32_10_t *state)
Update Philox4_32_10 state to skip ahead n subsequences.

__device__ void *skipahead_sequence*(unsigned long long n, curandStateXORWOW_t *state)
Update XORWOW state to skip ahead n subsequences.

__device__ void *skipahead_subsequence*(unsigned long long n, curandStateMRG32k3a_t *state)
Update MRG32k3a state to skip ahead n subsequences.

__device__ unsigned int *temper*(mtgp32_kernel_params_t *k, unsigned int V, unsigned int T, int bid)

__device__ unsigned int *temper_single*(mtgp32_kernel_params_t *k, unsigned int V, unsigned int T, int bid)

Namespaces

curand_detail

Structs

curandStateMRG32k3a

curandStateMtgp32

curandStateScrambledSobol32

curandStateScrambledSobol64

curandStateSobol32

curandStateSobol64

curandStateTest

curandStateXORWOW

mtgp32_kernel_params

mtgp32_params_fast

Variables

__constant__ double *__cr_lgamma_table*

const dim3 *blockDim*

const unsigned int *non_zero*

const uint3 *threadIdx*

6.1.1. Macros

CR_CUDART_PI 3.1415926535897931e+0

CR_CUDART_TWO_TO_52 4503599627370496.0

CURAND_STD curand_detail

GCC_UNUSED_PARAMETER

KNUTH_FLOAT_CONST 60.0

MAGIC_DOUBLE_CONST 500.0

QUALIFIERS static __device__

6.1.2. Functions

__device__ static float **__cr_exp**(float a)

__device__ static double **__cr_lgamma_integer**(int a)

__device__ static float **__cr_log**(float a)

__device__ static float **__cr_pgammainc**(float a, float x)

__device__ static float **__cr_pgammaincinv**(float a, float y)

__device__ static float **__cr_rcp**(float a)

__device__ static float **__cr_rsqrt**(float a)

__device__ static int **__curand_find_trailing_zero**(unsigned long long x)

__device__ static int **__curand_find_trailing_zero**(unsigned int x)

template<typename **T**, int **n**>
__device__ static void **__curand_generate_skipahead_matrix_xor**(unsigned int matrix[])

__host__ __device__ static double **__curand_ldg_war**(const double *ptr)

__host__ __device__ static unsigned int **__curand_ldg_war**(const unsigned int *ptr)

__device__ static unsigned long long **__curand_umad**(unsigned int a, unsigned int b, unsigned long long c)

__device__ static unsigned long long **__curand_umul**(unsigned int a, unsigned int b)

__host__ static inline double ***__get__cr_lgamma_table_host**(void)

__device__ static inline unsigned int ***__get_mrg32k3a_matrix**(int n)

__host__ static inline unsigned int ***__get_mrg32k3a_matrix_host**(int n)

__device__ static inline unsigned int ***__get_precalculated_matrix**(int n)

__host__ static inline unsigned int ***__get_precalculated_matrix_host**(int n)

template<typename **T**>
__device__ static unsigned int **_curand_M2_double**(*T* x, curandDistributionM2Shift_t distributionM2)

template<typename **T**>

__device__ static uint4 **_curand_M2_double4**(*T* x, curandDistributionM2Shift_t distributionM2)

template<typename **T**>
__device__ static unsigned int **_curand_binary_search_double**(*T* x, curandDistributionShift_t distribution)

__device__ static float2 **_curand_box_muller**(unsigned int x, unsigned int y)

__device__ static double2 **_curand_box_muller_double**(unsigned int x0, unsigned int x1, unsigned int y0, unsigned int y1)

template<typename **T**>
__device__ static unsigned int **_curand_discrete**(*T* x, curandDiscreteDistribution_t discrete_distribution)

__device__ static void **_curand_init_inplace**(unsigned long long seed, unsigned long long subsequence, unsigned long long offset, curandStateXORWOW_t *state)

__device__ static void **_curand_init_scratch**(unsigned long long seed, unsigned long long subsequence, unsigned long long offset, curandStateXORWOW_t *state, unsigned int *scratch)

template<typename **T**>
__device__ static unsigned int **_curand_poisson**(*T* x, double lambda)

template<typename **T**>
__device__ static unsigned int **_curand_poisson_ITR_double**(*T* x, double lambda)

template<typename **T**>
__device__ static unsigned int **_curand_poisson_from_normal**(*T* x, double lambda)

__device__ static float **_curand_uniform**(unsigned long long x)

__device__ static float **_curand_uniform**(unsigned int x)

__device__ static float4 **_curand_uniform4**(uint4 x)

__device__ static double **_curand_uniform_double**(unsigned int x)

__device__ static double **_curand_uniform_double**(unsigned long long x)

__device__ static double **_curand_uniform_double_excluding_one**(unsigned long long x)

__device__ static double **_curand_uniform_double_excluding_one**(unsigned int x)

__device__ static double **_curand_uniform_double_hq**(unsigned int x, unsigned int y)

template<typename **T**, int **N**>
__device__ static void **_skipahead_inplace**(const unsigned long long x, *T* *state)

template<typename **T**, int **n**>
__device__ static void **_skipahead_scratch**(unsigned long long x, *T* *state, unsigned int *scratch)

template<typename **T**, int **N**>
__device__ static void **_skipahead_sequence_inplace**(unsigned long long x, *T* *state)

template<typename **T**, int **n**>

__device__ static void **_skipahead_sequence_scratch**(unsigned long long x, *T* *state, unsigned int *scratch)

__device__ static unsigned int **curand**(curandStateXORWOW_t *state)

Return 32-bits of pseudorandomness from an XORWOW generator.

Return 32-bits of pseudorandomness from the XORWOW generator in `state`, increment position of generator by one.

Parameters
state – - Pointer to state to update

Returns
32-bits of pseudorandomness as an unsigned int, all bits valid to use.

__device__ static unsigned long long **curand**(curandStateSobol64_t *state)

Return 64-bits of quasirandomness from a Sobol64 generator.

Return 64-bits of quasirandomness from the Sobol64 generator in `state`, increment position of generator by one.

Parameters
state – - Pointer to state to update

Returns
64-bits of quasirandomness as an unsigned long long, all bits valid to use.

__device__ static unsigned long long **curand**(curandStateScrambledSobol64_t *state)

Return 64-bits of quasirandomness from a scrambled Sobol64 generator.

Return 64-bits of quasirandomness from the scrambled Sobol32 generator in `state`, increment position of generator by one.

Parameters
state – - Pointer to state to update

Returns
64-bits of quasirandomness as an unsigned long long, all bits valid to use.

__device__ static unsigned int **curand**(curandStateTest_t *state)

__device__ static unsigned int **curand**(curandStatePhilox4_32_10_t *state)

Return 32-bits of pseudorandomness from an Philox4_32_10 generator.

Return 32-bits of pseudorandomness from the Philox4_32_10 generator in `state`, increment position of generator by one.

Parameters
state – - Pointer to state to update

Returns
32-bits of pseudorandomness as an unsigned int, all bits valid to use.

__device__ static unsigned int **curand**(curandStateMRG32k3a_t *state)

Return 32-bits of pseudorandomness from an MRG32k3a generator.

Return 32-bits of pseudorandomness from the MRG32k3a generator in `state`, increment position of generator by one.

Parameters
state – - Pointer to state to update

Returns
32-bits of pseudorandomness as an unsigned int, all bits valid to use.

__device__ static unsigned int **curand**(curandStateSobol32_t *state)

Return 32-bits of quasirandomness from a Sobol32 generator.

Return 32-bits of quasirandomness from the Sobol32 generator in `state`, increment position of generator by one.

Parameters
state – - Pointer to state to update

Returns
32-bits of quasirandomness as an unsigned int, all bits valid to use.

__device__ static unsigned int **curand**(curandStateScrambledSobol32_t *state)

Return 32-bits of quasirandomness from a scrambled Sobol32 generator.

Return 32-bits of quasirandomness from the scrambled Sobol32 generator in `state`, increment position of generator by one.

Parameters
state – - Pointer to state to update

Returns
32-bits of quasirandomness as an unsigned int, all bits valid to use.

__device__ static unsigned int **curand**(curandStateMtgp32_t *state)

Return 32-bits of pseudorandomness from a mtgp32 generator.

Return 32-bits of pseudorandomness from the mtgp32 generator in `state`, increment position of generator by the number of threads in the block. Note the number of threads in the block can not exceed 256.

Parameters
state – - Pointer to state to update

Returns
32-bits of pseudorandomness as an unsigned int, all bits valid to use.

__device__ static uint4 **curand4**(curandStatePhilox4_32_10_t *state)

Return tuple of 4 32-bit pseudorandoms from a Philox4_32_10 generator.

Return 128 bits of pseudorandomness from the Philox4_32_10 generator in `state`, increment position of generator by four.

Parameters
state – - Pointer to state to update

Returns
128-bits of pseudorandomness as a uint4, all bits valid to use.

__host__ static curandStatus_t **curandMakeMTGP32Constants**(const mtgp32_params_fast_t params[], mtgp32_kernel_params_t *p)

Set up constant parameters for the mtgp32 generator.

This host-side helper function re-organizes CURAND_NUM_MTGP32_PARAMS sets of generator parameters for use by kernel functions and copies the result to the specified location in device memory.

Parameters

- **params** – - Pointer to an array of type mtgp32_params_fast_t in host memory
- **p** – - pointer to a structure of type mtgp32_kernel_params_t in device memory.

Returns

- CURAND_STATUS_ALLOCATION_FAILED if host memory could not be allocated
- CURAND_STATUS_INITIALIZATION_FAILED if the copy to device memory failed
- CURAND_STATUS_SUCCESS otherwise

template<typename **ParamsType**>
__host__ static curandStatus_t **curandMakeMTGP32ConstantsImpl**(const mtgp32_params_fast_t params[], *ParamsType* *p, const int block_num)

__host__ static curandStatus_t **curandMakeMTGP32KernelState**(curandStateMtgp32_t *s, mtgp32_params_fast_t params[], mtgp32_kernel_params_t *k, int n, unsigned long long seed)

Set up initial states for the mtgp32 generator.

This host-side helper function initializes a number of states (one parameter set per state) for an mtgp32 generator. To accomplish this it allocates a state array in host memory, initializes that array, and copies the result to device memory.

Parameters

- **s** – - pointer to an array of states in device memory
- **params** – - Pointer to an array of type mtgp32_params_fast_t in host memory
- **k** – - pointer to a structure of type mtgp32_kernel_params_t in device memory
- **n** – - number of parameter sets/states to initialize
- **seed** – - seed value

Returns

- CURAND_STATUS_ALLOCATION_FAILED if host memory state could not be allocated
- CURAND_STATUS_INITIALIZATION_FAILED if the copy to device memory failed
- CURAND_STATUS_SUCCESS otherwise

template<typename **STATE**>
__device__ static unsigned int **curand_M2_double**(*STATE* *state, curandDistributionM2Shift_t distributionM2)

template<typename **STATE**>
__device__ static uint4 **curand_M2_double4**(*STATE* *state, curandDistributionM2Shift_t distributionM2)

__device__ static double **curand_MRG32k3a**(curandStateMRG32k3a_t *state)

template<typename **STATE**>
__device__ static unsigned int **curand__discrete**(*STATE* state, curandDiscreteDistribution_t discrete_distribution)

template<typename **STATE**>
__NV_SILENCE_DEPRECATION_BEGIN __device__ static uint4 **curand__discrete4**(*STATE* state, curandDiscrete-Distribution_t dis-crete_distribution)

template<typename **STATE**>
__device__ static unsigned int **curand_binary_search_double**(*STATE* *state, curandDistributionShift_t distribution)

template<typename **R**>
__device__ static float2 **curand_box_muller**(*R* *state)

template<typename **R**>
__device__ static double2 **curand_box_muller2_double**(*R* *state)

template<typename **R**>
__device__ static float4 **curand_box_muller4**(*R* *state)

template<typename **R**>
__NV_SILENCE_DEPRECATION_BEGIN __device__ static double4 **curand_box_muller4_double**(*R* *state)

template<typename **R**>
__device__ static double2 **curand_box_muller_double**(*R* *state)

__device__ static float2 **curand_box_muller_mrg**(curandStateMRG32k3a_t *state)

__device__ static double2 **curand_box_muller_mrg_double**(curandStateMRG32k3a_t *state)

__device__ static unsigned int **curand_discrete**(curandStatePhilox4_32_10_t *state, curandDiscreteDistribution_t discrete_distribution)

__device__ static unsigned int **curand_discrete**(curandStateSobol32_t *state, curandDiscreteDistribution_t discrete_distribution)

__device__ static unsigned int **curand_discrete**(curandStateMRG32k3a_t *state, curandDiscreteDistribution_t discrete_distribution)

__NV_SILENCE_DEPRECATION_END __device__ static unsigned int **curand_discrete**(curandStateXORWOW_t *state, curandDis-creteDistri-bution_t dis-crete_distribution)

__device__ static unsigned int **curand_discrete**(curandStateScrambledSobol64_t *state, curandDiscreteDistribution_t discrete_distribution)

__device__ static unsigned int **curand_discrete**(curandStateScrambledSobol32_t *state, curandDiscreteDistribution_t discrete_distribution)

__device__ static unsigned int **curand_discrete**(curandStateSobol64_t *state, curandDiscreteDistribution_t discrete_distribution)

__device__ static unsigned int **curand_discrete**(curandStateMtgp32_t *state, curandDiscreteDistribution_t discrete_distribution)

__device__ static uint4 **curand_discrete4**(curandStatePhilox4_32_10_t *state, curandDiscreteDistribution_t discrete_distribution)

__device__ static void **curand_init**(unsigned long long seed, unsigned long long subsequence, unsigned long long offset, curandStateTest_t *state)

__device__ static void **curand_init**(curandDirectionVectors64_t direction_vectors, unsigned long long scramble_c, unsigned long long offset, curandStateScrambledSobol64_t *state)

Initialize Scrambled Sobol64 state.

Initialize Sobol64 state in `state` with the given `direction vectors` and `offset`.

The direction vector is a device pointer to an array of 64 unsigned long longs. All input values of `offset` are legal.

Parameters

- **direction_vectors** – - Pointer to array of 64 unsigned long longs representing the direction vectors for the desired dimension
- **scramble_c** – Scramble constant
- **offset** – - Absolute offset into sequence
- **state** – - Pointer to state to initialize

__device__ static void **curand_init**(curandDirectionVectors64_t direction_vectors, unsigned long long offset, curandStateSobol64_t *state)

Initialize Sobol64 state.

Initialize Sobol64 state in `state` with the given `direction vectors` and `offset`.

The direction vector is a device pointer to an array of 64 unsigned long longs. All input values of `offset` are legal.

Parameters

- **direction_vectors** – - Pointer to array of 64 unsigned long longs representing the direction vectors for the desired dimension
- **offset** – - Absolute offset into sequence

- **state** – - Pointer to state to initialize

__device__ static void **curand_init**(curandDirectionVectors32_t direction_vectors, unsigned int offset, curandStateSobol32_t *state)

Initialize Sobol32 state.

Initialize Sobol32 state in `state` with the given `direction vectors` and `offset`.

The direction vector is a device pointer to an array of 32 unsigned ints. All input values of `offset` are legal.

Parameters

- **direction_vectors** – - Pointer to array of 32 unsigned ints representing the direction vectors for the desired dimension
- **offset** – - Absolute offset into sequence
- **state** – - Pointer to state to initialize

__device__ static void **curand_init**(unsigned long long seed, unsigned long long subsequence, unsigned long long offset, curandStateXORWOW_t *state)

Initialize XORWOW state.

Initialize XORWOW state in `state` with the given `seed`, `subsequence`, and `offset`.

All input values of `seed`, `subsequence`, and `offset` are legal. Large values for `subsequence` and `offset` require more computation and so will take more time to complete.

A value of 0 for `seed` sets the state to the values of the original published version of the `xorwow` algorithm.

Parameters

- **seed** – - Arbitrary bits to use as a seed
- **subsequence** – - Subsequence to start at
- **offset** – - Absolute offset into sequence
- **state** – - Pointer to state to initialize

__device__ static void **curand_init**(unsigned long long seed, unsigned long long subsequence, unsigned long long offset, curandStatePhilox4_32_10_t *state)

Initialize Philox4_32_10 state.

Initialize Philox4_32_10 state in `state` with the given `seed`, p\ subsequence, and `offset`.

All input values for `seed`, `subseqence` and `offset` are legal. Each of the possible values of seed selects an independent sequence of length . The first . values of the sequence are skipped. I.e., subsequences are of length .

Parameters

- **seed** – - Arbitrary bits to use as a seed
- **subsequence** – - Subsequence to start at
- **offset** – - Absolute offset into subsequence
- **state** – - Pointer to state to initialize

__device__ static void **curand_init**(unsigned long long seed, unsigned long long subsequence, unsigned long long offset, curandStateMRG32k3a_t *state)

Initialize MRG32k3a state.

Initialize MRG32k3a state in `state` with the given `seed`, `subsequence`, and `offset`.

All input values of `seed`, `subsequence`, and `offset` are legal. `subsequence` will be truncated to 51 bits to avoid running into the next sequence

A value of 0 for `seed` sets the state to the values of the original published version of the `MRG32k3a` algorithm.

Parameters

- **seed** – - Arbitrary bits to use as a seed
- **subsequence** – - Subsequence to start at
- **offset** – - Absolute offset into sequence
- **state** – - Pointer to state to initialize

__device__ static void **curand_init**(curandDirectionVectors32_t direction_vectors, unsigned int scramble_c, unsigned int offset, curandStateScrambledSobol32_t *state)

Initialize Scrambled Sobol32 state.

Initialize Sobol32 state in `state` with the given `direction vectors` and `offset`.

The direction vector is a device pointer to an array of 32 unsigned ints. All input values of `offset` are legal.

Parameters

- **direction_vectors** – - Pointer to array of 32 unsigned ints representing the direction vectors for the desired dimension
- **scramble_c** – Scramble constant
- **offset** – - Absolute offset into sequence
- **state** – - Pointer to state to initialize

__device__ static float **curand_log_normal**(curandStateXORWOW_t *state, float mean, float stddev)

Return a log-normally distributed float from an XORWOW generator.

Return a single log-normally distributed float derived from a normal distribution with mean `mean` and standard deviation `stddev` from the XORWOW generator in `state`, increment position of generator by one.

The implementation uses a Box-Muller transform to generate two normally distributed results, transforms them to log-normal distribution, then returns them one at a time. See curand_log_normal2() for a more efficient version that returns both results at once.

Parameters

- **state** – - Pointer to state to update
- **mean** – - Mean of the related normal distribution

- **stddev** – - Standard deviation of the related normal distribution

Returns
Log-normally distributed float with mean `mean` and standard deviation `stddev`

__device__ static float **curand_log_normal**(curandStateScrambledSobol32_t *state, float mean, float stddev)

Return a log-normally distributed float from a scrambled Sobol32 generator.

Return a single log-normally distributed float derived from a normal distribution with mean `mean` and standard deviation `stddev` from the scrambled Sobol32 generator in `state`, increment position of generator by one.

The implementation uses the inverse cumulative distribution function to generate a normally distributed result, then transforms the result to log-normal.

Parameters

- **state** – - Pointer to state to update
- **mean** – - Mean of the related normal distribution
- **stddev** – - Standard deviation of the related normal distribution

Returns
Log-normally distributed float with mean `mean` and standard deviation `stddev`

__device__ static float **curand_log_normal**(curandStatePhilox4_32_10_t *state, float mean, float stddev)

Return a log-normally distributed float from an Philox4_32_10 generator.

Return a single log-normally distributed float derived from a normal distribution with mean `mean` and standard deviation `stddev` from the Philox4_32_10 generator in `state`, increment position of generator by one.

The implementation uses a Box-Muller transform to generate two normally distributed results, transforms them to log-normal distribution, then returns them one at a time. See curand_log_normal2() for a more efficient version that returns both results at once.

Parameters

- **state** – - Pointer to state to update
- **mean** – - Mean of the related normal distribution
- **stddev** – - Standard deviation of the related normal distribution

Returns
Log-normally distributed float with mean `mean` and standard deviation `stddev`

__device__ static float **curand_log_normal**(curandStateScrambledSobol64_t *state, float mean, float stddev)

Return a log-normally distributed float from a scrambled Sobol64 generator.

Return a single log-normally distributed float derived from a normal distribution with mean `mean` and standard deviation `stddev` from the scrambled Sobol64 generator in `state`, increment position of generator by one.

The implementation uses the inverse cumulative distribution function to generate normally distributed results, then converts to log-normal distribution.

Parameters

- **state** – - Pointer to state to update
- **mean** – - Mean of the related normal distribution
- **stddev** – - Standard deviation of the related normal distribution

Returns
Log-normally distributed float with mean `mean` and standard deviation `stddev`

__device__ static float **curand_log_normal**(curandStateMtgp32_t *state, float mean, float stddev)

Return a log-normally distributed float from an MTGP32 generator.

Return a single log-normally distributed float derived from a normal distribution with mean `mean` and standard deviation `stddev` from the MTGP32 generator in `state`, increment position of generator.

The implementation uses the inverse cumulative distribution function to generate a normally distributed result, then transforms the result to log-normal.

Parameters

- **state** – - Pointer to state to update
- **mean** – - Mean of the related normal distribution
- **stddev** – - Standard deviation of the related normal distribution

Returns
Log-normally distributed float with mean `mean` and standard deviation `stddev`

__device__ static float **curand_log_normal**(curandStateSobol64_t *state, float mean, float stddev)

Return a log-normally distributed float from a Sobol64 generator.

Return a single log-normally distributed float derived from a normal distribution with mean `mean` and standard deviation `stddev` from the Sobol64 generator in `state`, increment position of generator by one.

The implementation uses the inverse cumulative distribution function to generate normally distributed results, then converts to log-normal distribution.

Parameters

- **state** – - Pointer to state to update
- **mean** – - Mean of the related normal distribution
- **stddev** – - Standard deviation of the related normal distribution

Returns
Log-normally distributed float with mean `mean` and standard deviation `stddev`

__device__ static float **curand_log_normal**(curandStateSobol32_t *state, float mean, float stddev)

Return a log-normally distributed float from a Sobol32 generator.

Return a single log-normally distributed float derived from a normal distribution with mean `mean` and standard deviation `stddev` from the Sobol32 generator in `state`, increment position of generator by one.

The implementation uses the inverse cumulative distribution function to generate a normally distributed result, then transforms the result to log-normal.

Parameters

- **`state`** – - Pointer to state to update
- **`mean`** – - Mean of the related normal distribution
- **`stddev`** – - Standard deviation of the related normal distribution

Returns

Log-normally distributed float with mean `mean` and standard deviation `stddev`

__device__ static float **`curand_log_normal`**(curandStateMRG32k3a_t *state, float mean, float stddev)

Return a log-normally distributed float from an MRG32k3a generator.

Return a single log-normally distributed float derived from a normal distribution with mean `mean` and standard deviation `stddev` from the MRG32k3a generator in `state`, increment position of generator by one.

The implementation uses a Box-Muller transform to generate two normally distributed results, transforms them to log-normal distribution, then returns them one at a time. See curand_log_normal2() for a more efficient version that returns both results at once.

Parameters

- **`state`** – - Pointer to state to update
- **`mean`** – - Mean of the related normal distribution
- **`stddev`** – - Standard deviation of the related normal distribution

Returns

Log-normally distributed float with mean `mean` and standard deviation `stddev`

__device__ static float2 **`curand_log_normal2`**(curandStateMRG32k3a_t *state, float mean, float stddev)

Return two normally distributed floats from an MRG32k3a generator.

Return two log-normally distributed floats derived from a normal distribution with mean `mean` and standard deviation `stddev` from the MRG32k3a generator in `state`, increment position of generator by two.

The implementation uses a Box-Muller transform to generate two normally distributed results, then transforms them to log-normal.

Parameters

- **`state`** – - Pointer to state to update
- **`mean`** – - Mean of the related normal distribution
- **`stddev`** – - Standard deviation of the related normal distribution

Returns

Log-normally distributed float2 where each element is from a distribution with mean `mean` and standard deviation `stddev`

__device__ static float2 **`curand_log_normal2`**(curandStatePhilox4_32_10_t *state, float mean, float stddev)

Return two normally distributed floats from an Philox4_32_10 generator.

Return two log-normally distributed floats derived from a normal distribution with mean `mean` and standard deviation `stddev` from the Philox4_32_10 generator in `state`, increment position of generator by two.

The implementation uses a Box-Muller transform to generate two normally distributed results, then transforms them to log-normal.

Parameters

- **`state`** – - Pointer to state to update
- **`mean`** – - Mean of the related normal distribution
- **`stddev`** – - Standard deviation of the related normal distribution

Returns

Log-normally distributed float2 where each element is from a distribution with mean `mean` and standard deviation `stddev`

__device__ static float2 **`curand_log_normal2`**(curandStateXORWOW_t *state, float mean, float stddev)

Return two normally distributed floats from an XORWOW generator.

Return two log-normally distributed floats derived from a normal distribution with mean `mean` and standard deviation `stddev` from the XORWOW generator in `state`, increment position of generator by two.

The implementation uses a Box-Muller transform to generate two normally distributed results, then transforms them to log-normal.

Parameters

- **`state`** – - Pointer to state to update
- **`mean`** – - Mean of the related normal distribution
- **`stddev`** – - Standard deviation of the related normal distribution

Returns

Log-normally distributed float2 where each element is from a distribution with mean `mean` and standard deviation `stddev`

__device__ static double2 **`curand_log_normal2_double`**(curandStateMRG32k3a_t *state, double mean, double stddev)

Return two log-normally distributed doubles from an MRG32k3a generator.

Return two log-normally distributed doubles derived from a normal distribution with mean `mean` and standard deviation `stddev` from the MRG32k3a generator in `state`, increment position of generator by two.

The implementation uses a Box-Muller transform to generate two normally distributed results, and transforms them to log-normal distribution,.

Parameters

- **state** – - Pointer to state to update
- **mean** – - Mean of the related normal distribution
- **stddev** – - Standard deviation of the related normal distribution

Returns
Log-normally distributed double2 where each element is from a distribution with mean `mean` and standard deviation `stddev`

__device__ static double2 **curand_log_normal2_double**(curandStateXORWOW_t *state, double mean, double stddev)

Return two log-normally distributed doubles from an XORWOW generator.

Return two log-normally distributed doubles derived from a normal distribution with mean `mean` and standard deviation `stddev` from the XORWOW generator in `state`, increment position of generator by two.

The implementation uses a Box-Muller transform to generate two normally distributed results, and transforms them to log-normal distribution,.

Parameters

- **state** – - Pointer to state to update
- **mean** – - Mean of the related normal distribution
- **stddev** – - Standard deviation of the related normal distribution

Returns
Log-normally distributed double2 where each element is from a distribution with mean `mean` and standard deviation `stddev`

__device__ static double2 **curand_log_normal2_double**(curandStatePhilox4_32_10_t *state, double mean, double stddev)

Return two log-normally distributed doubles from an Philox4_32_10 generator.

Return two log-normally distributed doubles derived from a normal distribution with mean `mean` and standard deviation `stddev` from the Philox4_32_10 generator in `state`, increment position of generator by four.

The implementation uses a Box-Muller transform to generate two normally distributed results, and transforms them to log-normal distribution,.

Parameters

- **state** – - Pointer to state to update
- **mean** – - Mean of the related normal distribution
- **stddev** – - Standard deviation of the related normal distribution

Returns
Log-normally distributed double4 where each element is from a distribution with mean `mean` and standard deviation `stddev`

__device__ static float4 **curand_log_normal4**(curandStatePhilox4_32_10_t *state, float mean, float stddev)

Return four normally distributed floats from an Philox4_32_10 generator.

Return four log-normally distributed floats derived from a normal distribution with mean `mean` and standard deviation `stddev` from the Philox4_32_10 generator in `state`, increment position of generator by four.

The implementation uses a Box-Muller transform to generate two normally distributed results, then transforms them to log-normal.

Parameters

- **`state`** – - Pointer to state to update
- **`mean`** – - Mean of the related normal distribution
- **`stddev`** – - Standard deviation of the related normal distribution

Returns

Log-normally distributed float4 where each element is from a distribution with mean `mean` and standard deviation `stddev`

__NV_SILENCE_DEPRECATION_BEGIN __device__ static double4 **`curand_log_normal4_double`**(curandStatePhilox4 *state, double mean, double stddev)

__device__ static double **`curand_log_normal_double`**(curandStateXORWOW_t *state, double mean, double stddev)

Return a log-normally distributed double from an XORWOW generator.

Return a single normally distributed double derived from a normal distribution with mean `mean` and standard deviation `stddev` from the XORWOW generator in `state`, increment position of generator.

The implementation uses a Box-Muller transform to generate two normally distributed results, transforms them to log-normal distribution, then returns them one at a time. See curand_log_normal2_double() for a more efficient version that returns both results at once.

Parameters

- **`state`** – - Pointer to state to update
- **`mean`** – - Mean of the related normal distribution
- **`stddev`** – - Standard deviation of the related normal distribution

Returns

Log-normally distributed double with mean `mean` and standard deviation `stddev`

__NV_SILENCE_DEPRECATION_END __device__ static double **curand_log_normal_double**(curandStateMRG32k3a *state, double mean, double stddev)

Return a log-normally distributed double from an MRG32k3a generator.

Return a single normally distributed double derived from a normal distribution with mean `mean` and standard deviation `stddev` from the MRG32k3a generator in `state`, increment position of generator.

The implementation uses a Box-Muller transform to generate two normally distributed results, transforms them to log-normal distribution, then returns them one at a time. See curand_log_normal2_double() for a more efficient version that returns both results at once.

Parameters

- **state** – - Pointer to state to update
- **mean** – - Mean of the related normal distribution
- **stddev** – - Standard deviation of the related normal distribution

Returns

Log-normally distributed double with mean `mean` and standard deviation `stddev`

__device__ static double **curand_log_normal_double**(curandStateMtgp32_t *state, double mean, double stddev)

Return a log-normally distributed double from an MTGP32 generator.

Return a single log-normally distributed double derived from a normal distribution with mean `mean` and standard deviation `stddev` from the MTGP32 generator in `state`, increment position of generator.

The implementation uses the inverse cumulative distribution function to generate normally distributed results, and transforms them into log-normal distribution.

Parameters

- **state** – - Pointer to state to update
- **mean** – - Mean of the related normal distribution
- **stddev** – - Standard deviation of the related normal distribution

Returns

Log-normally distributed double with mean `mean` and standard deviation `stddev`

__device__ static double **curand_log_normal_double**(curandStateSobol32_t *state, double mean, double stddev)

Return a log-normally distributed double from a Sobol32 generator.

Return a single log-normally distributed double derived from a normal distribution with mean `mean` and standard deviation `stddev` from the Sobol32 generator in `state`, increment position of generator by one.

The implementation uses the inverse cumulative distribution function to generate normally distributed results, and transforms them into log-normal distribution.

Parameters

- **state** – - Pointer to state to update
- **mean** – - Mean of the related normal distribution
- **stddev** – - Standard deviation of the related normal distribution

Returns
Log-normally distributed double with mean `mean` and standard deviation `stddev`

__device__ static double **curand_log_normal_double**(curandStateScrambledSobol64_t *state, double mean, double stddev)

Return a log-normally distributed double from a scrambled Sobol64 generator.

Return a single normally distributed double derived from a normal distribution with mean `mean` and standard deviation `stddev` from the scrambled Sobol64 generator in `state`, increment position of generator by one.

The implementation uses the inverse cumulative distribution function to generate normally distributed results.

Parameters

- **state** – - Pointer to state to update
- **mean** – - Mean of the related normal distribution
- **stddev** – - Standard deviation of the related normal distribution

Returns
Log-normally distributed double with mean `mean` and standard deviation `stddev`

__device__ static double **curand_log_normal_double**(curandStateSobol64_t *state, double mean, double stddev)

Return a log-normally distributed double from a Sobol64 generator.

Return a single normally distributed double derived from a normal distribution with mean `mean` and standard deviation `stddev` from the Sobol64 generator in `state`, increment position of generator by one.

The implementation uses the inverse cumulative distribution function to generate normally distributed results.

Parameters

- **state** – - Pointer to state to update
- **mean** – - Mean of the related normal distribution
- **stddev** – - Standard deviation of the related normal distribution

Returns
Log-normally distributed double with mean `mean` and standard deviation `stddev`

__device__ static double **curand_log_normal_double**(curandStateScrambledSobol32_t *state, double mean, double stddev)

Return a log-normally distributed double from a scrambled Sobol32 generator.

Return a single log-normally distributed double derived from a normal distribution with mean `mean` and standard deviation `stddev` from the scrambled Sobol32 generator in `state`, increment position of generator by one.

The implementation uses the inverse cumulative distribution function to generate normally distributed results, and transforms them into log-normal distribution.

Parameters

- **`state`** – - Pointer to state to update
- **`mean`** – - Mean of the related normal distribution
- **`stddev`** – - Standard deviation of the related normal distribution

Returns

Log-normally distributed double with mean `mean` and standard deviation `stddev`

__device__ static double **`curand_log_normal_double`**(curandStatePhilox4_32_10_t *state, double mean, double stddev)

Return a log-normally distributed double from an Philox4_32_10 generator.

Return a single normally distributed double derived from a normal distribution with mean `mean` and standard deviation `stddev` from the Philox4_32_10 generator in `state`, increment position of generator.

The implementation uses a Box-Muller transform to generate two normally distributed results, transforms them to log-normal distribution, then returns them one at a time. See curand_log_normal2_double() for a more efficient version that returns both results at once.

Parameters

- **`state`** – - Pointer to state to update
- **`mean`** – - Mean of the related normal distribution
- **`stddev`** – - Standard deviation of the related normal distribution

Returns

Log-normally distributed double with mean `mean` and standard deviation `stddev`

__device__ static float **`curand_mtgp32_single`**(curandStateMtgp32_t *state)

Return a uniformly distributed float from a mtgp32 generator.

Return a uniformly distributed float between `0.0f` and `1.0f` from the mtgp32 generator in `state`, increment position of generator. Output range excludes `0.0f` but includes `1.0f`. Denormalized floating point outputs are never returned.

Note: This alternate derivation of a uniform float is provided for completeness with the original source

Parameters

`state` – - Pointer to state to update

Returns

uniformly distributed float between `0.0f` and `1.0f`

__device__ static float **`curand_mtgp32_single_specific`**(curandStateMtgp32_t *state, unsigned char index, unsigned char n)

Return a uniformly distributed float from a specific position in a mtgp32 generator.

Return a uniformly distributed float between `0.0f` and `1.0f` from position `index` of the mtgp32 generator in `state`, and increment position of generator by `n` positions, which must be the total number of positions updated in the state by the thread block, for this invocation. Output range excludes `0.0f` but includes `1.0f`. Denormalized floating point outputs are never returned.

Note 1: Thread indices must range from 0...`n` - 1. The number of positions updated may not exceed 256. A thread block may update more than one state, but a given state may not be updated by more than one thread block.

Note 2: This alternate derivation of a uniform float is provided for completeness with the original source

Parameters

- **`state`** – - Pointer to state to update
- **`index`** – - Index (0..255) of the position within the state to draw from and update
- **`n`** – - The total number of postions in this state that are being updated by this invocation

Returns

uniformly distributed float between `0.0f` and `1.0f`

__device__ static unsigned int **`curand_mtgp32_specific`**(curandStateMtgp32_t *state, unsigned char index, unsigned char n)

Return 32-bits of pseudorandomness from a specific position in a mtgp32 generator.

Return 32-bits of pseudorandomness from position `index` of the mtgp32 generator in `state`, increment position of generator by `n` positions, which must be the total number of positions updated in the state by the thread block, for this invocation.

Note : Thread indices must range from 0... n - 1. The number of positions updated may not exceed 256. A thread block may update more than one state, but a given state may not be updated by more than one thread block.

Parameters

- **`state`** – - Pointer to state to update
- **`index`** – - Index (0..255) of the position within the state to draw from and update
- **`n`** – - The total number of postions in this state that are being updated by this invocation

Returns

32-bits of pseudorandomness as an unsigned int, all bits valid to use.

__device__ static float **`curand_normal`**(curandStateScrambledSobol32_t *state)

Return a normally distributed float from a scrambled Sobol32 generator.

Return a single normally distributed float with mean `0.0f` and standard deviation `1.0f` from the scrambled Sobol32 generator in `state`, increment position of generator by one.

The implementation uses the inverse cumulative distribution function to generate normally distributed results.

Parameters

`state` – - Pointer to state to update

Returns
Normally distributed float with mean `0.0f` and standard deviation `1.0f`

__device__ static float **curand_normal**(curandStateScrambledSobol64_t *state)

Return a normally distributed float from a scrambled Sobol64 generator.

Return a single normally distributed float with mean `0.0f` and standard deviation `1.0f` from the scrambled Sobol64 generator in `state`, increment position of generator by one.

The implementation uses the inverse cumulative distribution function to generate normally distributed results.

Parameters
state – - Pointer to state to update

Returns
Normally distributed float with mean `0.0f` and standard deviation `1.0f`

__device__ static float **curand_normal**(curandStateMRG32k3a_t *state)

Return a normally distributed float from an MRG32k3a generator.

Return a single normally distributed float with mean `0.0f` and standard deviation `1.0f` from the MRG32k3a generator in `state`, increment position of generator by one.

The implementation uses a Box-Muller transform to generate two normally distributed results, then returns them one at a time. See curand_normal2() for a more efficient version that returns both results at once.

Parameters
state – - Pointer to state to update

Returns
Normally distributed float with mean `0.0f` and standard deviation `1.0f`

__NV_SILENCE_DEPRECATION_END __device__ static float **curand_normal**(curandStateXORWOW_t *state)

Return a normally distributed float from an XORWOW generator.

Return a single normally distributed float with mean `0.0f` and standard deviation `1.0f` from the XORWOW generator in `state`, increment position of generator by one.

The implementation uses a Box-Muller transform to generate two normally distributed results, then returns them one at a time. See curand_normal2() for a more efficient version that returns both results at once.

Parameters
state – - Pointer to state to update

Returns
Normally distributed float with mean `0.0f` and standard deviation `1.0f`

__device__ static float **curand_normal**(curandStateSobol64_t *state)

Return a normally distributed float from a Sobol64 generator.

Return a single normally distributed float with mean `0.0f` and standard deviation `1.0f` from the Sobol64 generator in `state`, increment position of generator by one.

The implementation uses the inverse cumulative distribution function to generate normally distributed results.

Parameters
state – - Pointer to state to update

Returns
Normally distributed float with mean `0.0f` and standard deviation `1.0f`

__device__ static float **curand_normal**(curandStateMtgp32_t *state)

Return a normally distributed float from a MTGP32 generator.

Return a single normally distributed float with mean `0.0f` and standard deviation `1.0f` from the MTGP32 generator in `state`, increment position of generator.

The implementation uses the inverse cumulative distribution function to generate normally distributed results.

Parameters
state – - Pointer to state to update

Returns
Normally distributed float with mean `0.0f` and standard deviation `1.0f`

__device__ static float **curand_normal**(curandStatePhilox4_32_10_t *state)

Return a normally distributed float from an Philox4_32_10 generator.

Return a single normally distributed float with mean `0.0f` and standard deviation `1.0f` from the Philox4_32_10 generator in `state`, increment position of generator by one.

The implementation uses a Box-Muller transform to generate two normally distributed results, then returns them one at a time. See curand_normal2() for a more efficient version that returns both results at once.

Parameters
state – - Pointer to state to update

Returns
Normally distributed float with mean `0.0f` and standard deviation `1.0f`

__device__ static float **curand_normal**(curandStateSobol32_t *state)

Return a normally distributed float from a Sobol32 generator.

Return a single normally distributed float with mean `0.0f` and standard deviation `1.0f` from the Sobol32 generator in `state`, increment position of generator by one.

The implementation uses the inverse cumulative distribution function to generate normally distributed results.

Parameters
state – - Pointer to state to update

Returns
Normally distributed float with mean `0.0f` and standard deviation `1.0f`

__device__ static float2 **curand_normal2**(curandStatePhilox4_32_10_t *state)

Return two normally distributed floats from an Philox4_32_10 generator.

Return two normally distributed floats with mean `0.0f` and standard deviation `1.0f` from the Philox4_32_10 generator in `state`, increment position of generator by two.

The implementation uses a Box-Muller transform to generate two normally distributed results.

Parameters
state – - Pointer to state to update

Returns
Normally distributed float2 where each element is from a distribution with mean `0.0f` and standard deviation `1.0f`

__device__ static float2 **curand_normal2**(curandStateXORWOW_t *state)

Return two normally distributed floats from an XORWOW generator.

Return two normally distributed floats with mean `0.0f` and standard deviation `1.0f` from the XORWOW generator in `state`, increment position of generator by two.

The implementation uses a Box-Muller transform to generate two normally distributed results.

Parameters
state – - Pointer to state to update

Returns
Normally distributed float2 where each element is from a distribution with mean `0.0f` and standard deviation `1.0f`

__device__ static float2 **curand_normal2**(curandStateMRG32k3a_t *state)

Return two normally distributed floats from an MRG32k3a generator.

Return two normally distributed floats with mean `0.0f` and standard deviation `1.0f` from the MRG32k3a generator in `state`, increment position of generator by two.

The implementation uses a Box-Muller transform to generate two normally distributed results.

Parameters
state – - Pointer to state to update

Returns
Normally distributed float2 where each element is from a distribution with mean `0.0f` and standard deviation `1.0f`

__NV_SILENCE_DEPRECATION_END __device__ static double2 **curand_normal2_double**(curandStateMRG32k3a_t *state)

Return two normally distributed doubles from an MRG32k3a generator.

Return two normally distributed doubles with mean `0.0` and standard deviation `1.0` from the MRG32k3a generator in `state`, increment position of generator.

The implementation uses a Box-Muller transform to generate two normally distributed results.

Parameters
state – - Pointer to state to update

Returns
Normally distributed double2 where each element is from a distribution with mean `0.0` and standard deviation `1.0`

__device__ static double2 **curand_normal2_double**(curandStateXORWOW_t *state)

Return two normally distributed doubles from an XORWOW generator.

Return two normally distributed doubles with mean `0.0` and standard deviation `1.0` from the XORWOW generator in `state`, increment position of generator by 2.

The implementation uses a Box-Muller transform to generate two normally distributed results.

Parameters
state – - Pointer to state to update

Returns
Normally distributed double2 where each element is from a distribution with mean `0.0` and standard deviation `1.0`

__device__ static double2 **curand_normal2_double**(curandStatePhilox4_32_10_t *state)

Return two normally distributed doubles from an Philox4_32_10 generator.

Return two normally distributed doubles with mean `0.0` and standard deviation `1.0` from the Philox4_32_10 generator in `state`, increment position of generator by 2.

The implementation uses a Box-Muller transform to generate two normally distributed results.

Parameters
state – - Pointer to state to update

Returns
Normally distributed double2 where each element is from a distribution with mean `0.0` and standard deviation `1.0`

__device__ static float4 **curand_normal4**(curandStatePhilox4_32_10_t *state)

Return four normally distributed floats from an Philox4_32_10 generator.

Return four normally distributed floats with mean `0.0f` and standard deviation `1.0f` from the Philox4_32_10 generator in `state`, increment position of generator by four.

The implementation uses a Box-Muller transform to generate two normally distributed results.

Parameters
state – - Pointer to state to update

Returns
Normally distributed float2 where each element is from a distribution with mean `0.0f` and standard deviation `1.0f`

__NV_SILENCE_DEPRECATION_BEGIN __device__ static double4 **curand_normal4_double**(curandStatePhilox4_32_
*state)

__device__ static double **curand_normal_double**(curandStateSobol64_t *state)

Return a normally distributed double from a Sobol64 generator.

Return a single normally distributed double with mean `0.0` and standard deviation `1.0` from the Sobol64 generator in `state`, increment position of generator by one.

The implementation uses the inverse cumulative distribution function to generate normally distributed results.

Parameters
state – - Pointer to state to update

Returns
Normally distributed double with mean `0.0` and standard deviation `1.0`

__device__ static double **curand_normal_double**(curandStateMRG32k3a_t *state)

Return a normally distributed double from an MRG32k3a generator.

Return a single normally distributed double with mean `0.0` and standard deviation `1.0` from the XORWOW generator in `state`, increment position of generator.

The implementation uses a Box-Muller transform to generate two normally distributed results, then returns them one at a time. See curand_normal2_double() for a more efficient version that returns both results at once.

Parameters
state – - Pointer to state to update

Returns
Normally distributed double with mean `0.0` and standard deviation `1.0`

__device__ static double **curand_normal_double**(curandStateMtgp32_t *state)

Return a normally distributed double from an MTGP32 generator.

Return a single normally distributed double with mean `0.0` and standard deviation `1.0` from the MTGP32 generator in `state`, increment position of generator.

The implementation uses the inverse cumulative distribution function to generate normally distributed results.

Parameters
state – - Pointer to state to update

Returns
Normally distributed double with mean `0.0` and standard deviation `1.0`

__device__ static double **curand_normal_double**(curandStateScrambledSobol64_t *state)

Return a normally distributed double from a scrambled Sobol64 generator.

Return a single normally distributed double with mean `0.0` and standard deviation `1.0` from the scrambled Sobol64 generator in `state`, increment position of generator by one.

The implementation uses the inverse cumulative distribution function to generate normally distributed results.

Parameters
state – - Pointer to state to update

Returns
Normally distributed double with mean `0.0` and standard deviation `1.0`

__device__ static double **curand_normal_double**(curandStatePhilox4_32_10_t *state)

Return a normally distributed double from an Philox4_32_10 generator.

Return a single normally distributed double with mean `0.0` and standard deviation `1.0` from the Philox4_32_10 generator in `state`, increment position of generator.

The implementation uses a Box-Muller transform to generate two normally distributed results, then returns them one at a time. See curand_normal2_double() for a more efficient version that returns both results at once.

Parameters
state – - Pointer to state to update

Returns
Normally distributed double with mean `0.0` and standard deviation `1.0`

__device__ static double **curand_normal_double**(curandStateScrambledSobol32_t *state)

Return a normally distributed double from a scrambled Sobol32 generator.

Return a single normally distributed double with mean `0.0` and standard deviation `1.0` from the scrambled Sobol32 generator in `state`, increment position of generator by one.

The implementation uses the inverse cumulative distribution function to generate normally distributed results.

Parameters
state – - Pointer to state to update

Returns
Normally distributed double with mean `0.0` and standard deviation `1.0`

__device__ static double **curand_normal_double**(curandStateXORWOW_t *state)

Return a normally distributed double from an XORWOW generator.

Return a single normally distributed double with mean `0.0` and standard deviation `1.0` from the XORWOW generator in `state`, increment position of generator.

The implementation uses a Box-Muller transform to generate two normally distributed results, then returns them one at a time. See curand_normal2_double() for a more efficient version that returns both results at once.

Parameters
state – - Pointer to state to update

Returns
Normally distributed double with mean `0.0` and standard deviation `1.0`

__device__ static double **curand_normal_double**(curandStateSobol32_t *state)

Return a normally distributed double from an Sobol32 generator.

Return a single normally distributed double with mean `0.0` and standard deviation `1.0` from the Sobol32 generator in `state`, increment position of generator by one.

The implementation uses the inverse cumulative distribution function to generate normally distributed results.

Parameters
state – - Pointer to state to update

Returns
Normally distributed double with mean `0.0` and standard deviation `1.0`

__device__ static unsigned int **curand_poisson**(curandStateSobol64_t *state, double lambda)

Return a Poisson-distributed unsigned int from a Sobol64 generator.

Return a single unsigned int from a Poisson distribution with lambda `lambda` from the Sobol64 generator in `state`, increment position of generator by one.

Parameters

- **state** – - Pointer to state to update
- **lambda** – - Lambda of the Poisson distribution

Returns
Poisson-distributed unsigned int with lambda `lambda`

__device__ static unsigned int **curand_poisson**(curandStateScrambledSobol32_t *state, double lambda)

Return a Poisson-distributed unsigned int from a scrambled Sobol32 generator.

Return a single unsigned int from a Poisson distribution with lambda `lambda` from the scrambled Sobol32 generator in `state`, increment the position of the generator by one.

Parameters

- **state** – - Pointer to state to update
- **lambda** – - Lambda of the Poisson distribution

Returns
Poisson-distributed unsigned int with lambda `lambda`

__device__ static unsigned int **curand_poisson**(curandStateMtgp32_t *state, double lambda)

Return a Poisson-distributed unsigned int from a MTGP32 generator.

Return a single int from a Poisson distribution with lambda `lambda` from the MTGP32 generator in `state`, increment the position of the generator by one.

Parameters

- **state** – - Pointer to state to update
- **lambda** – - Lambda of the Poisson distribution

Returns

Poisson-distributed unsigned int with lambda `lambda`

__device__ static unsigned int **curand_poisson**(curandStateScrambledSobol64_t *state, double lambda)

Return a Poisson-distributed unsigned int from a scrambled Sobol64 generator.

Return a single unsigned int from a Poisson distribution with lambda `lambda` from the scrambled Sobol64 generator in `state`, increment position of generator by one.

Parameters

- **state** – - Pointer to state to update
- **lambda** – - Lambda of the Poisson distribution

Returns

Poisson-distributed unsigned int with lambda `lambda`

__device__ static unsigned int **curand_poisson**(curandStateSobol32_t *state, double lambda)

Return a Poisson-distributed unsigned int from a Sobol32 generator.

Return a single unsigned int from a Poisson distribution with lambda `lambda` from the Sobol32 generator in `state`, increment the position of the generator by one.

Parameters

- **state** – - Pointer to state to update
- **lambda** – - Lambda of the Poisson distribution

Returns

Poisson-distributed unsigned int with lambda `lambda`

__device__ static unsigned int **curand_poisson**(curandStatePhilox4_32_10_t *state, double lambda)

Return a Poisson-distributed unsigned int from a Philox4_32_10 generator.

Return a single unsigned int from a Poisson distribution with lambda `lambda` from the Philox4_32_10 generator in `state`, increment the position of the generator by a variable amount, depending on the algorithm used.

Parameters

- **state** – - Pointer to state to update
- **lambda** – - Lambda of the Poisson distribution

Returns
Poisson-distributed unsigned int with lambda `lambda`

__device__ static unsigned int **curand_poisson**(curandStateXORWOW_t *state, double lambda)

Return a Poisson-distributed unsigned int from a XORWOW generator.

Return a single unsigned int from a Poisson distribution with lambda `lambda` from the XORWOW generator in `state`, increment the position of the generator by a variable amount, depending on the algorithm used.

Parameters

- **state** – - Pointer to state to update
- **lambda** – - Lambda of the Poisson distribution

Returns
Poisson-distributed unsigned int with lambda `lambda`

__device__ static unsigned int **curand_poisson**(curandStateMRG32k3a_t *state, double lambda)

Return a Poisson-distributed unsigned int from a MRG32k3A generator.

Return a single unsigned int from a Poisson distribution with lambda `lambda` from the MRG32k3a generator in `state`, increment the position of the generator by a variable amount, depending on the algorithm used.

Parameters

- **state** – - Pointer to state to update
- **lambda** – - Lambda of the Poisson distribution

Returns
Poisson-distributed unsigned int with lambda `lambda`

__device__ static uint4 **curand_poisson4**(curandStatePhilox4_32_10_t *state, double lambda)

Return four Poisson-distributed unsigned ints from a Philox4_32_10 generator.

Return a four unsigned ints from a Poisson distribution with lambda `lambda` from the Philox4_32_10 generator in `state`, increment the position of the generator by a variable amount, depending on the algorithm used.

Parameters

- **state** – - Pointer to state to update
- **lambda** – - Lambda of the Poisson distribution

Returns
Poisson-distributed unsigned int with lambda `lambda`

template<typename **STATE**>
__device__ static unsigned int **curand_poisson_from_normal**(*STATE* state, double lambda)

template<typename **STATE**>
__device__ static uint4 **curand_poisson_from_normal4**(*STATE* state, double lambda)

template<typename **T**>

__device__ static unsigned int **curand_poisson_gammainc**(*T* state, float lambda)

template<typename **T**>
__device__ static uint4 **curand_poisson_gammainc4**(*T* state, float lambda)

template<typename **T**>
__device__ static unsigned int **curand_poisson_knuth**(*T* *state, float lambda)

template<typename **T**>
__device__ static uint4 **curand_poisson_knuth4**(*T* *state, float lambda)

__device__ static float **curand_uniform**(curandStateMtgp32_t *state)

Return a uniformly distributed float from a MTGP32 generator.

Return a uniformly distributed float between `0.0f` and `1.0f` from the MTGP32 generator in `state`, increment position of generator. Output range excludes `0.0f` but includes `1.0f`. Denormalized floating point outputs are never returned.

Parameters
state – - Pointer to state to update

Returns
uniformly distributed float between `0.0f` and `1.0f`

__device__ static float **curand_uniform**(curandStateTest_t *state)

__device__ static float **curand_uniform**(curandStateSobol32_t *state)

Return a uniformly distributed float from a Sobol32 generator.

Return a uniformly distributed float between `0.0f` and `1.0f` from the Sobol32 generator in `state`, increment position of generator. Output range excludes `0.0f` but includes `1.0f`. Denormalized floating point outputs are never returned.

The implementation is guaranteed to use a single call to `curand()`.

Parameters
state – - Pointer to state to update

Returns
uniformly distributed float between `0.0f` and `1.0f`

__device__ static float **curand_uniform**(curandStateScrambledSobol64_t *state)

Return a uniformly distributed float from a scrambled Sobol64 generator.

Return a uniformly distributed float between `0.0f` and `1.0f` from the scrambled Sobol64 generator in `state`, increment position of generator. Output range excludes `0.0f` but includes `1.0f`. Denormalized floating point outputs are never returned.

The implementation is guaranteed to use a single call to `curand()`.

Parameters
state – - Pointer to state to update

Returns
uniformly distributed float between `0.0f` and `1.0f`

__NV_SILENCE_DEPRECATION_END __device__ static float **curand_uniform**(curandStatePhilox4_32_10_t *state)

Return a uniformly distributed float from a Philox4_32_10 generator.

Return a uniformly distributed float between `0.0f` and `1.0f` from the Philox4_32_10 generator in `state`, increment position of generator. Output range excludes `0.0f` but includes `1.0f`. Denormalized floating point outputs are never returned.

Parameters
`state` – - Pointer to state to update

Returns
uniformly distributed float between `0.0` and `1.0`

__device__ static float **`curand_uniform`**(curandStateScrambledSobol32_t *state)

Return a uniformly distributed float from a scrambled Sobol32 generator.

Return a uniformly distributed float between `0.0f` and `1.0f` from the scrambled Sobol32 generator in `state`, increment position of generator. Output range excludes `0.0f` but includes `1.0f`. Denormalized floating point outputs are never returned.

The implementation is guaranteed to use a single call to `curand()`.

Parameters
`state` – - Pointer to state to update

Returns
uniformly distributed float between `0.0f` and `1.0f`

__device__ static float **`curand_uniform`**(curandStateSobol64_t *state)

Return a uniformly distributed float from a Sobol64 generator.

Return a uniformly distributed float between `0.0f` and `1.0f` from the Sobol64 generator in `state`, increment position of generator. Output range excludes `0.0f` but includes `1.0f`. Denormalized floating point outputs are never returned.

The implementation is guaranteed to use a single call to `curand()`.

Parameters
`state` – - Pointer to state to update

Returns
uniformly distributed float between `0.0f` and `1.0f`

__device__ static float **`curand_uniform`**(curandStateMRG32k3a_t *state)

Return a uniformly distributed float from an MRG32k3a generator.

Return a uniformly distributed float between `0.0f` and `1.0f` from the MRG32k3a generator in `state`, increment position of generator. Output range excludes `0.0f` but includes `1.0f`. Denormalized floating point outputs are never returned.

The implementation returns up to 23 bits of mantissa, with the minimum return value 2^{-32}

Parameters
`state` – - Pointer to state to update

Returns
uniformly distributed float between `0.0f` and `1.0f`

__device__ static float **`curand_uniform`**(curandStateXORWOW_t *state)

Return a uniformly distributed float from an XORWOW generator.

Return a uniformly distributed float between `0.0f` and `1.0f` from the XORWOW generator in `state`, increment position of generator. Output range excludes `0.0f` but includes `1.0f`. Denormalized floating point outputs are never returned.

The implementation may use any number of calls to `curand()` to get enough random bits to create the return value. The current implementation uses one call.

Parameters
state – - Pointer to state to update

Returns
uniformly distributed float between `0.0f` and `1.0f`

__device__ static double2 **curand_uniform2_double**(curandStatePhilox4_32_10_t *state)

Return a uniformly distributed tuple of 2 doubles from an Philox4_32_10 generator.

Return a uniformly distributed 2 doubles (double4) between `0.0` and `1.0` from the Philox4_32_10 generator in `state`, increment position of generator by 4. Output range excludes `0.0` but includes `1.0`. Denormalized floating point outputs are never returned.

Parameters
state – - Pointer to state to update

Returns
2 uniformly distributed doubles between `0.0` and `1.0`

__device__ static float4 **curand_uniform4**(curandStatePhilox4_32_10_t *state)

Return a uniformly distributed tuple of 4 floats from a Philox4_32_10 generator.

Return a uniformly distributed 4 floats between `0.0f` and `1.0f` from the Philox4_32_10 generator in `state`, increment position of generator by 4. Output range excludes `0.0f` but includes `1.0f`. Denormalized floating point outputs are never returned.

Parameters
state – - Pointer to state to update

Returns
uniformly distributed float between `0.0` and `1.0`

__NV_SILENCE_DEPRECATION_BEGIN __device__ static double4 **curand_uniform4_double**(curandStatePhilox4_32 *state)

__device__ static double **curand_uniform_double**(curandStateScrambledSobol32_t *state)

Return a uniformly distributed double from a scrambled Sobol32 generator.

Return a uniformly distributed double between `0.0` and `1.0` from the scrambled Sobol32 generator in `state`, increment position of generator. Output range excludes `0.0` but includes `1.0`. Denormalized floating point outputs are never returned.

The implementation is guaranteed to use a single call to `curand()` to preserve the quasirandom properties of the sequence.

Note that the implementation uses only 32 random bits to generate a single double precision value.

Parameters
state – - Pointer to state to update

Returns
uniformly distributed double between `0.0` and `1.0`

__device__ static double **curand_uniform_double**(curandStateScrambledSobol64_t *state)

Return a uniformly distributed double from a scrambled Sobol64 generator.

Return a uniformly distributed double between `0.0` and `1.0` from the scrambled Sobol64 generator in `state`, increment position of generator. Output range excludes `0.0` but includes `1.0`. Denormalized floating point outputs are never returned.

The implementation is guaranteed to use a single call to `curand()` to preserve the quasirandom properties of the sequence.

Parameters
`state` – - Pointer to state to update

Returns
uniformly distributed double between `0.0` and `1.0`

__device__ static double **`curand_uniform_double`**(curandStateMtgp32_t *state)

Return a uniformly distributed double from a MTGP32 generator.

Return a uniformly distributed double between `0.0f` and `1.0f` from the MTGP32 generator in `state`, increment position of generator. Output range excludes `0.0f` but includes `1.0f`. Denormalized floating point outputs are never returned.

Note that the implementation uses only 32 random bits to generate a single double precision value.

Parameters
`state` – - Pointer to state to update

Returns
uniformly distributed double between `0.0f` and `1.0f`

__device__ static double **`curand_uniform_double`**(curandStatePhilox4_32_10_t *state)

Return a uniformly distributed double from a Philox4_32_10 generator.

Return a uniformly distributed double between `0.0f` and `1.0f` from the Philox4_32_10 generator in `state`, increment position of generator. Output range excludes `0.0f` but includes `1.0f`. Denormalized floating point outputs are never returned.

Note that the implementation uses only 32 random bits to generate a single double precision value.

`curand_uniform2_double()` is recommended for higher quality uniformly distributed double precision values.

Parameters
`state` – - Pointer to state to update

Returns
uniformly distributed double between `0.0f` and `1.0f`

__device__ static double **`curand_uniform_double`**(curandStateMRG32k3a_t *state)

Return a uniformly distributed double from an MRG32k3a generator.

Return a uniformly distributed double between `0.0` and `1.0` from the MRG32k3a generator in `state`, increment position of generator. Output range excludes `0.0` but includes `1.0`. Denormalized floating point outputs are never returned.

Note the implementation returns at most 32 random bits of mantissa as outlined in the seminal paper by L'Ecuyer.

Parameters
`state` – - Pointer to state to update

Returns
uniformly distributed double between `0.0` and `1.0`

__device__ static double **curand_uniform_double**(curandStateTest_t *state)

__device__ static double **curand_uniform_double**(curandStateSobol32_t *state)

Return a uniformly distributed double from a Sobol32 generator.

Return a uniformly distributed double between `0.0` and `1.0` from the Sobol32 generator in `state`, increment position of generator. Output range excludes `0.0` but includes `1.0`. Denormalized floating point outputs are never returned.

The implementation is guaranteed to use a single call to `curand()` to preserve the quasirandom properties of the sequence.

Note that the implementation uses only 32 random bits to generate a single double precision value.

Parameters
state – - Pointer to state to update

Returns
uniformly distributed double between `0.0` and `1.0`

__device__ static double **curand_uniform_double**(curandStateSobol64_t *state)

Return a uniformly distributed double from a Sobol64 generator.

Return a uniformly distributed double between `0.0` and `1.0` from the Sobol64 generator in `state`, increment position of generator. Output range excludes `0.0` but includes `1.0`. Denormalized floating point outputs are never returned.

The implementation is guaranteed to use a single call to `curand()` to preserve the quasirandom properties of the sequence.

Parameters
state – - Pointer to state to update

Returns
uniformly distributed double between `0.0` and `1.0`

__device__ static double **curand_uniform_double**(curandStateXORWOW_t *state)

Return a uniformly distributed double from an XORWOW generator.

Return a uniformly distributed double between `0.0` and `1.0` from the XORWOW generator in `state`, increment position of generator. Output range excludes `0.0` but includes `1.0`. Denormalized floating point outputs are never returned.

The implementation may use any number of calls to `curand()` to get enough random bits to create the return value. The current implementation uses exactly two calls.

Parameters
state – - Pointer to state to update

Returns
uniformly distributed double between `0.0` and `1.0`

static unsigned int **ini_func1**(unsigned int x)

static unsigned int **ini_func2**(unsigned int x)

__host__ static int **mtgp32_init_by_array**(unsigned int state[], const mtgp32_params_fast_t *para, unsigned int *array, int length)

__host__ static int **mtgp32_init_by_str**(unsigned int state[], const mtgp32_params_fast_t *para, unsigned char *array)

__host__ static void **mtgp32_init_state**(unsigned int state[], const mtgp32_params_fast_t *para, unsigned int seed)

__device__ static unsigned int **para_rec**(mtgp32_kernel_params_t *k, unsigned int X1, unsigned int X2, unsigned int Y, int bid)

__device__ static void **skipahead**(unsigned long long n, curandStateMRG32k3a_t *state)

Update MRG32k3a state to skip n elements.

Update the MRG32k3a state in `state` to skip ahead n elements.

All values of n are valid. Large values require more computation and so will take more time to complete.

Parameters

- **n** – - Number of elements to skip
- **state** – - Pointer to state to update

template<typename **T**>
__device__ static curand_detail::enable_if<curand_detail::is_same<curandStateSobol64_t*, *T*>::value || curand_detail::

Update Sobol64 state to skip n elements.

Update the Sobol64 state in `state` to skip ahead n elements.

All values of n are valid.

Parameters

- **n** – - Number of elements to skip
- **state** – - Pointer to state to update

__device__ static void **skipahead**(unsigned long long n, curandStateXORWOW_t *state)

Update XORWOW state to skip n elements.

Update the XORWOW state in `state` to skip ahead n elements.

All values of n are valid. Large values require more computation and so will take more time to complete.

Parameters

- **n** – - Number of elements to skip
- **state** – - Pointer to state to update

__device__ static void **skipahead**(unsigned long long n, curandStateTest_t *state)

template<typename **T**>

__device__ static curand_detail::enable_if<curand_detail::is_same<curandStateSobol32_t*, *T*>::value || curand_detail::

Update Sobol32 state to skip n elements.

Update the Sobol32 state in `state` to skip ahead n elements.

All values of n are valid.

Parameters

- **n** – - Number of elements to skip
- **state** – - Pointer to state to update

__device__ static void **skipahead**(unsigned long long n, curandStatePhilox4_32_10_t *state)

Update Philox4_32_10 state to skip n elements.

Update the Philox4_32_10 state in `state` to skip ahead n elements.

All values of n are valid.

Parameters

- **n** – - Number of elements to skip
- **state** – - Pointer to state to update

__device__ static void **skipahead_sequence**(unsigned long long n, curandStateMRG32k3a_t *state)

Update MRG32k3a state to skip ahead n sequences.

Update the MRG32k3a state in `state` to skip ahead n sequences. Each sequence is elements long, so this means the function will skip ahead * n elements.

All values of n are valid. Large values require more computation and so will take more time to complete.

Parameters

- **n** – - Number of sequences to skip
- **state** – - Pointer to state to update

__device__ static void **skipahead_sequence**(unsigned long long n, curandStatePhilox4_32_10_t *state)

Update Philox4_32_10 state to skip ahead n subsequences.

Update the Philox4_32_10 state in `state` to skip ahead n subsequences. Each subsequence is elements long, so this means the function will skip ahead * n elements.

All values of n are valid.

Parameters

- **n** – - Number of subsequences to skip
- **state** – - Pointer to state to update

__device__ static void **skipahead_sequence**(unsigned long long n, curandStateXORWOW_t *state)

Update XORWOW state to skip ahead n subsequences.

Update the XORWOW state in `state` to skip ahead n subsequences. Each subsequence is elements long, so this means the function will skip ahead * n elements.

All values of n are valid. Large values require more computation and so will take more time to complete.

Parameters

- **n** – - Number of subsequences to skip
- **state** – - Pointer to state to update

__device__ static void **skipahead_subsequence**(unsigned long long n, curandStateMRG32k3a_t *state)

Update MRG32k3a state to skip ahead n subsequences.

Update the MRG32k3a state in `state` to skip ahead n subsequences. Each subsequence is

elements long, so this means the function will skip ahead * n elements.

Valid values of n are 0 to . Note n will be masked to 51 bits

Parameters

- **n** – - Number of subsequences to skip
- **state** – - Pointer to state to update

__device__ static unsigned int **temper**(mtgp32_kernel_params_t *k, unsigned int V, unsigned int T, int bid)

__device__ static unsigned int **temper_single**(mtgp32_kernel_params_t *k, unsigned int V, unsigned int T, int bid)

6.1.3. Variables

static __constant__ double __cr_lgamma_table [] = {0.00000000000000000e-1,0.00000000000000000e-1,6.93147180559945309e-1,1.79175946922805500e0,3.17805383034794562e0,4.78749174278204599e0,6.57925121201010099e0,8.52516136106541430e0,1.06046029027452502e1}

const dim3 **blockDim**

static const unsigned int **non_zero** = 0x4d544750

const uint3 **threadIdx**

6.2. Host API

Macros

CURANDAPI

CURAND_VER_BUILD

CURAND_VER_MAJOR

CURAND_VER_MINOR

CURAND_VER_PATCH

Enumerations

curandDirectionVectorSet
CURAND choice of direction vector set.

curandOrdering
CURAND ordering of results in memory.

curandRngType
CURAND generator types.

curandStatus
CURAND function call status types.

Functions

curandStatus_t *curandCreateGenerator*(**curandGenerator_t *generator, curandRngType_t rng_type**)
Create new random number generator.

curandStatus_t *curandCreateGeneratorHost*(**curandGenerator_t *generator, curandRngType_t rng_type**)
Create new host CPU random number generator.

curandStatus_t *curandCreatePoissonDistribution*(**double lambda, curandDiscreteDistribution_t *discrete_distribution**)
Construct the histogram array for a Poisson distribution.

curandStatus_t *curandDestroyDistribution*(**curandDiscreteDistribution_t discrete_distribution**)
Destroy the histogram array for a discrete distribution (e.g.

curandStatus_t *curandDestroyGenerator*(**curandGenerator_t generator**)
Destroy an existing generator.

curandStatus_t *curandGenerate*(**curandGenerator_t generator, unsigned int *outputPtr, size_t num**)
Generate 32-bit pseudo or quasirandom numbers.

curandStatus_t *curandGenerateBinomial*(curandGenerator_t generator, unsigned int *outputPtr, size_t num, unsigned int n, double p)

curandStatus_t *curandGenerateBinomialMethod*(curandGenerator_t generator, unsigned int *outputPtr, size_t num, unsigned int n, double p, curandMethod_t method)

curandStatus_t *curandGenerateLogNormal*(curandGenerator_t generator, float *outputPtr, size_t n, float mean, float stddev)
Generate log-normally distributed floats.

curandStatus_t *curandGenerateLogNormalDouble*(curandGenerator_t generator, double *outputPtr, size_t n, double mean, double stddev)
Generate log-normally distributed doubles.

curandStatus_t *curandGenerateLongLong*(curandGenerator_t generator, unsigned long long *outputPtr, size_t num)
Generate 64-bit quasirandom numbers.

curandStatus_t *curandGenerateNormal*(curandGenerator_t generator, float *outputPtr, size_t n, float mean, float stddev)
Generate normally distributed doubles.

curandStatus_t *curandGenerateNormalDouble*(curandGenerator_t generator, double *outputPtr, size_t n, double mean, double stddev)
Generate normally distributed doubles.

curandStatus_t *curandGeneratePoisson*(curandGenerator_t generator, unsigned int *outputPtr, size_t n, double lambda)
Generate Poisson-distributed unsigned ints.

curandStatus_t *curandGeneratePoissonMethod*(curandGenerator_t generator, unsigned int *outputPtr, size_t n, double lambda, curandMethod_t method)

curandStatus_t *curandGenerateSeeds*(curandGenerator_t generator)
Setup starting states.

curandStatus_t *curandGenerateUniform*(curandGenerator_t generator, float *outputPtr, size_t num)
Generate uniformly distributed floats.

curandStatus_t *curandGenerateUniformDouble*(curandGenerator_t generator, double *outputPtr, size_t num)
Generate uniformly distributed doubles.

curandStatus_t *curandGetDirectionVectors32*(curandDirectionVectors32_t *vectors[], curandDirectionVectorSet_t set)
Get direction vectors for 32-bit quasirandom number generation.

curandStatus_t *curandGetDirectionVectors64*(curandDirectionVectors64_t *vectors[], curandDirectionVectorSet_t set)
Get direction vectors for 64-bit quasirandom number generation.

curandStatus_t *curandGetProperty*(libraryPropertyType type, int *value)
Return the value of the curand property.

curandStatus_t *curandGetScrambleConstants32*(unsigned int **constants)
Get scramble constants for 32-bit scrambled Sobol' .

curandStatus_t ***curandGetScrambleConstants64*****(unsigned long long **constants)**
Get scramble constants for 64-bit scrambled Sobol' .

curandStatus_t ***curandGetVersion*****(int *version)**
Return the version number of the library.

curandStatus_t ***curandSetGeneratorOffset*****(curandGenerator_t generator, unsigned long long offset)**
Set the absolute offset of the pseudo or quasirandom number generator.

curandStatus_t ***curandSetGeneratorOrdering*****(curandGenerator_t generator, curandOrdering_t order)**
Set the ordering of results of the pseudo or quasirandom number generator.

curandStatus_t ***curandSetPseudoRandomGeneratorSeed*****(curandGenerator_t generator, unsigned long long seed)**
Set the seed value of the pseudo-random number generator.

curandStatus_t ***curandSetQuasiRandomGeneratorDimensions*****(curandGenerator_t generator, unsigned int num_dimensions)**
Set the number of dimensions.

curandStatus_t ***curandSetStream*****(curandGenerator_t generator, cudaStream_t stream)**
Set the current stream for CURAND kernel launches.

6.2.1. Macros

CURANDAPI

CURAND_VER_BUILD 49

CURAND_VER_MAJOR 10

CURAND_VER_MINOR 4

CURAND_VER_PATCH 5

6.2.2. Enumerations

enum **curandDirectionVectorSet**
CURAND choice of direction vector set.

Values:

enumerator **CURAND_DIRECTION_VECTORS_32_JOEKUO6** = 101
Specific set of 32-bit direction vectors generated from polynomials recommended by S. Joe and F. Y. Kuo, for up to 20,000 dimensions.

enumerator **CURAND_SCRAMBLED_DIRECTION_VECTORS_32_JOEKUO6** = 102

Specific set of 32-bit direction vectors generated from polynomials recommended by S. Joe and F. Y. Kuo, for up to 20,000 dimensions, and scrambled.

enumerator **CURAND_DIRECTION_VECTORS_64_JOEKUO6** = 103

Specific set of 64-bit direction vectors generated from polynomials recommended by S. Joe and F. Y. Kuo, for up to 20,000 dimensions.

enumerator **CURAND_SCRAMBLED_DIRECTION_VECTORS_64_JOEKUO6** = 104

Specific set of 64-bit direction vectors generated from polynomials recommended by S. Joe and F. Y. Kuo, for up to 20,000 dimensions, and scrambled.

enum **curandOrdering**

CURAND ordering of results in memory.

Values:

enumerator **CURAND_ORDERING_PSEUDO_BEST** = 100

Best ordering for pseudorandom results.

enumerator **CURAND_ORDERING_PSEUDO_DEFAULT** = 101

Specific default thread sequence for pseudorandom results, same as CURAND_ORDERING_PSEUDO_BEST.

enumerator **CURAND_ORDERING_PSEUDO_SEEDED** = 102

Specific seeding pattern for fast lower quality pseudorandom results.

enumerator **CURAND_ORDERING_PSEUDO_LEGACY** = 103

Specific legacy sequence for pseudorandom results, guaranteed to remain the same for all cuRAND release.

enumerator **CURAND_ORDERING_PSEUDO_DYNAMIC** = 104

Specific ordering adjusted to the device it is being executed on, provides the best performance.

enumerator **CURAND_ORDERING_QUASI_DEFAULT** = 201

Specific n-dimensional ordering for quasirandom results.

enum **curandRngType**

CURAND generator types.

Values:

enumerator **CURAND_RNG_TEST** = 0

enumerator **CURAND_RNG_PSEUDO_DEFAULT** = 100

Default pseudorandom generator.

enumerator **CURAND_RNG_PSEUDO_XORWOW** = 101
XORWOW pseudorandom generator.

enumerator **CURAND_RNG_PSEUDO_MRG32K3A** = 121
MRG32k3a pseudorandom generator.

enumerator **CURAND_RNG_PSEUDO_MTGP32** = 141
Mersenne Twister MTGP32 pseudorandom generator.

enumerator **CURAND_RNG_PSEUDO_MT19937** = 142
Mersenne Twister MT19937 pseudorandom generator.

enumerator **CURAND_RNG_PSEUDO_PHILOX4_32_10** = 161
PHILOX-4x32-10 pseudorandom generator.

enumerator **CURAND_RNG_QUASI_DEFAULT** = 200
Default quasirandom generator.

enumerator **CURAND_RNG_QUASI_SOBOL32** = 201
Sobol32 quasirandom generator.

enumerator **CURAND_RNG_QUASI_SCRAMBLED_SOBOL32** = 202
Scrambled Sobol32 quasirandom generator.

enumerator **CURAND_RNG_QUASI_SOBOL64** = 203
Sobol64 quasirandom generator.

enumerator **CURAND_RNG_QUASI_SCRAMBLED_SOBOL64** = 204
Scrambled Sobol64 quasirandom generator.

enum **curandStatus**
CURAND function call status types.
Values:

enumerator **CURAND_STATUS_SUCCESS** = 0
No errors.

enumerator **CURAND_STATUS_VERSION_MISMATCH** = 100
Header file and linked library version do not match.

enumerator **CURAND_STATUS_NOT_INITIALIZED** = 101
Generator not initialized.

enumerator **CURAND_STATUS_ALLOCATION_FAILED** = 102
Memory allocation failed.

enumerator **CURAND_STATUS_TYPE_ERROR** = 103
Generator is wrong type.

enumerator **CURAND_STATUS_OUT_OF_RANGE** = 104
Argument out of range.

enumerator **CURAND_STATUS_LENGTH_NOT_MULTIPLE** = 105
Length requested is not a multple of dimension.

enumerator **CURAND_STATUS_DOUBLE_PRECISION_REQUIRED** = 106
GPU does not have double precision required by MRG32k3a.

enumerator **CURAND_STATUS_LAUNCH_FAILURE** = 201
Kernel launch failure.

enumerator **CURAND_STATUS_PREEXISTING_FAILURE** = 202
Preexisting failure on library entry.

enumerator **CURAND_STATUS_INITIALIZATION_FAILED** = 203
Initialization of CUDA failed.

enumerator **CURAND_STATUS_ARCH_MISMATCH** = 204
Architecture mismatch, GPU does not support requested feature.

enumerator **CURAND_STATUS_INTERNAL_ERROR** = 999
Internal library error.

6.2.3. Functions

curandStatus_t **curandCreateGenerator**(curandGenerator_t *generator, curandRngType_t rng_type)

Create new random number generator.

Creates a new random number generator of type `rng_type` and returns it in `*generator`.

Legal values for `rng_type` are:

- CURAND_RNG_PSEUDO_DEFAULT
- CURAND_RNG_PSEUDO_XORWOW
- CURAND_RNG_PSEUDO_MRG32K3A
- CURAND_RNG_PSEUDO_MTGP32
- CURAND_RNG_PSEUDO_MT19937
- CURAND_RNG_PSEUDO_PHILOX4_32_10
- CURAND_RNG_QUASI_DEFAULT

- CURAND_RNG_QUASI_SOBOL32
- CURAND_RNG_QUASI_SCRAMBLED_SOBOL32
- CURAND_RNG_QUASI_SOBOL64
- CURAND_RNG_QUASI_SCRAMBLED_SOBOL64

When `rng_type` is CURAND_RNG_PSEUDO_DEFAULT, the type chosen is CURAND_RNG_PSEUDO_XORWOW.

When `rng_type` is CURAND_RNG_QUASI_DEFAULT, the type chosen is CURAND_RNG_QUASI_SOBOL32.

The default values for `rng_type` = CURAND_RNG_PSEUDO_XORWOW are:

- `seed` = 0
- `offset` = 0
- `ordering` = CURAND_ORDERING_PSEUDO_DEFAULT

The default values for `rng_type` = CURAND_RNG_PSEUDO_MRG32K3A are:

- `seed` = 0
- `offset` = 0
- `ordering` = CURAND_ORDERING_PSEUDO_DEFAULT

The default values for `rng_type` = CURAND_RNG_PSEUDO_MTGP32 are:

- `seed` = 0
- `offset` = 0
- `ordering` = CURAND_ORDERING_PSEUDO_DEFAULT

The default values for `rng_type` = CURAND_RNG_PSEUDO_MT19937 are:

- `seed` = 0
- `offset` = 0
- `ordering` = CURAND_ORDERING_PSEUDO_DEFAULT
- The default values for `rng_type` = CURAND_RNG_PSEUDO_PHILOX4_32_10 are:
- `seed` = 0
- `offset` = 0
- `ordering` = CURAND_ORDERING_PSEUDO_DEFAULT

The default values for `rng_type` = CURAND_RNG_QUASI_SOBOL32 are:

- `dimensions` = 1
- `offset` = 0
- `ordering` = CURAND_ORDERING_QUASI_DEFAULT

The default values for `rng_type` = CURAND_RNG_QUASI_SOBOL64 are:

- `dimensions` = 1
- `offset` = 0
- `ordering` = CURAND_ORDERING_QUASI_DEFAULT

The default values for `rng_type` = CURAND_RNG_QUASI_SCRAMBBLED_SOBOL32 are:

- `dimensions` = 1
- `offset` = 0
- `ordering` = CURAND_ORDERING_QUASI_DEFAULT

The default values for `rng_type` = CURAND_RNG_QUASI_SCRAMBLED_SOBOL64 are:

- `dimensions` = 1
- `offset` = 0
- `ordering` = CURAND_ORDERING_QUASI_DEFAULT

Parameters

- **`generator`** – - Pointer to generator
- **`rng_type`** – - Type of generator to create

Returns

- CURAND_STATUS_ALLOCATION_FAILED, if memory could not be allocated
- CURAND_STATUS_INITIALIZATION_FAILED if there was a problem setting up the GPU
- CURAND_STATUS_VERSION_MISMATCH if the header file version does not match the dynamically linked library version
- CURAND_STATUS_TYPE_ERROR if the value for `rng_type` is invalid
- CURAND_STATUS_SUCCESS if generator was created successfully

curandStatus_t **`curandCreateGeneratorHost`**(curandGenerator_t *generator, curandRngType_t rng_type)

Create new host CPU random number generator.

Creates a new host CPU random number generator of type `rng_type` and returns it in `*generator`.

Legal values for `rng_type` are:

- CURAND_RNG_PSEUDO_DEFAULT
- CURAND_RNG_PSEUDO_XORWOW
- CURAND_RNG_PSEUDO_MRG32K3A
- CURAND_RNG_PSEUDO_MTGP32
- CURAND_RNG_PSEUDO_MT19937
- CURAND_RNG_PSEUDO_PHILOX4_32_10
- CURAND_RNG_QUASI_DEFAULT
- CURAND_RNG_QUASI_SOBOL32
- CURAND_RNG_QUASI_SCRAMBLED_SOBOL32
- CURAND_RNG_QUASI_SOBOL64
- CURAND_RNG_QUASI_SCRAMBLED_SOBOL64

When `rng_type` is CURAND_RNG_PSEUDO_DEFAULT, the type chosen is CURAND_RNG_PSEUDO_XORWOW.

When `rng_type` is CURAND_RNG_QUASI_DEFAULT, the type chosen is CURAND_RNG_QUASI_SOBOL32.

The default values for `rng_type` = CURAND_RNG_PSEUDO_XORWOW are:

- `seed` = 0
- `offset` = 0
- `ordering` = CURAND_ORDERING_PSEUDO_DEFAULT

The default values for `rng_type` = CURAND_RNG_PSEUDO_MRG32K3A are:

- `seed` = 0
- `offset` = 0
- `ordering` = CURAND_ORDERING_PSEUDO_DEFAULT

The default values for `rng_type` = CURAND_RNG_PSEUDO_MTGP32 are:

- `seed` = 0
- `offset` = 0
- `ordering` = CURAND_ORDERING_PSEUDO_DEFAULT

The default values for `rng_type` = CURAND_RNG_PSEUDO_MT19937 are:

- `seed` = 0
- `offset` = 0
- `ordering` = CURAND_ORDERING_PSEUDO_DEFAULT
- The default values for `rng_type` = CURAND_RNG_PSEUDO_PHILOX4_32_10 are:
- `seed` = 0
- `offset` = 0
- `ordering` = CURAND_ORDERING_PSEUDO_DEFAULT

The default values for `rng_type` = CURAND_RNG_QUASI_SOBOL32 are:

- `dimensions` = 1
- `offset` = 0
- `ordering` = CURAND_ORDERING_QUASI_DEFAULT

The default values for `rng_type` = CURAND_RNG_QUASI_SOBOL64 are:

- `dimensions` = 1
- `offset` = 0
- `ordering` = CURAND_ORDERING_QUASI_DEFAULT

The default values for `rng_type` = CURAND_RNG_QUASI_SCRAMBLED_SOBOL32 are:

- `dimensions` = 1
- `offset` = 0
- `ordering` = CURAND_ORDERING_QUASI_DEFAULT

The default values for `rng_type` = CURAND_RNG_QUASI_SCRAMBLED_SOBOL64 are:

- `dimensions` = 1
- `offset` = 0
- `ordering` = CURAND_ORDERING_QUASI_DEFAULT

Parameters

- **`generator`** – - Pointer to generator
- **`rng_type`** – - Type of generator to create

Returns

- CURAND_STATUS_ALLOCATION_FAILED if memory could not be allocated
- CURAND_STATUS_INITIALIZATION_FAILED if there was a problem setting up the GPU
- CURAND_STATUS_VERSION_MISMATCH if the header file version does not match the dynamically linked library version
- CURAND_STATUS_TYPE_ERROR if the value for `rng_type` is invalid
- CURAND_STATUS_SUCCESS if generator was created successfully

curandStatus_t **`curandCreatePoissonDistribution`**(double lambda,
curandDiscreteDistribution_t
*discrete_distribution)

Construct the histogram array for a Poisson distribution.

Construct the histogram array for the Poisson distribution with lambda `lambda`. For lambda greater than 2000, an approximation with a normal distribution is used.

Parameters

- **`lambda`** – - lambda for the Poisson distribution
- **`discrete_distribution`** – - pointer to the histogram in device memory

Returns

- CURAND_STATUS_ALLOCATION_FAILED if memory could not be allocated
- CURAND_STATUS_DOUBLE_PRECISION_REQUIRED if the GPU does not support double precision
- CURAND_STATUS_INITIALIZATION_FAILED if there was a problem setting up the GPU
- CURAND_STATUS_NOT_INITIALIZED if the distribution pointer was null
- CURAND_STATUS_PREEXISTING_FAILURE if there was an existing error from a previous kernel launch
- CURAND_STATUS_OUT_OF_RANGE if lambda is non-positive or greater than 400,000
- CURAND_STATUS_SUCCESS if the histogram was generated successfully

curandStatus_t **curandDestroyDistribution**(curandDiscreteDistribution_t discrete_distribution)

Destroy the histogram array for a discrete distribution (e.g.

Poisson).

Destroy the histogram array for a discrete distribution created by curandCreatePoissonDistribution.

Parameters

discrete_distribution – - pointer to device memory where the histogram is stored

Returns

- CURAND_STATUS_NOT_INITIALIZED if the histogram was never created
- CURAND_STATUS_SUCCESS if the histogram was destroyed successfully

curandStatus_t **curandDestroyGenerator**(curandGenerator_t generator)

Destroy an existing generator.

Destroy an existing generator and free all memory associated with its state.

Parameters

generator – - Generator to destroy

Returns

- CURAND_STATUS_NOT_INITIALIZED if the generator was never created
- CURAND_STATUS_SUCCESS if generator was destroyed successfully

curandStatus_t **curandGenerate**(curandGenerator_t generator, unsigned int *outputPtr, size_t num)

Generate 32-bit pseudo or quasirandom numbers.

Use `generator` to generate `num` 32-bit results into the device memory at `outputPtr`. The device memory must have been previously allocated and be large enough to hold all the results. Launches are done with the stream set using *curandSetStream()*, or the null stream if no stream has been set.

Results are 32-bit values with every bit random.

Parameters

- **generator** – - Generator to use
- **outputPtr** – - Pointer to device memory to store CUDA-generated results, or Pointer to host memory to store CPU-generated results
- **num** – - Number of random 32-bit values to generate

Returns

- CURAND_STATUS_ALLOCATION_FAILED if memory could not be allocated
- CURAND_STATUS_NOT_INITIALIZED if the generator was never created
- CURAND_STATUS_PREEXISTING_FAILURE if there was an existing error from a previous kernel launch

- CURAND_STATUS_LENGTH_NOT_MULTIPLE if the number of output samples is not a multiple of the quasirandom dimension
- CURAND_STATUS_LAUNCH_FAILURE if the kernel launch failed for any reason
- CURAND_STATUS_TYPE_ERROR if the generator is a 64 bit quasirandom generator. (use *curandGenerateLongLong()* with 64 bit quasirandom generators)
- CURAND_STATUS_SUCCESS if the results were generated successfully

curandStatus_t **curandGenerateBinomial**(curandGenerator_t generator, unsigned int *outputPtr, size_t num, unsigned int n, double p)

curandStatus_t **curandGenerateBinomialMethod**(curandGenerator_t generator, unsigned int *outputPtr, size_t num, unsigned int n, double p, curandMethod_t method)

curandStatus_t **curandGenerateLogNormal**(curandGenerator_t generator, float *outputPtr, size_t n, float mean, float stddev)

Generate log-normally distributed floats.

Use `generator` to generate `n` float results into the device memory at `outputPtr`. The device memory must have been previously allocated and be large enough to hold all the results. Launches are done with the stream set using *curandSetStream()*, or the null stream if no stream has been set.

Results are 32-bit floating point values with log-normal distribution based on an associated normal distribution with mean `mean` and standard deviation `stddev`.

Normally distributed results are generated from pseudorandom generators with a Box-Muller transform, and so require `n` to be even. Quasirandom generators use an inverse cumulative distribution function to preserve dimensionality. The normally distributed results are transformed into log-normal distribution.

There may be slight numerical differences between results generated on the GPU with generators created with *curandCreateGenerator()* and results calculated on the CPU with generators created with *curandCreateGeneratorHost()*. These differences arise because of differences in results for transcendental functions. In addition, future versions of CURAND may use newer versions of the CUDA math library, so different versions of CURAND may give slightly different numerical values.

Parameters

- **`generator`** – - Generator to use
- **`outputPtr`** – - Pointer to device memory to store CUDA-generated results, or Pointer to host memory to store CPU-generated results
- **`n`** – - Number of floats to generate
- **`mean`** – - Mean of associated normal distribution
- **`stddev`** – - Standard deviation of associated normal distribution

Returns

- CURAND_STATUS_ALLOCATION_FAILED if memory could not be allocated
- CURAND_STATUS_NOT_INITIALIZED if the generator was never created
- CURAND_STATUS_PREEXISTING_FAILURE if there was an existing error from a previous kernel launch

- CURAND_STATUS_LAUNCH_FAILURE if the kernel launch failed for any reason
- CURAND_STATUS_LENGTH_NOT_MULTIPLE if the number of output samples is not a multiple of the quasirandom dimension, or is not a multiple of two for pseudorandom generators
- CURAND_STATUS_SUCCESS if the results were generated successfully

curandStatus_t **curandGenerateLogNormalDouble**(curandGenerator_t generator, double *outputPtr, size_t n, double mean, double stddev)

Generate log-normally distributed doubles.

Use `generator` to generate `n` double results into the device memory at `outputPtr`. The device memory must have been previously allocated and be large enough to hold all the results. Launches are done with the stream set using *curandSetStream()*, or the null stream if no stream has been set.

Results are 64-bit floating point values with log-normal distribution based on an associated normal distribution with mean `mean` and standard deviation `stddev`.

Normally distributed results are generated from pseudorandom generators with a Box-Muller transform, and so require `n` to be even. Quasirandom generators use an inverse cumulative distribution function to preserve dimensionality. The normally distributed results are transformed into log-normal distribution.

There may be slight numerical differences between results generated on the GPU with generators created with *curandCreateGenerator()* and results calculated on the CPU with generators created with *curandCreateGeneratorHost()*. These differences arise because of differences in results for transcendental functions. In addition, future versions of CURAND may use newer versions of the CUDA math library, so different versions of CURAND may give slightly different numerical values.

Parameters

- **`generator`** – - Generator to use
- **`outputPtr`** – - Pointer to device memory to store CUDA-generated results, or Pointer to host memory to store CPU-generated results
- **`n`** – - Number of doubles to generate
- **`mean`** – - Mean of normal distribution
- **`stddev`** – - Standard deviation of normal distribution

Returns

- CURAND_STATUS_ALLOCATION_FAILED if memory could not be allocated
- CURAND_STATUS_NOT_INITIALIZED if the generator was never created
- CURAND_STATUS_PREEXISTING_FAILURE if there was an existing error from a previous kernel launch
- CURAND_STATUS_LAUNCH_FAILURE if the kernel launch failed for any reason
- CURAND_STATUS_LENGTH_NOT_MULTIPLE if the number of output samples is not a multiple of the quasirandom dimension, or is not a multiple of two for pseudorandom generators
- CURAND_STATUS_DOUBLE_PRECISION_REQUIRED if the GPU does not support double precision

- CURAND_STATUS_SUCCESS if the results were generated successfully

curandStatus_t **curandGenerateLongLong**(curandGenerator_t generator, unsigned long long *outputPtr, size_t num)

Generate 64-bit quasirandom numbers.

Use `generator` to generate `num` 64-bit results into the device memory at `outputPtr`. The device memory must have been previously allocated and be large enough to hold all the results. Launches are done with the stream set using *curandSetStream()*, or the null stream if no stream has been set.

Results are 64-bit values with every bit random.

Parameters

- **`generator`** – - Generator to use
- **`outputPtr`** – - Pointer to device memory to store CUDA-generated results, or Pointer to host memory to store CPU-generated results
- **`num`** – - Number of random 64-bit values to generate

Returns

- CURAND_STATUS_NOT_INITIALIZED if the generator was never created
- CURAND_STATUS_PREEXISTING_FAILURE if there was an existing error from a previous kernel launch
- CURAND_STATUS_LENGTH_NOT_MULTIPLE if the number of output samples is not a multiple of the quasirandom dimension
- CURAND_STATUS_LAUNCH_FAILURE if the kernel launch failed for any reason
- CURAND_STATUS_TYPE_ERROR if the generator is not a 64 bit quasirandom generator
- CURAND_STATUS_SUCCESS if the results were generated successfully

curandStatus_t **curandGenerateNormal**(curandGenerator_t generator, float *outputPtr, size_t n, float mean, float stddev)

Generate normally distributed doubles.

Use `generator` to generate `n` float results into the device memory at `outputPtr`. The device memory must have been previously allocated and be large enough to hold all the results. Launches are done with the stream set using *curandSetStream()*, or the null stream if no stream has been set.

Results are 32-bit floating point values with mean `mean` and standard deviation `stddev`.

Normally distributed results are generated from pseudorandom generators with a Box-Muller transform, and so require `n` to be even. Quasirandom generators use an inverse cumulative distribution function to preserve dimensionality.

There may be slight numerical differences between results generated on the GPU with generators created with *curandCreateGenerator()* and results calculated on the CPU with generators created with *curandCreateGeneratorHost()*. These differences arise because of differences in results for transcendental functions. In addition, future versions of CURAND may use newer versions of the CUDA math library, so different versions of CURAND may give slightly different numerical values.

Parameters

- **generator** – - Generator to use
- **outputPtr** – - Pointer to device memory to store CUDA-generated results, or Pointer to host memory to store CPU-generated results
- **n** – - Number of floats to generate
- **mean** – - Mean of normal distribution
- **stddev** – - Standard deviation of normal distribution

Returns

- CURAND_STATUS_ALLOCATION_FAILED if memory could not be allocated
- CURAND_STATUS_NOT_INITIALIZED if the generator was never created
- CURAND_STATUS_PREEXISTING_FAILURE if there was an existing error from a previous kernel launch
- CURAND_STATUS_LAUNCH_FAILURE if the kernel launch failed for any reason
- CURAND_STATUS_LENGTH_NOT_MULTIPLE if the number of output samples is not a multiple of the quasirandom dimension, or is not a multiple of two for pseudorandom generators
- CURAND_STATUS_SUCCESS if the results were generated successfully

curandStatus_t **curandGenerateNormalDouble**(curandGenerator_t generator, double *outputPtr, size_t n, double mean, double stddev)

Generate normally distributed doubles.

Use `generator` to generate `n` double results into the device memory at `outputPtr`. The device memory must have been previously allocated and be large enough to hold all the results. Launches are done with the stream set using *curandSetStream()*, or the null stream if no stream has been set.

Results are 64-bit floating point values with mean `mean` and standard deviation `stddev`.

Normally distributed results are generated from pseudorandom generators with a Box-Muller transform, and so require `n` to be even. Quasirandom generators use an inverse cumulative distribution function to preserve dimensionality.

There may be slight numerical differences between results generated on the GPU with generators created with *curandCreateGenerator()* and results calculated on the CPU with generators created with *curandCreateGeneratorHost()*. These differences arise because of differences in results for transcendental functions. In addition, future versions of CURAND may use newer versions of the CUDA math library, so different versions of CURAND may give slightly different numerical values.

Parameters

- **generator** – - Generator to use
- **outputPtr** – - Pointer to device memory to store CUDA-generated results, or Pointer to host memory to store CPU-generated results
- **n** – - Number of doubles to generate
- **mean** – - Mean of normal distribution

- **stddev** – - Standard deviation of normal distribution

Returns

- CURAND_STATUS_ALLOCATION_FAILED if memory could not be allocated
- CURAND_STATUS_NOT_INITIALIZED if the generator was never created
- CURAND_STATUS_PREEXISTING_FAILURE if there was an existing error from a previous kernel launch
- CURAND_STATUS_LAUNCH_FAILURE if the kernel launch failed for any reason
- CURAND_STATUS_LENGTH_NOT_MULTIPLE if the number of output samples is not a multiple of the quasirandom dimension, or is not a multiple of two for pseudorandom generators
- CURAND_STATUS_DOUBLE_PRECISION_REQUIRED if the GPU does not support double precision
- CURAND_STATUS_SUCCESS if the results were generated successfully

curandStatus_t **curandGeneratePoisson**(curandGenerator_t generator, unsigned int *outputPtr, size_t n, double lambda)

Generate Poisson-distributed unsigned ints.

Use `generator` to generate n unsigned int results into device memory at `outputPtr`. The device memory must have been previously allocated and must be large enough to hold all the results. Launches are done with the stream set using *curandSetStream()*, or the null stream if no stream has been set.

Results are 32-bit unsigned int point values with Poisson distribution, with lambda `lambda`.

Parameters

- **generator** – - Generator to use
- **outputPtr** – - Pointer to device memory to store CUDA-generated results, or Pointer to host memory to store CPU-generated results
- **n** – - Number of unsigned ints to generate
- **lambda** – - lambda for the Poisson distribution

Returns

- CURAND_STATUS_ALLOCATION_FAILED if memory could not be allocated
- CURAND_STATUS_NOT_INITIALIZED if the generator was never created
- CURAND_STATUS_PREEXISTING_FAILURE if there was an existing error from a previous kernel launch
- CURAND_STATUS_LAUNCH_FAILURE if the kernel launch failed for any reason
- CURAND_STATUS_LENGTH_NOT_MULTIPLE if the number of output samples is not a multiple of the quasirandom dimension
- CURAND_STATUS_DOUBLE_PRECISION_REQUIRED if the GPU or sm does not support double precision
- CURAND_STATUS_OUT_OF_RANGE if lambda is non-positive or greater than 400,000

- CURAND_STATUS_SUCCESS if the results were generated successfully

curandStatus_t **curandGeneratePoissonMethod**(curandGenerator_t generator, unsigned int *outputPtr, size_t n, double lambda, curandMethod_t method)

curandStatus_t **curandGenerateSeeds**(curandGenerator_t generator)

Setup starting states.

Generate the starting state of the generator. This function is automatically called by generation functions such as *curandGenerate()* and *curandGenerateUniform()*. It can be called manually for performance testing reasons to separate timings for starting state generation and random number generation.

Parameters

generator – - Generator to update

Returns

- CURAND_STATUS_ALLOCATION_FAILED if memory could not be allocated
- CURAND_STATUS_NOT_INITIALIZED if the generator was never created
- CURAND_STATUS_PREEXISTING_FAILURE if there was an existing error from a previous kernel launch
- CURAND_STATUS_LAUNCH_FAILURE if the kernel launch failed for any reason
- CURAND_STATUS_SUCCESS if the seeds were generated successfully

curandStatus_t **curandGenerateUniform**(curandGenerator_t generator, float *outputPtr, size_t num)

Generate uniformly distributed floats.

Use `generator` to generate `num` float results into the device memory at `outputPtr`. The device memory must have been previously allocated and be large enough to hold all the results. Launches are done with the stream set using *curandSetStream()*, or the null stream if no stream has been set.

Results are 32-bit floating point values between `0.0f` and `1.0f`, excluding `0.0f` and including `1.0f`.

Parameters

- **generator** – - Generator to use
- **outputPtr** – - Pointer to device memory to store CUDA-generated results, or Pointer to host memory to store CPU-generated results
- **num** – - Number of floats to generate

Returns

- CURAND_STATUS_ALLOCATION_FAILED if memory could not be allocated
- CURAND_STATUS_NOT_INITIALIZED if the generator was never created
- CURAND_STATUS_PREEXISTING_FAILURE if there was an existing error from a previous kernel launch
- CURAND_STATUS_LAUNCH_FAILURE if the kernel launch failed for any reason

- CURAND_STATUS_LENGTH_NOT_MULTIPLE if the number of output samples is not a multiple of the quasirandom dimension
- CURAND_STATUS_SUCCESS if the results were generated successfully

curandStatus_t **curandGenerateUniformDouble**(curandGenerator_t generator, double *outputPtr, size_t num)

Generate uniformly distributed doubles.

Use `generator` to generate `num` double results into the device memory at `outputPtr`. The device memory must have been previously allocated and be large enough to hold all the results. Launches are done with the stream set using *curandSetStream()*, or the null stream if no stream has been set.

Results are 64-bit double precision floating point values between `0.0` and `1.0`, excluding `0.0` and including `1.0`.

Parameters

- **generator** – - Generator to use
- **outputPtr** – - Pointer to device memory to store CUDA-generated results, or Pointer to host memory to store CPU-generated results
- **num** – - Number of doubles to generate

Returns

- CURAND_STATUS_ALLOCATION_FAILED if memory could not be allocated
- CURAND_STATUS_NOT_INITIALIZED if the generator was never created
- CURAND_STATUS_PREEXISTING_FAILURE if there was an existing error from a previous kernel launch
- CURAND_STATUS_LAUNCH_FAILURE if the kernel launch failed for any reason
- CURAND_STATUS_LENGTH_NOT_MULTIPLE if the number of output samples is not a multiple of the quasirandom dimension
- CURAND_STATUS_DOUBLE_PRECISION_REQUIRED if the GPU does not support double precision
- CURAND_STATUS_SUCCESS if the results were generated successfully

curandStatus_t **curandGetDirectionVectors32**(curandDirectionVectors32_t *vectors[], curandDirectionVectorSet_t set)

Get direction vectors for 32-bit quasirandom number generation.

Get a pointer to an array of direction vectors that can be used for quasirandom number generation. The resulting pointer will reference an array of direction vectors in host memory.

The array contains vectors for many dimensions. Each dimension has 32 vectors. Each individual vector is an unsigned int.

Legal values for `set` are:

- CURAND_DIRECTION_VECTORS_32_JOEKUO6 (20,000 dimensions)
- CURAND_SCRAMBLED_DIRECTION_VECTORS_32_JOEKUO6 (20,000 dimensions)

Parameters

- **vectors** – - Address of pointer in which to return direction vectors
- **set** – - Which set of direction vectors to use

Returns

- CURAND_STATUS_OUT_OF_RANGE if the choice of set is invalid
- CURAND_STATUS_SUCCESS if the pointer was set successfully

curandStatus_t **curandGetDirectionVectors64**(curandDirectionVectors64_t *vectors[], curandDirectionVectorSet_t set)

Get direction vectors for 64-bit quasirandom number generation.

Get a pointer to an array of direction vectors that can be used for quasirandom number generation. The resulting pointer will reference an array of direction vectors in host memory.

The array contains vectors for many dimensions. Each dimension has 64 vectors. Each individual vector is an unsigned long long.

Legal values for `set` are:

- CURAND_DIRECTION_VECTORS_64_JOEKUO6 (20,000 dimensions)
- CURAND_SCRAMBLED_DIRECTION_VECTORS_64_JOEKUO6 (20,000 dimensions)

Parameters

- **vectors** – - Address of pointer in which to return direction vectors
- **set** – - Which set of direction vectors to use

Returns

- CURAND_STATUS_OUT_OF_RANGE if the choice of set is invalid
- CURAND_STATUS_SUCCESS if the pointer was set successfully

curandStatus_t **curandGetProperty**(libraryPropertyType type, int *value)

Return the value of the curand property.

Return in `*value` the number for the property described by `type` of the dynamically linked CURAND library.

Parameters

- **type** – - CUDA library property
- **value** – - integer value for the requested property

Returns

- CURAND_STATUS_SUCCESS if the property value was successfully returned
- CURAND_STATUS_OUT_OF_RANGE if the property type is not recognized

curandStatus_t **curandGetScrambleConstants32**(unsigned int **constants)

Get scramble constants for 32-bit scrambled Sobol' .

Get a pointer to an array of scramble constants that can be used for quasirandom number generation. The resulting pointer will reference an array of unsinged ints in host memory.

The array contains constants for many dimensions. Each dimension has a single unsigned int constant.

Parameters

constants – - Address of pointer in which to return scramble constants

Returns

- CURAND_STATUS_SUCCESS if the pointer was set successfully

curandStatus_t **curandGetScrambleConstants64**(unsigned long long **constants)

Get scramble constants for 64-bit scrambled Sobol' .

Get a pointer to an array of scramble constants that can be used for quasirandom number generation. The resulting pointer will reference an array of unsinged long longs in host memory.

The array contains constants for many dimensions. Each dimension has a single unsigned long long constant.

Parameters

constants – - Address of pointer in which to return scramble constants

Returns

- CURAND_STATUS_SUCCESS if the pointer was set successfully

curandStatus_t **curandGetVersion**(int *version)

Return the version number of the library.

Return in `*version` the version number of the dynamically linked CURAND library. The format is the same as CUDART_VERSION from the CUDA Runtime. The only supported configuration is CURAND version equal to CUDA Runtime version.

Parameters

version – - CURAND library version

Returns

- CURAND_STATUS_SUCCESS if the version number was successfully returned

curandStatus_t **curandSetGeneratorOffset**(curandGenerator_t generator, unsigned long long offset)

Set the absolute offset of the pseudo or quasirandom number generator.

Set the absolute offset of the pseudo or quasirandom number generator.

All values of offset are valid. The offset position is absolute, not relative to the current position in the sequence.

Parameters

- **generator** – - Generator to modify
- **offset** – - Absolute offset position

Returns

- CURAND_STATUS_NOT_INITIALIZED if the generator was never created
- CURAND_STATUS_SUCCESS if generator offset was set successfully

curandStatus_t **curandSetGeneratorOrdering**(curandGenerator_t generator, curandOrdering_t order)

Set the ordering of results of the pseudo or quasirandom number generator.

Set the ordering of results of the pseudo or quasirandom number generator.

Legal values of `order` for pseudorandom generators are:

- CURAND_ORDERING_PSEUDO_DEFAULT
- CURAND_ORDERING_PSEUDO_BEST
- CURAND_ORDERING_PSEUDO_SEEDED
- CURAND_ORDERING_PSEUDO_LEGACY

Legal values of `order` for quasirandom generators are:

- CURAND_ORDERING_QUASI_DEFAULT

Parameters

- **generator** – - Generator to modify
- **order** – - Ordering of results

Returns

- CURAND_STATUS_NOT_INITIALIZED if the generator was never created
- CURAND_STATUS_OUT_OF_RANGE if the ordering is not valid
- CURAND_STATUS_SUCCESS if generator ordering was set successfully

curandStatus_t **curandSetPseudoRandomGeneratorSeed**(curandGenerator_t generator, unsigned long long seed)

Set the seed value of the pseudo-random number generator.

Set the seed value of the pseudorandom number generator. All values of seed are valid. Different seeds will produce different sequences. Different seeds will often not be statistically correlated with each other, but some pairs of seed values may generate sequences which are statistically correlated.

Parameters

- **generator** – - Generator to modify
- **seed** – - Seed value

Returns

- CURAND_STATUS_NOT_INITIALIZED if the generator was never created

- CURAND_STATUS_TYPE_ERROR if the generator is not a pseudorandom number generator
- CURAND_STATUS_SUCCESS if generator seed was set successfully

curandStatus_t **curandSetQuasiRandomGeneratorDimensions**(curandGenerator_t generator, unsigned int num_dimensions)

Set the number of dimensions.

Set the number of dimensions to be generated by the quasirandom number generator.

Legal values for `num_dimensions` are 1 to 20000.

Parameters

- **generator** – - Generator to modify
- **num_dimensions** – - Number of dimensions

Returns

- CURAND_STATUS_NOT_INITIALIZED if the generator was never created
- CURAND_STATUS_OUT_OF_RANGE if num_dimensions is not valid
- CURAND_STATUS_TYPE_ERROR if the generator is not a quasirandom number generator
- CURAND_STATUS_SUCCESS if generator ordering was set successfully

curandStatus_t **curandSetStream**(curandGenerator_t generator, cudaStream_t stream)

Set the current stream for CURAND kernel launches.

Set the current stream for CURAND kernel launches. All library functions will use this stream until set again.

Parameters

- **generator** – - Generator to modify
- **stream** – - Stream to use or ::NULL for null stream

Returns

- CURAND_STATUS_NOT_INITIALIZED if the generator was never created
- CURAND_STATUS_SUCCESS if stream was set successfully

Device API

Host API

Chapter 7. Structs

7.1. curandStateMRG32k3a

Defined in curand_kernel.h

struct **curandStateMRG32k3a**

Public Members

float **boxmuller_extra**

double **boxmuller_extra_double**

int **boxmuller_flag**

int **boxmuller_flag_double**

unsigned int **s1**[3]

unsigned int **s2**[3]

7.2. curandStateMtgp32

Defined in curand_mtgp32.h

struct **curandStateMtgp32**

Public Members

mtgp32_kernel_params_t ***k**

int **offset**

int **pIdx**

unsigned int **s**[1024]

7.3. curandStateScrambledSobol32

Defined in curand_kernel.h

struct **curandStateScrambledSobol32**

Public Members

unsigned int **c**

unsigned int **direction_vectors**[32]

unsigned int **i**

unsigned int **x**

7.4. curandStateScrambledSobol64

Defined in curand_kernel.h

struct **curandStateScrambledSobol64**

Public Members

unsigned long long **c**

unsigned long long **direction_vectors**[64]

unsigned long long **i**

unsigned long long **x**

7.5. curandStateSobol32

Defined in curand_kernel.h

struct **curandStateSobol32**

Public Members

unsigned int **c**

unsigned int **direction_vectors**[32]

unsigned int **i**

unsigned int **x**

7.6. curandStateSobol64

Defined in curand_kernel.h

struct **curandStateSobol64**

Public Members

unsigned long long **c**

unsigned long long **direction_vectors**[64]

unsigned long long **i**

unsigned long long **x**

7.7. curandStateTest

Defined in curand_kernel.h

struct **curandStateTest**

Public Members

unsigned int **v**

7.8. curandStateXORWOW

Defined in curand_kernel.h

struct **curandStateXORWOW**

Public Members

float **boxmuller_extra**

double **boxmuller_extra_double**

int **boxmuller_flag**

int **boxmuller_flag_double**

unsigned int **d**

unsigned int **v**[5]

7.9. mtgp32_kernel_params

Defined in curand_mtgp32.h

struct **mtgp32_kernel_params**

Public Members

unsigned int **mask**[1]

unsigned int **param_tbl**[200][16]

unsigned int **pos_tbl**[200]

unsigned int **sh1_tbl**[200]

unsigned int **sh2_tbl**[200]

unsigned int **single_temper_tbl**[200][16]

unsigned int **temper_tbl**[200][16]

7.10. mtgp32_params_fast

Defined in curand_mtgp32.h

struct **mtgp32_params_fast**

Public Members

unsigned int **flt_tmp_tbl**[16]

unsigned int **mask**

int **mexp**

unsigned char **poly_sha1**[21]

int **pos**

int **sh1**

int **sh2**

unsigned int **tbl**[16]

unsigned int **tmp_tbl**[16]

curandStateMRG32k3a

curandStateMtgp32

curandStateScrambledSobol32

curandStateScrambledSobol64

curandStateSobol32

curandStateSobol64

curandStateTest

curandStateXORWOW

curand_detail::enable_if

curand_detail::enable_if< true, T >

curand_detail::is_same

curand_detail::is_same< T, T >

mtgp32_kernel_params

mtgp32_params_fast

Chapter 8. Bibliography

[1] Mutsuo Saito. A Variant of Mersenne Twister Suitable for Graphic Processors. *arXiv:1005.4973v2 [cs.MS]*, Jun 2010.

[2] S. Joe and F. Y. Kuo. Remark on Algorithm 659: Implementing Sobol's quasirandom sequence generator. *ACM Transactions on Mathematical Software*, 29:49-57, March 2003.

[3] Jiri Matousek. Journal of Complexity. *ACM Transactions on Mathematical Software*, 14(4):527-556, December 1998.

[4] Art B. Owen. Local Antithetic Sampling with Scrambled Nets. *The Annals of Statistics*, 36(5):2319-2343, 2008.

[5] George Marsaglia. Xorshift RNGs. *Journal of Statistical Software*, 8(14), 2003. Available at http://www.jstatsoft.org/v08/i14/paper.

[6] Pierre L'Ecuyer and Richard Simard. TestU01: A C library for empirical testing of random number generators. *ACM Transactions on Mathematical Software*, 33(4), August 2007. Available at http://www.iro.umontreal.ca/~lecuyer/myftp/papers/testu01.pdf.

[7] Andrew Rukhin and Juan Soto and James Nechvatal and Miles Smid and Elaine Barker and Stefan Leigh and Mark Levenson and Mark Vangel and David Banks and Alan Heckert and James Dray and San Vo. "A Statistical Test Suite for the Validation of Random Number Generators and Pseudorandom Number Generators for Cryptographic Applications. Special Publication 800-22 Revision 1a, National Institute of Standards and Technology, April 2010. http://csrc.nist.gov/groups/ST/toolkit/rng/index.html.

[8] M. Matsumoto and T. Nishimura. Mersenne Twister: A 623-dimensionally equidistributed uniform pseudorandom number generator. *ACM Transactions on Modeling and Computer Simulation*, 8(1):3-30, January 1988.

[9] Pierre L'Ecuyer. Good Parameters and Implementations for Combined Multiple Recursive Random Number Generators. *Operations Research*, 47(1), Jan-Feb 1999.

[10] Pierre L'Ecuyer and Richard Simard and E. Jack Chen and W. David Kelton. An Object-Oriented Random-Number Package with Many Long Streams and Substreams. *Operations Research*, 50(6), Nov-Dec 2002.

[11] Karl Pearson. On the criterion that a given system of deviations from the probable in the case of a correlated system of variables is such that it can be reasonably supposed to have arisen from random sampling. *Philosophical Magazine*, 50(302):157-175, July 1900.

[12] R. L. Placket. Karl Pearson and the chi-squared test. *International Statistics Review*, 51:59-72, 1983.

[13] Carlos M. Jarque and Anil K. Bera. Efficient tests for normality, homoscedasticity and serial independence of regression residuals. *Economics Letters*, 6(3):255-259, 1980.

[14] A. Kolmogorov. Sulla determinazione empirica di una legge di distribuzione. *G. Inst. Ital. Attuari*, 4(83), 1933.

[15] Frank J. Massey. The Kolmogorov-Smirnov test for goodness of fit. *Journal of the American Statistical Association*, 46(253):68-78, 1951.

[16] T. W. Anderson and D. A. Darling. Asymptotic theory of certain “goodness-of-fit” criteria based on stochastic processes. *Annals of Mathematical Statistics*, 23(2):193-212, 1952.

[17] John. K. Salmon, Mark A. Moraes, Ron O. Dror, and David E. Shaw. Parallel Random Numbers: As Easy as 1, 2, 3 *D.E Shaw Research, New York, NY 10036, USA*, 2011.

[18] P. Trędak, C. Woolley. Efficient implementation of Mersenne Twister MT19937 Random Number Generator on the GPU *GPU Technology Conference*, 2013.

Chapter 9. Acknowledgements

NVIDIA would like to thank the following individuals and institutions for their contributions:

- Portions of the MTGP32 (Mersenne Twister for GPU) library routines were written by Mutsuo Saito and Makoto Matsumoto.
- Portions of the PHILOX4x32 library routines were developed by D. E. Shaw Research.

Chapter 10. Notices

10.1. Notice

This document is provided for information purposes only and shall not be regarded as a warranty of a certain functionality, condition, or quality of a product. NVIDIA Corporation (“NVIDIA”) makes no representations or warranties, expressed or implied, as to the accuracy or completeness of the information contained in this document and assumes no responsibility for any errors contained herein. NVIDIA shall have no liability for the consequences or use of such information or for any infringement of patents or other rights of third parties that may result from its use. This document is not a commitment to develop, release, or deliver any Material (defined below), code, or functionality.

NVIDIA reserves the right to make corrections, modifications, enhancements, improvements, and any other changes to this document, at any time without notice.

Customer should obtain the latest relevant information before placing orders and should verify that such information is current and complete.

NVIDIA products are sold subject to the NVIDIA standard terms and conditions of sale supplied at the time of order acknowledgement, unless otherwise agreed in an individual sales agreement signed by authorized representatives of NVIDIA and customer (“Terms of Sale”). NVIDIA hereby expressly objects to applying any customer general terms and conditions with regards to the purchase of the NVIDIA product referenced in this document. No contractual obligations are formed either directly or indirectly by this document.

NVIDIA products are not designed, authorized, or warranted to be suitable for use in medical, military, aircraft, space, or life support equipment, nor in applications where failure or malfunction of the NVIDIA product can reasonably be expected to result in personal injury, death, or property or environmental damage. NVIDIA accepts no liability for inclusion and/or use of NVIDIA products in such equipment or applications and therefore such inclusion and/or use is at customer’s own risk.

NVIDIA makes no representation or warranty that products based on this document will be suitable for any specified use. Testing of all parameters of each product is not necessarily performed by NVIDIA. It is customer’s sole responsibility to evaluate and determine the applicability of any information contained in this document, ensure the product is suitable and fit for the application planned by customer, and perform the necessary testing for the application in order to avoid a default of the application or the product. Weaknesses in customer’s product designs may affect the quality and reliability of the NVIDIA product and may result in additional or different conditions and/or requirements beyond those contained in this document. NVIDIA accepts no liability related to any default, damage, costs, or problem which may be based on or attributable to: (i) the use of the NVIDIA product in any manner that is contrary to this document or (ii) customer product designs.

No license, either expressed or implied, is granted under any NVIDIA patent right, copyright, or other NVIDIA intellectual property right under this document. Information published by NVIDIA regarding third-party products or services does not constitute a license from NVIDIA to use such products or

services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property rights of the third party, or a license from NVIDIA under the patents or other intellectual property rights of NVIDIA.

Reproduction of information in this document is permissible only if approved in advance by NVIDIA in writing, reproduced without alteration and in full compliance with all applicable export laws and regulations, and accompanied by all associated conditions, limitations, and notices.

THIS DOCUMENT AND ALL NVIDIA DESIGN SPECIFICATIONS, REFERENCE BOARDS, FILES, DRAWINGS, DIAGNOSTICS, LISTS, AND OTHER DOCUMENTS (TOGETHER AND SEPARATELY, "MATERIALS") ARE BEING PROVIDED "AS IS." NVIDIA MAKES NO WARRANTIES, EXPRESSED, IMPLIED, STATUTORY, OR OTHERWISE WITH RESPECT TO THE MATERIALS, AND EXPRESSLY DISCLAIMS ALL IMPLIED WARRANTIES OF NONINFRINGEMENT, MERCHANTABILITY, AND FITNESS FOR A PARTICULAR PURPOSE. TO THE EXTENT NOT PROHIBITED BY LAW, IN NO EVENT WILL NVIDIA BE LIABLE FOR ANY DAMAGES, INCLUDING WITHOUT LIMITATION ANY DIRECT, INDIRECT, SPECIAL, INCIDENTAL, PUNITIVE, OR CONSEQUENTIAL DAMAGES, HOWEVER CAUSED AND REGARDLESS OF THE THEORY OF LIABILITY, ARISING OUT OF ANY USE OF THIS DOCUMENT, EVEN IF NVIDIA HAS BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES. Notwithstanding any damages that customer might incur for any reason whatsoever, NVIDIA's aggregate and cumulative liability towards customer for the products described herein shall be limited in accordance with the Terms of Sale for the product.

10.2. OpenCL

OpenCL is a trademark of Apple Inc. used under license to the Khronos Group Inc.

10.3. Trademarks

NVIDIA and the NVIDIA logo are trademarks or registered trademarks of NVIDIA Corporation in the U.S. and other countries. Other company and product names may be trademarks of the respective companies with which they are associated.

Copyright

©2007-2026, NVIDIA Corporation & affiliates. All rights reserved