



NVIDIA BlueField-2 DPU Firmware Release Notes v24.35.4506 LTS

Table of contents

Firmware Compatible Products	4
Changes and New Features	28
Bug Fixes in this Firmware Version	29
Known Issues	31
PreBoot Drivers (FlexBoot/UEFI)	35
Release Notes History	36
Changes and New Feature History	36
Bug Fixes History	42
Legal Notices and 3rd Party Licenses	49

Info

This is a long-term support (LTS) release. LTS is the practice of maintaining a software product for an extended period of time (up to three years) to help increase product stability. LTS releases include bug fixes and security patches.

Release Notes Update History

Revision	Date	Description
24.35.4506	December 31, 2024	Initial release of this Release Notes version, This version introduces Bug Fixes .

Overview

Firmware which is added at the time of manufacturing, is used to run user programs on the device and can be thought of as the software that allows hardware to run. Embedded firmware is used to control the functions of various hardware devices and systems, much like a computer's operating system (OS) controls the function of software applications. Firmware may be written into read-only memory (ROM), erasable programmable read-only memory (EPROM) or flash memory.

NVIDIA BlueField-2 DPU provides innovative acceleration, security, and efficiency in every host. BlueField-2 data center infrastructure combines the power of the NVIDIA ConnectX®-6 Dx with programmable Arm® cores and hardware offloads for software-defined storage, networking, security, and management workloads.

NVIDIA BlueField-2 also delivers superior performance, security, and reduced TCO for cloud computing platforms, enabling organizations to efficiently build and operate virtualized, containerized, and bare-metal infrastructures at massive scale.

Firmware Download

Please visit [Firmware Downloads](#).

Document Revision History

A list of the changes made to this document are provided in [Document Revision History](#).

Firmware Compatible Products

These are the release notes for the NVIDIA® BlueField-2 SmartNICs firmware. This firmware supports the following protocols:

- InfiniBand - QDR, FDR, EDR, HDR100, HDR
- Ethernet - 1GbE, 10GbE, 25GbE, 40GbE, 50GbE¹, 100GbE¹, 200GbE²
- PCI Express 4.0, supporting backwards compatibility for v3.0, v2.0 and v1.1

¹. Speed that supports both NRZ and PAM4 modes in Force mode and Auto-Negotiation mode.

². Speed that supports PAM4 mode only.

Supported Devices

NVIDIA SKU	Legacy OPN	PSID	Description
P1004/699210040230	N/A	NVD000000015	BlueField-2 A30X; P1004 SKU 205; Generic; GA100; 24GB HBM2e; PCIe passive Dual Slot 230W GEN4; DPU Crypto ON W/ Bkt; 1 Dongle; Black; HF; VCPD
900-9D219-0086-ST1	MBF2 M516A - CECOT	MT_000000375	BlueField-2 E-Series DPU 100GbE Dual-Port QSFP56; PCIe Gen4 x16; Crypto and Secure Boot Enabled; 16GB on-board DDR; 1GbE OOB management; FHHL
900-9D219-0086-ST0	MBF2 M516A -EECOT	MT_000000376	BlueField-2 E-Series DPU 100GbE/EDR/HDR100 VPI Dual-Port QSFP56; PCIe Gen4 x16; Crypto and Secure Boot Enabled; 16GB on-board DDR; 1GbE OOB management; FHHL
900-9D219-	MBF2 M516A	MT_0000	BlueField-2 E-Series DPU 100GbE/EDR/HDR100 VPI Dual-Port QSFP56; PCIe Gen4 x16; Crypto Disabled; 16GB on-board

NVIDIA SKU	Legacy OPN	PSID	Description
0056-ST1	- EENOT	00377	DDR; 1GbE OOB management; FHHL
900-9D206-0053-SQ0	MBF2 H332A - AENOT	MT_000000539	BlueField-2 P-Series DPU 25GbE Dual-Port SFP56; PCIe Gen4 x8; Crypto Disabled; 16GB on-board DDR; 1GbE OOB management; HHHH
900-9D206-0063-ST2	MBF2 H332A -AEEOT	MT_000000540	BlueField-2 P-Series DPU 25GbE Dual-Port SFP56; PCIe Gen4 x8; Crypto Enabled; 16GB on-board DDR; 1GbE OOB management; HHHH
900-9D206-0083-ST3	MBF2 H332A - AECOT	MT_000000541	BlueField-2 P-Series DPU 25GbE Dual-Port SFP56; PCIe Gen4 x8; Crypto and Secure Boot Enabled; 16GB on-board DDR; 1GbE OOB management; HHHH
900-9D219-0066-ST0	MBF2 M516A -EEEOT	MT_000000559	BlueField-2 E-Series DPU 100GbE/EDR/HDR100 VPI Dual-Port QSFP56; PCIe Gen4 x16; Crypto Enabled; 16GB on-board DDR; 1GbE OOB management; FHHL
900-9D219-0056-SN1	MBF2 M516A - CENOT	MT_000000560	BlueField-2 E-Series DPU 100GbE Dual-Port QSFP56; PCIe Gen4 x16; Crypto Disabled; 16GB on-board DDR; 1GbE OOB management; FHHL
900-9D219-0066-ST2	MBF2 M516A -CEEOT	MT_000000561	BlueField-2 E-Series DPU 100GbE Dual-Port QSFP56; PCIe Gen4 x16; Crypto Enabled; 16GB on-board DDR; 1GbE OOB management; FHHL
900-9D219-0006-ST0	MBF2 H516A -CEEOT	MT_000000702	BlueField-2 DPU 100GbE Dual-Port QSFP56; PCIe Gen4 x16; Crypto; 16GB on-board DDR; 1GbE OOB management; FHHL
900-9D219-0056-ST2	MBF2 H516A - CENOT	MT_000000703	BlueField-2 DPU 100GbE Dual-Port QSFP56; PCIe Gen4 x16; Crypto Disabled; 16GB on-board DDR; 1GbE OOB management; FHHL
900-9D219-	MBF2 H516A -EEEOT	MT_0000	BlueField-2 DPU 100GbE/EDR/HDR100 VPI Dual-Port QSFP56; PCIe Gen4 x16; Crypto Enabled; 16GB on-board DDR; 1GbE OOB management; FHHL

NVIDIA SKU	Legacy OPN	PSID	Description
0066-ST3		00704	
900-9D219-0056-SQ0	MBF2 H516A - EENOT	MT_000000705	BlueField-2 DPU 100GbE/EDR/HDR100 VPI Dual-Port QSFP56; PCIe Gen4 x16; Crypto Disabled; 16GB on-board DDR; 1GbE OOB management; FHHL
900-9D250-0038-ST1	MBF2 M345A - HESOT	MT_000000715	BlueField-2 E-Series DPU; 200GbE/HDR single-port QSFP56; PCIe Gen4 x16; Secure Boot Enabled; Crypto Disabled; 16GB on-board DDR; 1GbE OOB management; HHHL
900-9D250-0048-ST1	MBF2 M345A - HECOT	MT_000000716	BlueField-2 E-Series DPU; 200GbE/HDR single-port QSFP56; PCIe Gen4 x16; Secure Boot Enabled; Crypto Enabled; 16GB on-board DDR; 1GbE OOB management; HHHL
900-9D218-0073-ST1	MBF2 H512C - AESOT	MT_000000723	BlueField-2 P-Series DPU 25GbE Dual-Port SFP56; integrated BMC; PCIe Gen4 x8; Secure Boot Enabled; Crypto Disabled; 16GB on-board DDR; 1GbE OOB management; FHHL
900-9D218-0083-ST2	MBF2 H512C - AECOT	MT_000000724	BlueField-2 P-Series DPU 25GbE Dual-Port SFP56; integrated BMC; PCIe Gen4 x8; Secure Boot Enabled; Crypto Enabled; 16GB on-board DDR; 1GbE OOB management; FHHL
900-9D208-0086-ST4	MBF2 M516C -EECOT	MT_000000728	BlueField-2 E-Series DPU 100GbE/EDR/HDR100 VPI Dual-Port QSFP56; integrated BMC; PCIe Gen4 x16; Secure Boot Enabled; Crypto Enabled; 16GB on-board DDR; 1GbE OOB management; Tall Bracket; FHHL
900-9D208-0086-SQ0	MBF2 H516C - CECOT	MT_000000729	BlueField-2 P-Series DPU 100GbE Dual-Port QSFP56; integrated BMC; PCIe Gen4 x16; Secure Boot Enabled; Crypto Enabled; 16GB on-board DDR; 1GbE OOB management; Tall Bracket; FHHL
900-9D208-0076-ST5	MBF2 M516C - CESOT	MT_000000731	BlueField-2 E-Series DPU 100GbE Dual-Port QSFP56; integrated BMC; PCIe Gen4 x16; Secure Boot Enabled; Crypto Disabled; 16GB on-board DDR; 1GbE OOB management; Tall Bracket; FHHL
900-9D208-	MBF2 M516C -EESOT	MT_0000	BlueField-2 E-Series DPU 100GbE/EDR/HDR100 VPI Dual-Port QSFP56; integrated BMC; PCIe Gen4 x16; Secure Boot

NVIDIA SKU	Legacy OPN	PSID	Description
0076-ST6		00732	Enabled; Crypto Disabled; 16GB on-board DDR; 1GbE OOB management; Tall Bracket; FHHL
900-9D208-0086-ST3	MBF2 M516C - CECOT	MT_000000733	BlueField-2 E-Series DPU 100GbE Dual-Port QSFP56; integrated BMC; PCIe Gen4 x16; Secure Boot Enabled; Crypto Enabled; 16GB on-board DDR; 1GbE OOB management; Tall Bracket; FHHL
900-9D208-0076-ST2	MBF2 H516C -EESOT	MT_000000737	BlueField-2 P-Series DPU 100GbE/EDR/HDR100 VPI Dual-Port QSFP56; integrated BMC; PCIe Gen4 x16; Secure Boot Enabled; Crypto Disabled; 16GB on-board DDR; 1GbE OOB management; Tall Bracket; FHHL
900-9D208-0076-ST1	MBF2 H516C - CESOT	MT_000000738	BlueField-2 P-Series DPU 100GbE Dual-Port QSFP56; integrated BMC; PCIe Gen4 x16; Secure Boot Enabled; Crypto Disabled; 16GB on-board DDR; 1GbE OOB management; Tall Bracket; FHHL
900-9D218-0083-ST4	MBF2 H532C - AECOT	MT_000000765	BlueField-2 P-Series DPU 25GbE Dual-Port SFP56; integrated BMC; PCIe Gen4 x8; Secure Boot Enabled; Crypto Enabled; 32GB on-board DDR; 1GbE OOB management; FHHL
900-9D218-0073-ST0	MBF2 H532C - AESOT	MT_000000766	BlueField-2 P-Series DPU 25GbE Dual-Port SFP56; integrated BMC; PCIe Gen4 x8; Secure Boot Enabled; Crypto Disabled; 32GB on-board DDR; 1GbE OOB management; FHHL
900-9D208-0076-ST3	MBF2 H536C - CESOT	MT_000000767	BlueField-2 P-Series DPU 100GbE Dual-Port QSFP56; integrated BMC; PCIe Gen4 x16; Secure Boot Enabled; Crypto Disabled; 32GB on-board DDR; 1GbE OOB management; FHHL
900-9D208-0086-ST2	MBF2 H536C - CECOT	MT_000000768	BlueField-2 P-Series DPU 100GbE Dual-Port QSFP56; integrated BMC; PCIe Gen4 x16; Secure Boot Enabled; Crypto Enabled; 32GB on-board DDR; 1GbE OOB management; FHHL
900-9D250-0048-ST0	MBF2 M355A -VECOT	MT_000000786	BlueField-2 E-Series DPU; 200GbE single-port QSFP56; PCIe Gen4 x16; Secure Boot Enabled; Crypto Enabled; 32GB on-board DDR; 1GbE OOB management
900-9D250-	MBF2 M355A -VESOT	MT_0000	BlueField-2 E-Series DPU; 200GbE single-port QSFP56; PCIe Gen4 x16; Secure Boot Enabled; Crypto Disabled; 32GB on-board DDR; 1GbE OOB management

NVIDIA SKU	Legacy OPN	PSID	Description
0038-ST3		00787	
900-9D218-0073-ST4	MBF2 H512C - AEUOT	MT_0 0000 0097 2	BlueField-2 P-Series DPU 25GbE Dual-Port SFP56; integrated BMC; PCIe Gen4 x8; Secure Boot Enabled with UEFI disabled; Crypto Disabled; 16GB on-board DDR; 1GbE OOB management
900-9D208-0076-STA	MBF2 H516C - CEUOT	MT_0 0000 0097 3	BlueField-2 P-Series DPU 100GbE Dual-Port QSFP56; integrated BMC; PCIe Gen4 x16; Secure Boot Enabled with UEFI disabled; Crypto Disabled; 16GB on-board DDR; 1GbE OOB management
900-9D208-0076-STB	MBF2 H536C - CEUOT	MT_0 0000 0100 8	BlueField®-2 P-Series DPU 100GbE Dual-Port QSFP56; integrated BMC; PCIe Gen4 x16; Secure Boot Enabled with UEFI Disabled; Crypto Disabled; 32GB on-board DDR; 1GbE OOB management; Tall Bracket; FHHL

Note

Please be aware that not all firmware binaries contain FlexBoot or UEFI, support may vary between cards.

Driver Software, Tools and Switch Firmware

The following are the drivers' software, tools, switch/HCA firmware versions tested that you can upgrade from or downgrade to when using this firmware version:

	Supported Version
NVIDIA BlueField-2 Firmware	24.35.4030 / 24.35.3502 / 24.35.3006
BlueField DPU OS Software	3.9.7
MLNX_OFED	5.8-5.1.1.2 / 5.8-4.1.5.0 / 5.8-3.0.7.0 Note: For the list of the supported Operating Systems, please refer to the driver's Release Notes.

	Supported Version
MLNX_EN (MLNX_OFED based code)	5.8-5.1.1.2 / 5.8-4.1.5.0 / 5.8-3.0.7.0 Note: For the list of the supported Operating Systems, please refer to the driver's Release Notes.
WinOF-2	3.10.52010 / 3.10.51000 / 3.10.50000 Note: For the list of the supported Operating Systems, please refer to the driver's Release Notes.
MFT	4.22.1-417 / 4.22.1-406 / 4.22.1-307 Note: For the list of the supported Operating Systems, please refer to the driver's Release Notes.
FlexBoot	3.6.902 Note: Please be aware that not all firmware binaries contain FlexBoot or UEFI, support may vary between cards.
UEFI	14.29.15 Note: Please be aware that not all firmware binaries contain FlexBoot or UEFI, support may vary between cards.
MLNX-OS	3.10.5002 onwards
Cumulus	5.4 onwards
NVIDIA Quantum-2 Firmware	31.2010.5108 onwards
NVIDIA Quantum Firmware	27.2010.5108 onwards

Validated and Supported Cables and Modules

Validated and Supported 100GbE Cables

Speed	Part Number	Marketing Description
100 GbE	MCP1600-C001	NVIDIA passive copper cable, ETH 100GbE, 100Gb/s, QSFP, PVC, 1m 30AWG
100 GbE	MCP1600-C001E30N	NVIDIA passive copper cable, ETH 100GbE, 100Gb/s, QSFP28, 1m, black, 30AWG, CA-N
100 GbE	MCP1600-C001LZ	NVIDIA passive copper Cable, ETH 100GbE, 100Gb/s, QSFP, 1m, LSZH, 30AWG

Speed	Part Number	Marketing Description
100 GbE	MCP1600-C002	NVIDIA passive copper cable, ETH 100GbE, 100Gb/s, QSFP, PVC, 2m 30AWG
100 GbE	MCP1600-C002E30N	NVIDIA passive copper cable, ETH 100GbE, 100Gb/s, QSFP28, 2m, black, 30AWG, CA-N
100 GbE	MCP1600-C003	NVIDIA passive copper cable, ETH 100GbE, 100Gb/s, QSFP, PVC, 3m 28AWG
100 GbE	MCP1600-C003E26N	NVIDIA passive copper cable, ETH 100GbE, 100Gb/s, QSFP28, 3m, black, 26AWG, CA-N
100 GbE	MCP1600-C003E30L	NVIDIA passive copper cable, ETH 100GbE, 100Gb/s, QSFP28, 3m, black, 30AWG, CA-L
100 GbE	MCP1600-C003LZ	NVIDIA passive copper cable, ETH 100GbE, 100Gb/s, QSFP, 3m, LSZH, 26AWG
100 GbE	MCP1600-C005AM	NVIDIA passive copper cable, ETH 100GbE, 100Gb/s, QSFP, 5m, 26AWG
100 GbE	MCP1600-C005E26L	NVIDIA passive copper cable, ETH 100GbE, 100Gb/s, QSFP28, 5m, black, 26AWG, CA-L
100 GbE	MCP1600-C00A	NVIDIA passive copper cable, ETH 100GbE, 100Gb/s, QSFP, PVC, 0.5m 30AWG
100 GbE	MCP1600-C00AE30N	NVIDIA passive copper cable, ETH 100GbE, 100Gb/s, QSFP28, 0.5m, black, 30AWG, CA-N
100 GbE	MCP1600-C00BE30N	NVIDIA passive copper cable, ETH 100GbE, 100Gb/s, QSFP28, 0.75m, black, 30AWG, CA-N
100 GbE	MCP1600-C01A	NVIDIA passive copper cable, ETH 100GbE, 100Gb/s, QSFP, PVC, 1.5m 30AWG
100 GbE	MCP1600-C01AE30N	NVIDIA passive copper cable, ETH 100GbE, 100Gb/s, QSFP28, 1.5m, black, 30AWG, CA-N
100 GbE	MCP1600-C02A	NVIDIA passive copper cable, ETH 100GbE, 100Gb/s, QSFP, PVC, 2.5m 30AWG
100 GbE	MCP1600-C02AE26N	NVIDIA passive copper cable, ETH 100GbE, 100Gb/s, QSFP28, 2.5m, black, 26AWG, CA-N
100 GbE	MCP1600-C02AE30L	NVIDIA passive copper cable, ETH 100GbE, 100Gb/s, QSFP28, 2.5m, black, 30AWG, CA-L

Speed	Part Number	Marketing Description
100 GbE	MCP1600-C03A	NVIDIA passive copper cable, ETH 100GbE, 100Gb/s, QSFP, PVC, 3.5m 26AWG
100 GbE	MCP1600-E001	NVIDIA passive copper cable, IB EDR, up to 100Gb/s, QSFP, LSZH, 1m 30AWG
100 GbE	MCP1600-E002	NVIDIA passive copper cable, IB EDR, up to 100Gb/s, QSFP, LSZH, 2m 28AWG
100 GbE	MCP1600-E003	NVIDIA passive copper cable, IB EDR, up to 100Gb/s, QSFP, LSZH, 3m 26AWG
100 GbE	MCP1600-E01A	NVIDIA passive copper cable, IB EDR, up to 100Gb/s, QSFP, LSZH, 1.5m 30AWG
100 GbE	MCP1600-E02A	NVIDIA passive copper cable, IB EDR, up to 100Gb/s, QSFP, LSZH, 2.5m 26AWG
100 GbE	MCP7F00-A001R	NVIDIA passive copper hybrid cable, ETH 100GbE to 4x25GbE, QSFP28 to 4xSFP28, colored pull-tabs, 1m, 30AWG
100 GbE	MCP7F00-A001R30N	NVIDIA passive copper hybrid cable, ETH 100GbE to 4x25GbE, QSFP28 to 4xSFP28, 1m, colored, 30AWG, CA-N
100 GbE	MCP7F00-A002R	NVIDIA passive copper hybrid cable, ETH 100GbE to 4x25GbE, QSFP28 to 4xSFP28, colored pull-tabs, 2m, 30AWG
100 GbE	MCP7F00-A002R30N	NVIDIA passive copper hybrid cable, ETH 100GbE to 4x25GbE, QSFP28 to 4xSFP28, 2m, colored, 30AWG, CA-N
100 GbE	MCP7F00-A003R26N	NVIDIA passive copper hybrid cable, ETH 100GbE to 4x25GbE, QSFP28 to 4xSFP28, 3m, colored, 26AWG, CA-N
100 GbE	MCP7F00-A003R30L	NVIDIA passive copper hybrid cable, ETH 100GbE to 4x25GbE, QSFP28 to 4xSFP28, 3m, colored, 30AWG, CA-L
100 GbE	MCP7F00-A005R26L	NVIDIA passive copper hybrid cable, ETH 100GbE to 4x25GbE, QSFP28 to 4xSFP28, 5m, colored, 26AWG, CA-L
100 GbE	MCP7F00-A01AR	NVIDIA passive copper hybrid cable, ETH 100GbE to 4x25GbE, QSFP28 to 4xSFP28, colored pull-tabs, 1.5m, 30AWG
100 GbE	MCP7F00-A01AR30N	NVIDIA passive copper hybrid cable, ETH 100GbE to 4x25GbE, QSFP28 to 4xSFP28, 1.5m, colored, 30AWG, CA-N
100 GbE	MCP7F00-A02AR26N	NVIDIA passive copper hybrid cable, ETH 100GbE to 4x25GbE, QSFP28 to 4xSFP28, 2.5m, colored, 26AWG, CA-N

Speed	Part Number	Marketing Description
100 GbE	MCP7F00-A02AR30L	NVIDIA passive copper hybrid cable, ETH 100GbE to 4x25GbE, QSFP28 to 4xSFP28, 2.5m, colored, 30AWG, CA-L
100 GbE	MCP7F00-A02ARLZ	NVIDIA passive copper hybrid cable, ETH 100GbE to 4x25GbE, QSFP28 to 4xSFP28, 2.5m, LSZH, colored, 28AWG
100 GbE	MCP7F00-A03AR26L	NVIDIA passive copper hybrid cable, ETH 100GbE to 4x25GbE, QSFP28 to 4xSFP28, 3.5m, colored, 26AWG, CA-L
100 GbE	MCP7H00-G001	NVIDIA passive copper hybrid cable, ETH 100Gb/s to 2x50Gb/s, QSFP28 to 2xQSFP28, 1m, 30AWG
100 GbE	MCP7H00-G001R	NVIDIA passive copper hybrid cable, ETH 100Gb/s to 2x50Gb/s, QSFP28 to 2xQSFP28, colored pull-tabs, 1m, 30AWG
100 GbE	MCP7H00-G001R30N	NVIDIA passive copper hybrid cable, ETH 100Gb/s to 2x50Gb/s, QSFP28 to 2xQSFP28, 1m, colored, 30AWG, CA-N
100 GbE	MCP7H00-G002R	NVIDIA passive copper hybrid cable, ETH 100Gb/s to 2x50Gb/s, QSFP28 to 2xQSFP28, colored pull-tabs, 2m, 30AWG
100 GbE	MCP7H00-G002R30N	NVIDIA passive copper hybrid cable, ETH 100Gb/s to 2x50Gb/s, QSFP28 to 2xQSFP28, 2m, colored, 30AWG, CA-N
100 GbE	MCP7H00-G003R	NVIDIA passive copper hybrid cable, ETH 100Gb/s to 2x50Gb/s, QSFP28 to 2xQSFP28, colored pull-tabs, 3m, 28AWG
100 GbE	MCP7H00-G003R26N	NVIDIA passive copper hybrid cable, ETH 100Gb/s to 2x50Gb/s, QSFP28 to 2xQSFP28, 3m, colored, 26AWG, CA-N
100 GbE	MCP7H00-G003R30L	NVIDIA passive copper hybrid cable, ETH 100Gb/s to 2x50Gb/s, QSFP28 to 2xQSFP28, 3m, colored, 30AWG, CA-L
100 GbE	MCP7H00-G004R26L	NVIDIA passive copper hybrid cable, ETH 100Gb/s to 2x50Gb/s, QSFP28 to 2xQSFP28, 4m, colored, 26AWG, CA-L
100 GbE	MCP7H00-G01AR	NVIDIA passive copper hybrid cable, ETH 100Gb/s to 2x50Gb/s, QSFP28 to 2xQSFP28, colored pull-tabs, 1.5m, 30AWG
100 GbE	MCP7H00-G01AR30N	NVIDIA passive copper hybrid cable, ETH 100Gb/s to 2x50Gb/s, QSFP28 to 2xQSFP28, 1.5m, colored, 30AWG, CA-N
100 GbE	MCP7H00-G02AR	NVIDIA passive copper hybrid cable, ETH 100Gb/s to 2x50Gb/s, QSFP28 to 2xQSFP28, colored pull-tabs, 2.5m, 30AWG
100 GbE	MCP7H00-G02AR26N	NVIDIA passive copper hybrid cable, ETH 100Gb/s to 2x50Gb/s, QSFP28 to 2xQSFP28, 2.5m, colored, 26AWG, CA-N

Speed	Part Number	Marketing Description
100 GbE	MCP7H00-G02AR30L	NVIDIA passive copper hybrid cable, ETH 100Gb/s to 2x50Gb/s, QSFP28 to 2xQSFP28, 2.5m, colored, 30AWG, CA-L
100 GbE	MFA1A00-C003	NVIDIA active fiber cable, ETH 100GbE, 100Gb/s, QSFP, LSZH, 3m
100 GbE	MFA1A00-C005	NVIDIA active fiber cable, ETH 100GbE, 100Gb/s, QSFP, LSZH, 5m
100 GbE	MFA1A00-C010	NVIDIA active fiber cable, ETH 100GbE, 100Gb/s, QSFP, LSZH, 10m
100 GbE	MFA1A00-C015	NVIDIA active fiber cable, ETH 100GbE, 100Gb/s, QSFP, LSZH, 15m
100 GbE	MFA1A00-C020	NVIDIA active fiber cable, ETH 100GbE, 100Gb/s, QSFP, LSZH, 20m
100 GbE	MFA1A00-C030	NVIDIA active fiber cable, ETH 100GbE, 100Gb/s, QSFP, LSZH, 30m
100 GbE	MFA1A00-C050	NVIDIA active fiber cable, ETH 100GbE, 100Gb/s, QSFP, LSZH, 50m
100 GbE	MFA1A00-C100	NVIDIA active fiber cable, ETH 100GbE, 100Gb/s, QSFP, LSZH, 100m
100 GbE	MFA7A20-C003	NVIDIA active fiber hybrid solution, ETH 100GbE to 2x50GbE, QSFP28 to 2xQSFP28, 3m
100 GbE	MFA7A20-C005	NVIDIA active fiber hybrid solution, ETH 100GbE to 2x50GbE, QSFP28 to 2xQSFP28, 5m
100 GbE	MFA7A20-C010	NVIDIA active fiber hybrid solution, ETH 100GbE to 2x50GbE, QSFP28 to 2xQSFP28, 10m
100 GbE	MFA7A20-C020	NVIDIA active fiber hybrid solution, ETH 100GbE to 2x50GbE, QSFP28 to 2xQSFP28, 20m
100 GbE	MFA7A50-C003	NVIDIA active fiber hybrid solution, ETH 100GbE to 4x25GbE, QSFP28 to 4xSFP28, 3m
100 GbE	MFA7A50-C005	NVIDIA active fiber hybrid solution, ETH 100GbE to 4x25GbE, QSFP28 to 4xSFP28, 5m
100 GbE	MFA7A50-C010	NVIDIA active fiber hybrid solution, ETH 100GbE to 4x25GbE, QSFP28 to 4xSFP28, 10m

Speed	Part Number	Marketing Description
100 GbE	MFA7A50-C015	NVIDIA active fiber hybrid solution, ETH 100GbE to 4x25GbE, QSFP28 to 4xSFP28, 15m
100 GbE	MFA7A50-C020	NVIDIA active fiber hybrid solution, ETH 100GbE to 4x25GbE, QSFP28 to 4xSFP28, 20m
100 GbE	MFA7A50-C030	NVIDIA active fiber hybrid solution, ETH 100GbE to 4x25GbE, QSFP28 to 4xSFP28, 30m
100 GbE	MMA1B00-C100D	NVIDIA transceiver, 100GbE, QSFP28, MPO, 850nm, SR4, up to 100m, DDMI
100 GbE	MMA1B00-C100D_FF	NVIDIA transceiver, 100GbE, QSFP28, MPO, 850nm, SR4, up to 100m, DDMI
100 GbE	MMA1L10-CR	NVIDIA optical transceiver, 100GbE, 100Gb/s, QSFP28, LC-LC, 1310nm, LR4 up to 10km
100 GbE	MMA1L30-CM	NVIDIA optical module, 100GbE, 100Gb/s, QSFP28, LC-LC, 1310nm, CWDM4, up to 2km
100 GbE	MMS1C10-CM	NVIDIA active optical module, 100Gb/s, QSFP, MPO, 1310nm, PSM4, up to 500m

Validated and Supported 56GbE Cables

Speed	Part Number	Marketing Description
56GbE	MC2207126-004	NVIDIA passive copper cable, VPI, up to 56Gb/s, QSFP, 4m
56GbE	MC2207128-003	NVIDIA passive copper cable, VPI, up to 56Gb/s, QSFP, 3m
56GbE	MC2207128-0A2	NVIDIA passive copper cable, VPI, up to 56Gb/s, QSFP, 2.5m
56GbE	MC2207130-001	NVIDIA passive copper cable, VPI, up to 56Gb/s, QSFP, 1m
56GbE	MC2207130-002	NVIDIA passive copper cable, VPI, up to 56Gb/s, QSFP, 2m

Speed	Part Number	Marketing Description
56GbE	MC2207130-00A	NVIDIA passive copper cable, VPI, up to 56Gb/s, QSFP, 0.5m
56GbE	MC2207130-0A1	NVIDIA passive copper cable, VPI, up to 56Gb/s, QSFP, 1.5m
56GbE	MC220731V-003	NVIDIA active fiber cable, VPI, up to 56Gb/s, QSFP, 3m
56GbE	MC220731V-005	NVIDIA active fiber cable, VPI, up to 56Gb/s, QSFP, 5m
56GbE	MC220731V-010	NVIDIA active fiber cable, VPI, up to 56Gb/s, QSFP, 10m
56GbE	MC220731V-015	NVIDIA active fiber cable, VPI, up to 56Gb/s, QSFP, 15m
56GbE	MC220731V-020	NVIDIA active fiber cable, VPI, up to 56Gb/s, QSFP, 20m
56GbE	MC220731V-025	NVIDIA active fiber cable, VPI, up to 56Gb/s, QSFP, 25m
56GbE	MC220731V-030	NVIDIA active fiber cable, VPI, up to 56Gb/s, QSFP, 30m
56GbE	MC220731V-040	NVIDIA active fiber cable, VPI, up to 56Gb/s, QSFP, 40m
56GbE	MC220731V-050	NVIDIA active fiber cable, VPI, up to 56Gb/s, QSFP, 50m
56GbE	MC220731V-075	NVIDIA active fiber cable, VPI, up to 56Gb/s, QSFP, 75m
56GbE	MC220731V-100	NVIDIA active fiber cable, VPI, up to 56Gb/s, QSFP, 100m
56GbE	MCP1700-F001C	NVIDIA passive copper cable, VPI, up to 56Gb/s, QSFP, 1m, Red pull-tab
56GbE	MCP1700-F001D	NVIDIA passive copper cable, VPI, up to 56Gb/s, QSFP, 1m, Yellow pull-tab
56GbE	MCP1700-F002C	NVIDIA passive copper cable, VPI, up to 56Gb/s, QSFP, 2m, Red pull-tab

Speed	Part Number	Marketing Description
56GbE	MCP1700-F002D	NVIDIA passive copper cable, VPI, up to 56Gb/s, QSFP, 2m, Yellow pull-tab
56GbE	MCP1700-F003C	NVIDIA passive copper cable, VPI, up to 56Gb/s, QSFP, 3m, Red pull-tab
56GbE	MCP1700-F003D	NVIDIA passive copper cable, VPI, up to 56Gb/s, QSFP, 3m, Yellow pull-tab
56GbE	MCP170L-F001	NVIDIA passive copper cable, VPI, up to 56Gb/s, QSFP, LSZH, 1m
56GbE	MCP170L-F002	NVIDIA passive copper cable, VPI, up to 56Gb/s, QSFP, LSZH, 2m
56GbE	MCP170L-F003	NVIDIA passive copper cable, VPI, up to 56Gb/s, QSFP, LSZH, 3m
56GbE	MCP170L-F00A	NVIDIA passive copper cable, VPI, up to 56Gb/s, QSFP, LSZH, 0.5m
56GbE	MCP170L-F01A	NVIDIA passive copper cable, VPI, up to 56Gb/s, QSFP, LSZH, 1.5m

Validated and Supported 40GbE Cables

Speed	Part Number	Marketing Description
40GbE	MC2206128-004	NVIDIA passive copper cable, VPI, up to 40Gb/s, QSFP, 4m
40GbE	MC2206128-005	NVIDIA passive copper cable, VPI, up to 40Gb/s, QSFP, 5m
40GbE	MC2206130-001	NVIDIA passive copper cable, VPI, up to 40Gb/s, QSFP, 1m
40GbE	MC2206130-002	NVIDIA passive copper cable, VPI, up to 40Gb/s, QSFP, 2m
40GbE	MC2206130-003	NVIDIA passive copper cable, VPI, up to 40Gb/s, QSFP, 3m

Speed	Part Number	Marketing Description
40GbE	MC2206130-00A	NVIDIA passive copper cable, VPI, up to 40Gb/s, QSFP, 0.5m
40GbE	MC2210126-004	NVIDIA passive copper cable, ETH 40GbE, 40Gb/s, QSFP, 4m
40GbE	MC2210126-005	NVIDIA passive copper cable, ETH 40GbE, 40Gb/s, QSFP, 5m
40GbE	MC2210128-003	NVIDIA passive copper cable, ETH 40GbE, 40Gb/s, QSFP, 3m
40GbE	MC2210130-001	NVIDIA passive copper cable, ETH 40GbE, 40Gb/s, QSFP, 1m
40GbE	MC2210130-002	NVIDIA passive copper cable, ETH 40GbE, 40Gb/s, QSFP, 2m
40GbE	MC2210310-003	NVIDIA active fiber cable, ETH 40GbE, 40Gb/s, QSFP, 3m
40GbE	MC2210310-005	NVIDIA active fiber cable, ETH 40GbE, 40Gb/s, QSFP, 5m
40GbE	MC2210310-010	NVIDIA active fiber cable, ETH 40GbE, 40Gb/s, QSFP, 10m
40GbE	MC2210310-015	NVIDIA active fiber cable, ETH 40GbE, 40Gb/s, QSFP, 15m
40GbE	MC2210310-020	NVIDIA active fiber cable, ETH 40GbE, 40Gb/s, QSFP, 20m
40GbE	MC2210310-030	NVIDIA active fiber cable, ETH 40GbE, 40Gb/s, QSFP, 30m
40GbE	MC2210310-050	NVIDIA active fiber cable, ETH 40GbE, 40Gb/s, QSFP, 50m
40GbE	MC2210310-100	NVIDIA active fiber cable, ETH 40GbE, 40Gb/s, QSFP, 100m
40GbE	MC2210411-SR4E	NVIDIA optical module, 40Gb/s, QSFP, MPO, 850nm, up to 300m
40GbE	MC2609125-005	NVIDIA passive copper hybrid cable, ETH 40GbE to 4x10GbE, QSFP to 4xSFP+, 5m

Speed	Part Number	Marketing Description
40GbE	MC260913-0-001	NVIDIA passive copper hybrid cable, ETH 40GbE to 4x10GbE, QSFP to 4xSFP+, 1m
40GbE	MC260913-0-003	NVIDIA passive copper hybrid cable, ETH 40GbE to 4x10GbE, QSFP to 4xSFP+, 3m
40GbE	MCP1700-B001E	NVIDIA passive copper cable, ETH 40GbE, 40Gb/s, QSFP, 1m, black pull-tab
40GbE	MCP1700-B002E	NVIDIA passive copper cable, ETH 40GbE, 40Gb/s, QSFP, 2m, black pull-tab
40GbE	MCP1700-B003E	NVIDIA passive copper cable, ETH 40GbE, 40Gb/s, QSFP, 3m, black pull-tab
40GbE	MCP1700-B01AE	NVIDIA passive copper cable, ETH 40GbE, 40Gb/s, QSFP, 1.5m, black pull-tab
40GbE	MCP1700-B02AE	NVIDIA passive copper cable, ETH 40GbE, 40Gb/s, QSFP, 2.5m, black pull-tab
40GbE	MCP7900-X01AA	NVIDIA passive copper hybrid cable, ETH 40GbE to 4x10GbE, QSFP to 4xSFP+, 1.5m, blue pull-tab, customized label
40GbE	MCP7904-X002A	NVIDIA passive copper hybrid cable, ETH 40GbE to 4x10GbE, QSFP to 4xSFP+, 2m, black pull-tab, customized label
40GbE	MCP7904-X003A	NVIDIA passive copper hybrid cable, ETH 40GbE to 4x10GbE, QSFP to 4xSFP+, 3m, black pull-tab, customized label
40GbE	MCP7904-X01AA	NVIDIA passive copper hybrid cable, ETH 40GbE to 4x10GbE, QSFP to 4xSFP+, 1.5m, black pull-tab, customized label
40GbE	MCP7904-X02AA	NVIDIA passive copper hybrid cable, ETH 40GbE to 4x10GbE, QSFP to 4xSFP+, 2.5m, black pull-tab, customized label
40GbE	MMA1B00-B150D	NVIDIA transceiver, 40GbE, QSFP+, MPO, 850nm, SR4, up to 150m, DDMI

Validated and Supported 25GbE Cables

Speed	Part Number	Marketing Description
25GbE	MAM1Q00A-QSA28	NVIDIA cable module, ETH 25GbE, 100Gb/s to 25Gb/s, QSFP28 to SFP28
25GbE	MCP2M00-A001	NVIDIA passive copper cable, ETH, up to 25Gb/s, SFP28, 1m, 30AWG
25GbE	MCP2M00-A001E30N	NVIDIA passive copper cable, ETH, up to 25Gb/s, SFP28, 1m, black, 30AWG, CA-N
25GbE	MCP2M00-A002	NVIDIA passive copper cable, ETH, up to 25Gb/s, SFP28, 2m, 30AWG
25GbE	MCP2M00-A002E30N	NVIDIA passive copper cable, ETH, up to 25Gb/s, SFP28, 2m, black, 30AWG, CA-N
25GbE	MCP2M00-A003E26N	NVIDIA passive copper cable, ETH, up to 25Gb/s, SFP28, 3m, black, 26AWG, CA-N
25GbE	MCP2M00-A003E30L	NVIDIA passive copper cable, ETH, up to 25Gb/s, SFP28, 3m, black, 30AWG, CA-L
25GbE	MCP2M00-A004E26L	NVIDIA passive copper cable, ETH, up to 25Gb/s, SFP28, 4m, black, 26AWG, CA-L
25GbE	MCP2M00-A005E26L	NVIDIA passive copper cable, ETH, up to 25Gb/s, SFP28, 5m, black, 26AWG, CA-L
25GbE	MCP2M00-A00A	NVIDIA passive copper cable, ETH, up to 25Gb/s, SFP28, 0.5m, 30AWG
25GbE	MCP2M00-A00AE30N	NVIDIA passive copper cable, ETH, up to 25Gb/s, SFP28, 0.5m, black, 30AWG, CA-N
25GbE	MCP2M00-A01AE30N	NVIDIA passive copper cable, ETH, up to 25Gb/s, SFP28, 1.5m, black, 30AWG, CA-N
25GbE	MCP2M00-A02AE26N	NVIDIA passive copper cable, ETH, up to 25Gb/s, SFP28, 2.5m, black, 26AWG, CA-N
25GbE	MCP2M00-A02AE30L	NVIDIA passive copper cable, ETH, up to 25Gb/s, SFP28, 2.5m, black, 30AWG, CA-L
25GbE	MFA2P10-A003	NVIDIA active optical cable 25GbE, SFP28, 3m
25GbE	MFA2P10-A005	NVIDIA active optical cable 25GbE, SFP28, 5m

Speed	Part Number	Marketing Description
25GbE	MFA2P10-A007	NVIDIA active optical cable 25GbE, SFP28, 7m
25GbE	MFA2P10-A010	NVIDIA active optical cable 25GbE, SFP28, 10m
25GbE	MFA2P10-A015	NVIDIA active optical cable 25GbE, SFP28, 15m
25GbE	MFA2P10-A020	NVIDIA active optical cable 25GbE, SFP28, 20m
25GbE	MFA2P10-A030	NVIDIA active optical cable 25GbE, SFP28, 30m
25GbE	MFA2P10-A050	NVIDIA active optical cable 25GbE, SFP28, 50m
25GbE	MMA2P00-AS	NVIDIA transceiver, 25GbE, SFP28, LC-LC, 850nm, SR, up to 150m

Validated and Supported 10GbE Cables

Speed	Part Number	Marketing Description
10GbE	MAM1Q00A-QSA	NVIDIA cable module, ETH 10GbE, 40Gb/s to 10Gb/s, QSFP to SFP+
10GbE	MC2309124-005	NVIDIA passive copper hybrid cable, ETH 10GbE, 10Gb/s, QSFP to SFP+, 5m
10GbE	MC2309124-007	NVIDIA passive copper hybrid cable, ETH 10GbE, 10Gb/s, QSFP to SFP+, 7m
10GbE	MC2309130-001	NVIDIA passive copper hybrid cable, ETH 10GbE, 10Gb/s, QSFP to SFP+, 1m
10GbE	MC2309130-002	NVIDIA passive copper hybrid cable, ETH 10GbE, 10Gb/s, QSFP to SFP+, 2m
10GbE	MC2309130-003	NVIDIA passive copper hybrid cable, ETH 10GbE, 10Gb/s, QSFP to SFP+, 3m

Speed	Part Number	Marketing Description
10GbE	MC2309130-00A	NVIDIA passive copper hybrid cable, ETH 10GbE, 10Gb/s, QSFP to SFP+, 0.5m
10GbE	MC3309124-004	NVIDIA passive copper cable, ETH 10GbE, 10Gb/s, SFP+, 4m
10GbE	MC3309124-005	NVIDIA passive copper cable, ETH 10GbE, 10Gb/s, SFP+, 5m
10GbE	MC3309124-006	NVIDIA passive copper cable, ETH 10GbE, 10Gb/s, SFP+, 6m
10GbE	MC3309124-007	NVIDIA passive copper cable, ETH 10GbE, 10Gb/s, SFP+, 7m
10GbE	MC3309130-001	NVIDIA passive copper cable, ETH 10GbE, 10Gb/s, SFP+, 1m
10GbE	MC3309130-002	NVIDIA passive copper cable, ETH 10GbE, 10Gb/s, SFP+, 2m
10GbE	MC3309130-003	NVIDIA passive copper cable, ETH 10GbE, 10Gb/s, SFP+, 3m
10GbE	MC3309130-00A	NVIDIA passive copper cable, ETH 10GbE, 10Gb/s, SFP+, 0.5m
10GbE	MC3309130-0A1	NVIDIA passive copper cable, ETH 10GbE, 10Gb/s, SFP+, 1.5m
10GbE	MC3309130-0A2	NVIDIA passive copper cable, ETH 10GbE, 10Gb/s, SFP+, 2.5m
10GbE	MCP2100-X001B	NVIDIA passive copper cable, ETH 10GbE, 10Gb/s, SFP+, 1m, blue pull-tab, connector label
10GbE	MCP2100-X002B	NVIDIA passive copper cable, ETH 10GbE, 10Gb/s, SFP+, 2m, blue pull-tab, connector label
10GbE	MCP2100-X003B	NVIDIA passive copper cable, ETH 10GbE, 10Gb/s, SFP+, 3m, blue pull-tab, connector label
10GbE	MCP2101-X001B	NVIDIA passive copper cable, ETH 10GbE, 10Gb/s, SFP+, 1m, Green pull-tab, connector label
10GbE	MCP2104-X001B	NVIDIA passive copper cable, ETH 10GbE, 10Gb/s, SFP+, 1m, black pull-tab, connector label

Speed	Part Number	Marketing Description
10GbE	MCP2104-X002B	NVIDIA passive copper cable, ETH 10GbE, 10Gb/s, SFP+, 2m, black pull-tab, connector label
10GbE	MCP2104-X003B	NVIDIA passive copper cable, ETH 10GbE, 10Gb/s, SFP+, 3m, black pull-tab, connector label
10GbE	MCP2104-X01AB	NVIDIA passive copper cable, ETH 10GbE, 10Gb/s, SFP+, 1.5m, black pull-tab, connector label
10GbE	MCP2104-X02AB	NVIDIA passive copper cable, ETH 10GbE, 10Gb/s, SFP+, 2.5m, black pull-tab, connector label
N/A	MFM1T02A-LR	NVIDIA SFP+ optical module for 10GBASE-LR
N/A	MFM1T02A-SR	NVIDIA SFP+ optical module for 10GBASE-SR

Validated and Supported 1GbE Cables

Speed	Part Number	Marketing Description
1GbE	MC3208011-SX	NVIDIA optical module, ETH 1GbE, 1Gb/s, SFP, LC-LC, SX 850nm, up to 500m
1GbE	MC3208411-T	NVIDIA module, ETH 1GbE, 1Gb/s, SFP, Base-T, up to 100m

Validated and Supported HDR Cables

Speed	Part Number	Marketing Description
HDR	MCP7H50-H001R30	NVIDIA passive copper hybrid cable, IB HDR 200Gb/s to 2x100Gb/s, QSFP56 to 2xQSFP56, LSZH, colored, 1m, 30AWG
HDR	MCP7H50-H002R26	NVIDIA passive copper hybrid cable, IB HDR 200Gb/s to 2x100Gb/s, QSFP56 to 2xQSFP56, LSZH, colored, 2m, 26AWG

Speed	Part Number	Marketing Description
HDR	MCP7H50-H01AR30	NVIDIA passive copper hybrid cable, IB HDR 200Gb/s to 2x100Gb/s, QSFP56 to 2xQSFP56, LSZH, colored, 1.5m, 30AWG

Validated and Supported EDR Cables

Speed	Part Number	Marketing Description
EDR	MCP1600-E001	NVIDIA passive copper cable, IB EDR, up to 100Gb/s, QSFP, LSZH, 1m 30AWG
EDR	MCP1600-E001E30	NVIDIA passive copper cable, IB EDR, up to 100Gb/s, QSFP28, 1m, black, 30AWG
EDR	MCP1600-E002	NVIDIA passive copper cable, IB EDR, up to 100Gb/s, QSFP, LSZH, 2m 28AWG
EDR	MCP1600-E002E30	NVIDIA passive copper cable, IB EDR, up to 100Gb/s, QSFP28, 2m, black, 30AWG
EDR	MCP1600-E003	NVIDIA passive copper cable, IB EDR, up to 100Gb/s, QSFP, LSZH, 3m 26AWG
EDR	MCP1600-E003E26	NVIDIA passive copper cable, IB EDR, up to 100Gb/s, QSFP28, 3m, black, 26AWG
EDR	MCP1600-E004E26	NVIDIA passive copper cable, IB EDR, up to 100Gb/s, QSFP28, 4m, black, 26AWG
EDR	MCP1600-E005E26	NVIDIA passive copper cable, IB EDR, up to 100Gb/s, QSFP28, 5m, black, 26AWG
EDR	MCP1600-E00A	NVIDIA passive copper cable, IB EDR, up to 100Gb/s, QSFP, LSZH, 0.5m 30AWG
EDR	MCP1600-E00AE30	NVIDIA passive copper cable, IB EDR, up to 100Gb/s, QSFP28, 0.5m, black, 30AWG
EDR	MCP1600-E00BE30	NVIDIA passive copper cable, IB EDR, up to 100Gb/s, QSFP28, 0.75m, black, 30AWG
EDR	MCP1600-E01A	NVIDIA passive copper cable, IB EDR, up to 100Gb/s, QSFP, LSZH, 1.5m 30AWG

Speed	Part Number	Marketing Description
EDR	MCP1600-E01AE30	NVIDIA passive copper cable, IB EDR, up to 100Gb/s, QSFP28, 1.5m, black, 30AWG
EDR	MCP1600-E01BE30	NVIDIA passive copper cable, IB EDR, up to 100Gb/s, QSFP28, 1.25m, black, 30AWG
EDR	MCP1600-E02A	NVIDIA passive copper cable, IB EDR, up to 100Gb/s, QSFP, LSZH, 2.5m 26AWG
EDR	MCP1600-E02AE26	NVIDIA passive copper cable, IB EDR, up to 100Gb/s, QSFP28, 2.5m, black, 26AWG
EDR	MFA1A00-E001	NVIDIA active fiber cable, IB EDR, up to 100Gb/s, QSFP, LSZH, 1m
EDR	MFA1A00-E003	NVIDIA active fiber cable, IB EDR, up to 100Gb/s, QSFP, LSZH, 3m
EDR	MFA1A00-E005	NVIDIA active fiber cable, IB EDR, up to 100Gb/s, QSFP, LSZH, 5m
EDR	MFA1A00-E010	NVIDIA active fiber cable, IB EDR, up to 100Gb/s, QSFP, LSZH, 10m
EDR	MFA1A00-E010_FF	NVIDIA active fiber cable, IB EDR, up to 100Gb/s, QSFP, LSZH, 10m
EDR	MFA1A00-E015	NVIDIA active fiber cable, IB EDR, up to 100Gb/s, QSFP, LSZH, 15m
EDR	MFA1A00-E020	NVIDIA active fiber cable, IB EDR, up to 100Gb/s, QSFP, LSZH, 20m
EDR	MFA1A00-E030	NVIDIA active fiber cable, IB EDR, up to 100Gb/s, QSFP, LSZH, 30m
EDR	MFA1A00-E050	NVIDIA active fiber cable, IB EDR, up to 100Gb/s, QSFP, LSZH, 50m
EDR	MFA1A00-E100	NVIDIA active fiber cable, IB EDR, up to 100Gb/s, QSFP, LSZH, 100m
EDR	MMA1B00-E100	NVIDIA transceiver, IB EDR, up to 100Gb/s, QSFP28, MPO, 850nm, SR4, up to 100m

Validated and Supported FDR Cables

Speed	Part Number	Marketing Description
FDR	MC2207126-004	NVIDIA passive copper cable, VPI, up to 56Gb/s, QSFP, 4m
FDR	MC2207128-003	NVIDIA passive copper cable, VPI, up to 56Gb/s, QSFP, 3m
FDR	MC2207128-0A2	NVIDIA passive copper cable, VPI, up to 56Gb/s, QSFP, 2.5m
FDR	MC2207130-001	NVIDIA passive copper cable, VPI, up to 56Gb/s, QSFP, 1m
FDR	MC2207130-002	NVIDIA passive copper cable, VPI, up to 56Gb/s, QSFP, 2m
FDR	MC2207130-00A	NVIDIA passive copper cable, VPI, up to 56Gb/s, QSFP, 0.5m
FDR	MC2207130-0A1	NVIDIA passive copper cable, VPI, up to 56Gb/s, QSFP, 1.5m
FDR	MC220731V-003	NVIDIA active fiber cable, VPI, up to 56Gb/s, QSFP, 3m
FDR	MC220731V-005	NVIDIA active fiber cable, VPI, up to 56Gb/s, QSFP, 5m
FDR	MC220731V-010	NVIDIA active fiber cable, VPI, up to 56Gb/s, QSFP, 10m
FDR	MC220731V-015	NVIDIA active fiber cable, VPI, up to 56Gb/s, QSFP, 15m
FDR	MC220731V-020	NVIDIA active fiber cable, VPI, up to 56Gb/s, QSFP, 20m
FDR	MC220731V-025	NVIDIA active fiber cable, VPI, up to 56Gb/s, QSFP, 25m
FDR	MC220731V-030	NVIDIA active fiber cable, VPI, up to 56Gb/s, QSFP, 30m
FDR	MC220731V-040	NVIDIA active fiber cable, VPI, up to 56Gb/s, QSFP, 40m

Speed	Part Number	Marketing Description
FDR	MC220731V-050	NVIDIA active fiber cable, VPI, up to 56Gb/s, QSFP, 50m
FDR	MC220731V-075	NVIDIA active fiber cable, VPI, up to 56Gb/s, QSFP, 75m
FDR	MC220731V-100	NVIDIA active fiber cable, VPI, up to 56Gb/s, QSFP, 100m
FDR	MCP1700-F001C	NVIDIA passive copper cable, VPI, up to 56Gb/s, QSFP, 1m, Red pull-tab
FDR	MCP1700-F001D	NVIDIA passive copper cable, VPI, up to 56Gb/s, QSFP, 1m, Yellow pull-tab
FDR	MCP1700-F002C	NVIDIA passive copper cable, VPI, up to 56Gb/s, QSFP, 2m, Red pull-tab
FDR	MCP1700-F002D	NVIDIA passive copper cable, VPI, up to 56Gb/s, QSFP, 2m, Yellow pull-tab
FDR	MCP1700-F003C	NVIDIA passive copper cable, VPI, up to 56Gb/s, QSFP, 3m, Red pull-tab
FDR	MCP1700-F003D	NVIDIA passive copper cable, VPI, up to 56Gb/s, QSFP, 3m, Yellow pull-tab
FDR	MCP170L-F001	NVIDIA passive copper cable, VPI, up to 56Gb/s, QSFP, LSZH, 1m
FDR	MCP170L-F002	NVIDIA passive copper cable, VPI, up to 56Gb/s, QSFP, LSZH, 2m
FDR	MCP170L-F003	NVIDIA passive copper cable, VPI, up to 56Gb/s, QSFP, LSZH, 3m
FDR	MCP170L-F00A	NVIDIA passive copper cable, VPI, up to 56Gb/s, QSFP, LSZH, 0.5m
FDR	MCP170L-F01A	NVIDIA passive copper cable, VPI, up to 56Gb/s, QSFP, LSZH, 1.5m

Validated and Supported QDR Cables

Speed	Part Number	Marketing Description
QDR	MC2206125-007	NVIDIA passive copper cable, IB QDR, 40Gb/s, QSFP,7m

Changes and New Features

Note

Security Hardening Enhancements: This release contains important reliability improvements and security hardening enhancements. NVIDIA recommends upgrading your devices' firmware to this release to improve the devices' firmware security and reliability.

Info

To generate PLDM packages for firmware updates, users must install and use the MFT version that corresponds with the respective firmware release.

Feature/Change	Description
	24.35.4506
Bug Fixes	See <i>Bug Fixes in this Firmware Version</i> section.

Bug Fixes in this Firmware Version

Internal Ref.	Issue
3887759	Description: Fixed an issue that caused Completion Timeout to mistakenly be treated as Advisory Non-Fatal error. Now Completion Timeout is treated as uncorrectable error.
	Keywords: Completion Timeout, Advisory Non-Fatal error
	Discovered in Version: 24.35.3006
	Fixed in Release: 24.35.4030
3817699	Description: Fixed an issue that caused the TX to hang and create a "TX timeout" error in dmesg after unplugging the device forcefully during server warm reboot.
	Keywords: hotplug, virtio, nvme, warm reboot, TX timeout
	Discovered in Version: 24.35.3006
	Fixed in Release: 24.35.4030
3588590	Description: Fixed an issue on the customized server with an independent power supply that resulted in an assert with ext_synd as 0x4010 during a power cycle process.
	Keywords: Virtio full emulation, independent power supply
	Discovered in Version: 24.35.3006
	Fixed in Release: 24.35.4030
3813815	Description: Fixed an issue that result in no traffic after live migration resume of vDPA when using DOCA version 2.6.0 onwards.
	Keywords: vDPA, Live Migration, DOCA
	Discovered in Version: 24.35.3006
	Fixed in Release: 24.35.4030

Internal Ref.	Issue
358874 2	<p>Description: Fixed an issue on the server with an independent power supply where the virtio devices are hotplugged that led to a timeout when power cycling the server. The following errors were provided: "DESTROY_GENERAL_OBJECT(0xa03)" and "MODIFY_GENERAL_OBJECT(0xa01)".</p> <p>Keywords: Virtio full emulation, independent power supply</p> <p>Discovered in Version: 24.35.3006</p> <p>Fixed in Release: 24.35.4030</p>
374519 2 / 389593 8	<p>Description: Fixed an issue on the customized server with an independent power supply, that led to a non-functional virtio when power cycling the server during stressful traffic. The following error was provided: "DESTROY_GENERAL_OBJECT(0xa03) No done completion".</p> <p>Keywords: Virtio full emulation, independent power supply</p> <p>Discovered in Version: 24.35.3006</p> <p>Fixed in Release: 24.35.4030</p>

Known Issues

VF Network Function Limitations in SRIOV Legacy Mode

Dual Port Device	Single Port Device
127 VF per PF (254 functions)	127

VF Network Function Limitations in Switchdev Mode

Dual Port Device	Single Port Device
127 VF per PF (254 functions)	127

VF+SF Network Function Limitations in Switchdev Mode

Dual Port Device	Single Port Device
<ul style="list-style-type: none"> • 127 VF per PF (254 functions) • 512 PF+VF+SF per PF (1024 functions) 	<ul style="list-style-type: none"> • 127 VF (127 functions) • 512 PF+VF+SF per PF (512 functions)

For known issues prior to version 24.33.1048, please refer to the [NVIDIA BlueField-2 DPU documentation](#).

Internal Ref.	Issue
3525865	Description: Unexpected system behavior might be observed if the driver is loaded while reset is in progress.
	Workaround: N/A
	Keywords: Sync 1 reset, firmware reset
	Discovered in Version: 24.35.3006
3512352	Description: Firmware reset sync 1 is currently not working properly. Occasionally, running it does not reset to the device.
	Workaround: N/A

Internal Ref.	Issue
	Keywords: Firmware reset sync 1
	Discovered in Version: 24.35.3006
3267506	Description: CRC is included in the traffic byte counters as a port byte counter.
	Workaround: N/A
	Keywords: Counters, CRC
	Discovered in Version: 24.35.2000
3147454	Description: Multi PF is not supported in NVIDIA BlueField-2 Multi-Host environments. Setting 4 PFs (mlxconfig NUM_OF_PF-4) on a Multi-Host environment may trigger firmware asserts and the ARcatVerM may hang.
	Workaround: N/A
	Keywords: Multi PF
	Discovered in Version: 24.34.1002
2169950	Description: When decapsulation on a packet occurs, the FCS indication is not calculated correctly.
	Workaround: N/A
	Keywords: FCS
	Discovered in Version: 24.34.1002
3141072	Description: The "max_shaper_rate" configuration query via QEEC mlxreg returns a value translated to hardware granularity.
	Workaround: N/A
	Keywords: RX Rate-Limiter, Multi-host
	Discovered in Version: 24.34.1002
3106146	Description: Live migration of MPV affiliated function pair is not supported when port numbers are changed. Each function should stay on the same port number as before migration.
	Workaround: N/A
	Keywords: MPV live migration
	Discovered in Version: 24.34.1002
2870970	Description: GTP encapsulation (flex parser profile 3) is limited to the NIC domain.

Internal Ref.	Issue
	Encapsulating in the FDB domain will render a 0-size length in GTP header.
	Workaround: N/A
	Keywords: GTP encapsulation
	Discovered in Version: 24.34.1002
2661049	Description: Asynchronous reboot of Arm while the RSHIM driver is active may cause Poisoned Completion to return and consequently cause a host crash.
	Workaround: N/A
	Keywords: RSHIM driver
	Discovered in Version: 24.33.1048
2899026 / 2853408	Description: Some pre-OS environments may fail when sensing a hot plug operation during their boot stage.
	Workaround: N/A
	Keywords: BIOS; Hot plug; Virtio-net
	Discovered in Version: 24.33.1048
2870213	Description: Servers do not recover after configuring <code>PCI_SWITCH_EMULATION_NUM_PORT</code> to 32 followed by power cycle.
	Workaround: N/A
	Keywords: VirtIO-net; power cycle
	Discovered in Version: 24.33.1048
2855592	Description: When working with 3rd party device (e.g., Paragon) in 25GbE speed, the 25GbE speed must be configured in force mode.
	Workaround: N/A
	Keywords: Force mode, 3rd party devices, 25GbE
	Discovered in Version: 24.33.1048
2850003	Description: Occasionally, when rising a logical link, the link recovery counter is increase by 1.
	Workaround: N/A
	Keywords: Link recovery counter
	Discovered in Version: 24.33.1048

Internal Ref.	Issue
261675 5	Description: Forward action for IPoIB is not supported on RX RDMA Flow Table.
	Workaround: N/A
	Keywords: Steering, IPoIB
	Discovered in Version: 24.33.1048

PreBoot Drivers (FlexBoot/UEFI)

FlexBoot Changes and New Features

For further information, please refer to the [FlexBoot Release Notes](#).

UEFI Changes and Major New Features

For further information, please refer to the [UEFI Release Notes](#).

Release Notes History

Changes and New Feature History

Feature/Change	Description
	24.35.4030
Bug Fixes	See <i>Bug Fixes in this Firmware Version</i> section.

Feature/Change	Description
	24.35.3502
Bug Fixes	See <i>Bug Fixes in this Firmware Version</i> section.

Feature/Change	Description
	24.35.3006
Bug Fixes	See <i>Bug Fixes in this Firmware Version</i> section.

Feature/Change	Description
	24.35.2000
PCC Algorithm	Enables the users to collect more information from NP to RP for PCC algorithm. To achieve this, the NP ingress bytes information was added to the RTT response packet sent from the NP side.
HPCC: Support per-IP and per-QP methods	Enables the user to configure the PCC algorithm shaper coalescing mode using nvconfig to select CC algorithm shaper coalescing for IB and ROCE. The new parameters are <code>IB_CC_SHAPER_COALESCE</code> and <code>ROCE_CC_SHAPER_COALESCE</code> .
Bug Fixes	See <i>Bug Fixes in this Firmware Version</i> section.

Feature/Change	Description
24.35.1012	
HPCC, Programmable Congestion Control	HPCC related configurations in is now supported via the mlxconfig utility.
UDP	Added support for copy modify header steering action to/from the UDP field.
Resource Dump	<p>Added the following resource dump segments:</p> <ul style="list-style-type: none"> • SEG_HW_STE_FULLL that includes dump to STE and all its dependencies • SEG_FW_STE_FULLL that include dump to FW_STE and to HW_STE_FULLL in range
Striding WQE - Headroom and Tail-room	As the software requires additional space before and after a packet is scattered for its processing for stridden RQ, the hardware will allocate the required room while scattering packets to spare a copy.
Connections per Second (CPS)	Improved security offload's Connections per Second (CPS) rate using the general object DEK (PSP TLS etc).
VirtIO vDPA Performance Virtualization	Increased the VirtIO hardware offload message rate to 20/20 MPPS for 256 virtual devices by optimizing the datapath application code.
Open SNAPI: Communication Channel	<p>Open SNAPI steering hop optimization:</p> <ul style="list-style-type: none"> • Only packets with dmac/dlid 0 will enter the SNAPI steering channel. Meaning if the Open SNAPI communication channel exists, all other traffic will have only 1 steering hop penalty • SW must use dlid/dmac == 0 in address vector of a SNAPI QP • cross eSwitch, Open SNAPI is now allowed if LAG is enabled
SHA Calculations	Added support for SHA calculations via the MMO engine.
UPT Performance	Optimized latency for UPT traffic.
NONDNIC, LAG	Added LAG support on NODNIC interfaces to enable traffic functionality on other ports after the LAG is enabled.

Feature/Change	Description
QoS Priority Trust Default State	<p>QoS priority trust default state can now be changed using the new nvconfig below:</p> <ul style="list-style-type: none"> • QOS_TRUST_STATE_P1 • QOS_TRUST_STATE_P2 <p>The values that can be used to set the default state are:</p> <ul style="list-style-type: none"> • TRUST_PORT • TRUST_PCP • TRUST_DSCP • TRUST_DSCP_PCP
VirtIO Full Emulation	Implemented a transitional device which supports both drivers conforming to the spec 1.x and allows legacy drivers to support virtio legacy driver (virtio 0.95).
Bug Fixes	See <i>Bug Fixes in this Firmware Version</i> section.

Feature/Change	Description
24.34.1002	
LLDP Properties Implementation on RDE	Added LLDPEnable, LLDPTransmit and LLDPReceive properties to the RDE Port schema implementation.
PPS Offset	Added a 22 nanosecond of propagation delay to the cable delay of the PPS signal when using PPS out.
Programmable CC, PPCC, MAD, IBCC	Added support for PPCC register with bulk operations, MAD for algorithm configuration and tunable parameters.
Programmable Counters	Added support for programmable counters for PCC via PPCC register and MAD.
Bug Fixes	See <i>Bug Fixes</i> section.

Feature/Change	Description
24.33.1048	
NVIDIA BlueField-2 DPU NIC Operation Mode	In this mode, the DPU behaves exactly like a ConnectX SmartNIC from the perspective of the external host. As part of this operation mode, this new capability allows the host Physical Function:

Feature/Change	Description
	<ul style="list-style-type: none"> to supply pages to the Host eSwitch functions to execute the same flows as a Host PF on a regular ConnectX device <p>For further information, see section "NVIDIA BlueField-2 DPU NIC Operation Mode" in this document.</p>
200Gb/s Throughput on Crypto Capable Devices	<p>Enabled 200Gb/s out-of-the-box throughput on crypto capable devices.</p> <p>Note: If any crypto offloads is in use, 200Gb/s throughput can be achieved only after the next firmware reset</p>
VF Migration	<p>Added support for VF migration. The hypervisor can now suspend its VF, meaning from that point the VF cannot perform action such as send/receive traffic or run any command. In this firmware version only the suspend resume mode is supported (on the same VM).</p>
MADs	<p>Added a new MAD of class SMP that has the attributes <code>hierarchy_Info</code> as defined in the IB Specification and is used to query the hierarchy information stored on the node and the physical port.</p>
NV Configurations via the Relevant Reset Flow	<p>Added <code>pci_rescan_needed</code> field to the MFRL access register to indicate whether a PCI rescan is needed based on the NV configurations issued by the software.</p> <p>Note: If the Keep Link Up NV configuration is changed, phyless reset will be blocked.</p>
Increasing Firmware's Queue Depth Limit	<p>Changing the mlxconfig parameter allows the user to expose different value of max queue depth in NVMe CAP on static emulated functions which results in NVMe module creating longer NVMe queues.</p>
RSHIM PF Interrupts Implementation	<p>Added support for interrupts on the RSHIM PFs to enable gracefully stop of the RSHIM host driver.</p>
ICM Pages	<p>Added a new register (<code>vhca_icm_ctrl_access_reg</code>) to enable querying and limiting the ICM pages in use.</p>
VF Migration	<p>Added support for VF migration.</p>
NetworkPort Schema Replacement	<p>Replaced the deprecated NetworkPort schema with Port schema in NIC RDE implementation.</p>
RShim PF	<p>Added support for "<code>mlxfwreset --sync 1</code>" for the RShim PF.</p>

Feature/Change	Description
Steering Definer	Added support for creating a steering definer with a dword selector using <code>create_match_definer_object</code> and the "SELECT" format.
XRQ QP Errors Enhancements	Enhanced the XRQ QP error information provided to the user in case QP goes into an error state. In such case, QUERY_QP will provide information on the syndrome type and which side caused the error.
HW Steering: WQE Insertion Rules	<p>[Beta] Added HW Steering support for the following:</p> <ul style="list-style-type: none"> • set, add and copy inline STC action • set and copy actions for several fields using <code>modify_pattern</code> object and inline stc modify action • FDB mode in HW steering using FDB_RX and FDB_TX flow table types • ASO flow meter action via STC • flow counter query using ASO WQE • allocation of large bulks for the objects: STE, ASO flow meter and modify argument • jumbo match RTC • count action in STC
Holdover Mode	Added support for holdover mode to comply to SyncE specifications (EEC compliance) to limit the maximum phase transient response upon link loss.
SyncE Enhancements	Added support for noise filtering to comply to the SyncE specifications requirements.
ibstat	Updated the ibstat status reported when the phy link is down. Now <code>QUERY_VPORT_STATE.max_tx_speed</code> of UPLINK will not be reported as 0 anymore.
ZTRCC	Added support for advanced ZTR_RTTCC algorithm based on the Programmable CC platform to achieve better congestion control without dependency on the switch ECN marking.
SMPs	Disabled the option to send SMPs from unauthorized hosts.
Dynamic Completion Event Moderation for vDPA	DIM is used to tune moderation parameter dynamically using an <code>mlxreg</code> command. To disable this capability, run:

Feature/Change	Description
	<pre>mlxreg -d /dev/mst/mt41686_pciconf0 --reg_id 0xc00d --reg_len 0x8 -s "0x4.1:1=0x0"</pre>
UPT Performance Improvement	Improved UPT PPS performance.
SW Steering Cache	Modified the TX or RX cache invalidation behavior. TX or RX cache invalidation now does not occur automatically but only when the software performs the sync operation using the using sync_steering command.
Mega Allocations in Bulk Allocator Mechanism	Modified the maximum bulk size per single allocation from "log_table_size - log_num_unisizes", to allocate any range size, to remove limitations that HWS objects such as counters and modify arguments might encounter.
Dynamic Flex Parser over a VF	<p>Added support for creating a dynamic flex parser on untrusted function, and changed the flex parser cap for untrusted function to the following:</p> <ul style="list-style-type: none"> • maximum flex parser node = 2 • maximum dw sample = 4
Changing all the Crypto Features to Wrapped or Cleartext	<p>Crypto features can be in either wrapped or unwrapped mode. Meaning, the key can be wrapped or in plaintext when running the CREATE_DEK PRM command. To comply with the requirements specified in FIPS publication, all the created DEKs must be wrapped.</p> <p>This feature adds new NV_CONFIG per device to control this mode, and enables the user to change all the crypto features to wrapped or cleartext.</p>
ICM Direct Access by the Software to write/modify the DEK Objects	<p>[Beta] This new capability enables the software to directly access ICM and write/modify the DEK objects. Such change improves the DEK object update rate by re-using DEK object instead of creating a new one.</p> <p>In addition, added the following:</p> <ul style="list-style-type: none"> • New for DEK object: bulk allocation, modify_dek cmd, and new mode - sw_wrapped. • New general object INT_KEK

Feature/Change	Description
Bug Fixes	See <i>Bug Fixes</i> section.

Bug Fixes History

Internal Ref.	Issue
3887759	Description: Fixed an issue that caused Completion Timeout to mistakenly be treated as Advisory Non-Fatal error. Now Completion Timeout is treated as uncorrectable error.
	Keywords: Completion Timeout, Advisory Non-Fatal error
	Discovered in Version: 24.35.3006
	Fixed in Release: 24.35.4030
3817699	Description: Fixed an issue that caused the TX to hang and create a "TX timeout" error in dmesg after unplugging the device forcefully during server warm reboot.
	Keywords: hotplug, virtio, nvme, warm reboot, TX timeout
	Discovered in Version: 24.35.3006
	Fixed in Release: 24.35.4030
3588590	Description: Fixed an issue on the customized server with an independent power supply that resulted in an assert with ext_synd as 0x4010 during a power cycle process.
	Keywords: Virtio full emulation, independent power supply
	Discovered in Version: 24.35.3006
	Fixed in Release: 24.35.4030
3813815	Description: Fixed an issue that result in no traffic after live migration resume of vDPA when using DOCA version 2.6.0 onwards.
	Keywords: vDPA, Live Migration, DOCA
	Discovered in Version: 24.35.3006
	Fixed in Release: 24.35.4030
3588742	Description: Fixed an issue on the server with an independent power supply where the virtio devices are hotplugged that led to a timeout when power

Internal Ref.	Issue
	cycling the server. The following errors were provided: "DESTROY_GENERAL_OBJECT(0xa03)" and "MODIFY_GENERAL_OBJECT(0xa01)".
	Keywords: Virtio full emulation, independent power supply
	Discovered in Version: 24.35.3006
	Fixed in Release: 24.35.4030
374519 2 / 389593 8	Description: Fixed an issue on the customized server with an independent power supply, that led to a non-functional virtio when power cycling the server during stressful traffic. The following error was provided: "DESTROY_GENERAL_OBJECT(0xa03) No done completion".
	Keywords: Virtio full emulation, independent power supply
	Discovered in Version: 24.35.3006
	Fixed in Release: 24.35.4030

Internal Ref.	Issue
367034 9	Description: Fixed an issue that prevented the Power Controller Control bit in the Slot Control register from returning to default when forcing the Unplug sequence.
	Keywords: Power Controller Control
	Discovered in Version: 24.35.2000
	Fixed in Release: 24.35.3502
367032 4	Description: Fixed an assert with ext_synd as 0x8ce5 during a power cycle process for a virtio case on the customized server with an independent power supply.
	Keywords: virtio, assert
	Discovered in Version: 24.35.2000
	Fixed in Release: 24.35.3502

Internal Ref.	Issue
3217896	Description: Fixed RDE PATCH operation status code reported in case the property is "read-only".
	Keywords: RDE
	Discovered in Version: 24.35.1012
	Fixed in Release: 24.35.2000
3241357	Description: Fixed an issue in MCTP-over-PCIe, where the VDM message with the type Route-to-Root Complex, the target ID was not set as 0x0.
	Keywords: MCTP-over-PCIe, VDM message
	Discovered in Version: 24.35.1012
	Fixed in Release: 24.35.2000
3250924	Description: Fixed an issue that resulted in NVMe driver not loading on a hotplug-able device when VIRTIO_EMULATION_HOTPLUG_TRANS was enabled by mlxconfig.
	Keywords: VIRTIO_EMULATION_HOTPLUG_TRANS, NVMe
	Discovered in Version: 24.35.1012
	Fixed in Release: 24.35.2000
3215393	Description: Fixed an issue that caused the virtual QoS mechanism to stop traffic from reaching the full line rate of 200GbE on each direction when LAG was enabled.
	Keywords: Virtual QoS mechanism, 200GbE, LAG
	Discovered in Version: 24.35.1012
	Fixed in Release: 24.35.2000

Internal Ref.	Issue
3023205	<p>Description: Fixed an issue that resulted in:</p> <ul style="list-style-type: none"> • data corruption • NVMF queue getting stuck, following backend controller timeout and RNR NAK exceeded syndrome on initiator <p>due to mistakes in access to the internal database NVMF Backend Controller as a result of wrong data in the database.</p>

Internal Ref.	Issue
	<p>Keywords: data_corruption</p> <p>Discovered in Version: 24.33.1048</p> <p>Fixed in Release: 24.34.1002</p>
3101645	<p>Description: Fixed an issue that caused some requests to get stuck in the pacer, thus not allowing detach NVMMF namespace command to progress when the pacer was configured to use byte in flight limitation mechanism and NVMMF backend controller timeout happened under traffic.</p> <p>Keywords: CMD queue</p> <p>Discovered in Version: 24.33.1048</p> <p>Fixed in Release: 24.34.1002</p>
3021669	<p>Description: Added a new NVconfig parameter "MULTI_PCI_RESOURCE_SHARE" to support modes that allow choosing the utilization of the card's resources on each host in Socket-Direct / Multi host setup.</p> <p>Keywords: Performance</p> <p>Discovered in Version: 24.33.1048</p> <p>Fixed in Release: 24.34.1002</p>
2665773	<p>Description: Added 50 Usec delay during PML1 exit to avoid any PCIe replay timer timeout.</p> <p>Keywords: PCIe, PML1</p> <p>Discovered in Version: 24.33.1048</p> <p>Fixed in Release: 24.34.1002</p>
3134894	<p>Description: Fixed an issue where <code>set_flow_table_entry</code> failed when <code>aso_flow_meter</code> action was used.</p> <p>Keywords: ASO Flow Meter, FW Steering</p> <p>Discovered in Version: 24.33.1048</p> <p>Fixed in Release: 24.34.1002</p>
3039007	<p>Description: Enabled Multi-Host RX Rate-limiter configuration via the QEEC mlxreg and the max_shaper_rate field.</p> <p>Keywords: RX Rate-Limiter, Multi-host</p>

Internal Ref.	Issue
	Discovered in Version: 24.33.1048
	Fixed in Release: 24.34.1002
3059379	Description: Added "Command Unsupported" response code in cases when running the MCTP control command "Get Vendor Defined Messages Supported", and there were no supported VDMs.
	Keywords: MCTP control command
	Discovered in Version: 24.33.1048
	Fixed in Release: 24.34.1002
2994292	Description: Fixed a race condition occurred between the duplicate read and QP commands (2RST, 2ERR and Destroy) in the signature that caused the command to hang.
	Keywords: Race condition
	Discovered in Version: 24.33.1048
	Fixed in Release: 24.34.1002
3068927	Description: Added support for dynamic MSI-X when in SmartNIC mode.
	Keywords: Dynamic MSI-X
	Discovered in Version: 24.33.1048
	Fixed in Version: 24.34.1002
3110286	Description: Fixed an issue where vPort counters had wrong values.
	Keywords: vPort counters
	Discovered in Version: 24.33.1048
	Fixed in Version: 24.34.1002
2887966	Description: A hardware issue in the illegal_flowq that raises even when there is drop, results in the adapter card getting stuck during high scale traffic.
	Keywords: Performance
	Discovered in Version: 24.33.1048
	Fixed in Version: 24.34.1002
3056461	Description: Creating a Channel Service Object with bad parameters that lead to command rollback, results in the command getting stuck.

Internal Ref.	Issue
	Keywords: Open SNAPI
	Discovered in Version: 24.33.1048
	Fixed in Version: 24.34.1002

Internal Ref.	Issue
270 211 8	<p>Description: Changed the policy of VDPA queue number capability.</p> <ul style="list-style-type: none"> • When the devices count ≤ 8, the VDPA queue number in cap is 256 • When the device count ≥ 32, the VDPA queue number in cap is 64 • When the devices count is in 9~31, the VDPA queue number in cap is 128. <p>Here the devices counts all port functions configured in mlxconfig, including pf, vf and sf.</p>
	Keywords: VDPA
	Discovered in Version: 24.32.1010
	Fixed in Version: 24.33.1048
299 125 5	<p>Description: Fixed an issue that caused the host driver to hang when the received packet was bigger than the received buffer (according to the device's MTU) as the device reported a packet length bigger than the received buffer length.</p>
	Keywords: virtio net RX packet, RX buffer
	Discovered in Version: 24.32.1010
	Fixed in Version: 24.33.1048
302 173 4	<p>Description: Fixed an issue that caused BMC to fail to detect the PCIe device when using the MCTP-over-PCIe protocol.</p>
	Keywords: BMC, MCTP-over-PCIe protocol, PCIe
	Discovered in Version: 24.32.1010
	Fixed in Version: 24.33.1048
280 294 3	<p>Description: Implemented SLD detection code. Surprise Down Error Reporting Capable value was changed from 1 to 0 in boards where the downstream perst was not controlled thus causing SLD detection not to function properly.</p>
	Keywords: SLD detection, Surprise Down Error Reporting Capable

Internal Ref.	Issue
	Discovered in Version: 24.32.1010
	Fixed in Version: 24.33.1048
251 345 3	Description: Fixed rare lanes skew issue that caused CPU to timeout in Rec.idle.
	Keywords: PCIe
	Discovered in Version: 24.32.1010
	Fixed in Version: 24.33.1048
293 243 6	Description: Optimized the virtio data path to reach line speed for Tx bandwidth.
	Keywords: VDPA, virtio full emulation
	Discovered in Version: 24.32.1010
	Fixed in Version: 24.33.1048
290 770 7	Description: Fixed a configuration issue which flipped the MSB of Partition Key field in CNP packets and led to P_KEY mismatch between CNP packets and regular packets.
	Keywords: Partition Key, PKEY, CNP, ECN
	Discovered in Version: 24.32.1010
	Fixed in Version: 24.33.1048

Legal Notices and 3rd Party Licenses

The following are the drivers' software, tools and HCA firmware legal notices and 3rd party licenses.

Product	Version	Legal Notices and 3rd Party Licenses
Firmware	xx.35.40xx	<ul style="list-style-type: none">• HCA Firmware EULA• License• 3rd Party Notice
MLNX_OFED	5.8-5.1.1.2	<ul style="list-style-type: none">• License• 3rd Part Notice
MFT FreeBSD	4.22.1-417	<ul style="list-style-type: none">• License• 3rd Party Notice
MFT Linux		<ul style="list-style-type: none">• License• 3rd Party Notice
MFT VMware		<ul style="list-style-type: none">• License• 3rd Party Notice
MFT Windows		<ul style="list-style-type: none">• License• 3rd Party Notice

Notice
This document is provided for information purposes only and shall not be regarded as a warranty of a certain functionality, condition, or quality of a product. NVIDIA Corporation ("NVIDIA") makes no representations or warranties, expressed or implied, as to the accuracy or completeness of the information contained in this document and assumes no responsibility for any errors contained herein. NVIDIA shall have no liability for the consequences or use of such information or for any infringement of patents or other rights of third parties that may result from its use. This document is not a commitment to develop, release, or deliver any Material (defined below), code, or functionality. NVIDIA reserves the right to make corrections, modifications, enhancements, improvements, and any other changes to this document, at any time without notice. Customer should obtain the latest relevant information before placing orders and should verify that such information is current and complete. NVIDIA products are sold subject to the NVIDIA standard terms and conditions of sale supplied at the time of order acknowledgement, unless otherwise agreed in an individual sales agreement signed by authorized representatives of NVIDIA and customer ("Terms of Sale"). NVIDIA hereby expressly objects to applying any customer general terms and

conditions with regards to the purchase of the NVIDIA product referenced in this document. No contractual obligations are formed either directly or indirectly by this document. NVIDIA products are not designed, authorized, or warranted to be suitable for use in medical, military, aircraft, space, or life support equipment, nor in applications where failure or malfunction of the NVIDIA product can reasonably be expected to result in personal injury, death, or property or environmental damage. NVIDIA accepts no liability for inclusion and/or use of NVIDIA products in such equipment or applications and therefore such inclusion and/or use is at customer's own risk. NVIDIA makes no representation or warranty that products based on this document will be suitable for any specified use. Testing of all parameters of each product is not necessarily performed by NVIDIA. It is customer's sole responsibility to evaluate and determine the applicability of any information contained in this document, ensure the product is suitable and fit for the application planned by customer, and perform the necessary testing for the application in order to avoid a default of the application or the product. Weaknesses in customer's product designs may affect the quality and reliability of the NVIDIA product and may result in additional or different conditions and/or requirements beyond those contained in this document. NVIDIA accepts no liability related to any default, damage, costs, or problem which may be based on or attributable to: (i) the use of the NVIDIA product in any manner that is contrary to this document or (ii) customer product designs. No license, either expressed or implied, is granted under any NVIDIA patent right, copyright, or other NVIDIA intellectual property right under this document. Information published by NVIDIA regarding third-party products or services does not constitute a license from NVIDIA to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property rights of the third party, or a license from NVIDIA under the patents or other intellectual property rights of NVIDIA. THIS DOCUMENT AND ALL NVIDIA DESIGN SPECIFICATIONS, REFERENCE BOARDS, FILES, DRAWINGS, DIAGNOSTICS, LISTS, AND OTHER DOCUMENTS (TOGETHER AND SEPARATELY, "MATERIALS") ARE BEING PROVIDED "AS IS." NVIDIA MAKES NO WARRANTIES, EXPRESSED, IMPLIED, STATUTORY, OR OTHERWISE WITH RESPECT TO THE MATERIALS, AND EXPRESSLY DISCLAIMS ALL IMPLIED WARRANTIES OF NONINFRINGEMENT, MERCHANTABILITY, AND FITNESS FOR A PARTICULAR PURPOSE. TO THE EXTENT NOT PROHIBITED BY LAW, IN NO EVENT WILL NVIDIA BE LIABLE FOR ANY DAMAGES, INCLUDING WITHOUT LIMITATION ANY DIRECT, INDIRECT, SPECIAL, INCIDENTAL, PUNITIVE, OR CONSEQUENTIAL DAMAGES, HOWEVER CAUSED AND REGARDLESS OF THE THEORY OF LIABILITY, ARISING OUT OF ANY USE OF THIS DOCUMENT, EVEN IF NVIDIA HAS BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES. Notwithstanding any damages that customer might incur for any reason whatsoever, NVIDIA's aggregate and cumulative liability towards customer for the products described herein shall be limited in accordance with the Terms of Sale for the product. **Trademarks** NVIDIA and the NVIDIA logo are trademarks and/or registered trademarks of NVIDIA Corporation in the U.S. and other countries. Other company and product names may be trademarks of the respective companies with which they are associated.

© Copyright 2024, NVIDIA. PDF Generated on 01/02/2025