



NVIDIA ConnectX-6 Lx Adapter Cards Firmware Release Notes v26.39.5124 LTS (2023 LTS U6)

Table of contents

Firmware Compatible Products	4
Changes and New Features	6
Bug Fixes in this Firmware Version	10
Known Issues	11
PreBoot Drivers (FlexBoot/UEFI)	15
Validated and Supported Cables and Switches	16
Supported Non-Volatile Configurations	36
Release Notes History	42
Changes and New Feature History	42
Bug Fixes History	45
Legal Notices and 3rd Party Licenses	50

Info

This is a long-term support (LTS) release. LTS is the practice of maintaining a software product for an extended period of time (up to three years) to help increase product stability. LTS releases include bug fixes and security patches.

Release Notes Update History

Version	Date	Description
26.39.5124	January 2026	Initial release of this Release Notes version.

Overview

Firmware which is added at the time of manufacturing, is used to run user programs on the device and can be thought of as the software that allows hardware to run. Embedded firmware is used to control the functions of various hardware devices and systems, much like a computer's operating system (OS) controls the function of software applications. Firmware may be written into read-only memory (ROM), erasable programmable read-only memory (EPROM) or flash memory.

Firmware Download

Please visit the [firmware webpage](#).

Document Revision History

A list of the changes made to this document are provided in [Document Revision History](#).

Firmware Compatible Products

The chapter contains the following sections:

These are the release notes for the NVIDIA® ConnectX®-6 Lx adapters firmware. This firmware supports the following protocols:

- Ethernet - 1GbE, 10GbE, 25GbE, 50GbE
- PCI Express 4.0, supporting backwards compatibility for v3.0, v2.0 and v1.1

¹. Speed that supports both NRZ and PAM4 modes in Force mode and Auto-Negotiation mode.

Note

When connecting an NVIDIA-to-NVIDIA adapter card in ETH PAM4 speeds, Auto-Neg should always be enabled.

Supported Devices

This firmware supports the devices and protocols listed below:

Refer to the hardware [documentation](#) for the list of supported devices.

Driver Software, Tools and Switch Firmware

The following are the drivers' software, tools, switch/HCA firmware versions tested that you can upgrade from or downgrade to when using this firmware version:

	Supported Version
ConnectX-6 Lx Firmware	26.39.5124 / 26.39.5050 / 26.39.4082
MLNX_OFED	23.10-6.1.6.1 / 23.10-5.1.4.0 / 23.10-4.0.9.1 Note: For the list of the supported Operating Systems, please refer to the driver's Release Notes.
MLNX_EN (MLNX_OFED based code)	23.10-6.1.6.1 / 23.10-5.1.4.0 / 23.10-4.0.9.1 Note: For the list of the supported Operating Systems, please refer to the driver's Release Notes.
WinOF-2	23.10.51000 / 23.10.50000 / 23.7.50000 Note: For the list of the supported Operating Systems, please refer to the driver's Release Notes.
MFT	4.26.1-35 / 4.26.1-31 / 4.26.1-18 Note: For the list of the supported Operating Systems, please refer to the driver's Release Notes.
mstflint	4.26.1-35 / 4.26.1-31 / 4.26.1-18 Note: For the list of the supported Operating Systems, please refer to the driver's Release Notes.
FlexBoot	3.7.300
UEFI	14.32.17
Cumulus	5.4 onwards

Changes and New Features

Important Notes

Note

SR-IOV - Virtual Functions (VF) per Port - The maximum Virtual Functions (VF) per port is 127. For further information, see [Known Issues](#).

Note

It is recommended to enable the "above 4G decoding" BIOS setting for features that require a large amount of PCIe resources (e.g., SR-IOV with numerous VFs, PCIe Emulated Switch, Large BAR Requests).

i Note

Security Hardening Enhancements: This release contains important reliability improvements and security hardening enhancements. NVIDIA recommends upgrading your devices' firmware to this release to improve the devices' firmware security and reliability.

i Info

To generate PLDM packages for firmware updates, users must install and use the MFT version that corresponds with the respective firmware release.

Customer Affecting Changes

Changes in This Release

Introduced in Version	Description
-----------------------	-------------

26.39.5124	<p>Transition to 2023 Microsoft UEFI Certificate Authority</p> <p>To align with updated Microsoft UEFI Secure Boot requirements and the upcoming end-of-life of the 2011 Certificate Authority (CA), NVIDIA is transitioning to the 2023 CA.</p> <p>This is the final release signed with the 2011 CA. Beginning in February 2026, all releases will be signed exclusively with the 2023 CA. To ensure successful loading of the Expansion ROM (ExpROM) during the UEFI Secure Boot process, system BIOS and operating system trust stores must be updated to include the 2023 CA.</p> <p>Note: Systems must be updated to recognize the 2023 CA to prevent UEFI drivers or ExpROMs from failing to load during boot before June 27, 2026.</p>
------------	--

Unsupported Features and Commands

Unsupported Features

The following advanced feature are unsupported in the current firmware version:

- The following service types:
 - SyncUMR
 - Mellanox transport
 - RAW IPv6
- INT-A not supported for EQs only MSI-X
- PCI VPD write flow (RO flow supported)
- Streaming Receive Queue (STRQ) and collapsed CQ
- Subnet Manager (SM) on VFs
- RoCE LAG in Multi-Host/Socket-Direct

Unsupported Commands

- QUERY_MAD_DEMUX
- SET_MAD_DEMUX
- CREATE_RQ - MEMORY_RQ_RMP
- MODIFY_LAG_ASYNC_EVENT

Bug Fixes in this Firmware Version

Internal Ref.	Issue
4727305 / 4718947	Description: Fixed an issue in the steering definers used for LAG with IPv6 traffic.
	Keywords: LAG, IPv6 traffic, steering
	Discovered in Version: 26.39.5050
	Fixed in Release: 26.39.5124

For a list of old Bug Fixes, please see [Bug Fixes History](#).

Known Issues

VF Network Function Limitations in SRIOV Legacy Mode

Dual Port Device	Single Port Device
127 VF per PF (254 functions)	127

VF Network Function Limitations in Switchdev Mode

Dual Port Device	Single Port Device
127 VF per PF (254 functions)	127

VF+SF Network Function Limitations in Switchdev Mode

Dual Port Device	Single Port Device
<ul style="list-style-type: none">• 127 VF per PF (254 functions)• 512 PF+VF+SF per PF (1024 functions)	<ul style="list-style-type: none">• 127 VF (127 functions)• 512 PF+VF+SF per PF (512 functions)

Known Issues

Internal Ref.	Issue
3464393	Description: PhyLess Reset is currently not supported.
	Workaround: N/A
	Keywords: PhyLess Reset
	Discovered in Version: 26.39.1002

Internal Ref.	Issue
3525865	Description: Unexpected system behavior might be observed if the driver is loaded while reset is in progress.
	Workaround: N/A
	Keywords: Sync 1 reset, firmware reset
	Discovered in Version: 26.39.1002
2878841	Description: Firmware rollback fails for the signature retransmit flow if the QPN field is configured in the mkey (as it only allows the given QP to use this Mkey) as the firmware rollback flow relies on an internal QP that uses the mkey.
	Workaround: N/A
	Keywords: Signature retransmit flow
	Discovered in Version: 26.37.1014
3267506	Description: CRC is included in the traffic byte counters as a port byte counter.
	Workaround: N/A
	Keywords: Counters, CRC
	Discovered in Version: 26.35.2000
3200779	Description: Changing dynamic PCIe link width is not supported.
	Workaround: N/A
	Keywords: PCIe
	Discovered in Version: 26.34.1002
3141072	Description: The "max_shaper_rate" configuration query via QEEC mlxreg returns a value translated to hardware granularity.
	Workaround: N/A
	Keywords: RX Rate-Limiter, Multi-host
	Discovered in Version: 26.34.1002

Internal Ref.	Issue
2870970	<p>Description: GTP encapsulation (flex parser profile 3) is limited to the NIC domain. Encapsulating in the FDB domain will render a 0-size length in GTP header.</p>
	<p>Workaround: N/A</p>
	<p>Keywords: GTP encapsulation</p>
	<p>Discovered in Version: 26.34.1002</p>
2864238	<p>Description: VPD cannot be accessed after firmware upgrade or reset when the following sequence is performed:</p> <ol style="list-style-type: none"> 1. Upgrade to a new firmware and perform a cold reboot 2. Downgrade to an old firmware 3. Run fwreset 4. Upgrade to a new firmware 5. Run fwreset
	<p>Workaround: Run the upgrade or reset sequence as follow:</p> <ol style="list-style-type: none"> 1. Upgrade to a new firmware and perform a cold reboot 2. Downgrade to an old firmware 3. Run fwreset 4. Upgrade to a new firmware 5. <u>Perform a cold reboot</u>
	<p>Keywords: VDP</p>
	<p>Discovered in Version: 26.32.1010</p>
2834990	<p>Description: On rare occasions, when toggling both sides of the link, the link may not rise.</p>
	<p>Workaround: Toggle the port to free it.</p>
	<p>Keywords: Port toggling, link</p>
	<p>Discovered in Version: 26.31.1014</p>

Internal Ref.	Issue
2667681	<p>Description: As the Connection Tracking (CT) is not moved to SW state after receiving a TCP RST packet, any packet that matches the windows even after the RST is marked as a valid packets.</p>
	<p>Workaround: N/A</p>
	<p>Keywords: Connection Tracking</p>
	<p>Discovered in Version: 26.31.1014</p>
2201468	<p>Description: Running multiple resets ("mlxfwreset --sync=1") simultaneously is not functioning properly,</p>
	<p>Workaround: Wait a few seconds until you run "mlxfwreset --sync=0".</p>
	<p>Keywords: mlxfwreset, reset-sync, reset, sync</p>
	<p>Discovered in Version: 26.28.1002</p>

PreBoot Drivers (FlexBoot/UEFI)

FlexBoot Changes and New Features

For further information, please refer to the [FlexBoot Release Notes](#).

UEFI Changes and Major New Features

For further information, please refer to the [UEFI Release Notes](#).

Validated and Supported Cables and Switches

Validated and Supported Cables and Modules

Cables Lifecycle Legend

Lifecycle Phase	Definition
EOL	End of Life
LTB	Last Time Buy
HVM	GA level
MP	GA level
P-Rel	GA level
Preliminary	Engineering Sample
Prototype	Engineering Sample

200GbE Cables

IB Data Rate	Eth Data Rate	NVIDIA P/N	Legacy P/N	Description	LifeCycle Phase
N/A	200GE	980-9154C-00V001	MCP1650-V001E30	NVIDIA Passive Copper cable, 200GbE, 200Gb/s, QSFP56, LSZH, 1m, black pulltab, 30AWG	LTB [HVM]
N/A	200GE	980-9154D-00V002	MCP1650-V002E26	NVIDIA Passive Copper cable, 200GbE, 200Gb/s, QSFP56, LSZH, 2m, black pulltab, 26AWG	LTB [HVM]

IB Data Rate	Eth Data Rate	NVIDIA P/N	Legacy P/N	Description	LifeCycle Phase
N/A	200GE	980-9I54H-00V00A	MCP1650-V00AE30	NVIDIA Passive Copper cable, 200GbE, 200Gb/s, QSFP56, LSZH, 0.5m, black pulltab, 30AWG	LTB [HVM]
N/A	200GE	980-9I54I-00V01A	MCP1650-V01AE30	NVIDIA Passive Copper cable, 200GbE, 200Gb/s, QSFP56, LSZH, 1.5m, black pulltab, 30AWG	LTB [HVM]
N/A	200GE	980-9I54L-00V02A	MCP1650-V02AE26	NVIDIA Passive Copper cable, 200GbE, 200Gb/s, QSFP56, LSZH, 2.5m, black pulltab, 26AWG	LTB [HVM]
N/A	200GE	980-9I98H-00V001	MCP7H50-V001R30	NVIDIA passive copper hybrid cable, 200GbE 200Gb/s to 2x100Gb/s, QSFP56 to 2xQSFP56, colored, 1m, 30AWG	LTB [HVM]
N/A	200GE	980-9I98I-00V002	MCP7H50-V002R26	NVIDIA passive copper hybrid cable, 200GbE 200Gb/s to 2x100Gb/s, QSFP56 to 2xQSFP56, colored, 2m, 26AWG	LTB [HVM]
N/A	200GE	980-9I98J-00V003	MCP7H50-V003R26	NVIDIA passive copper hybrid cable, 200GbE 200Gb/s to 2x100Gb/s, QSFP56 to 2xQSFP56, colored, 3m, 26AWG	EOL [HVM]
N/A	200GE	980-9I98K-00V01A	MCP7H50-V01AR30	NVIDIA passive copper hybrid cable, 200GbE 200Gb/s to 2x100Gb/s, QSFP56 to 2xQSFP56, colored, 1.5m, 30AWG	EOL [HVM]
N/A	200GE	980-9I98M-00V02A	MCP7H50-V02AR26	NVIDIA passive copper hybrid cable, 200GbE 200Gb/s to 2x100Gb/s, QSFP56 to 2xQSFP56, colored, 2.5m, 26AWG	LTB [HVM]

IB Data Rate	Eth Data Rate	NVIDIA P/N	Legacy P/N	Description	LifeCycle Phase
N/A	200GE	980-9IA3X-00V001	MCP7H70-V001R30	NVIDIA passive copper hybrid cable, 200GbE 200Gb/s to 4x50Gb/s, QSFP56 to 4xSFP56, colored, 1m, 30AWG	EOL [P-Rel]
N/A	200GE	980-9IA3Y-00V002	MCP7H70-V002R26	NVIDIA passive copper hybrid cable, 200GbE 200Gb/s to 4x50Gb/s, QSFP56 to 4xSFP56, colored, 2m, 26AWG	EOL [P-Rel]
N/A	200GE	980-9I43Z-00V003	MCP7H70-V003R26	NVIDIA passive copper hybrid cable, 200GbE 200Gb/s to 4x50Gb/s, QSFP56 to 4x4SFP56, colored, 3m, 26AWG	EOL [P-Rel]
N/A	200GE	980-9I430-00V01A	MCP7H70-V01AR30	NVIDIA passive copper hybrid cable, 200GbE 200Gb/s to 4x50Gb/s, QSFP56 to 4xSFP56, colored, 1.5m, 30AWG	EOL [P-Rel]
N/A	200GE	980-9I431-00V02A	MCP7H70-V02AR26	NVIDIA passive copper hybrid cable, 200GbE 200Gb/s to 4x50Gb/s, QSFP56 to 4xSFP56, colored, 2.5m, 26AWG	EOL [P-Rel]

100GbE Cables

IB Data Rate	Eth Data Rate	NVIDIA P/N	Legacy P/N	Description	LifeCycle Phase
N/A	100GE	980-9I620-00C001	MCP1600-C001E30N	NVIDIA Passive Copper cable, ETH 100GbE, 100Gb/s, QSFP28, 1m, Black, 30AWG, CA-N	HVM
N/A	100GE	980-9I62V-00C002	MCP1600-C002E30N	NVIDIA Passive Copper cable, ETH 100GbE, 100Gb/s, QSFP28, 2m, Black, 30AWG, CA-N	HVM

IB Data Rate	Eth Data Rate	NVIDIA P/N	Legacy P/N	Description	LifeCycle Phase
N/A	100GE	980-9I62Z-00C003	MCP1600-C003E26N	NVIDIA Passive Copper cable, ETH 100GbE, 100Gb/s, QSFP28, 3m, Black, 26AWG, CA-N	EOL [HVM]
N/A	100GE	980-9I620-00C003	MCP1600-C003E30L	NVIDIA Passive Copper cable, ETH 100GbE, 100Gb/s, QSFP28, 3m, Black, 30AWG, CA-L	HVM
N/A	100GE	980-9I627-00C00A	MCP1600-C00AE30N	NVIDIA Passive Copper cable, ETH 100GbE, 100Gb/s, QSFP28, 0.5m, Black, 30AWG, CA-N	EOL [HVM]
N/A	100GE	980-9I62C-00C01A	MCP1600-C01AE30N	NVIDIA Passive Copper cable, ETH 100GbE, 100Gb/s, QSFP28, 1.5m, Black, 30AWG, CA-N	HVM
N/A	100GE	980-9I62I-00C02A	MCP1600-C02AE30L	NVIDIA Passive Copper cable, ETH 100GbE, 100Gb/s, QSFP28, 2.5m, Black, 30AWG, CA-L	HVM
EDR	100GE	980-9I62P-00C001	MCP1600-E001	NVIDIA Passive Copper cable, IB EDR, up to 100Gb/s, QSFP, LSZH, 1m 30AWG	EOL [HVM]
EDR	100GE	980-9I62S-00C002	MCP1600-E002	NVIDIA Passive Copper cable, IB EDR, up to 100Gb/s, QSFP, LSZH, 2m 28AWG	EOL [HVM]
EDR	100GE	980-9I62V-00C003	MCP1600-E003	NVIDIA Passive Copper cable, IB EDR, up to 100Gb/s, QSFP, LSZH, 3m 26AWG	EOL [HVM]
EDR	100GE	980-9I623-00C01A	MCP1600-E01A	NVIDIA Passive Copper cable, IB EDR, up to 100Gb/s, QSFP, LSZH, 1.5m 30AWG	EOL [HVM]
EDR	100GE	980-9I626-00C02A	MCP1600-E02A	NVIDIA Passive Copper cable, IB EDR, up to 100Gb/s, QSFP, LSZH, 2.5m 26AWG	EOL [HVM]

IB Data Rate	Eth Data Rate	NVIDIA P/N	Legacy P/N	Description	LifeCycle Phase
N/A	100GE	980-9I645-00C001	MCP7F00-A001R	NVIDIA passive copper hybrid cable, ETH 100GbE to 4x25GbE, QSFP28 to 4xSFP28, colored pulltabs, 1m, 30AWG	EOL [HVM]
N/A	100GE	980-9I486-00C001	MCP7F00-A001R30N	NVIDIA passive copper hybrid cable, ETH 100GbE to 4x25GbE, QSFP28 to 4xSFP28, 1m, Colored, 30AWG, CA-N	LTB [HVM]
N/A	100GE	980-9I48A-00C002	MCP7F00-A002R	NVIDIA passive copper hybrid cable, ETH 100GbE to 4x25GbE, QSFP28 to 4xSFP28, colored pulltabs, 2m, 30AWG	EOL [HVM]
N/A	100GE	980-9I48B-00C002	MCP7F00-A002R30N	NVIDIA passive copper hybrid cable, ETH 100GbE to 4x25GbE, QSFP28 to 4xSFP28, 2m, Colored, 30AWG, CA-N	LTB [HVM]
N/A	100GE	980-9I48G-00C003	MCP7F00-A003R26N	NVIDIA passive copper hybrid cable, ETH 100GbE to 4x25GbE, QSFP28 to 4xSFP28, 3m, Colored, 26AWG, CA-N	EOL [HVM]
N/A	100GE	980-9I48H-00C003	MCP7F00-A003R30L	NVIDIA passive copper hybrid cable, ETH 100GbE to 4x25GbE, QSFP28 to 4xSFP28, 3m, Colored, 30AWG, CA-L	LTB [HVM]
N/A	100GE	980-9I48J-00C005	MCP7F00-A005R26L	NVIDIA passive copper hybrid cable, ETH 100GbE to 4x25GbE, QSFP28 to 4xSFP28, 5m, Colored, 26AWG, CA-L	LTB [HVM]
N/A	100GE	980-9I48M-00C01A	MCP7F00-A01AR	NVIDIA passive copper hybrid cable, ETH 100GbE to 4x25GbE, QSFP28 to 4xSFP28, colored pulltabs, 1.5m, 30AWG	EOL [HVM]
N/A	100GE	980-9I48N-00C01A	MCP7F00-A01AR30N	NVIDIA passive copper hybrid cable, ETH 100GbE to 4x25GbE, QSFP28 to 4xSFP28, 1.5m, Colored, 30AWG, CA-N	LTB [HVM]

IB Data Rate	Eth Data Rate	NVIDIA P/N	Legacy P/N	Description	LifeCycle Phase
N/A	100GE	980-9I48S-00C02A	MCP7F00-A02AR26N	NVIDIA passive copper hybrid cable, ETH 100GbE to 4x25GbE, QSFP28 to 4xSFP28, 2.5m, Colored, 26AWG, CA-N	EOL [HVM]
N/A	100GE	980-9I48T-00C02A	MCP7F00-A02AR30L	NVIDIA passive copper hybrid cable, ETH 100GbE to 4x25GbE, QSFP28 to 4xSFP28, 2.5m, Colored, 30AWG, CA-L	LTB [HVM]
N/A	100GE	980-9I48U-00C02A	MCP7F00-A02ARLZ	NVIDIA passive copper hybrid cable, ETH 100GbE to 4x25GbE, QSFP28 to 4xSFP28, 2.5m, LSZH, Colored, 28AWG	EOL [P-Rel]
N/A	100GE	980-9I48X-00C03A	MCP7F00-A03AR26L	NVIDIA passive copper hybrid cable, ETH 100GbE to 4x25GbE, QSFP28 to 4xSFP28, 3.5m, Colored, 26AWG, CA-L	EOL [HVM]
N/A	100GE	980-9I61C-00C005	MCP7H00-G00000	NVIDIA® passive copper hybrid cable, ETH 100Gb/s to 2x50Gb/s, QSFP28 to 2xQSFP28, 5m, Colored, 26AWG, CA-L	Preliminary
N/A	100GE	980-9I61D-00C001	MCP7H00-G001	NVIDIA passive copper hybrid cable, ETH 100Gb/s to 2x50Gb/s, QSFP28 to 2xQSFP28, 1m, 30AWG	EOL [HVM]
N/A	100GE	980-9I99F-00C001	MCP7H00-G001R	NVIDIA passive copper hybrid cable, ETH 100Gb/s to 2x50Gb/s, QSFP28 to 2xQSFP28, colored pulltabs, 1m, 30AWG	EOL [HVM]
N/A	100GE	980-9I99G-00C001	MCP7H00-G001R30N	NVIDIA passive copper hybrid cable, ETH 100Gb/s to 2x50Gb/s, QSFP28 to 2xQSFP28, 1m, Colored, 30AWG, CA-N	LTB [HVM]

IB Data Rate	Eth Data Rate	NVIDIA P/N	Legacy P/N	Description	LifeCycle Phase
N/A	100GE	980-9I99J-00C002	MCP7H00-G002R	NVIDIA passive copper hybrid cable, ETH 100Gb/s to 2x50Gb/s, QSFP28 to 2xQSFP28, colored pulltabs, 2m, 30AWG	EOL [HVM]
N/A	100GE	980-9I99K-00C002	MCP7H00-G002R26N	NVIDIA® passive copper hybrid cable, ETH 100Gb/s to 2x50Gb/s, QSFP28 to 2xQSFP28, 2m, Colored, 26AWG, CA-N	Preliminary
N/A	100GE	980-9I99L-00C002	MCP7H00-G002R30N	NVIDIA passive copper hybrid cable, ETH 100Gb/s to 2x50Gb/s, QSFP28 to 2xQSFP28, 2m, Colored, 30AWG, CA-N	LTB [HVM]
N/A	100GE	980-9I99O-00C003	MCP7H00-G003R	NVIDIA passive copper hybrid cable, ETH 100Gb/s to 2x50Gb/s, QSFP28 to 2xQSFP28, colored pulltabs, 3m, 28AWG	EOL [HVM]
N/A	100GE	980-9I99Q-00C003	MCP7H00-G003R26N	NVIDIA passive copper hybrid cable, ETH 100Gb/s to 2x50Gb/s, QSFP28 to 2xQSFP28, 3m, Colored, 26AWG, CA-N	EOL [HVM]
N/A	100GE	980-9I39R-00C003	MCP7H00-G003R30L	NVIDIA passive copper hybrid cable, ETH 100Gb/s to 2x50Gb/s, QSFP28 to 2xQSFP28, 3m, Colored, 30AWG, CA-L	LTB [HVM]
N/A	100GE	980-9I99S-00C004	MCP7H00-G004R26L	NVIDIA passive copper hybrid cable, ETH 100Gb/s to 2x50Gb/s, QSFP28 to 2xQSFP28, 4m, Colored, 26AWG, CA-L	EOL [HVM]

IB Data Rate	Eth Data Rate	NVIDIA P/N	Legacy P/N	Description	LifeCycle Phase
N/A	100GE	980-9I99W-00C01A	MCP7H00-G01AR	NVIDIA passive copper hybrid cable, ETH 100Gb/s to 2x50Gb/s, QSFP28 to 2xQSFP28, colored pulltabs, 1.5m, 30AWG	EOL [HVM]
N/A	100GE	980-9I99X-00C01A	MCP7H00-G01AR30N	NVIDIA passive copper hybrid cable, ETH 100Gb/s to 2x50Gb/s, QSFP28 to 2xQSFP28, 1.5m, Colored, 30AWG, CA-N	LTB [HVM]
N/A	100GE	980-9I992-00C02A	MCP7H00-G02AR	NVIDIA passive copper hybrid cable, ETH 100Gb/s to 2x50Gb/s, QSFP28 to 2xQSFP28, colored pulltabs, 2.5m, 30AWG	EOL [HVM]
N/A	100GE	980-9I994-00C02A	MCP7H00-G02AR26N	NVIDIA passive copper hybrid cable, ETH 100Gb/s to 2x50Gb/s, QSFP28 to 2xQSFP28, 2.5m, Colored, 26AWG, CA-N	EOL [HVM]
N/A	100GE	980-9I395-00C02A	MCP7H00-G02AR30L	NVIDIA passive copper hybrid cable, ETH 100Gb/s to 2x50Gb/s, QSFP28 to 2xQSFP28, 2.5m, Colored, 30AWG, CA-L	LTB [HVM]
N/A	100GE	980-9I13S-00C003	MFA1A00-C003	NVIDIA active fiber cable, ETH 100GbE, 100Gb/s, QSFP, LSZH, 3m	HVM
N/A	100GE	980-9I13X-00C005	MFA1A00-C005	NVIDIA active fiber cable, ETH 100GbE, 100Gb/s, QSFP, LSZH, 5m	HVM
N/A	100GE	980-9I134-00C010	MFA1A00-C010	NVIDIA active fiber cable, ETH 100GbE, 100Gb/s, QSFP, LSZH, 10m	HVM

IB Data Rate	Eth Data Rate	NVIDIA P/N	Legacy P/N	Description	LifeCycle Phase
N/A	100GE	980-9I13A-00C015	MFA1A00-C015	NVIDIA active fiber cable, ETH 100GbE, 100Gb/s, QSFP, LSZH, 15m	HVM
N/A	100GE	980-9I13F-00C020	MFA1A00-C020	NVIDIA active fiber cable, ETH 100GbE, 100Gb/s, QSFP, LSZH, 20m	HVM
N/A	100GE	980-9I13N-00C030	MFA1A00-C030	NVIDIA active fiber cable, ETH 100GbE, 100Gb/s, QSFP, LSZH, 30m	HVM
N/A	100GE	980-9I130-00C050	MFA1A00-C050	NVIDIA active fiber cable, ETH 100GbE, 100Gb/s, QSFP, LSZH, 50m	HVM
N/A	100GE	980-9I13B-00C100	MFA1A00-C100	NVIDIA active fiber cable, ETH 100GbE, 100Gb/s, QSFP, LSZH, 100m	LTB [HVM]
N/A	100GE	980-9I37H-00C003	MFA7A20-C003	NVIDIA active fiber hybrid solution, ETH 100GbE to 2x50GbE, QSFP28 to 2xQSFP28, 3m	EOL [HVM]
N/A	100GE	980-9I37I-00C005	MFA7A20-C005	NVIDIA active fiber hybrid solution, ETH 100GbE to 2x50GbE, QSFP28 to 2xQSFP28, 5m	EOL [HVM]
N/A	100GE	980-9I40J-00C010	MFA7A20-C010	NVIDIA active fiber hybrid solution, ETH 100GbE to 2x50GbE, QSFP28 to 2xQSFP28, 10m	EOL [HVM]
N/A	100GE	980-9I40K-00C020	MFA7A20-C020	NVIDIA active fiber hybrid solution, ETH 100GbE to 2x50GbE, QSFP28 to 2xQSFP28, 20m	EOL [HVM]
N/A	100GE	980-9I40L-00C002	MFA7A20-C02A	NVIDIA® active fiber hybrid solution, ETH 100GbE to 2x50GbE, QSFP28 to 2xQSFP28, 2.5m	Preliminary

IB Data Rate	Eth Data Rate	NVIDIA P/N	Legacy P/N	Description	LifeCycle Phase
N/A	100GE	980-9I40M-00C003	MFA7A20-C03A	NVIDIA® active fiber hybrid solution, ETH 100GbE to 2x50GbE, QSFP28 to 2xQSFP28, 3.5m	Preliminary
N/A	100GE	980-9I40N-00C003	MFA7A50-C003	NVIDIA active fiber hybrid solution, ETH 100GbE to 4x25GbE, QSFP28 to 4xSFP28, 3m	EOL [HVM]
N/A	100GE	980-9I40O-00C005	MFA7A50-C005	NVIDIA active fiber hybrid solution, ETH 100GbE to 4x25GbE, QSFP28 to 4xSFP28, 5m	EOL [HVM]
N/A	100GE	980-9I49P-00C010	MFA7A50-C010	NVIDIA active fiber hybrid solution, ETH 100GbE to 4x25GbE, QSFP28 to 4xSFP28, 10m	EOL [HVM]
N/A	100GE	980-9I49Q-00C015	MFA7A50-C015	NVIDIA active fiber hybrid solution, ETH 100GbE to 4x25GbE, QSFP28 to 4xSFP28, 15m	EOL [HVM]
N/A	100GE	980-9I49R-00C020	MFA7A50-C020	NVIDIA active fiber hybrid solution, ETH 100GbE to 4x25GbE, QSFP28 to 4xSFP28, 20m	EOL [HVM]
N/A	100GE	980-9I49S-00C030	MFA7A50-C030	NVIDIA active fiber hybrid solution, ETH 100GbE to 4x25GbE, QSFP28 to 4xSFP28, 30m	EOL [HVM]
N/A	100GE	980-9I149-00CS00	MMA1B00-C100D	NVIDIA transceiver, 100GbE, QSFP28, MPO, 850nm, SR4, up to 100m, DDMI	HVM

Note

The spilt cables cables above can be used as split cables when ConnectX-6 Lx adapter card in on the split side.

25GbE Cables

IB Data Rate	Eth Data Rate	NVIDIA P/N	Legacy OPN	Description	LifeCycle Phase
N/A	25GE	980-9I78I-00A000	MAM1Q00A-QSA28	NVIDIA cable module, ETH 25GbE, 100Gb/s to 25Gb/s, QSFP28 to SFP28	HVM
N/A	25GE	980-9I63J-00A001	MCP2M00-A001	NVIDIA Passive Copper cable, ETH, up to 25Gb/s, SFP28, 1m, 30AWG	EOL [HVM]
N/A	25GE	980-9I63L-00A001	MCP2M00-A001E30N	NVIDIA Passive Copper cable, ETH, up to 25Gb/s, SFP28, 1m, Black, 30AWG, CA-N	LTB [HVM]
N/A	25GE	980-9I63M-00A002	MCP2M00-A002	NVIDIA Passive Copper cable, ETH, up to 25Gb/s, SFP28, 2m, 30AWG	EOL [HVM]
N/A	25GE	980-9I63N-00A002	MCP2M00-A002E26N	NVIDIA® Passive Copper cable, ETH, up to 25Gb/s, SFP28, 2m, Black, 26AWG, CA-N	Preliminary
N/A	25GE	980-9I63O-00A002	MCP2M00-A002E30N	NVIDIA Passive Copper cable, ETH, up to 25Gb/s, SFP28, 2m, Black, 30AWG, CA-N	LTB [HVM]

IB Data Rate	Eth Data Rate	NVIDIA P/N	Legacy OPN	Description	LifeCycle Phase
N/A	25GE	980-9I63R-00A003	MCP2M00-A003E26N	NVIDIA Passive Copper cable, ETH, up to 25Gb/s, SFP28, 3m, Black, 26AWG, CA-N	EOL [HVM]
N/A	25GE	980-9I63S-00A003	MCP2M00-A003E30L	NVIDIA Passive Copper cable, ETH, up to 25Gb/s, SFP28, 3m, Black, 30AWG, CA-L	LTB [HVM]
N/A	25GE	980-9I63T-00A004	MCP2M00-A004E26L	NVIDIA Passive Copper cable, ETH, up to 25Gb/s, SFP28, 4m, Black, 26AWG, CA-L	EOL [HVM]
N/A	25GE	980-9I63V-00A005	MCP2M00-A005E26L	NVIDIA Passive Copper cable, ETH, up to 25Gb/s, SFP28, 5m, Black, 26AWG, CA-L	LTB [HVM]
N/A	25GE	980-9I63W-00A00A	MCP2M00-A00A	NVIDIA Passive Copper cable, ETH, up to 25Gb/s, SFP28, 0.5m, 30AWG	EOL [HVM]
N/A	25GE	980-9I63X-00A00A	MCP2M00-A00AE30N	NVIDIA Passive Copper cable, ETH, up to 25Gb/s, SFP28, 0.5m, Black, 30AWG, CA-N	EOL [HVM]
N/A	25GE	980-9I63Z-00A01A	MCP2M00-A01AE30N	NVIDIA Passive Copper cable, ETH, up to 25Gb/s, SFP28, 1.5m, Black, 30AWG, CA-N	LTB [HVM]
N/A	25GE	980-9I631-00A02A	MCP2M00-A02AE26N	NVIDIA Passive Copper cable, ETH, up to 25Gb/s, SFP28, 2.5m, Black, 26AWG, CA-N	EOL [HVM]
N/A	25GE	980-9I632-00A02A	MCP2M00-A02AE30L	NVIDIA Passive Copper cable, ETH, up to 25Gb/s, SFP28, 2.5m, Black, 30AWG, CA-L	LTB [HVM]

IB Data Rate	Eth Data Rate	NVIDIA P/N	Legacy OPN	Description	LifeCycle Phase
N/A	25GE	980-9IA1T-00A003	MFA2P10-A003	NVIDIA active optical cable 25GbE, SFP28, 3m	EOL [HVM]
N/A	25GE	980-9I53W-00A005	MFA2P10-A005	NVIDIA active optical cable 25GbE, SFP28, 5m	EOL [HVM]
N/A	25GE	980-9I53Z-00A007	MFA2P10-A007	NVIDIA active optical cable 25GbE, SFP28, 7m	EOL [HVM]
N/A	25GE	980-9I532-00A010	MFA2P10-A010	NVIDIA active optical cable 25GbE, SFP28, 10m	EOL [HVM]
N/A	25GE	980-9I535-00A015	MFA2P10-A015	NVIDIA active optical cable 25GbE, SFP28, 15m	EOL [HVM]
N/A	25GE	980-9I536-00A020	MFA2P10-A020	NVIDIA active optical cable 25GbE, SFP28, 20m	EOL [HVM]
N/A	25GE	980-9I539-00A030	MFA2P10-A030	NVIDIA active optical cable 25GbE, SFP28, 30m	EOL [HVM]
N/A	25GE	980-9I53A-00A050	MFA2P10-A050	NVIDIA active optical cable 25GbE, SFP28, 50m	EOL [HVM]
N/A	25GE	980-9I094-00AR00	MMA2L20-AR	NVIDIA optical transceiver, 25GbE, 25Gb/s, SFP28, LC-LC, 1310nm, LR up to 10km	MP
N/A	25GE	980-9I595-00AM00	MMA2P00-AS	NVIDIA transceiver, 25GbE, SFP28, LC-LC, 850nm, SR	HVM
N/A	25GE	980-9I34B-00AS00	MMA2P00-AS-SP	NVIDIA transceiver, 25GbE, SFP28, LC-LC, 850nm, SR, up to 100m, single package	EOL [HVM]
N/A	25GE	980-9I34D-00AS00	MMA2P00-AS_FF	NVIDIA transceiver, 25GbE, SFP28, LC-LC, 850nm, SR, up to 100m	EOL [HVM]

10GbE Cables

IB Data Rate	Eth Data Rate	NVIDIA P/N	Legacy OPN	Description	LifeCycle Phase
N/A	10GE	980-9I71G-00J000	MAM1Q00A-QSA	NVIDIA cable module, ETH 10GbE, 40Gb/s to 10Gb/s, QSFP to SFP+	HVM
N/A	10GE	980-9I65P-00J005	MC2309124-005	NVIDIA passive copper hybrid cable, ETH 10GbE, 10Gb/s, QSFP to SFP+, 5m	EOL [P-Rel]
N/A	10GE	980-9I65Q-00J007	MC2309124-007	NVIDIA passive copper hybrid cable, ETH 10GbE, 10Gb/s, QSFP to SFP+, 7m	EOL [P-Rel]
N/A	10GE	980-9I65R-00J001	MC2309130-001	NVIDIA passive copper hybrid cable, ETH 10GbE, 10Gb/s, QSFP to SFP+, 1m	EOL [HVM]
N/A	10GE	980-9I65S-00J002	MC2309130-002	NVIDIA passive copper hybrid cable, ETH 10GbE, 10Gb/s, QSFP to SFP+, 2m	EOL [HVM]
N/A	10GE	980-9I65T-00J003	MC2309130-003	NVIDIA passive copper hybrid cable, ETH 10GbE, 10Gb/s, QSFP to SFP+, 3m	EOL [HVM]
N/A	10GE	980-9I65U-00J00A	MC2309130-00A	NVIDIA passive copper hybrid cable, ETH 10GbE, 10Gb/s, QSFP to SFP+, 0.5m	EOL [HVM] [HIBERN/ATE]
N/A	10GE	980-9I682-00J004	MC3309124-004	NVIDIA passive copper cable, ETH 10GbE, 10Gb/s, SFP+, 4m	EOL [HVM]
N/A	10GE	980-9I683-00J005	MC3309124-005	NVIDIA passive copper cable, ETH 10GbE, 10Gb/s, SFP+, 5m	EOL [HVM]
N/A	10GE	980-9I684-00J006	MC3309124-006	NVIDIA passive copper cable, ETH 10GbE, 10Gb/s, SFP+, 6m	EOL [HVM]

IB Data Rate	Eth Data Rate	NVIDIA P/N	Legacy OPN	Description	LifeCycle Phase
N/A	10GE	980-9I685-00J007	MC3309124-007	NVIDIA passive copper cable, ETH 10GbE, 10Gb/s, SFP+, 7m	EOL [HVM]
N/A	10GE	980-9I686-00J001	MC3309130-001	NVIDIA passive copper cable, ETH 10GbE, 10Gb/s, SFP+, 1m	EOL [HVM]
N/A	10GE	980-9I688-00J002	MC3309130-002	NVIDIA passive copper cable, ETH 10GbE, 10Gb/s, SFP+, 2m	EOL [HVM]
N/A	10GE	980-9I68B-00J003	MC3309130-003	NVIDIA passive copper cable, ETH 10GbE, 10Gb/s, SFP+, 3m	EOL [HVM]
N/A	10GE	980-9I68F-00J00A	MC3309130-00A	NVIDIA passive copper cable, ETH 10GbE, 10Gb/s, SFP+, 0.5m	EOL [HVM]
N/A	10GE	980-9I68G-00J01A	MC3309130-0A1	NVIDIA passive copper cable, ETH 10GbE, 10Gb/s, SFP+, 1.5m	EOL [HVM]
N/A	10GE	980-9I68H-00J02A	MC3309130-0A2	NVIDIA passive copper cable, ETH 10GbE, 10Gb/s, SFP+, 2.5m	EOL [HVM]
N/A	10GE	980-9I68A-00J001	MCP2100-X001B	NVIDIA passive copper cable, ETH 10GbE, 10Gb/s, SFP+, 1m, Blue Pulltab, Connector Label	EOL [HVM] [HIBERN/ATE]
N/A	10GE	980-9I68B-00J002	MCP2100-X002B	NVIDIA passive copper cable, ETH 10GbE, 10Gb/s, SFP+, 2m, Blue Pulltab, Connector Label	EOL [HVM] [HIBERN/ATE]
N/A	10GE	980-9I68C-00J003	MCP2100-X003B	NVIDIA passive copper cable, ETH 10GbE, 10Gb/s, SFP+, 3m, Blue Pulltab, Connector Label	EOL [HVM]

IB Data Rate	Eth Data Rate	NVIDIA P/N	Legacy OPN	Description	LifeCycle Phase
N/A	10GE	980-9I68E-00J001	MCP2104-X001B	NVIDIA passive copper cable, ETH 10GbE, 10Gb/s, SFP+, 1m, Black Pulltab, Connector Label	EOL [HVM] [HIBERN/ATE]
N/A	10GE	980-9I68F-00J002	MCP2104-X002B	NVIDIA passive copper cable, ETH 10GbE, 10Gb/s, SFP+, 2m, Black Pulltab, Connector Label	EOL [HVM]
N/A	10GE	980-9I68G-00J003	MCP2104-X003B	NVIDIA passive copper cable, ETH 10GbE, 10Gb/s, SFP+, 3m, Black Pulltab, Connector Label	EOL [HVM]
N/A	10GE	980-9I68H-00J01A	MCP2104-X01AB	NVIDIA passive copper cable, ETH 10GbE, 10Gb/s, SFP+, 1.5m, Black Pulltab, Connector Label	EOL [HVM]
N/A	10GE	980-9I68I-00J02A	MCP2104-X02AB	NVIDIA passive copper cable, ETH 10GbE, 10Gb/s, SFP+, 2.5m, Black Pulltab, Connector Label	EOL [HVM]
N/A	10GE	930-90000-0000-343	MFM1T02A-LR	NVIDIA SFP+ optical module for 10GBASE-LR	HVM
N/A	10GE	MFM1T02A-LR-F	MFM1T02A-LR-F	NVIDIA optical module, ETH 10GbE, 10Gb/s, SFP+, LC-LC, 1310nm, LR up to 10km	HVM
N/A	10GE	930-90000-0000-409	MFM1T02A-SR	NVIDIA SFP+ optical module for 10GBASE-SR	HVM
N/A	10GE	MFM1T02A-SR-F	MFM1T02A-SR-F	NVIDIA optical module, ETH 10GbE, 10Gb/s, SFP+, LC-LC, 850nm, SR up to 300m	HVM

IB Data Rate	Eth Data Rate	NVIDIA P/N	Legacy OPN	Description	LifeCycle Phase
N/A	10GE	MFM1T02A-SR-P	MFM1T02A-SR-P	NVIDIA optical module, ETH 10GbE, 10Gb/s, SFP+, LC-LC, 850nm, SR up to 300m	HVM

1GbE Cables

IB Data Rate	Eth Data Rate	NVIDIA P/N	Legacy OPN	Description	LifeCycle Phase
N/A	1GE	980-9I270-00IM00	MC3208011-SX	NVIDIA Optical module, ETH 1GbE, 1Gb/s, SFP, LC-LC, SX 850nm, up to 500m	EOL [P-Rel]
N/A	1GE	980-9I251-00IS00	MC3208411-T	NVIDIA module, ETH 1GbE, 1Gb/s, SFP, Base-T, up to 100m	HVM

Supported 3rd Party Cables and Modules

Speed	Cable OPN	Description
10GbE	74752-9096	Dell Active DAC SFP+, Cisco PN SFP-H10GB-CU5M, Molex PN 74752-9096
10GbE	74752-9096 (SFP-H10GB-SU5M)	Cisco-Molex INC Active DAC SFP+ 5m
10GbE	74752-9521	CISCO-MOLEX SFP28/SFP+ 10G Passive copper cable
10GbE	74752-9521 (SFP-H10GB-CU5M)	Cisco 10GBASE SFP+ modules
10GbE	BN-QS-SP-CBL-5M	40G QSFP+ to 4xSFP+ DAC Breakout Direct Attach Cable 5m

Speed	Cable OPN	Description
10GbE	BN-QS-SP-CBL-5M	40G QSFP+ to 4xSFP+ DAC Breakout Direct Attach Cable 5m
10GbE	CAB-SFP-SFP-1M	Arista 10GBASE-CR SFP+ Cable 1 Meter
10GbE	CAB-SFP-SFP-1M	Arista Compatible 10G SFP+ Passive Cable 1m
10GbE	CAB-SFP-SFP-3M	Arista 10GBASE-CR SFP+ Cable 3 Meter
10GbE	CAB-SFP-SFP-5M	Arista 10GBASE-CR SFP+ Cable 5 Meter
10GbE	CAB-SFP-SFP-5M	Arista Compatible 10G SFP+ Passive Cable 5m
10GbE	FTLX1471D3BCL-ME	10GBASE-LR SFP+ 1310nm 10km DOM Transceiver Module
10GbE	FTLX8570D3BCL-C2	Cisco FET-10G 10-2566-02 FTLX8570D3BCL-C2 10Gbps Fabric Extender SFP+ Module
10GbE	FTLX8571D3BCL-ME	10gb SFP 850nm Optic Transceiver
10GbE	L45593-D178-B50	QSFP-4SFP10G-CU5M
10GbE	SFP-10G-SR	Cisco 10GBASE-SR SFP+ transceiver module for MMF, 850-nm wavelength, LC duplex connector
10GbE	SFP-10GB-SR	Cisco SFP+ 10GB SR optic module
10GbE	SFP-H10GB-CU1M	Cisco 1-m 10G SFP+ Twinax cable assembly, passive
10GbE	SFP-H10GB-CU3M	Cisco 3-m 10G SFP+ Twinax cable assembly, passive
10GbE	SFP-H10GB-CU5M	Cisco 5-m 10G SFP+ Twinax cable assembly, passive
10GbE	DM7053	10G-Base-T MethodElec modules
25GbE	FTLF8536P4BCL	TRANSCEIVER 25GBE SFP SR
25GbE	LTF8507-PC07	HISENSE ACTIVE FIBER CABLE, 25GBE
25GbE	SFP-H25G-CU3M	CISCO 25GBASE-CR1 COPPER CABLE 3-METER NDCCGJ-C403

Tested Switches

100GbE Switches

Speed	Switch Silicon	OPN # / Name	Description	Vendor
100GbE	Spectrum-3	MSN4600-XXXX	64-port Non-blocking 100GbE Open Ethernet Switch System	NVIDIA
100GbE	Spectrum-2	MSN3700C-XXXX	32-port Non-blocking 100GbE Open Ethernet Switch System	NVIDIA
100GbE	Spectrum-2	MSN3420-XXXX	48 SFP + 12 QSFP ports Non-blocking 100GbE Open Ethernet Switch System	NVIDIA
100GbE	Spectrum	MSN2410-XXXX	48-port 25GbE + 8-port 100GbE Open Ethernet Switch System	NVIDIA
100GbE	Spectrum	MSN2700-XXXX	32-port Non-blocking 100GbE Open Ethernet Switch System	NVIDIA
100GbE	N/A	QFX5200-32C-32	32-port 100GbE Ethernet Switch System	Juniper
100GbE	N/A	S6820-56HF	48 SFP+ + 8 QSFP Ports 100GbE Switch Ethernet	H3C
100GbE	N/A	CE6860-1-48S8CQ-EI	Huawei 100GbE Ethernet switch	Huawei
100GbE	N/A	7060CX-32S	32-port 100GbE Ethernet Switch System	Arista
100GbE	N/A	3232C	32-port 100GbE Ethernet Switch System	Cisco
100GbE	N/A	N9K-C9236C	36-port 100GbE Ethernet Switch System	Cisco
100GbE	N/A	93180YC-EX	48-port 25GbE + 6-port 100GbE Ethernet Switch System	Cisco
100GbE	N/A	T7032-IX7	32-port 100GbE Ethernet Switch System	Quanta

10/40GbE Switches

Speed	Switch Silicon	OPN # / Name	Description	Vendor
10GbE	N/A	5548UP	32x 10GbE SFP+ Switch System	Cisco
10/40GbE	N/A	7050Q	16 x 40GbE QSFP+ Switch System	Arista
10/40GbE	N/A	7050S	48x 10GbE SFP+ and 4 x 40GbE QSFP+ Switch System	Arista
10/40GbE	N/A	G8264	48x 10GbE SFP+ and 4 x 40GbE QSFP+ Switch System	Lenovo
10/40GbE	N/A	QFX3500	48x 10GbE SFP+ and 4 x 40GbE QSFP+ Switch System	Juniper
10/40GbE	N/A	S4810P-AC	48x 10GbE SFP+ and 4 x 40GbE QSFP+ Switch System	Force10
10/40GbE	N/A	3064	48x 10GbE SFP+ and 4 x 40GbE QSFP+ Switch System	Cisco
10/40GbE	N/A	8164F	48x 10GbE SFP+ and 2 x 40GbE QSFP+ Switch System	Dell
10/40GbE	N/A	S5000	48x 10GbE SFP+ and 4 x 40GbE QSFP+ Switch System	Dell
10/40GbE	N/A	3132Q	4x 10GbE SFP+ and 32 x 40GbE QSFP+ Switch System	Cisco
40GbE	N/A	7050QX	32x 40GbE QSFP+ Switch System	Arista
40GbE	N/A	G8316	16x 40GbE QSFP+ Switch System	Lenovo
40GbE	N/A	S6000	32x 40GbE QSFP+ Switch System	Dell

PRM Revision Compatibility

This firmware version complies with the following Programmer's Reference Manual:

- Adapters Programmer's Reference Manual (PRM), Rev 0.53 or later, which has Command Interface Revision 0x5. The command interface revision can be retrieved by means of the QUERY_FW command and is indicated by the field cmd_interface_rev.

Supported Non-Volatile Configurations

Configuration	mlxconfig Parameter Name	Class
NV_MEMIC_CONF	MEMIC_BAR_SIZE	GLOBAL (0)
	MEMIC_SIZE_LIMIT	
NV_HOST_CHAINING_CONF	HOST_CHAINING_MODE	
	HOST_CHAINING_DESCRIPTOR	
	HOST_CHAINING_TOTAL_BUFFER_SIZE	
NV_FLEX_PARS_CONF	FLEX_PARSER_PROFILE_ENABLE	
	FLEX_IPV4_OVER_VXLAN_PORT	
NV_ROCE_1_5_CONF	ROCE_NEXT_PROTOCOL	
NV_INTERNAL_RESOURCE_CONF	ESWITCH_HAIRPIN_DESCRIPTOR	
	ESWITCH_HAIRPIN_TOT_BUFFER_SIZE	
NV_GLOBAL_PCI_CONF	NON_PREFETCHABLE_PF_BAR	
	NUM_OF_VFS	
	SRIOV_EN	
	PF_LOG_BAR_SIZE	
	VF_LOG_BAR_SIZE	
	NUM_PF_MSIX	
	NUM_VF_MSIX	
NV_TPT_CONF	INT_LOG_MAX_PAYLOAD_SIZE	
NV_POWER_CONF	SW_RECOVERY_ON_ERRORS	
	RESET_WITH_HOST_ON_ERRORS	
	ADVANCED_POWER_SETTINGS	
NV_GLOBAL_MASK	ece_disable_mask	

Configuration	mlxconfig Parameter Name	Class
NV_SW_OFFLOAD_CONFIG	CQE_COMPRESSION	
	IP_OVER_VXLAN_EN	
	PCI_ATOMIC_MODE	
	LRO_LOG_TIMEOUT0	
	LRO_LOG_TIMEOUT1	
	LRO_LOG_TIMEOUT2	
	LRO_LOG_TIMEOUT3	
	log_max_outstandng_wqe	
	NV_config.sr_enable (ConnectX-6 Dx and above)	
NV_IB_DC_CONF	LOG_DCR_HASH_TABLE_SIZE	
	DCR_LIFO_SIZE	

Configuration	mlxconfig Parameter Name	Class
NV_VPI_LINK_TYPE	LINK_TYPE	PHYSICAL_PO (2)
NV_ROCE_CC	ROCE_CC_PRIO_MASK	
	ROCE_CC_ALGORITHM	
NV_ROCE_CC_ECN	CLAMP_TGT_RATE_AFTER_TIME_INC	
	CLAMP_TGT_RATE	
	RPG_TIME_RESET	
	RPG_BYTE_RESET	
	RPG_THRESHOLD	
	RPG_MAX_RATE	
	RPG_AI_RATE	
	RPG_HAI_RATE	
	RPG_GD	
	RPG_MIN_DEC_FAC	
	RPG_MIN_RATE	
	RATE_TO_SET_ON_FIRST_CNP	
	DCE_TCP_G	
	DCE_TCP_RTT	
	RATE_REDUCE_MONITOR_PERIOD	
	INITIAL_ALPHA_VALUE	
	MIN_TIME_BETWEEN_CNPS	
	CNP_802P_PRIO	
CNP_DSCP		
NV_LLDP_NB_CONF	LLDP_NB_DCBX	
	LLDP_NB_RX_MODE	
	LLDP_NB_TX_MODE	

Configuration	mlxconfig Parameter Name	Class
NV_LLDP_NB_DCBX	DCBX_IEEE	
	DCBX_CEE	
	DCBX_WILLING	
NV_KEEP_LINK_UP	KEEP_ETH_LINK_UP	
	KEEP_IB_LINK_UP	
	KEEP_LINK_UP_ON_BOOT	
	KEEP_LINK_UP_ON_STANDBY	
NV_QOS_CONF	NUM_OF_VL	
	NUM_OF_TC	
	NUM_OF_PFC	
NV_MPFS_CONF	DUP_MAC_ACTION	
	SRIOV_IB_ROUTING_MODE	
	IB_ROUTING_MODE	

Configuration	mlxconfig Parameter Name	Class
NV_HCA_CONF	PCI_WR_ORDERING	HOST-FUNCTION (3)
	MULTI_PORT_VHCA_EN	
NV_EXTERNAL_PORT_CTRL	PORT_OWNER	
	ALLOW_RD_COUNTERS	
	RENEG_ON_CHANGE	
	TRACER_ENABLE	
NV_ROM_BOOT_CONF2	IP_VER	
	BOOT_UNDI_NETWORK_WAIT	
NV_ROM_UEFI_CONF	UEFI_HII_EN	
NV_ROM_UEFI_DEBUG_LEVEL	BOOT_DBG_LOG	
	UEFI_LOGS	
NV_ROM_BOOT_CONF1	BOOT_VLAN	
	LEGACY_BOOT_PROTOCOL	
	BOOT_RETRY_CNT	
	BOOT_LACP_DIS	
	BOOT_VLAN_EN	
NV_ROM_IB_BOOT_CONF	BOOT_PKEY	
NV_PCI_CONF	ADVANCED_PCI_SETTINGS	HOST (7)
SAFE_MODE_CONF	SAFE_MODE_THRESHOLD	
	SAFE_MODE_ENABLE	

Release Notes History

Changes and New Feature History

Note

This section includes history of changes and new feature of 3 major releases back. For older releases history, please refer to the relevant firmware versions.

Feature/Change	Description
26.39.5050	
General	Stability improvements.

Feature/Change	Description
26.39.4082	
General	Stability improvements.

Feature/Change	Description
26.39.3560	
General	Stability improvements.

Feature/Change	Description
26.39.3004	
General	Stability improvements.

Feature/Change	Description
26.39.2048	
Bug Fixes	See <i>Bug Fixes in this Firmware Version</i> section.

Feature/Change	Description
26.39.1002	
Expansion ROM	Added a caching mechanism to improved expansion ROM performance and to avoid any slow boot occurrences when loading the expansion ROM driver.
Live Migration Support for Image Size above 4GB	Added support for image size above 4GB when performing a live migration by splitting the image to chunks.
Crypto Algorithms	Extended the role-based authentication to cover all crypto algorithms. Now the TLS, IPsec, MACsec, GCM, mem2mem, and NISP work when <pre>nv_crypto_conf.crypto_policy = CRYPTO_POLICY_FIPS_LEVEL_2,</pre> meaning all cryptographic engines can also work in wrapped mode and not only in plaintext mode.
Programmable Congestion Control	Programmable Congestion Control is now the default CC mechanism. ZTR_RTTCC is the default CC algorithm when ECE is enabled and the CC algorithm negotiation succeeds, otherwise PCC DCQCN will be used.
Reserved mkey	Added new support for reserved mkey index range. When enabled, a range of mkey indexes is reserved for mkey by name use.
Bug Fixes	See <i>Bug Fixes in this Firmware Version</i> section.

Feature/Change	Description
26.38.1900	

Feature/Change	Description
QKEY Mitigation in the Kernel	<p>QKEY creation with the MSB set is available now for non-privileged users as well.</p> <p>To allow non-privileged users to create QKEY with MSB set, the below new module parameter was added to <code>ib_uverbs</code> module:</p> <ul style="list-style-type: none"> • Module Parameter: <code>enforce_qkey_check</code> • Description: Force QKEY MSB check for non-privileged user on UD QP creation • Default: 0 (disabled) <p>Note: In this release, this module parameter is disabled by default to ensure backward compatibility and give customers the opportunity to update their applications accordingly. In the upcoming release, it will be enabled by default, and later on deprecated.</p>

Feature/Change	Description
26.38.1002	
INT Packets	Added support for forwarding INT packets to the user application for monitoring purposes by matching the BTH acknowledge request bit (<code>bth_a</code>).
QKEY Mitigation in the Kernel	Non-privileged users are now blocked by default from setting controlled/privileged QKEYs (QKEY with MSB set).
Bug Fixes	See <i>Bug Fixes in this Firmware Version</i> section.

Feature/Change	Description
26.37.1014	
Monitoring Cloud Guest RoCE Statistics on Cloud Provider	This new capability enables the VM to track and limit its Vport's activity. This is done using the new <code>q_counters</code> counter which enables aggregation of other Vport's from PF GVMF.
Linux Bridge Offload	Added a flow rule that enables offloading of multicast traffic by broadcasting it to multi-Flow-Table in FDB.
PCC Algorithms	Enables a smooth and statically switch between PCC algorithms. In addition, the user can now switch between PCC algorithms while running traffic.

Feature/Change	Description
Hardware Steering: Bulk Allocation	Added support for 32 actions in the header modify pattern using bulk allocation.
Bug Fixes	See <i>Bug Fixes in this Firmware Version</i> section.

Bug Fixes History

Note

This section includes history of bug fixes of 3 major releases back. For older releases history, please refer to the relevant firmware versions Release Notes in <https://docs.mellanox.com/category/adapterfw>.

This version does not include bug fixes.

Internal Ref.	Issue
4039634	Description: Fixed an issue that caused traffic failure when modifying the <code>VIRTIO_NET_F_MRG_RXBUF</code> bit for the VDPA device during traffic.
	Keywords: VDPA, MRG_RXBUF
	Discovered in Version: 26.39.3560
	Fixed in Release: 26.39.4082
4149510	Description: Fixed an issue that resulted in setup crash when <code>create_sq</code> used invalid mbox. Now the invalid mbox is replaced with a valid DB.
	Keywords: mbox
	Discovered in Version: 26.39.3560
	Fixed in Release: 26.39.4082

Internal Ref.	Issue
4149393	Description: Added address validation in MLNX OEM CMD 0x0032 (get debug info) to be 4-bytes aligned.
	Keywords: Address validation, 0x0032
	Discovered in Version: 26.39.3560
	Fixed in Release: 26.39.4082
4148435	Description: Removed the logical port rate limiter to prevent the internal loopback traffic from exceeding the physical port network link speed when using the ESW scheduling feature.
	Keywords: Logical port rate limiter
	Discovered in Version: 26.39.3560
	Fixed in Release: 26.39.4082

Internal Ref.	Issue
3887760	Description: Fixed an issue that caused Completion Timeout to mistakenly be treated as Advisory Non-Fatal error. Now Completion Timeout is treated as uncorrectable error.
	Keywords: Completion Timeout, Advisory Non-Fatal error
	Discovered in Version: 26.39.2048
	Fixed in Release: 26.39.3560

Internal Ref.	Issue
	Description:
	Keywords:
	Discovered in Version: 26.39.2048
	Fixed in Release: 26.39.3004

Internal Ref.	Issue
3669258	Description: Fixed a rare issue that prevented changes in mlxconfig from taking effect upon warm reboot.
	Keywords: mlxconfig
	Discovered in Version: 26.38.1002
	Fixed in Release: 26.39.2048

Internal Ref.	Issue
3628848	Description: Updated the number of channels (ports) that are displayed in the iLO from 1 to 2 (num_channels_per_pkg=2) for dual port adapter cards.
	Keywords: Number of channels (ports)
	Discovered in Version: 26.38.1002
	Fixed in Release: 26.39.1002
3602169	Description: Added a locking mechanism to protect the firmware from a race condition between insertion and deletion of the same rule in parallel. Such behavior occasionally resulted in firmware accessing a memory that has already been released, thus causing IOMMU / translation error. Note: This fix will not impact insertion rate for tables owned by SW steering.
	Keywords: Firmware steering
	Discovered in Version: 26.38.1002
	Fixed in Release: 26.39.1002
3571251	Description: Fixed an issue that resulted in migration data corruption when running parallel <code>save_vhca_state/load_vhca_state</code> commands on the same PF.
	Keywords: VF live migration
	Discovered in Version: 26.38.1002
	Fixed in Release: 26.39.1002

Internal Ref.	Issue
3365411	Description: Fixed a link failure that occurred due to a wrong 'is_inphi_cable' indication.
	Keywords: Link failure
	Discovered in Version: 26.37.1014
	Fixed in Release: 26.38.1002
3331179	Description: Improved token calculation.
	Keywords: Token calculation
	Discovered in Version: 26.37.1014
	Fixed in Release: 26.38.1002
3491841	Description: Fixed a firmware assert that occurred when tried to verify if the module supported "swap".
	Keywords: Firmware assert
	Discovered in Version: 26.37.1014
	Fixed in Release: 26.38.1002

Internal Ref.	Issue
3434928	Description: Modified the RDE behavior to return an error if the chassis ID subtype is AgentId, or Port ID subtype is ChassisComp.
	Keywords: RDE
	Discovered in Version: 26.36.1010
	Fixed in Release: 26.37.1014
3438177	Description: Enabled VF LAG hash mode. The <code>LAG_RESOURCE_ALLOCATION</code> mlxconfig field is now modifiable.
	Keywords: VF LAG
	Discovered in Version: 26.36.1010
	Fixed in Release: 26.37.1014

Internal Ref.	Issue
2797986	Description: Fixed an issue that prevented the adapter card from handling WoL packets when the host powered up directly into the standby mode.
	Keywords: WoL packets
	Discovered in Version: 26.36.1010
	Fixed in Release: 26.37.1014
3327847	Description: CNP received, handled, and ignored counters in the hardware counters cannot work after moving to Programmable Congestion Control mode.
	Keywords: CNP, Programmable Congestion Control
	Discovered in Version: 26.36.1010
	Fixed in Release: 26.37.1014

Legal Notices and 3rd Party Licenses

The following are the drivers' software, tools and HCA firmware legal notices and 3rd party licenses.

Product	Version	Legal Notices and 3rd Party Licenses
Firmware	xx.39.5124	<ul style="list-style-type: none">• HCA Firmware EULA• 3rd Party Unify Notice• License
MLNX_OFED	23.10-6.1.6.1	<ul style="list-style-type: none">• License• 3rd Part Notice
MFT FreeBSD	4.26.1-35	<ul style="list-style-type: none">• 3rd Party Notice• License
MFT Linux		<ul style="list-style-type: none">• 3rd Party Notice• License
MFT VMware		<ul style="list-style-type: none">• 3rd Party Notice• License
MFT Windows		<ul style="list-style-type: none">• 3rd Party Notice• License
msfflint		<ul style="list-style-type: none">• 3rd Party Notice• License

Notice

This document is provided for information purposes only and shall not be regarded as a warranty of a certain functionality, condition, or quality of a product. NVIDIA Corporation ("NVIDIA") makes no representations or warranties, expressed or implied, as to the accuracy or completeness of the information contained in this document and assumes no responsibility for any errors contained herein. NVIDIA shall have no liability for the consequences or use of such information or for any infringement of patents or other rights of third parties that may result from its use. This document is not a commitment to develop, release, or deliver any Material (defined below), code, or functionality.

NVIDIA reserves the right to make corrections, modifications, enhancements, improvements, and any other changes to this document, at any time without notice.

Customer should obtain the latest relevant information before placing orders and should verify that such information is current and complete.

NVIDIA products are sold subject to the NVIDIA standard terms and conditions of sale supplied at the time of order acknowledgement, unless otherwise agreed in an individual sales agreement signed by authorized representatives of NVIDIA and customer ("Terms of Sale"). NVIDIA hereby expressly objects to applying any customer general terms and conditions with regards to the purchase of the NVIDIA product referenced in this document. No contractual obligations are formed either directly or indirectly by this document.

NVIDIA products are not designed, authorized, or warranted to be suitable for use in medical, military, aircraft, space, or life support equipment, nor in applications where failure or malfunction of the NVIDIA product can reasonably be expected to result in personal injury, death, or property or environmental damage. NVIDIA accepts no liability for inclusion and/or use of NVIDIA products in such equipment or applications and therefore such inclusion and/or use is at customer's own risk.

NVIDIA makes no representation or warranty that products based on this document will be suitable for any specified use. Testing of all parameters of each product is not necessarily performed by NVIDIA. It is customer's sole responsibility to evaluate and determine the applicability of any information contained in this document, ensure the product is suitable and fit for the application planned by customer, and perform the necessary testing for the application in order to avoid a default of the application or the product. Weaknesses in customer's product designs may affect the quality and reliability of the NVIDIA product and may result in additional or different conditions and/or requirements beyond those contained in this document. NVIDIA accepts no liability related to any default, damage, costs, or problem which may be based on or attributable to: (i) the use of the NVIDIA product in any manner that is contrary to this document or (ii) customer product designs.

No license, either expressed or implied, is granted under any NVIDIA patent right, copyright, or other NVIDIA intellectual property right under this document. Information published by NVIDIA regarding third-party products or services does not constitute a license from NVIDIA to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property rights of the third party, or a license from NVIDIA under the patents or other intellectual property rights of NVIDIA.

Reproduction of information in this document is permissible only if approved in advance by NVIDIA in writing, reproduced without alteration and in full compliance with all applicable export laws and regulations, and accompanied by all associated conditions, limitations, and notices.

THIS DOCUMENT AND ALL NVIDIA DESIGN SPECIFICATIONS, REFERENCE BOARDS, FILES, DRAWINGS, DIAGNOSTICS, LISTS, AND OTHER DOCUMENTS (TOGETHER AND SEPARATELY, "MATERIALS") ARE BEING PROVIDED "AS IS." NVIDIA MAKES NO WARRANTIES, EXPRESSED, IMPLIED, STATUTORY, OR OTHERWISE WITH RESPECT TO THE MATERIALS, AND EXPRESSLY DISCLAIMS ALL IMPLIED WARRANTIES OF NON-INFRINGEMENT, MERCHANTABILITY, AND FITNESS FOR A PARTICULAR PURPOSE. TO THE EXTENT NOT PROHIBITED BY LAW, IN NO EVENT WILL NVIDIA BE LIABLE FOR ANY DAMAGES, INCLUDING WITHOUT LIMITATION ANY DIRECT, INDIRECT, SPECIAL, INCIDENTAL, PUNITIVE, OR CONSEQUENTIAL DAMAGES, HOWEVER CAUSED AND REGARDLESS OF THE THEORY OF LIABILITY, ARISING OUT OF

ANY USE OF THIS DOCUMENT, EVEN IF NVIDIA HAS BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES. Notwithstanding any damages that customer might incur for any reason whatsoever, NVIDIA's aggregate and cumulative liability towards customer for the products described herein shall be limited in accordance with the Terms of Sale for the product.

Trademarks

NVIDIA and the NVIDIA logo are trademarks and/or registered trademarks of NVIDIA Corporation in the U.S. and other countries. Other company and product names may be trademarks of the respective companies with which they are associated.

© Copyright 2026, NVIDIA. PDF Generated on 01/14/2026