




NVIDIA ConnectX-6 Adapter Cards Firmware Release Notes v20.39.2048 LTS

Table of Contents

1	Release Notes Update History.....	5
2	Overview	6
2.1	Firmware Download	6
2.2	Document Revision History	6
3	Firmware Compatible Products	7
3.1	Supported Devices	7
3.2	Driver Software, Tools and Switch Firmware	8
4	Changes and New Features.....	10
4.1	Important Notes.....	10
4.2	Changes and New Feature in this Firmware Version.....	10
4.3	Unsupported Features and Commands	10
4.3.1	Unsupported Features.....	10
4.3.2	Unsupported Commands	11
5	Bug Fixes in this Firmware Version.....	12
6	Known Issues.....	13
7	PreBoot Drivers (FlexBoot/UEFI)	23
7.1	FlexBoot Changes and New Features	23
7.2	UEFI Changes and Major New Features.....	23
8	Validated and Supported Cables and Switches	24
8.1	Validated and Supported Cables and Modules	24
8.1.1	Cables Lifecycle Legend	24
8.1.2	Switch and HCAs InfiniBand Cable Connectivity Matrix	24
8.1.3	Switch-to-Switch Connectivity	25
8.1.4	HCA-to-Switch Connectivity Matrix	25
8.1.5	HDR / 200GbE Cables.....	27
8.1.6	EDR / 100GbE Cables	36
8.1.7	FDR / 56GbE Cables	45
8.1.8	50GbE Cables	46
8.1.9	QDR Cables.....	47
8.1.10	FDR10 / 40GbE Cables	47
8.1.11	25GbE Cables	50
8.1.12	10GbE Cables	52

8.1.13	1GbE Cables	55
8.1.14	Supported 3rd Party Cables and Modules	55
8.2	Tested Switches	56
8.2.1	HDR / 200Gb/s Switches.....	56
8.2.2	EDR / 100Gb/s Switches	56
8.2.3	200GbE Switches	56
8.2.4	100GbE Switches	56
8.2.5	10/40GbE Switches	57
8.3	PRM Revision Compatibility	58
9	Supported Non-Volatile Configurations	59
10	Release Notes History	62
10.1	Changes and New Feature History	62
10.2	Bug Fixes History.....	63
11	Legal Notices and 3rd Party Licenses	65

 This is a long-term support (LTS) release. LTS is the practice of maintaining a software product for an extended period of time (up to three years) to help increase product stability. LTS releases include bug fixes and security patches.

1 Release Notes Update History

Version	Date	Description
20.39.2048	December 11, 2023	Initial release of this Release Notes version, This version introduces Changes and New Features and Bug Fixes .

2 Overview

Firmware which is added at the time of manufacturing, is used to run user programs on the device and can be thought of as the software that allows hardware to run. Embedded firmware is used to control the functions of various hardware devices and systems, much like a computer's operating system (OS) controls the function of software applications. Firmware may be written into read-only memory (ROM), erasable programmable read-only memory (EPROM) or flash memory.

2.1 Firmware Download

Please visit the [firmware webpage](#).

2.2 Document Revision History

A list of the changes made to this document are provided in [Document Revision History](#).

3 Firmware Compatible Products


The chapter contains the following sections:


These are the release notes for the NVIDIA® ConnectX®-6 adapters firmware. This firmware supports the following protocols:

- InfiniBand - SDR, QDR, FDR, EDR, HDR100, HDR
- Ethernet - 1GbE, 10GbE, 25GbE, 40GbE, 50GbE¹, 100GbE¹, 200GbE²
- PCI Express 4.0, supporting backwards compatibility for v3.0, v2.0 and v1.1

¹. Speed that supports both NRZ and PAM4 modes in Force mode and Auto-Negotiation mode.

². Speed that supports PAM4 mode only.

 When connecting an NVIDIA-to-NVIDIA adapter card in ETH PAM4 speeds, Auto-Neg should always be enabled.

 Please make sure to use a PCIe slot that can supply the required power to the ConnectX-6 adapter card as stated in section Specifications in the adapter card's User Manual.

3.1 Supported Devices

This firmware supports the devices and protocols listed below:

NVIDIA SKU	Legacy OPN	PSID	Device Name
900-9X603-0056-DT0	MCX653106A-EFAT	MT_0000000219	ConnectX-6 VPI adapter card; 100Gb/s (HDR100; EDR IB and 100GbE); dual-port QSFP56; PCIe3.0/4.0 2x8 in a row
900-9X6B4-0056-DT1	MCX614106A-CCAT	MT_0000000220	ConnectX-6 EN adapter card; 100GbE; dual-port QSFP56; Socket Direct 2x PCIe3.0 x16; tall bracket; ROHS R6
900-9X6B4-0058-DT1	MCX614106A-VCAT	MT_0000000221	ConnectX-6 EN adapter card; 200GbE; dual-port QSFP56; Socket Direct 2x PCIe3.0 x16; tall bracket; ROHS R6
900-9X6AF-0016-ST1	MCX653105A-ECAT	MT_0000000222	ConnectX-6 VPI adapter card; 100Gb/s (HDR100; EDR IB and 100GbE); single-port QSFP56; PCIe3.0 x16; tall bracket; ROHS R6
900-9X6AF-0018-MT2 / 900-9X6AF-0018-SS0	MCX653105A-HDAT / MCX653105A-HDAL	MT_0000000223	ConnectX-6 VPI adapter card; HDR IB (200Gb/s) and 200GbE; single- port QSFP56; PCIe4.0 x16; tall bracket; ROHS R6
900-9X6AF-0056-MT1	MCX653106A-ECAT	MT_0000000224	ConnectX-6 VPI adapter card; H100Gb/s (HDR100; EDR IB and 100GbE); dual-port QSFP56; PCIe3.0 x16; tall bracket; ROHS R6
900-9X6AF-0058-ST1 / 900-9X6AF-0058-SS0	MCX653106A-HDAT / MCX653106A-HDAL	MT_0000000225	ConnectX-6 VPI adapter card; HDR IB (200Gb/s) and 200GbE; dual-port QSFP56; PCIe4.0 x16; tall bracket; ROHS R6

NVIDIA SKU	Legacy OPN	PSID	Device Name
900-9X6B4-0018-DT2	MCX654105A-HCAT	MT_0000000226	ConnectX-6 VPI adapter card; HDR IB (200Gb/s) and 200GbE; single- port QSFP56; Socket Direct 2x PCIe3.0 x16; tall bracket; ROHS R6
900-9X6B4-0056-DT0	MCX654106A-ECAT	MT_0000000227	ConnectX-6 VPI adapter card; 100Gb/s (HDR100; EDR InfiniBand and 100GbE); dual-port QSFP56; Socket Direct 2x PCIe3.0 x16; tall bracket; ROHS R6
900-9X6B4-0058-DT0	MCX654106A-HCAT	MT_0000000228	ConnectX-6 VPI adapter card; HDR IB (200Gb/s) and 200GbE; dual-port QSFP56; Socket Direct 2x PCIe3.0 x16; tall bracket; ROHS R6
900-9X6AF-0018-MT1	MCX613105A-VDAT	MT_0000000234	ConnectX-6 EN adapter card; 200GbE; single-port QSFP56; PCIe4.0 x16; ROHS R6
900-9X6AF-0056-ST0	MCX613106A-CCAT	MT_0000000235	ConnectX-6 EN adapter card; 100GbE; dual-port QSFP56; PCIe3.0 x16; ROHS R6
900-9X6AF-0058-MT1	MCX613106A-VDAT	MT_0000000236	ConnectX-6 EN adapter card; 200GbE; dual-port QSFP56; PCIe4.0 x16; ROHS R6
900-9X603-0016-DT0	MCX653105A-EFAT	MT_0000000237	ConnectX-6 VPI adapter card; 100Gb/s (HDR100; EDR IB and 100GbE); single-port QSFP56; PCIe3.0/4.0 Socket Direct 2x8 in a row; ROHS R6
900-9X6B4-0018-DT1	MCX614105A-VCAT	MT_0000000284	ConnectX-6 EN adapter card kit; 200GbE; single-port QSFP56; Socket Direct 2x PCIe3.0 x16
900-9X657-0008-SIO	MCX613436A-VDAI	MT_0000000294	ConnectX-6 EN adapter card; 200GbE for OCP 3.0; with host management; Dual-port QSFP56; PCIe 4.0 x16; Internal Lock
900-9X657-0016-SIO	MCX653435A-EDAI	MT_0000000295	ConnectX®-6 VPI adapter card, 100Gb/s (HDR100, EDR IB and 100GbE) for OCP 3.0, with host management, Single-port QSFP56, PCIe 3.0/4.0 x16, Internal Lock
900-9X657-0018-SIO / 900-9X657-0018-SEO	MCX653435A-HDAI / MCX653435A-HDAE	MT_0000000296	ConnectX®-6 VPI adapter card, 200Gb/s (HDR IB and 200GbE) for OCP 3.0, with host management, Single-port QSFP56, PCIe4.0 x16, Internal Lock
900-9X657-0058-SI2 / 900-9X657-0058-SB0	MCX653436A-HDAI / MCX653436A-HDAB	MT_0000000297	ConnectX®-6 VPI adapter card, 200Gb/s (HDR IB and 200GbE) for OCP 3.0, with host management, Dual-port QSFP56, PCIe4.0 x16, Internal Lock
900-9X628-0016-ST0	MCX651105A-EDAT	MT_0000000473	ConnectX®-6 VPI adapter card, 100Gb/s (HDR100, EDR IB and 100GbE, single-port QSFP56, PCIe4.0 x8, tall bracket
900-9X657-0018-MIO	MCX653435M-HDAI	MT_0000000601	ConnectX-6 VPI adapter card; 200Gb/s (HDR IB and 200GbE) for OCP 3.0; with host management; Single-port QSFP56; Multi Host or Socket Direct; PCIe4.0 x16; Internal Lock


3.2 Driver Software, Tools and Switch Firmware


The following are the drivers' software, tools, switch/HCA firmware versions tested that you can upgrade from or downgrade to when using this firmware version:

	Supported Version
ConnectX-6 Firmware	20.39.2048 / 20.39.1002 / 20.38.1900
MLNX_OFED	23.10-1.1.9.0 / 23.10-0.5.5.0 / 23.07-0.5.1.2 Note: For the list of the supported Operating Systems, please refer to the driver's Release Notes.
MLNX_EN (MLNX_OFED based code)	23.10-1.1.9.0 / 23.10-0.5.5.0 / 23.07-0.5.1.2 Note: For the list of the supported Operating Systems, please refer to the driver's Release Notes.
WinOF-2	23.10.50000 / 23.7.50000 Note: For the list of the supported Operating Systems, please refer to the driver's Release Notes.
MFT	4.26.1 / 4.26.0 / 4.25.0 Note: For the list of the supported Operating Systems, please refer to the driver's Release Notes.
mstflint	4.26.1 / 4.26.0 / 4.25.0 Note: For the list of the supported Operating Systems, please refer to the driver's Release Notes.
FlexBoot	3.7.300
UEFI	14.32.17
MLNX-OS	3.10.5002 onwards
Cumulus	5.4 onwards
NVIDIA Quantum Firmware	27.2012.1010 onwards
SwitchX-IB 2 Firmware	15.2010.5108 onwards
SwitchX-IB Firmware	11.2008.3328 onwards


4 Changes and New Features


4.1 Important Notes

 SR-IOV - Virtual Functions (VF) per Port - The maximum Virtual Functions (VF) per port is 127. For further information, see [Known Issues](#).

 It is recommended to enable the “above 4G decoding” BIOS setting for features that require large amount of PCIe resources.

Such features are: SR-IOV with numerous VFs, PCIe Emulated Switch, and Large BAR Requests.

 Security Hardening Enhancements: This release contains important reliability improvements and security hardening enhancements. NVIDIA recommends upgrading your devices' firmware to this release to improve the devices' firmware security and reliability.

 When upgrading or changing the configuration on multi-host adapter cards, for the changes to take effect, PCIe restart must be simultaneously sent from both hosts (servers).

To do so, perform the following:

1. Shut down the server with the auxiliary card.
2. Shut down the server with the primary card.
3. Bring back the server with the primary card.
4. Bring back the server with the auxiliary card.

4.2 Changes and New Feature in this Firmware Version

Feature/Change	Description
20.39.2048	
Bug Fixes	See <i>Bug Fixes in this Firmware Version</i> section.

4.3 Unsupported Features and Commands

4.3.1 Unsupported Features

The following advanced feature are unsupported in the current firmware version:

- The following service types:
 - SyncUMR
 - Mellanox transport
 - RAW IPv6
- INT-A not supported for EQs only MSI-X
- PCI VPD write flow (RO flow supported)
- Streaming Receive Queue (STRQ) and collapsed CQ
- Subnet Manager (SM) on VFs
- RoCE LAG in Multi-Host/Socket-Direct

4.3.2 Unsupported Commands

- QUERY_MAD_DEMUX
- SET_MAD_DEMUX
- CREATE_RQ - MEMORY_RQ_RMP
- MODIFY_LAG_ASYNC_EVENT

5 Bug Fixes in this Firmware Version

For a list of old Bug Fixes, please see [Bug Fixes History](#).

Internal Ref.	Issue
3669258	Description: Fixed a rare issue that prevented changes in mlxconfig from taking effect upon warm reboot.
	Keywords: mlxconfig
	Discovered in Version: 20.38.1900
	Fixed in Release: 20.39.2048
3668253	Description: Removed the unmapped module in the INI to prevent firmware assert due to invalid local port (0x7f unmapped).
	Keywords: INI, firmware assert
	Discovered in Version: 20.38.1900
	Fixed in Release: 20.39.2048

6 Known Issues

VF Network Function Limitations in SRIOV Legacy Mode

Dual Port Device	Single Port Device
127 VF per PF (254 functions)	127

VF Network Function Limitations in Switchdev Mode

Dual Port Device	Single Port Device
127 VF per PF (254 functions)	127

VF+SF Network Function Limitations in Switchdev Mode

Dual Port Device	Single Port Device
<ul style="list-style-type: none"> • 127 VF per PF (254 functions) • 512 PF+VF+SF per PF (1024 functions) 	<ul style="list-style-type: none"> • 127 VF (127 functions) • 512 PF+VF+SF per PF (512 functions)

Known Issues

Internal Ref.	Issue
3575261	<p>Description: When using the SLRED function to measure eye in PAM4 speed, in some cases, the eye shape will not be correlative to the link margins.</p> <p>Workaround: N/A</p> <p>Keywords: SLRE</p> <p>Discovered in Version: 20.39.1002</p>
3525865	<p>Description: Unexpected system behavior might be observed if the driver is loaded while reset is in progress.</p> <p>Workaround: N/A</p> <p>Keywords: Sync 1 reset, firmware reset</p> <p>Discovered in Version: 20.39.1002</p>
3457472	<p>Description: Disabling the Relaxed Ordered (RO) capability (relaxed_ordering_read_pci_enabled=0) using the vhca_resource_manager is currently not functional.</p> <p>Workaround: N/A</p> <p>Keywords: Relaxed Ordered</p> <p>Discovered in Version: 20.37.1014</p>
2878841	<p>Description: Firmware rollback fails for the signature retransmit flow if the QPN field is configured in the mkey (as it only allows the given QP to use this Mkey) as the firmware rollback flow relies on an internal QP that uses the mkey.</p> <p>Workaround: N/A</p> <p>Keywords: Signature retransmit flow</p> <p>Discovered in Version: 20.37.1014</p>

Internal Ref.	Issue
3374237	<p>Description: Before deleting a VLAN from the header (pop_vlan), make sure a VLAN is present, otherwise you may experience a undefined behavior from the hardware which will result is a system crash.</p> <p>Workaround: N/A</p> <p>Keywords: VLAN</p> <p>Discovered in Version: 20.37.1014</p>
3171699	<p>Description: Occasionally, after a few toggles, link may not raise when changing the speed when in loopback mode.</p> <p>Workaround: N/A</p> <p>Keywords: Link speed, loopback</p> <p>Discovered in Version: 20.37.1014</p>
3329109	<p>Description: MFS1S50-H003E cable supports only HDR rate when used as a split cable.</p> <p>Workaround: N/A</p> <p>Keywords: HDR, split cable, MFS1S50-H003E</p> <p>Discovered in Version: 20.36.1010</p>
2844036	<p>Description: When using the "Dual Write" feature with QP buffer bigger than the maximum outstanding WQEs (128), the data being sent on the standby QP can be corrupted.</p> <p>Workaround: Limit the QP buffer size when using "Dual Write" up to 128 WQEs.</p> <p>Keywords: Dual-write, QP</p> <p>Discovered in Version: 20.36.1010</p>
3261861	<p>Description: Connecting an HDR device to an NDR device with Optical cables longer than 30m causes degradation in the bandwidth.</p> <p>Workaround: N/A</p> <p>Keywords: HDR-to-NDR, cables</p> <p>Discovered in Version: 20.35.1012</p>
3209624	<p>Description: To configure Adaptive Routing in RoCE through ROCE_ACCL access register or through cmdif mlxconfig, ROCE_ADAPTIVE_ROUTING_EN nvconfig parameter must be set.</p> <p>Workaround: N/A</p> <p>Keywords: Adaptive Routing in RoCE</p> <p>Discovered in Version: 20.34.1002</p>
3200779	<p>Description: Changing dynamic PCIe link width is not supported.</p> <p>Workaround: N/A</p> <p>Keywords: PCIe</p> <p>Discovered in Version: 20.34.1002</p>
3030570	<p>Description: "crypto policy" access registry can be modified only by the INI file.</p> <p>Workaround: N/A</p> <p>Keywords: AES_XTS</p> <p>Discovered in Version: 20.33.1048</p>

Internal Ref.	Issue
2793880	<p>Description: Checksum is not calculated correctly in IPoIP packet with LSO.</p> <p>Workaround: N/A</p> <p>Keywords: IPoIP, LSO, checksum</p> <p>Discovered in Version: 20.33.1048</p>
2864238	<p>Description: VPD cannot be accessed after firmware upgrade or reset when the following sequence is performed:</p> <ol style="list-style-type: none"> 1. Upgrade to a new firmware and perform a cold reboot 2. Downgrade to an old firmware 3. Run fwreset 4. Upgrade to a new firmware 5. Run fwreset <p>Workaround: Run the upgrade or reset sequence as follow:</p> <ol style="list-style-type: none"> 1. Upgrade to a new firmware and perform a cold reboot 2. Downgrade to an old firmware 3. Run fwreset 4. Upgrade to a new firmware 5. Perform a cold reboot <p>Keywords: VDP</p> <p>Discovered in Version: 20.32.1010</p>
2616755	<p>Description: Forward action for IPoIB is not supported on RX RDMA Flow Table.</p> <p>Workaround: N/A</p> <p>Keywords: Steering, IPoIB</p> <p>Discovered in Version: 20.32.1010</p>
2582094	<p>Description: When performing a stress toggle test vs. IXIA, the IXIA side is not ready for few seconds.</p> <p>Workaround: Wait for 1 sec between running the down and up commands.</p> <p>Keywords: Auto-negotiation.</p> <p>Discovered in Version: 20.31.1014</p>
2446583	<p>Description: On rare occasions, when both network devices are NVIDIA, PAM4 link will raise with several effective errors. These errors will not affect traffic once the link is up.</p> <p>Workaround: Clear counters once the link is up</p> <p>Keywords: Effective errors</p> <p>Discovered in Version: 20.29.2002</p>
SF 933911	<p>Description: PXE boot will not function if the adapter card is connected to a NVIDIA Quantum™ based switch over an HDR active optical cable.</p> <p>Workaround: Set KEEP_LINK_UP_ON_BOOT configuration to enable via mlxconfig. For further information please contact Support.</p> <p>Keywords: IB, Link Speed , Link Down, SDR , optical cable</p> <p>Discovered in Version: 20.30.1004</p>
2378593	<p>Description: Sub 1sec firmware update (fast reset flow) is not supported when updating from previous releases to the current one. Doing so may cause network disconnection events.</p> <p>Workaround: Use full reset flow for firmware upgrade/downgrade.</p>

Internal Ref.	Issue
	<p>Keywords: Sub 1sec firmware update</p> <p>Discovered in Version: 20.29.1016</p>
2213356	<p>Description: The following are the Steering Dump limitations:</p> <ul style="list-style-type: none"> • Supported only on ConnectX-5 adapter cards • Requires passing the version (FW/Stelib/MFT) and device type to stelib • Re-format is not supported • Advanced multi-port feature is not supported - LAG/ROCE_AFFILIATION/MPFS_LB/ESW_LB (only traffic vhca <-> wire) • Packet types supported: <ul style="list-style-type: none"> • Layer 2 Eth • Layer 3 IPv4/Ipv6/Grh • Layer 4 TCP/UDP/Bth/GreV0/GreV1 • Tunneling VXLAN/Geneve/GREv0/Mpls • FlexParser protocols are not supported (e.g AliVxlan/VxlanGpe etc..). • Compiles only on x86 <p>Workaround: N/A</p> <p>Keywords: Steering Bump</p> <p>Discovered in Version: 20.29.1016</p>
2365322	<p>Description: When configuring adapter card's Level Scheduling, a QoS tree leaf (QUEUE_GROUP) configured with default rate_limit and default bw_share, may not obey the QoS restrictions imposed by any of the leaf's ancestors.</p> <p>Workaround: To prevent such a case, configure at least one of the following QoS attributes of a leaf: <code>max_average_bw</code> or <code>bw_share</code></p> <p>Keywords: QoS</p> <p>Discovered in Version: 20.29.1016</p>
2239632	<p>Description: EDR linkup time might take up to 50sec when using HDR optical cable.</p> <p>Workaround: N/A</p> <p>Keywords: Cables, EDR</p> <p>Discovered in Version: 20.28.1002</p>
2145881	<p>Description: FDR link is unstable when using an FDR cable in ports: #27-#34.</p> <p>Workaround: N/A</p> <p>Keywords: FDR, cables</p> <p>Discovered in Version: 20.27.6008</p>
2149437	<p>Description: When the SLTP configuration is wrongly set, the "Bad status" explanation will not be presented (only error indication) to the user.</p> <p>Workaround: N/A</p> <p>Keywords: SLTP configuration</p> <p>Discovered in Version: 20.27.6008</p>
2071210	<p>Description: mlxconfig query for the BOOT_INTERRUPT_DIS TLV shows a wrong value in the "current value" field.</p> <p>Workaround: Use "next boot" indication to see the right value.</p> <p>Keywords: mlxconfig</p> <p>Discovered in Version: 20.27.1016</p>

Internal Ref.	Issue
1796936	<p>Description: 200GbE Optical cables in Auto-Negotiation mode work only in 200GbE speed.</p> <p>Workaround: N/A</p> <p>Keywords: Cables</p> <p>Discovered in Version: 20.27.1016</p>
1959529	<p>Description: When HDR Active Copper cables are used between Quantum switches, or between Quantum switch and ConnectX-6 HCA, the counter indicating 'Link Down' may have a value other than zero, after the first time the cable is connected. As this may happened only at the first time, it is recommend to clear the counters after the cluster is brought up.</p> <p>Workaround: Toggle the Active Copper or Optics cables as the switch performs a reset.</p> <p>Keywords: Cables, BER</p> <p>Discovered in Version: 20.27.1016</p>
1959529	<p>Description: Occasionally (up to 15% of connections), the link will go down when using ACC cables P/N: MCA1J00-H003E, MCA1J00-H004E and when connecting a Quantum switch to a Quantum switch.</p> <p>Workaround: N/A</p> <p>Keywords: Cables</p> <p>Discovered in Version: 20.27.1016</p>
1997329	<p>Description: Downgrading from firmware v20.26.4012 to firmware v20.26.1040 and lower is not supported on Windows OSes using the mlxfwmanager tool.</p> <p>Workaround: N/A</p> <p>Keywords: mlxfwmanager, firmware downgrade</p> <p>Discovered in Version: 20.26.4012</p>
1930619	<p>Description: PF_BAR2 and ATS cannot be enabled together, i.e. when PF_BAR2 is enabled, ATS cannot be enabled too.</p> <p>Workaround: N/A</p> <p>Keywords: ATS, SF, BAR2, Multi GVMI</p> <p>Discovered in Version: 20.26.1040</p>
-	<p>Description: In rare cases, following a server powerup, a fatal error (device's health compromised) message might appear with ext_synd 0x8d1d. The error will be accompanied by a failure to use mlxconfig and in some cases flash burning tools.</p> <p>Workaround: N/A</p> <p>Keywords: mlxconfig, flash tool, ext_synd 0x8d1d</p> <p>Discovered in Version: 20.26.1040</p>
1796936	<p>Description: HDR split cables support only HDR speed.</p> <p>Workaround: N/A</p> <p>Keywords: Link Speed, cables, Break-Out cables</p> <p>Discovered in Version: 20.26.1040</p>
1750460 / 2063991	<p>Description: BER issues might occur when using ConnectX-6 adapter cards in 100GbE link speed, and connecting with and 3rd party switch systems.</p> <p>Workaround: N/A</p>

Internal Ref.	Issue
	Keywords: BER, 100GbE, Spectrum-2
	Discovered in Version: 20.26.1040
1918749	Description: mlxlink tool displays a wrong speed when using ETH cables on ConnectX-6 adapter cards.
	Workaround: N/A
	Keywords: mlxlink
	Discovered in Version: 20.26.1040
1901198	Description: Firmware is not loaded on Multi-Host setups after reboot.
	Workaround: N/A
	Keywords: Firmware load, Multi-Host
	Discovered in Version: 20.26.1040
1842278	Description: DC LAG can function only in case there is a single PF per port without any active VFs.
	Workaround: N/A
	Keywords: DC LAG
	Discovered in Version: 20.26.1040
1796628	Description: Due to performance considerations, unicast loopback traffic will go through the NIC SX tables, and multicast loopback traffic will skip the NIC SX tables.
	Workaround: N/A
	Keywords: Performance, unicast loopback traffic, multicast loopback traffic
	Discovered in Version: 20.26.1040
1797493	Description: Firmware asserts may occur when setting the PF_BAR2_SIZE value higher than the maximum supported size.
	Workaround: Configure within limits (NIC PF_BAR_SIZE <= 4).
	Keywords: Multi-GVMI, Sub-Function, SFs, BAR2
	Discovered in Version: 20.26.1040
-	Description: Coherent Accelerator Processor Interface (CAPI) in ConnectX-6 firmware v20.25.7020 and above has low test coverage, however, it has no known issues.
	Workaround: N/A
	Keywords: CAPI
	Discovered in Version: 20.25.7020
-	Description: HDR optical cables and Split cables support only HDR speed.
	Workaround: N/A
	Keywords: Link Speed, cables, Break-Out cables
	Discovered in Version: 20.25.6000
1755286	Description: Port speed may change to SDR spontaneously, without a clear reason.
	Workaround: Keep the "keep_ib_link_up" bit at 0 in NVconfig to make sure the port is raised with the correct speed.
	Keywords: SDR, port speed

Internal Ref.	Issue
	Discovered in Version: 20.25.2006
1774135	<p>Description: PXE boot is not functional when connecting a splitter cable to the host.</p> <p>Workaround: Update the SM as follow:</p> <ul style="list-style-type: none"> • MLNX_OFED SM: <ul style="list-style-type: none"> • Set the default partition in the SM partitions.conf file as shown in the example below: Default=0x7fff, ipoib, rate=5:ALL=full; Note: "rate" must be set to "5" regardless to the other flags values. • MLNX-OS SM: Run the following CLI commands: <pre>no ib sm ib partition Default rate 5 ib sm</pre> • UFM SM: Use REST API to change default partition rate: PUT https://<some IP>/ufmRest/resources/networks/management <pre>{ "qos_parameters": { "rate_limit": 900 } }</pre> As a result, /opt/ufm/files/conf/opensm/partitions.conf will include the following line: management=0x7fff, ipoib, sl=0, rate=5, defmember=full : ALL, ALL_SWITCHES=full, SELF=full; <p>Keywords: PXE boot, splitter cable</p> <p>Discovered in Version: 20.25.2006</p>
1768814/1772474	<p>Description: Due to hardware limitation, REG_C cannot be passed over loopback when the FDB action is forwarded to multiple destinations.</p> <p>Workaround: N/A</p> <p>Keywords: Connection-Tracking</p> <p>Discovered in Version: 20.25.2006</p>
1770736	<p>Description: When a PF or ECPF with many VFs (SR-IOV), and/or SFs (Multi-GVMI) triggers an FLR, PCIe completion timeout might occur.</p> <p>Workaround: Increase the PCIe completion timeout.</p> <p>Keywords: Multi-GVMI, SR-IOV, Sub-Function, Virtual Function, PF FLR</p> <p>Discovered in Version: 20.25.2006</p>
1716334	<p>Description: When mlxconfig.PF_BAR2_EN is enabled, configuring more than 255 PCI functions will raise an assert.</p> <p>Workaround: When working with BAR2, configure SR-IOV to align to the 255 PCI functions limitation. mlxconfig.NUM_OF_VFS controls the number of configured SR-IOV VFs. e.g.:</p> <ul style="list-style-type: none"> • Smart NICs: 2 External Host PFs, 2 ARM ECPFs, 125 VFs per PF. • Non-smart NICs: 2 External Host PFs, 126 VFs per PF <p>Keywords: Multi-GVMI, PF_BAR2_EN, Sub-Functions, SR-IOV, VFs</p> <p>Discovered in Version: 20.25.1500 [Beta]</p>
1699214	Description: NODNIC VF is partially tested. It is fully tested only in ConnectX-5 adapter cards.

Internal Ref.	Issue
	<p>Workaround: N/A</p> <p>Keywords: NODNIC VF</p> <p>Discovered in Version: 20.25.1500 [Beta]</p>
1699214	<p>Description: NODNIC VF is partially tested. It is fully tested only in ConnectX-5 adapter cards.</p> <p>Workaround: N/A</p> <p>Keywords: NODNIC VF</p> <p>Discovered in Version: 20.25.1500 [Beta]</p>
-	<p>Description: The supported length of HDR copper cables is currently up to 2M.</p> <p>Workaround: N/A</p> <p>Keywords: HDR cables</p> <p>Discovered in Version: 20.25.1500 [Beta]</p>
-	<p>Description: In Ethernet mode, at 10/40GbE speeds, only NO-FEC in Force mode is supported. Other user configurations are overridden.</p> <p>Workaround: N/A</p> <p>Keywords: Ethernet, 10GbE, 40GbE, RS-FEC</p> <p>Discovered in Version: 20.25.1500 [Beta]</p>
1574876	<p>Description: DC RoCE LAG is functional only if the router posts VRRP address as the source MAC.</p> <p>Workaround: N/A</p> <p>Keywords: DC RoCE LAG</p> <p>Discovered in Version: 20.25.1500 [Beta]</p>
1498399	<p>Description: If the XRC switches between SRQ/RMPs while there is an outstanding ODP on the responder XRC QP, a CQE with an error might be generated (that is not a PFAULT abort).</p> <p>Workaround: N/A</p> <p>Keywords: XRC SRQ/RMP ODP</p> <p>Discovered in Version: 20.25.1500 [Beta]</p>
-	<p>Description: In some cases, the power consumption might be 10% higher than what is stated in the adapter cards User Manual.</p> <p>Workaround: Power consumption will be aligned with the User Manual statement in the next release</p> <p>Keywords: Power consumption</p> <p>Discovered in Version: 20.25.1500 [Beta]</p>
1546492	<p>Description: Executing the update_lid command while the IB port sniffer utility is active can stop the utility.</p> <p>Workaround: N/A</p> <p>Keywords: IB Sniffer</p> <p>Discovered in Version: 20.25.1500 [Beta]</p>

Internal Ref.	Issue
1537898	<p>Description: Initializing a function while the IB port sniffer utility is active can stop the utility.</p> <p>Workaround: N/A</p> <p>Keywords: IB Sniffer</p> <p>Discovered in Version: 20.25.1500 [Beta]</p>
1414290	<p>Description: When getting an inline scatter CQE on IB striding RQ, the stride index in the CQE will be zero.</p> <p>Workaround: N/A</p> <p>Keywords: Scatter CQE</p> <p>Discovered in Version: 20.25.1500 [Beta]</p>
1332714/1345824	<p>Description: The maximum “read” size of MTRC_STDB is limited to 272 Bytes.</p> <p>Workaround: Set the MTRC_STDB.read_size to the maximum value of 0x110=272 Bytes</p> <p>Keywords: Access register, MTRC_STDB, tracer to dmesg, fwtrace to dmesg</p> <p>Discovered in Version: 20.25.1500 [Beta]</p>
1408994	<p>Description: FTE with both forward (FWD) and encapsulation (ENCAP) actions is not supported in the SX NIC Flow Table.</p> <p>Workaround: N/A</p> <p>Keywords: SX NIC Flow Table</p> <p>Discovered in Version: 20.25.1500 [Beta]</p>
1027553	<p>Description: While using e-switch vport sVLAN stripping, the RX steering values on the sVLAN might not be accurate.</p> <p>Workaround: N/A</p> <p>Keywords: e-sw vport sVLAN stripping, RX steering</p> <p>Discovered in Version: 20.25.1500 [Beta]</p>
1799917	<p>Description: Untagged CVLAN packets in the Steering Flow Tables do not match the SVLAN tagged packets.</p> <p>Workaround: N/A</p> <p>Keywords: Steering Flow Tables, CVLAN/SVLAN packets</p> <p>Discovered in Version: .20.25.1500 [Beta]</p>
1277762	<p>Description: An Ethernet multicast loopback packet is not counted (even if it is not a local loopback packet) when running the nic_receive_steering_discard command.</p> <p>Workaround: N/A</p> <p>Keywords: Ethernet multicast loopback packet</p> <p>Discovered in Version: 20.25.1500 [Beta]</p>
1306342	<p>Description: Signature-accessing WQEs sent locally to the NVMeF target QPs that encounter signature errors, will not send a SIGERR CQE.</p> <p>Workaround: N/A</p> <p>Keywords: Signature-accessing WQEs, NVMeF target</p> <p>Discovered in Version: 20.25.1500 [Beta]</p>

Internal Ref.	Issue
1168594	Description: RoCE Dual Port Mode (a.k.a Multi-Port vHCA: MPV) is not supported in Multi-Host setups.
	Workaround: N/A
	Keywords: Multi-Port vHCA, Multi-Host
	Discovered in Version: 20.25.1500 [Beta]
1072337	Description: If a packet is modified in e-sw flow steering, the SX sniffer Flow Table (of the VF) will see the sniffed packet after the modification.
	Workaround: N/A
	Keywords: SX sniffer Flow Table
	Discovered in Version: 20.25.1500 [Beta]
1171013	Description: Signature Handover Operations is not supported when FPP (Function-Per-Port) mode is disabled.
	Workaround: N/A
	Keywords: Signature Handover Operations, FPP
	Discovered in Version: 20.25.1500 [Beta]
1059975	Description: NVMeF limitation: <ul style="list-style-type: none"> • Transaction size - up to 128KB per IO (non-inline) • Support up to 16K connections • Support single namespace per drive • Staging buffer size must be at least 16MB in order to allow SRQ size of 64 entries
	Workaround: N/A
	Keywords: NVMeF
	Discovered in Version: 20.25.1500 [Beta]

7 PreBoot Drivers (FlexBoot/UEFI)

7.1 FlexBoot Changes and New Features

For further information, please refer to the [FlexBoot Release Notes](#).

7.2 UEFI Changes and Major New Features

For further information, please refer to the [UEFI Release Notes](#).

8 Validated and Supported Cables and Switches

8.1 Validated and Supported Cables and Modules

8.1.1 Cables Lifecycle Legend

Lifecycle Phase	Definition
EOL	End of Life
LTB	Last Time Buy
HVM	GA level
MP	GA level
P-Rel	GA level
Preliminary	Engineering Sample
Prototype	Engineering Sample



NVIDIA does not support InfiniBand cables or modules not qualified or approved by NVIDIA.

8.1.2 Switch and HCAs InfiniBand Cable Connectivity Matrix

NVIDIA Quantum™ based switches and NVIDIA® ConnectX®-6 HCAs support HDR (PAM4, 50Gb/s per lane) and EDR (NRZ, 25Gb/s per lane) technologies. As the ConnectX adapter cards are identified by their maximum supported throughput (e.g. ConnectX-6 VPI 100Gb/s card can support either 2-lanes of 50Gb/s or 4-lanes of 25Gb/s), the exact connectivity will be determined by the cable that is being used.

As a reference:

Speed Mode	Speed Supported	Number of Lanes Used
HDR	200Gb/s InfiniBand	4 lanes of 50Gb/s
HDR100	100Gb/s InfiniBand	2 lanes of 50Gb/s
EDR	100Gb/s InfiniBand	4 lanes of 25Gb/s
FDR	56Gb/s	4 lanes of 14Gb/s

The following tables present the connectivity matrix, between NVIDIA Quantum based switches, ConnectX-6 HCA, and the cables.

8.1.3 Switch-to-Switch Connectivity

Switch	Switch	Cable					
		H cable DAC	H cable AOC	HDR DAC	HDR AOC	EDR DAC/AOC	FDR DAC/AOC
NVIDIA Quantum™	NVIDIA Quantum	No such cable	HDR100	HDR	HDR	EDR	N/A
NVIDIA Quantum	NVIDIA® Switch-IB®/ Switch-IB 2	N/A	N/A	EDR	N/A	EDR	N/A
NVIDIA Quantum	NVIDIA® SWITCHX®-2	N/A	N/A	N/A	N/A	N/A	FDR

8.1.4 HCA-to-Switch Connectivity Matrix


Adapter	Switch		Cable						
			Y cable DAC/AOC	HDR DAC	HDR AOC	HDR100 DAC/AOC (Copper Cables Only)	EDR DAC	EDR AOC	FDR DAC/AOC
ConnectX-6 200Gb/s	NVIDIA Quantum-2	NDR Switch	N/A	2 × HDR	2 × HDR	4 × HDR100	N/A	N/A	N/A
ConnectX-6 100Gb/s	NVIDIA Quantum-2		N/A	2 × EDR	N/A	4 × HDR100	N/A	N/A	N/A
ConnectX-4/ ConnectX-5	NVIDIA Quantum-2		N/A	2 × EDR	N/A	N/A	N/A	N/A	N/A
ConnectX-6 200Gb/s	NVIDIA Quantum	HDR Switch	HDR100	HDR	HDR	N/A	EDR	EDR	N/A
ConnectX-6 100Gb/s	NVIDIA Quantum		HDR100	EDR	EDR	N/A	EDR	EDR	N/A
ConnectX-4/ ConnectX-5	NVIDIA Quantum		N/A	EDR	N/A	N/A	EDR	EDR	FDR
ConnectX-3/ ConnectX-3 Pro	NVIDIA Quantum		N/A	N/A	N/A	N/A	N/A	FDR ^a	FDR ^a
ConnectX-6	Switch-IB/ Switch-IB 2	EDR Switch	N/A	EDR	N/A	N/A	EDR	EDR	N/A

Adapter	Switch		Cable						
			Y cable DAC/AOC	HDR DAC	HDR AOC	HDR100 DAC/AOC (Copper Cables Only)	EDR DAC	EDR AOC	FDR DAC/AOC
ConnectX-6	SWITCHX-2	FDR Switch	N/A	N/A	N/A	N/A	N/A	N/A	FDR

a. Connectivity between NVIDIA Quantum and ConnectX-3 and ConnectX-3 Pro is not supported when using ports #27-34.

8.1.4.1 VPI Protocol Support

ConnectX-6 VPI supports having one port as InfiniBand and the second port as Ethernet according to the following matrix of combinations.

 FDR is not supported in VPI mode.

This section provides details on the following tests:

To set the right configuration, run:

```
mlxconfig -d <mst device> s LINK_TYPE_P1=1/2 LINK_TYPE_P2=1/2
```

where:

- `LINK_TYPE_P1` - sets the configuring protocol for port 1
- `LINK_TYPE_P2` - sets the configuring protocol for port 2
- `(1/2)` - values used for the different protocols:
 - 1 - for InfiniBand
 - 2 - for Ethernet

Legend:

	Configuration Combination Support
V	Supported
X	Not supported

- | | |
|---------|------------|
| Port #1 | InfiniBand |
| Port #2 | Ethernet |

	Port #2 - Ethernet							
	200GbE/50GbE		100GbE/25GbE		40GbE/10GbE		1GbE	
Port #1 - InfiniBand	#1	#2	#1	#2	#1	#2	#1	#2
HDR / HDR100	V	V	V	V	V	X	V	V
EDR	V	V	V	V	V	X	V	V
FDR*	X	V	X	V	X	X	X	V
QDR/SDR	V	V	V	V	V	X	V	V

* FDR is not supported in VPI mode.

Port #2	InfiniBand
Port #1	Ethernet

	Port #2 - InfiniBand							
	HDR/HDR100		EDR		FDR*		QDR	
Port #1 - Ethernet	#1	#2	#1	#2	#1	#2	#1	#2
200GbE/50GbE	V	V	V	X	V	X	V	V
100GbE/25GbE	V	V	V	X	V	X	V	V
40GbE/10GbE	V	V	V	X	V	X	V	V
1GbE	V	V	V	X	V	X	V	V

* FDR is not supported in VPI mode.

8.1.5 HDR / 200GbE Cables

IB Data Rate	Eth Data Rate	NVIDIA P/N	Legacy OPN	Description	LifeCycle Phase
HDR	N/A	980-9I86N-00H 003*	MCA1J00-H003E*	NVIDIA Active Copper cable, IB HDR, up to 200Gb/s, QSFP56, 3m, yellow pulltab	EOL [MP]
HDR	N/A	980-9I86O-00H 004*	MCA1J00-H004E*	NVIDIA Active Copper cable, IB HDR, up to 200Gb/s, QSFP56, 4m, yellow pulltab	EOL [MP]

IB Data Rate	Eth Data Rate	NVIDIA P/N	Legacy OPN	Description	LifeCycle Phase
HDR	N/A	980-9I977-00H003*	MCA7J50-H003R*	NVIDIA Active copper hybrid cable, IB HDR 200Gb/s to 2xHDR100 100Gb/s, QSFP56 to 2xQSFP56, 3m, colored	EOL [MP]
HDR	N/A	980-9I978-00H004*	MCA7J50-H004R*	NVIDIA Active copper hybrid cable, IB HDR 200Gb/s to 2xHDR100 100Gb/s, QSFP56 to 2xQSFP56, 4m, colored	EOL [MP]
HDR	N/A	980-9I979-00H005	MCA7J50-H005R	NVIDIA Active copper hybrid cable, IB HDR 200Gb/s to 2xHDR100 100Gb/s, QSFP56 to 2xQSFP56, 5m, colored	EOL [Prototype]
HDR	200GE	980-9I548-00H001	MCP1650-H001E30	Nvidia Passive Copper cable, up to 200Gbps, QSFP56 to QSFP56, 1m	HVM
HDR	200GE	980-9I549-00H002	MCP1650-H002E26	Nvidia Passive Copper cable, up to 200Gbps, QSFP56 to QSFP56, 2m	HVM
HDR	200GE	980-9I54A-00H00A	MCP1650-H00AE30	Nvidia Passive Copper cable, up to 200Gbps, QSFP56 to QSFP56, 0.5m	HVM
HDR	200GE	980-9I54B-00H01A	MCP1650-H01AE30	Nvidia Passive Copper cable, up to 200Gbps, QSFP56 to QSFP56, 1.5 m	HVM
N/A	200GE	980-9I54C-00V001	MCP1650-V001E30	NVIDIA Passive Copper cable, 200GbE, 200Gb/s, QSFP56, LSZH, 1m, black pulltab, 30AWG	LTB [HVM]
N/A	200GE	980-9I54D-00V002	MCP1650-V002E26	NVIDIA Passive Copper cable, 200GbE, 200Gb/s, QSFP56, LSZH, 2m, black pulltab, 26AWG	LTB [HVM]
N/A	200GE	980-9I54E-00V002	MCP1650-V002E26_FF	NVIDIA Passive Copper cable, 200GbE, 200Gb/s, QSFP56, LSZH, 2m, black pulltab, 26AWG	EOL [HVM]
N/A	200GE	980-9I54G-00V003	MCP1650-V003E26	NVIDIA Passive Copper cable, 200GbE, 200Gb/s, QSFP56, LSZH, 3m, black pulltab, 26AWG	EOL [HVM]
N/A	200GE	980-9I54H-00V00A	MCP1650-V00AE30	NVIDIA Passive Copper cable, 200GbE, 200Gb/s, QSFP56, LSZH, 0.5m, black pulltab, 30AWG	LTB [HVM]

IB Data Rate	Eth Data Rate	NVIDIA P/N	Legacy OPN	Description	LifeCycle Phase
N/A	200GE	980-9I54I-00V01A	MCP1650-V01AE30	NVIDIA Passive Copper cable, 200GbE, 200Gb/s, QSFP56, LSZH, 1.5m, black pulltab, 30AWG	LTB [HVM]
N/A	200GE	980-9I54L-00V02A	MCP1650-V02AE26	NVIDIA Passive Copper cable, 200GbE, 200Gb/s, QSFP56, LSZH, 2.5m, black pulltab, 26AWG	LTB [HVM]
HDR	200GE	980-9I39E-00H001	MCP7H50-H001R30	Nvidia Passive copper splitter cable, 200Gbps to 2x100Gbps, QSFP56 to 2xQSFP56, 1m	HVM
HDR	200GE	980-9I99F-00H002	MCP7H50-H002R26	Nvidia Passive copper splitter cable, 200Gbps to 2x100Gbps, QSFP56 to 2xQSFP56, 2m	HVM
HDR	200GE	980-9I98G-00H01A	MCP7H50-H01AR30	Nvidia Passive copper splitter cable, 200Gbps to 2x100Gbps, QSFP56 to 2xQSFP56, 1.5m	HVM
N/A	200GE	980-9I98H-00V001	MCP7H50-V001R30	NVIDIA passive copper hybrid cable, 200GbE 200Gb/s to 2x100Gb/s, QSFP56 to 2xQSFP56, colored, 1m, 30AWG	LTB [HVM]
N/A	200GE	980-9I98I-00V002	MCP7H50-V002R26	NVIDIA passive copper hybrid cable, 200GbE 200Gb/s to 2x100Gb/s, QSFP56 to 2xQSFP56, colored, 2m, 26AWG	LTB [HVM]
N/A	200GE	980-9I98J-00V003	MCP7H50-V003R26	NVIDIA passive copper hybrid cable, 200GbE 200Gb/s to 2x100Gb/s, QSFP56 to 2xQSFP56, colored, 3m, 26AWG	EOL [HVM]
N/A	200GE	980-9I98K-00V01A	MCP7H50-V01AR30	NVIDIA passive copper hybrid cable, 200GbE 200Gb/s to 2x100Gb/s, QSFP56 to 2xQSFP56, colored, 1.5m, 30AWG	EOL [HVM]
N/A	200GE	980-9I98M-00V02A	MCP7H50-V02AR26	NVIDIA passive copper hybrid cable, 200GbE 200Gb/s to 2x100Gb/s, QSFP56 to 2xQSFP56, colored, 2.5m, 26AWG	LTB [HVM]
N/A	200GE	980-9IA3X-00V001	MCP7H70-V001R30	NVIDIA passive copper hybrid cable, 200GbE 200Gb/s to 4x50Gb/s, QSFP56 to 4xSFP56, colored, 1m, 30AWG	EOL [P-Rel]

IB Data Rate	Eth Data Rate	NVIDIA P/N	Legacy OPN	Description	LifeCycle Phase
N/A	200GE	980-9IA3Y-00V002	MCP7H70-V002R26	NVIDIA passive copper hybrid cable, 200GbE 200Gb/s to 4x50Gb/s, QSFP56 to 4xSFP56, colored, 2m, 26AWG	EOL [P-Rel]
N/A	200GE	980-9IA3Z-00V003	MCP7H70-V003R26	NVIDIA passive copper hybrid cable, 200GbE 200Gb/s to 4x50Gb/s, QSFP56 to 4xSFP56, colored, 3m, 26AWG	EOL [P-Rel]
N/A	200GE	980-9IA30-00V01A	MCP7H70-V01AR30	NVIDIA passive copper hybrid cable, 200GbE 200Gb/s to 4x50Gb/s, QSFP56 to 4xSFP56, colored, 1.5m, 30AWG	EOL [P-Rel]
N/A	200GE	980-9IA31-00V02A	MCP7H70-V02AR26	NVIDIA passive copper hybrid cable, 200GbE 200Gb/s to 4x50Gb/s, QSFP56 to 4xSFP56, colored, 2.5m, 26AWG	EOL [P-Rel]
HDR	200GE	980-9IA6K-00H001	MCP7Y60-H001	NVIDIA passive copper splitter cable, 400(2x200)Gbps to 2x200Gbps, OSFP to 2xQSFP56, 1m, fin to flat	MP
HDR	200GE	980-9IA6L-00H002	MCP7Y60-H002	NVIDIA passive copper splitter cable, 400(2x200)Gbps to 2x200Gbps, OSFP to 2xQSFP56, 2m, fin to flat	MP
HDR	200GE	980-9IA93M-00H01A	MCP7Y60-H01A	NVIDIA passive copper splitter cable, 400(2x200)Gbps to 2x200Gbps, OSFP to 2xQSFP56, 1.5m, fin to flat	MP
HDR	200GE	980-9IA93N-00H001	MCP7Y70-H001	NVIDIA passive copper splitter cable, 400(2x200)Gbps to 4x100Gbps, OSFP to 4xQSFP56, 1m, fin to flat	MP
HDR	200GE	980-9IA93O-00H002	MCP7Y70-H002	NVIDIA passive copper splitter cable, 400(2x200)Gbps to 4x100Gbps, OSFP to 4xQSFP56, 2m, fin to flat	MP
HDR	200GE	980-9IA7P-00H01A	MCP7Y70-H01A	NVIDIA passive copper splitter cable, 400(2x200)Gbps to 4x100Gbps, OSFP to 4xQSFP56, 1.5m, fin to flat	MP


IB Data Rate	Eth Data Rate	NVIDIA P/N	Legacy OPN	Description	LifeCycle Phase
HDR	N/A	980-9I123-00H003	MFS1S00-H003-LL	NVIDIA active fiber cable, IB HDR, up to 200Gb/s, QSFP56, LSZH, black pulltab, low latency, 3m	EOL [P-Rel]
HDR	N/A	980-9I124-00H003	MFS1S00-H003E	NVIDIA active fiber cable, IB HDR, up to 200Gb/s, QSFP56, LSZH, black pulltab, 3m	EOL [HVM]
HDR	200GE	980-9I457-00H003	MFS1S00-H003V	Nvidia active optical cable, up to 200Gbps , QSFP56 to QSFP56, 3m	MP
HDR	N/A	980-9I449-00H005	MFS1S00-H005-LL	NVIDIA active fiber cable, IB HDR, up to 200Gb/s, QSFP56, LSZH, black pulltab, low latency, 5m	EOL [P-Rel]
HDR	N/A	980-9I45A-00H005	MFS1S00-H005E	NVIDIA active fiber cable, IB HDR, up to 200Gb/s, QSFP56, LSZH, black pulltab, 5m	EOL [HVM]
HDR	200GE	980-9I45D-00H005	MFS1S00-H005V	Nvidia active optical cable, up to 200Gbps , QSFP56 to QSFP56, 5m	MP
HDR	N/A	980-9I44F-00H010	MFS1S00-H010-LL	NVIDIA active fiber cable, IB HDR, up to 200Gb/s, QSFP56, LSZH, black pulltab, low latency, 10m	EOL [P-Rel]
HDR	N/A	980-9I45G-00H010	MFS1S00-H010E	NVIDIA active fiber cable, IB HDR, up to 200Gb/s, QSFP56, LSZH, black pulltab, 10m	EOL [HVM]
HDR	N/A	980-9I45H-00H010	MFS1S00-H010E_FF	NVIDIA active fiber cable, IB HDR, up to 200Gb/s, QSFP56, LSZH, black pulltab, 10m	EOL [HVM]
HDR	200GE	980-9I45J-00H010	MFS1S00-H010V	Nvidia active optical cable, up to 200Gbps , QSFP56 to QSFP56, 10m	MP
HDR	N/A	980-9I44L-00H015	MFS1S00-H015-LL	NVIDIA active fiber cable, IB HDR, up to 200Gb/s, QSFP56, LSZH, black pulltab, low latency, 15m	EOL [P-Rel]
HDR	N/A	980-9I45M-00H015	MFS1S00-H015E	NVIDIA active fiber cable, IB HDR, up to 200Gb/s, QSFP56, LSZH, black pulltab, 15m	EOL [HVM]
HDR	200GE	980-9I45O-00H015	MFS1S00-H015V	Nvidia active optical cable, up to 200Gbps , QSFP56 to QSFP56, 15m	MP


IB Data Rate	Eth Data Rate	NVIDIA P/N	Legacy OPN	Description	LifeCycle Phase
HDR	N/A	980-9I44Q-00H020	MFS1S00-H020-LL	NVIDIA active fiber cable, IB HDR, up to 200Gb/s, QSFP56, LSZH, black pulltab, low latency, 20m	EOL [P-Rel]
HDR	N/A	980-9I45R-00H020	MFS1S00-H020E20	NVIDIA active fiber cable, IB HDR, up to 200Gb/s, QSFP56, LSZH, black pulltab, 20m	EOL [HVM]
HDR	200GE	980-9I45T-00H020	MFS1S00-H020V20	Nvidia active optical cable, up to 200Gbps , QSFP56 to QSFP56, 20m	MP
HDR	N/A	980-9I45X-00H030	MFS1S00-H030-LL	NVIDIA active fiber cable, IB HDR, up to 200Gb/s, QSFP56, LSZH, black pulltab, low latency, 30m	EOL [P-Rel]
HDR	N/A	980-9I45Y-00H030	MFS1S00-H030E30	NVIDIA active fiber cable, IB HDR, up to 200Gb/s, QSFP56, LSZH, black pulltab, 30m	EOL [HVM]
HDR	200GE	980-9I440-00H030	MFS1S00-H030V30	Nvidia active optical cable, up to 200Gbps , QSFP56 to QSFP56, 30m	MP
HDR	N/A	980-9I455-00H050	MFS1S00-H050E50	NVIDIA active fiber cable, IB HDR, up to 200Gb/s, QSFP56, LSZH, black pulltab, 50m	EOL [HVM]
HDR	200GE	980-9I447-00H050	MFS1S00-H050V50	Nvidia active optical cable, up to 200Gbps , QSFP56 to QSFP56, 50m	MP
HDR	N/A	980-9I44G-00H100	MFS1S00-H100E100	NVIDIA active fiber cable, IB HDR, up to 200Gb/s, QSFP56, LSZH, black pulltab, 100m	EOL [HVM]
HDR	200GE	980-9I44H-00H100	MFS1S00-H100V100	Nvidia active optical cable, up to 200Gbps , QSFP56 to QSFP56, 100m	MP
HDR	N/A	980-9I44I-00H130	MFS1S00-H130E130	NVIDIA active fiber cable, IB HDR, up to 200Gb/s, QSFP56, LSZH, black pulltab, 130m	EOL [HVM]
HDR	200GE	980-9I44K-00H130	MFS1S00-H130V130	Nvidia active optical cable, up to 200Gbps , QSFP56 to QSFP56, 130m	MP
HDR	N/A	980-9I45L-00H150	MFS1S00-H150E150	NVIDIA active fiber cable, IB HDR, up to 200Gb/s, QSFP56, LSZH, black pulltab, 150m	EOL [HVM]
HDR	200GE	980-9I44N-00H150	MFS1S00-H150V150	Nvidia active optical cable, up to 200Gbps , QSFP56 to QSFP56, 150m	MP

IB Data Rate	Eth Data Rate	NVIDIA P/N	Legacy OPN	Description	LifeCycle Phase
HDR	N/A	980-9I450-00H200	MFS1S00-H200E	NVIDIA active fiber cable, IB HDR, up to 200Gb/s, QSFP56, LSZH, black pulltab, 200m	EOL [EVT]
N/A	200GE	980-9I44P-00V003	MFS1S00-V003E	NVIDIA active fiber cable, 200GbE, 200Gb/s, QSFP56, LSZH, black pulltab, 3m	LTB [HVM]
N/A	200GE	980-9I45Q-00V005	MFS1S00-V005E	NVIDIA active fiber cable, 200GbE, 200Gb/s, QSFP56, LSZH, black pulltab, 5m	LTB [HVM]
N/A	200GE	980-9I45R-00V010	MFS1S00-V010E	NVIDIA active fiber cable, 200GbE, 200Gb/s, QSFP56, LSZH, black pulltab, 10m	LTB [HVM]
N/A	200GE	980-9I44S-00V015	MFS1S00-V015E	NVIDIA active fiber cable, 200GbE, 200Gb/s, QSFP56, LSZH, black pulltab, 15m	LTB [HVM]
N/A	200GE	980-9I44T-00V020	MFS1S00-V020E	NVIDIA active fiber cable, 200GbE, 200Gb/s, QSFP56, LSZH, black pulltab, 20m	LTB [HVM]
N/A	200GE	980-9I44U-00V030	MFS1S00-V030E	NVIDIA active fiber cable, 200GbE, 200Gb/s, QSFP56, LSZH, black pulltab, 30m	LTB [HVM]
N/A	200GE	980-9I44V-00V050	MFS1S00-V050E	NVIDIA active fiber cable, 200GbE, 200Gb/s, QSFP56, LSZH, black pulltab, 50m	LTB [HVM]
N/A	200GE	980-9I44W-00V100	MFS1S00-V100E	NVIDIA active fiber cable, 200GbE, 200Gb/s, QSFP56, LSZH, black pulltab, 100m	EOL [HVM] [HIBERN/ATE]
HDR	N/A	980-9I452-00H003	MFS1S50-H003E	NVIDIA active fiber splitter cable, IB HDR, 200Gb/s to 2x100Gb/s, QSFP56 to 2xQSFP56, LSZH, 3m	EOL [HVM]
HDR	200GE	980-9I445-00H003	MFS1S50-H003V	Nvidia active optical splitter cable, 200Gbps to 2x100Gbps, QSFP56 to 2xQSFP56, 3m	HVM
HDR	N/A	980-9I956-00H005	MFS1S50-H005E	NVIDIA active fiber splitter cable, IB HDR, 200Gb/s to 2x100Gb/s, QSFP56 to 2xQSFP56, LSZH, 5m	EOL [HVM]
HDR	200GE	980-9I969-00H005	MFS1S50-H005V	Nvidia active optical splitter cable, 200Gbps to 2x100Gbps, QSFP56 to 2xQSFP56, 5m	HVM
HDR	N/A	980-9I95A-00H010	MFS1S50-H010E	NVIDIA active fiber splitter cable, IB HDR, 200Gb/s to 2x100Gb/s, QSFP56 to 2xQSFP56, LSZH, 10m	EOL [HVM]

IB Data Rate	Eth Data Rate	NVIDIA P/N	Legacy OPN	Description	LifeCycle Phase
HDR	200GE	980-9I96D-00H010	MFS1S50-H010V	Nvidia active optical splitter cable, 200Gbps to 2x100Gbps , QSFP56 to 2x QSFP56, 10m	HVM
HDR	N/A	980-9I95E-00H015	MFS1S50-H015E	NVIDIA active fiber splitter cable, IB HDR, 200Gb/s to 2x100Gb/s, QSFP56 to 2xQSFP56 , LSZH, 15m	EOL [HVM]
HDR	200GE	980-9I96H-00H015	MFS1S50-H015V	Nvidia active optical splitter cable, 200Gbps to 2x100Gbps , QSFP56 to 2x QSFP56, 15m	HVM
HDR	N/A	980-9I95I-00H020	MFS1S50-H020E	NVIDIA active fiber splitter cable, IB HDR, 200Gb/s to 2x100Gb/s, QSFP56 to 2xQSFP56 , LSZH, 20m	EOL [HVM]
HDR	200GE	980-9I96L-00H020	MFS1S50-H020V	Nvidia active optical splitter cable, 200Gbps to 2x100Gbps , QSFP56 to 2x QSFP56, 20m	HVM
HDR	N/A	980-9I95M-00H030	MFS1S50-H030E	NVIDIA active fiber splitter cable, IB HDR, 200Gb/s to 2x100Gb/s, QSFP56 to 2xQSFP56 , LSZH, 30m	EOL [HVM]
HDR	200GE	980-9I96P-00H030	MFS1S50-H030V	Nvidia active optical splitter cable, 200Gbps to 2x100Gbps , QSFP56 to 2x QSFP56, 30m	HVM
HDR	200GE	980-9I95S-00H040	MFS1S50-H040V	Nvidia active optical splitter cable, 200Gbps to 2x100Gbps , QSFP56 to 2x QSFP56, 40m	Prototype
HDR	200GE	980-9I95T-00H050	MFS1S50-H050V	Nvidia active optical splitter cable, 200Gbps to 2x100Gbps , QSFP56 to 2x QSFP56, 50m	Prototype
N/A	200GE	980-9I95Q-00V003	MFS1S50-V003E	NVIDIA active fiber splitter cable, 200GbE, 200Gb/s to 2x100Gb/s, QSFP56 to 2xQSFP56, LSZH, black pulltab, 3m	EOL [HVM]
N/A	200GE	980-9I96R-00V005	MFS1S50-V005E	NVIDIA active fiber splitter cable, 200GbE, 200Gb/s to 2x100Gb/s, QSFP56 to 2xQSFP56, LSZH, black pulltab, 5m	EOL [HVM]
N/A	200GE	980-9I96S-00V010	MFS1S50-V010E	NVIDIA active fiber splitter cable, 200GbE, 200Gb/s to 2x100Gb/s, QSFP56 to 2xQSFP56, LSZH, black pulltab, 10m	EOL [HVM]

IB Data Rate	Eth Data Rate	NVIDIA P/N	Legacy OPN	Description	LifeCycle Phase
N/A	200GE	980-9I96T-00V015	MFS1S50-V015E	NVIDIA active fiber splitter cable, 200GbE, 200Gb/s to 2x100Gb/s, QSFP56 to 2xQSFP56, LSZH, black pulltab, 15m	EOL [HVM]
N/A	200GE	980-9I95U-00V020	MFS1S50-V020E	NVIDIA active fiber splitter cable, 200GbE, 200Gb/s to 2x100Gb/s, QSFP56 to 2xQSFP56, LSZH, black pulltab, 20m	EOL [HVM]
N/A	200GE	980-9I95V-00V030	MFS1S50-V030E	NVIDIA active fiber splitter cable, 200GbE, 200Gb/s to 2x100Gb/s, QSFP56 to 2xQSFP56, LSZH, black pulltab, 30m	EOL [HVM]
HDR	N/A	980-9I95Z-00H003	MFS1S90-H003E	NVIDIA active fiber splitter cable, IB HDR, 2x200Gb/s to 2x200Gb/s, 2xQSFP56 to 2xQSFP56, LSZH, 3m	EOL [HVM]
HDR	N/A	980-9I960-00H005	MFS1S90-H005E	NVIDIA active fiber splitter cable, IB HDR, 2x200Gb/s to 2x200Gb/s, 2xQSFP56 to 2xQSFP56, LSZH, 5m	EOL [HVM]
HDR	N/A	980-9I961-00H010	MFS1S90-H010E	NVIDIA active fiber splitter cable, IB HDR, 2x200Gb/s to 2x200Gb/s, 2xQSFP56 to 2xQSFP56, LSZH, 10m	LTB [HVM]
HDR	N/A	980-9I962-00H015	MFS1S90-H015E	NVIDIA active fiber splitter cable, IB HDR, 2x200Gb/s to 2x200Gb/s, 2xQSFP56 to 2xQSFP56, LSZH, 15m	EOL [HVM]
HDR	N/A	980-9I423-00H020	MFS1S90-H020E	NVIDIA active fiber splitter cable, IB HDR, 2x200Gb/s to 2x200Gb/s, 2xQSFP56 to 2xQSFP56, LSZH, 20m	LTB [HVM]
HDR	N/A	980-9I424-00H030	MFS1S90-H030E	NVIDIA active fiber splitter cable, IB HDR, 2x200Gb/s to 2x200Gb/s, 2xQSFP56 to 2xQSFP56, LSZH, 30m	EOL [HVM]
HDR	N/A	980-9I17S-00HS00	MMA1T00-HS	NVIDIA transceiver, HDR, QSFP56, MPO, 850nm, SR4, up to 100m	HVM
N/A	200GE	980-9I20T-00V000	MMA1T00-VS	NVIDIA transceiver, 200GbE, up to 200Gb/s, QSFP56, MPO, 850nm, SR4, up to 100m	HVM
HDR	N/A	980-9I055-00H000	MMS1W50-HM	NVIDIA transceiver, IB HDR, up to 200Gb/s, QSFP56, LC-LC, 1310nm, FR4	MP

 *These cables were approved for switch-to-switch connectivity. For switch-to-host connectivity there may be some issues. See Known Issue 1959529 in the Known Issues section.

 HDR links raise with RS_FEC.

8.1.6 EDR / 100GbE Cables

IB Data Rate	Eth Data Rate	NVIDIA P/N	Legacy OPN	Description	LifeCycle Phase
N/A	100GE	980-9I90Z-00C000	FTLC9152RGPL	100Gb/s Transceiver, QSFP28, LC-LC, 850nm SWDM4 up to 100m Over Multi-Mode Fiber	EOL [MP]
N/A	100GE	980-9I620-00C001	MCP1600-C001	NVIDIA Passive Copper cable, ETH 100GbE, 100Gb/s, QSFP, PVC, 1m 30AWG	EOL [HVM]
N/A	100GE	980-9I620-00C001	MCP1600-C001E30N	NVIDIA Passive Copper cable, ETH 100GbE, 100Gb/s, QSFP28, 1m, Black, 30AWG, CA-N	HVM
N/A	100GE	980-9I621-00C002	MCP1600-C002	NVIDIA Passive Copper cable, ETH 100GbE, 100Gb/s, QSFP, PVC, 2m 30AWG	EOL [HVM]
N/A	100GE	980-9I622-00C002	MCP1600-C002E26N	NVIDIA® Passive Copper cable, ETH 100GbE, 100Gb/s, QSFP28, 2m, Black, 26AWG, CA-N	Preliminary
N/A	100GE	980-9I62V-00C002	MCP1600-C002E30N	NVIDIA Passive Copper cable, ETH 100GbE, 100Gb/s, QSFP28, 2m, Black, 30AWG, CA-N	HVM
N/A	100GE	980-9I62X-00C003	MCP1600-C003	NVIDIA Passive Copper cable, ETH 100GbE, 100Gb/s, QSFP, PVC, 3m 28AWG	EOL [HVM]
N/A	100GE	980-9I62Z-00C003	MCP1600-C003E26N	NVIDIA Passive Copper cable, ETH 100GbE, 100Gb/s, QSFP28, 3m, Black, 26AWG, CA-N	EOL [HVM]
N/A	100GE	980-9I620-00C003	MCP1600-C003E30L	NVIDIA Passive Copper cable, ETH 100GbE, 100Gb/s, QSFP28, 3m, Black, 30AWG, CA-L	HVM

IB Data Rate	Eth Data Rate	NVIDIA P/N	Legacy OPN	Description	LifeCycle Phase
N/A	100GE	980-9I625-00C005	MCP1600-C005E26L	NVIDIA Passive Copper cable, ETH 100GbE, 100Gb/s, QSFP28, 5m, Black, 26AWG, CA-L	HVM
N/A	100GE	980-9I626-00C00A	MCP1600-C00A	NVIDIA Passive Copper cable, ETH 100GbE, 100Gb/s, QSFP, PVC, 0.5m 30AWG	EOL [HVM]
N/A	100GE	980-9I627-00C00A	MCP1600-C00AE30N	NVIDIA Passive Copper cable, ETH 100GbE, 100Gb/s, QSFP28, 0.5m, Black, 30AWG, CA-N	EOL [HVM]
N/A	100GE	980-9I629-00C00B	MCP1600-C00BE30N	NVIDIA Passive Copper cable, ETH 100GbE, 100Gb/s, QSFP28, 0.75m, Black, 30AWG, CA-N	EOL [HVM]
N/A	100GE	980-9I62B-00C01A	MCP1600-C01A	NVIDIA Passive Copper cable, ETH 100GbE, 100Gb/s, QSFP, PVC, 1.5m 30AWG	EOL [HVM]
N/A	100GE	980-9I62C-00C01A	MCP1600-C01AE30N	NVIDIA Passive Copper cable, ETH 100GbE, 100Gb/s, QSFP28, 1.5m, Black, 30AWG, CA-N	HVM
N/A	100GE	980-9I62G-00C02A	MCP1600-C02A	NVIDIA Passive Copper cable, ETH 100GbE, 100Gb/s, QSFP, PVC, 2.5m 30AWG	EOL [HVM]
N/A	100GE	980-9I62H-00C02A	MCP1600-C02AE26N	NVIDIA Passive Copper cable, ETH 100GbE, 100Gb/s, QSFP28, 2.5m, Black, 26AWG, CA-N	EOL [HVM]
N/A	100GE	980-9I62I-00C02A	MCP1600-C02AE30L	NVIDIA Passive Copper cable, ETH 100GbE, 100Gb/s, QSFP28, 2.5m, Black, 30AWG, CA-L	HVM
N/A	100GE	980-9I62M-00C03A	MCP1600-C03A	NVIDIA Passive Copper cable, ETH 100GbE, 100Gb/s, QSFP, PVC, 3.5m 26AWG	EOL [P-Rel]
EDR	100GE	980-9I62P-00C001	MCP1600-E001	NVIDIA Passive Copper cable, IB EDR, up to 100Gb/s, QSFP, LSZH, 1m 30AWG	EOL [HVM]
EDR	N/A	980-9I62Q-00E001	MCP1600-E001E30	NVIDIA Passive Copper cable, IB EDR, up to 100Gb/s, QSFP28, 1m, Black, 30AWG	HVM

IB Data Rate	Eth Data Rate	NVIDIA P/N	Legacy OPN	Description	LifeCycle Phase
EDR	100GE	980-9I62S-00C002	MCP1600-E002	NVIDIA Passive Copper cable, IB EDR, up to 100Gb/s, QSFP, LSZH, 2m 28AWG	EOL [HVM]
EDR	N/A	980-9I62T-00E002	MCP1600-E002E26	NVIDIA® Passive Copper cable, IB EDR, up to 100Gb/s, QSFP28, 2m, Black, 26AWG	Preliminary
EDR	N/A	980-9I62U-00E002	MCP1600-E002E30	NVIDIA Passive Copper cable, IB EDR, up to 100Gb/s, QSFP28, 2m, Black, 30AWG	HVM
EDR	100GE	980-9I62V-00C003	MCP1600-E003	NVIDIA Passive Copper cable, IB EDR, up to 100Gb/s, QSFP, LSZH, 3m 26AWG	EOL [HVM]
EDR	N/A	980-9I62W-00E003	MCP1600-E003E26	NVIDIA Passive Copper cable, IB EDR, up to 100Gb/s, QSFP28, 3m, Black, 26AWG	HVM
EDR	N/A	980-9I62Y-00E004	MCP1600-E004E26	NVIDIA Passive Copper cable, IB EDR, up to 100Gb/s, QSFP28, 4m, Black, 26AWG	EOL [HVM]
EDR	N/A	980-9I62Z-00E005	MCP1600-E005E26	NVIDIA Passive Copper cable, IB EDR, up to 100Gb/s, QSFP28, 5m, Black, 26AWG	HVM
EDR	N/A	980-9I620-00E00A	MCP1600-E00A	NVIDIA Passive Copper cable, IB EDR, up to 100Gb/s, QSFP, LSZH, 0.5m 30AWG	EOL [HVM]
EDR	N/A	980-9I621-00E00A	MCP1600-E00AE30	NVIDIA Passive Copper cable, IB EDR, up to 100Gb/s, QSFP28, 0.5m, Black, 30AWG	EOL [HVM]
EDR	N/A	980-9I622-00E00B	MCP1600-E00BE30	NVIDIA Passive Copper cable, IB EDR, up to 100Gb/s, QSFP28, 0.75m, Black, 30AWG	EOL [HVM] [HIBERN/ATE]
EDR	100GE	980-9I623-00C01A	MCP1600-E01A	NVIDIA Passive Copper cable, IB EDR, up to 100Gb/s, QSFP, LSZH, 1.5m 30AWG	EOL [HVM]
EDR	N/A	980-9I624-00E01A	MCP1600-E01AE30	NVIDIA Passive Copper cable, IB EDR, up to 100Gb/s, QSFP28, 1.5m, Black, 30AWG	HVM

IB Data Rate	Eth Data Rate	NVIDIA P/N	Legacy OPN	Description	LifeCycle Phase
EDR	N/A	980-91625-00E01C	MCP1600-E01BE30	NVIDIA Passive Copper cable, IB EDR, up to 100Gb/s, QSFP28, 1.25m, Black, 30AWG	EOL [HVM] [HIBERN/ATE]
EDR	100GE	980-91626-00C02A	MCP1600-E02A	NVIDIA Passive Copper cable, IB EDR, up to 100Gb/s, QSFP, LSZH, 2.5m 26AWG	EOL [HVM]
EDR	N/A	980-91627-00E02A	MCP1600-E02AE26	NVIDIA Passive Copper cable, IB EDR, up to 100Gb/s, QSFP28, 2.5m, Black, 26AWG	HVM
N/A	100GE	980-91645-00C001	MCP7F00-A001R	NVIDIA passive copper hybrid cable, ETH 100GbE to 4x25GbE, QSFP28 to 4xSFP28, colored pulltabs, 1m, 30AWG	EOL [HVM]
N/A	100GE	980-91486-00C001	MCP7F00-A001R30N	NVIDIA passive copper hybrid cable, ETH 100GbE to 4x25GbE, QSFP28 to 4xSFP28, 1m, Colored, 30AWG, CA-N	LTB [HVM]
N/A	100GE	980-9148A-00C002	MCP7F00-A002R	NVIDIA passive copper hybrid cable, ETH 100GbE to 4x25GbE, QSFP28 to 4xSFP28, colored pulltabs, 2m, 30AWG	EOL [HVM]
N/A	100GE	980-9148B-00C002	MCP7F00-A002R30N	NVIDIA passive copper hybrid cable, ETH 100GbE to 4x25GbE, QSFP28 to 4xSFP28, 2m, Colored, 30AWG, CA-N	LTB [HVM]
N/A	100GE	980-9148G-00C003	MCP7F00-A003R26N	NVIDIA passive copper hybrid cable, ETH 100GbE to 4x25GbE, QSFP28 to 4xSFP28, 3m, Colored, 26AWG, CA-N	EOL [HVM]
N/A	100GE	980-9148H-00C003	MCP7F00-A003R30L	NVIDIA passive copper hybrid cable, ETH 100GbE to 4x25GbE, QSFP28 to 4xSFP28, 3m, Colored, 30AWG, CA-L	LTB [HVM]
N/A	100GE	980-9148J-00C005	MCP7F00-A005R26L	NVIDIA passive copper hybrid cable, ETH 100GbE to 4x25GbE, QSFP28 to 4xSFP28, 5m, Colored, 26AWG, CA-L	LTB [HVM]
N/A	100GE	980-9148M-00C01A	MCP7F00-A01AR	NVIDIA passive copper hybrid cable, ETH 100GbE to 4x25GbE, QSFP28 to 4xSFP28, colored pulltabs, 1.5m, 30AWG	EOL [HVM]

IB Data Rate	Eth Data Rate	NVIDIA P/N	Legacy OPN	Description	LifeCycle Phase
N/A	100GE	980-9I48N-00C01A	MCP7F00-A01AR30N	NVIDIA passive copper hybrid cable, ETH 100GbE to 4x25GbE, QSFP28 to 4xSFP28, 1.5m, Colored, 30AWG, CA-N	LTB [HVM]
N/A	100GE	980-9I48S-00C02A	MCP7F00-A02AR26N	NVIDIA passive copper hybrid cable, ETH 100GbE to 4x25GbE, QSFP28 to 4xSFP28, 2.5m, Colored, 26AWG, CA-N	EOL [HVM]
N/A	100GE	980-9I48T-00C02A	MCP7F00-A02AR30L	NVIDIA passive copper hybrid cable, ETH 100GbE to 4x25GbE, QSFP28 to 4xSFP28, 2.5m, Colored, 30AWG, CA-L	LTB [HVM]
N/A	100GE	980-9I48U-00C02A	MCP7F00-A02ARLZ	NVIDIA passive copper hybrid cable, ETH 100GbE to 4x25GbE, QSFP28 to 4xSFP28, 2.5m, LSZH, Colored, 28AWG	EOL [P-Rel]
N/A	100GE	980-9I48X-00C03A	MCP7F00-A03AR26L	NVIDIA passive copper hybrid cable, ETH 100GbE to 4x25GbE, QSFP28 to 4xSFP28, 3.5m, Colored, 26AWG, CA-L	EOL [HVM]
N/A	100GE	980-9I61C-00C005	MCP7H00-G00000	NVIDIA® passive copper hybrid cable, ETH 100Gb/s to 2x50Gb/s, QSFP28 to 2xQSFP28, 5m, Colored, 26AWG, CA-L	Preliminary
N/A	100GE	980-9I61D-00C001	MCP7H00-G001	NVIDIA passive copper hybrid cable, ETH 100Gb/s to 2x50Gb/s, QSFP28 to 2xQSFP28, 1m, 30AWG	EOL [HVM]
N/A	100GE	980-9I99F-00C001	MCP7H00-G001R	NVIDIA passive copper hybrid cable, ETH 100Gb/s to 2x50Gb/s, QSFP28 to 2xQSFP28, colored pulltabs, 1m, 30AWG	EOL [HVM]
N/A	100GE	980-9I99G-00C001	MCP7H00-G001R30N	NVIDIA passive copper hybrid cable, ETH 100Gb/s to 2x50Gb/s, QSFP28 to 2xQSFP28, 1m, Colored, 30AWG, CA-N	LTB [HVM]
N/A	100GE	980-9I99J-00C002	MCP7H00-G002R	NVIDIA passive copper hybrid cable, ETH 100Gb/s to 2x50Gb/s, QSFP28 to 2xQSFP28, colored pulltabs, 2m, 30AWG	EOL [HVM]

IB Data Rate	Eth Data Rate	NVIDIA P/N	Legacy OPN	Description	LifeCycle Phase
N/A	100GE	980-9199K-00C002	MCP7H00-G002R26N	NVIDIA® passive copper hybrid cable, ETH 100Gb/s to 2x50Gb/s, QSFP28 to 2xQSFP28, 2m, Colored, 26AWG, CA-N	Preliminary
N/A	100GE	980-9199L-00C002	MCP7H00-G002R30N	NVIDIA passive copper hybrid cable, ETH 100Gb/s to 2x50Gb/s, QSFP28 to 2xQSFP28, 2m, Colored, 30AWG, CA-N	LTB [HVM]
N/A	100GE	980-9199O-00C003	MCP7H00-G003R	NVIDIA passive copper hybrid cable, ETH 100Gb/s to 2x50Gb/s, QSFP28 to 2xQSFP28, colored pulltabs, 3m, 28AWG	EOL [HVM]
N/A	100GE	980-9199Q-00C003	MCP7H00-G003R26N	NVIDIA passive copper hybrid cable, ETH 100Gb/s to 2x50Gb/s, QSFP28 to 2xQSFP28, 3m, Colored, 26AWG, CA-N	EOL [HVM]
N/A	100GE	980-9139R-00C003	MCP7H00-G003R30L	NVIDIA passive copper hybrid cable, ETH 100Gb/s to 2x50Gb/s, QSFP28 to 2xQSFP28, 3m, Colored, 30AWG, CA-L	LTB [HVM]
N/A	100GE	980-9199S-00C004	MCP7H00-G004R26L	NVIDIA passive copper hybrid cable, ETH 100Gb/s to 2x50Gb/s, QSFP28 to 2xQSFP28, 4m, Colored, 26AWG, CA-L	EOL [HVM]
N/A	100GE	980-9199W-00C01A	MCP7H00-G01AR	NVIDIA passive copper hybrid cable, ETH 100Gb/s to 2x50Gb/s, QSFP28 to 2xQSFP28, colored pulltabs, 1.5m, 30AWG	EOL [HVM]
N/A	100GE	980-9199X-00C01A	MCP7H00-G01AR30N	NVIDIA passive copper hybrid cable, ETH 100Gb/s to 2x50Gb/s, QSFP28 to 2xQSFP28, 1.5m, Colored, 30AWG, CA-N	LTB [HVM]
N/A	100GE	980-91992-00C02A	MCP7H00-G02AR	NVIDIA passive copper hybrid cable, ETH 100Gb/s to 2x50Gb/s, QSFP28 to 2xQSFP28, colored pulltabs, 2.5m, 30AWG	EOL [HVM]
N/A	100GE	980-91994-00C02A	MCP7H00-G02AR26N	NVIDIA passive copper hybrid cable, ETH 100Gb/s to 2x50Gb/s, QSFP28 to 2xQSFP28, 2.5m, Colored, 26AWG, CA-N	EOL [HVM]

IB Data Rate	Eth Data Rate	NVIDIA P/N	Legacy OPN	Description	LifeCycle Phase
N/A	100GE	980-91395-00C02A	MCP7H00-G02AR30L	NVIDIA passive copper hybrid cable, ETH 100Gb/s to 2x50Gb/s, QSFP28 to 2xQSFP28, 2.5m, Colored, 30AWG, CA-L	LTB [HVM]
N/A	100GE	980-9113S-00C003	MFA1A00-C003	NVIDIA active fiber cable, ETH 100GbE, 100Gb/s, QSFP, LSZH, 3m	HVM
N/A	100GE	980-9113X-00C005	MFA1A00-C005	NVIDIA active fiber cable, ETH 100GbE, 100Gb/s, QSFP, LSZH, 5m	HVM
N/A	100GE	980-91134-00C010	MFA1A00-C010	NVIDIA active fiber cable, ETH 100GbE, 100Gb/s, QSFP, LSZH, 10m	HVM
N/A	100GE	980-9113A-00C015	MFA1A00-C015	NVIDIA active fiber cable, ETH 100GbE, 100Gb/s, QSFP, LSZH, 15m	HVM
N/A	100GE	980-9113F-00C020	MFA1A00-C020	NVIDIA active fiber cable, ETH 100GbE, 100Gb/s, QSFP, LSZH, 20m	HVM
N/A	100GE	980-9113N-00C030	MFA1A00-C030	NVIDIA active fiber cable, ETH 100GbE, 100Gb/s, QSFP, LSZH, 30m	HVM
N/A	100GE	980-91130-00C050	MFA1A00-C050	NVIDIA active fiber cable, ETH 100GbE, 100Gb/s, QSFP, LSZH, 50m	HVM
N/A	100GE	980-9113B-00C100	MFA1A00-C100	NVIDIA active fiber cable, ETH 100GbE, 100Gb/s, QSFP, LSZH, 100m	LTB [HVM]
EDR	N/A	980-9113D-00E001	MFA1A00-E001	NVIDIA active fiber cable, IB EDR, up to 100Gb/s, QSFP, LSZH, 1m	HVM
EDR	N/A	980-9113F-00E003	MFA1A00-E003	NVIDIA active fiber cable, IB EDR, up to 100Gb/s, QSFP, LSZH, 3m	HVM
EDR	N/A	980-9113J-00E005	MFA1A00-E005	NVIDIA active fiber cable, IB EDR, up to 100Gb/s, QSFP, LSZH, 5m	HVM
EDR	N/A	980-9113M-00E007	MFA1A00-E007	NVIDIA active fiber cable, IB EDR, up to 100Gb/s, QSFP, LSZH, 7m	LTB [HVM]
EDR	N/A	980-9113O-00E010	MFA1A00-E010	NVIDIA active fiber cable, IB EDR, up to 100Gb/s, QSFP, LSZH, 10m	HVM
EDR	N/A	980-9113R-00E010	MFA1A00-E010_FF	NVIDIA active fiber cable, IB EDR, up to 100Gb/s, QSFP, LSZH, 10m	EOL [HVM] [HIBERN/ATE]

IB Data Rate	Eth Data Rate	NVIDIA P/N	Legacy OPN	Description	LifeCycle Phase
EDR	N/A	980-9I13S-00E015	MFA1A00-E015	NVIDIA active fiber cable, IB EDR, up to 100Gb/s, QSFP, LSZH, 15m	HVM
EDR	N/A	980-9I13V-00E020	MFA1A00-E020	NVIDIA active fiber cable, IB EDR, up to 100Gb/s, QSFP, LSZH, 20m	HVM
EDR	N/A	980-9I13Y-00E030	MFA1A00-E030	NVIDIA active fiber cable, IB EDR, up to 100Gb/s, QSFP, LSZH, 30m	HVM
EDR	N/A	980-9I133-00E050	MFA1A00-E050	NVIDIA active fiber cable, IB EDR, up to 100Gb/s, QSFP, LSZH, 50m	HVM
EDR	N/A	980-9I135-00E100	MFA1A00-E100	NVIDIA active fiber cable, IB EDR, up to 100Gb/s, QSFP, LSZH, 100m	LTB [HVM]
N/A	100GE	980-9I37H-00C003	MFA7A20-C003	NVIDIA active fiber hybrid solution, ETH 100GbE to 2x50GbE, QSFP28 to 2xQSFP28, 3m	EOL [HVM]
N/A	100GE	980-9I37I-00C005	MFA7A20-C005	NVIDIA active fiber hybrid solution, ETH 100GbE to 2x50GbE, QSFP28 to 2xQSFP28, 5m	EOL [HVM]
N/A	100GE	980-9I40J-00C010	MFA7A20-C010	NVIDIA active fiber hybrid solution, ETH 100GbE to 2x50GbE, QSFP28 to 2xQSFP28, 10m	EOL [HVM]
N/A	100GE	980-9I40K-00C020	MFA7A20-C020	NVIDIA active fiber hybrid solution, ETH 100GbE to 2x50GbE, QSFP28 to 2xQSFP28, 20m	EOL [HVM]
N/A	100GE	980-9I40L-00C002	MFA7A20-C02A	NVIDIA® active fiber hybrid solution, ETH 100GbE to 2x50GbE, QSFP28 to 2xQSFP28, 2.5m	Preliminary
N/A	100GE	980-9I40M-00C003	MFA7A20-C03A	NVIDIA® active fiber hybrid solution, ETH 100GbE to 2x50GbE, QSFP28 to 2xQSFP28, 3.5m	Preliminary
N/A	100GE	980-9I40N-00C003	MFA7A50-C003	NVIDIA active fiber hybrid solution, ETH 100GbE to 4x25GbE, QSFP28 to 4xSFP28, 3m	EOL [HVM]
N/A	100GE	980-9I40O-00C005	MFA7A50-C005	NVIDIA active fiber hybrid solution, ETH 100GbE to 4x25GbE, QSFP28 to 4xSFP28, 5m	EOL [HVM]

IB Data Rate	Eth Data Rate	NVIDIA P/N	Legacy OPN	Description	LifeCycle Phase
N/A	100GE	980-9I49P-00C010	MFA7A50-C010	NVIDIA active fiber hybrid solution, ETH 100GbE to 4x25GbE, QSFP28 to 4xSFP28, 10m	EOL [HVM]
N/A	100GE	980-9I49Q-00C015	MFA7A50-C015	NVIDIA active fiber hybrid solution, ETH 100GbE to 4x25GbE, QSFP28 to 4xSFP28, 15m	EOL [HVM]
N/A	100GE	980-9I49R-00C020	MFA7A50-C020	NVIDIA active fiber hybrid solution, ETH 100GbE to 4x25GbE, QSFP28 to 4xSFP28, 20m	EOL [HVM]
N/A	100GE	980-9I49S-00C030	MFA7A50-C030	NVIDIA active fiber hybrid solution, ETH 100GbE to 4x25GbE, QSFP28 to 4xSFP28, 30m	EOL [HVM]
N/A	100GE	980-9I149-00C500	MMA1B00-C100D	NVIDIA transceiver, 100GbE, QSFP28, MPO, 850nm, SR4, up to 100m, DDMI	HVM
N/A	100GE	980-9I17B-00C500	MMA1B00-C100D_FF	NVIDIA transceiver, 100GbE, QSFP28, MPO, 850nm, SR4, up to 100m, DDMI	EOL [HVM] [HIBERN/ATE]
N/A	100GE	980-9I17D-00C500	MMA1B00-C100T	NVIDIA® transceiver, 100GbE, QSFP28, MPO, 850nm, up to 100m, OTU4	Preliminary
EDR	N/A	980-9I17L-00E000	MMA1B00-E100	NVIDIA transceiver, IB EDR, up to 100Gb/s, QSFP28, MPO, 850nm, SR4, up to 100m	HVM
N/A	100GE	980-9I17P-00CR00	MMA1L10-CR	NVIDIA optical transceiver, 100GbE, 100Gb/s, QSFP28, LC-LC, 1310nm, LR4 up to 10km	HVM
N/A	100GE	980-9I17Q-00CM00	MMA1L30-CM	NVIDIA optical module, 100GbE, 100Gb/s, QSFP28, LC-LC, 1310nm, CWDM4, up to 2km	MP
N/A	100GE	980-9I16X-00C000	MMS1C10-CM	NVIDIA active optical module, 100Gb/s, QSFP, MPO, 1310nm, PSM4, up to 500m	EOL [MP]
N/A	100GE	980-9I042-00C000	MMS1V70-CM	NVIDIA transceiver, 100GbE, QSFP28, LC-LC, 1310nm, DR1	P-Rel



EDR links raise with RS-FEC.

8.1.7 FDR / 56GbE Cables

IB Data Rate	Eth Data Rate	NVIDIA P/N	Legacy OPN	Description	LifeCycle Phase
FDR	56GE	980-9I679-00L004	MC2207126-004	NVIDIA passive copper cable, VPI, up to 56Gb/s, QSFP, 4m	EOL [HVM]
FDR	56GE	980-9I67A-00L003	MC2207128-003	NVIDIA passive copper cable, VPI, up to 56Gb/s, QSFP, 3m	EOL [HVM]
FDR	56GE	980-9I67C-00L02A	MC2207128-0A2	NVIDIA passive copper cable, VPI, up to 56Gb/s, QSFP, 2.5m	EOL [MP]
FDR	56GE	980-9I67D-00L001	MC2207130-001	NVIDIA passive copper cable, VPI, up to 56Gb/s, QSFP, 1m	EOL [HVM]
FDR	56GE	980-9I67E-00L002	MC2207130-002	NVIDIA passive copper cable, VPI, up to 56Gb/s, QSFP, 2m	EOL [HVM]
FDR	56GE	980-9I67F-00L00A	MC2207130-00A	NVIDIA passive copper cable, VPI, up to 56Gb/s, QSFP, 0.5m	EOL [HVM]
FDR	56GE	980-9I67G-00L01A	MC2207130-0A1	NVIDIA passive copper cable, VPI, up to 56Gb/s, QSFP, 1.5m	EOL [HVM]
FDR	56GE	980-9I15U-00L003	MC220731V-003	NVIDIA active fiber cable, VPI, up to 56Gb/s, QSFP, 3m	EOL [HVM]
FDR	56GE	980-9I15V-00L005	MC220731V-005	NVIDIA active fiber cable, VPI, up to 56Gb/s, QSFP, 5m	EOL [HVM]
FDR	56GE	980-9I15W-00L010	MC220731V-010	NVIDIA active fiber cable, VPI, up to 56Gb/s, QSFP, 10m	EOL [HVM]
FDR	56GE	980-9I15X-00L015	MC220731V-015	NVIDIA active fiber cable, VPI, up to 56Gb/s, QSFP, 15m	EOL [HVM]
FDR	56GE	980-9I15Y-00L020	MC220731V-020	NVIDIA active fiber cable, VPI, up to 56Gb/s, QSFP, 20m	EOL [HVM]
FDR	56GE	980-9I15Z-00L025	MC220731V-025	NVIDIA active fiber cable, VPI, up to 56Gb/s, QSFP, 25m	EOL [HVM]
FDR	56GE	980-9I150-00L030	MC220731V-030	NVIDIA active fiber cable, VPI, up to 56Gb/s, QSFP, 30m	EOL [HVM]
FDR	56GE	980-9I151-00L040	MC220731V-040	NVIDIA active fiber cable, VPI, up to 56Gb/s, QSFP, 40m	EOL [HVM] [HIBERN/ATE]

IB Data Rate	Eth Data Rate	NVIDIA P/N	Legacy OPN	Description	LifeCycle Phase
FDR	56GE	980-91152-00L050	MC220731V-050	NVIDIA active fiber cable, VPI, up to 56Gb/s, QSFP, 50m	EOL [HVM]
FDR	56GE	980-91153-00L075	MC220731V-075	NVIDIA active fiber cable, VPI, up to 56Gb/s, QSFP, 75m	EOL [HVM]
FDR	56GE	980-91154-00L100	MC220731V-100	NVIDIA active fiber cable, VPI, up to 56Gb/s, QSFP, 100m	EOL [HVM]
FDR	56GE	980-91675-00L001	MCP170L-F001	NVIDIA passive copper cable, VPI, up to 56Gb/s, QSFP, LSZH, 1m	EOL [P-Rel]
FDR	56GE	980-91676-00L002	MCP170L-F002	NVIDIA passive copper cable, VPI, up to 56Gb/s, QSFP, LSZH, 2m	EOL [P-Rel]
FDR	56GE	980-91677-00L003	MCP170L-F003	NVIDIA passive copper cable, VPI, up to 56Gb/s, QSFP, LSZH, 3m	EOL [P-Rel] [HIBERN/ATE]
FDR	56GE	980-91678-00L00A	MCP170L-F00A	NVIDIA passive copper cable, VPI, up to 56Gb/s, QSFP, LSZH, 0.5m	EOL [P-Rel]
FDR	56GE	980-91679-00L01A	MCP170L-F01A	NVIDIA passive copper cable, VPI, up to 56Gb/s, QSFP, LSZH, 1.5m	EOL [P-Rel] [HIBERN/ATE]
FDR	N/A	980-9117M-00FS00	MMA1B00-F030D	NVIDIA transceiver, FDR, QSFP+, MPO, 850nm, SR4, up to 30m, DDMI	LTB [HVM]

8.1.8 50GbE Cables

IB Data Rate	Eth Data Rate	NVIDIA P/N	Legacy OPN	Description	LifeCycle Phase
N/A	50GE	980-91873-00G001	MCP2M50-G001E30	NVIDIA Passive Copper cable, 50GbE, 50Gb/s, SFP56, LSZH, 1m, black pulltab, 30AWG	EOL [P-Rel]
N/A	50GE	980-91874-00G002	MCP2M50-G002E26	NVIDIA Passive Copper cable, 50GbE, 50Gb/s, SFP56, LSZH, 2m, black pulltab, 26AWG	EOL [P-Rel]
N/A	50GE	980-91875-00G003	MCP2M50-G003E26	NVIDIA Passive Copper cable, 50GbE, 50Gb/s, SFP56, LSZH, 3m, black pulltab, 26AWG	EOL [P-Rel]

IB Data Rate	Eth Data Rate	NVIDIA P/N	Legacy OPN	Description	LifeCycle Phase
N/A	50GE	980-91876-00G00A	MCP2M50-G00AE30	NVIDIA Passive Copper cable, 50GbE, 50Gb/s, SFP56, LSZH, 0.5m, black pulltab, 30AWG	EOL [P-Rel]
N/A	50GE	980-91877-00G01A	MCP2M50-G01AE30	NVIDIA Passive Copper cable, 50GbE, 50Gb/s, SFP56, LSZH, 1.5m, black pulltab, 30AWG	EOL [P-Rel]
N/A	50GE	980-91878-00G02A	MCP2M50-G02AE26	NVIDIA Passive Copper cable, 50GbE, 50Gb/s, SFP56, LSZH, 2.5m, black pulltab, 26AWG	EOL [P-Rel]

8.1.9 QDR Cables

IB Data Rate	Eth Data Rate	NVIDIA P/N	Legacy Cables OPN	Description	LifeCycle Phase
QDR	NA	980-91665-00Q007	MC2206125-007	NVIDIA passive copper cable, IB QDR, 40Gb/s, QSFP, 7m	EOL [HVM]

8.1.10 FDR10 / 40GbE Cables

IB Data Rate	Eth Data Rate	NVIDIA P/N	Legacy OPN	Description	LifeCycle Phase
FDR10	40GE	980-9166U-00B004	MC2206128-004	NVIDIA passive copper cable, VPI, up to 40Gb/s, QSFP, 4m	EOL [HVM] [HIBERN/ATE]
FDR10	40GE	980-9166V-00B005	MC2206128-005	NVIDIA passive copper cable, VPI, up to 40Gb/s, QSFP, 5m	EOL [HVM]
FDR10	40GE	980-9166W-00B001	MC2206130-001	NVIDIA passive copper cable, VPI, up to 40Gb/s, QSFP, 1m	EOL [HVM]
FDR10	40GE	980-9166X-00B002	MC2206130-002	NVIDIA passive copper cable, VPI, up to 40Gb/s, QSFP, 2m	EOL [HVM]
FDR10	40GE	980-9166Y-00B003	MC2206130-003	NVIDIA passive copper cable, VPI, up to 40Gb/s, QSFP, 3m	EOL [HVM]
FDR10	40GE	980-9166Z-00B00A	MC2206130-00A	NVIDIA passive copper cable, VPI, up to 40Gb/s, QSFP, 0.5m	EOL [HVM]
FDR10	N/A	980-91140-00T003	MC2206310-003	NVIDIA active fiber cable, IB QDR/FDR10, 40Gb/s, QSFP, 3m	EOL [HVM]

IB Data Rate	Eth Data Rate	NVIDIA P/N	Legacy OPN	Description	LifeCycle Phase
FDR10	N/A	980-9I141-00T005	MC2206310-005	NVIDIA active fiber cable, IB QDR/FDR10, 40Gb/s, QSFP, 5m	EOL [HVM]
FDR10	N/A	980-9I142-00T010	MC2206310-010	NVIDIA active fiber cable, IB QDR/FDR10, 40Gb/s, QSFP, 10m	EOL [HVM]
FDR10	N/A	980-9I143-00T015	MC2206310-015	NVIDIA active fiber cable, IB QDR/FDR10, 40Gb/s, QSFP, 15m	EOL [HVM]
FDR10	N/A	980-9I144-00T020	MC2206310-020	NVIDIA active fiber cable, IB QDR/FDR10, 40Gb/s, QSFP, 20m	EOL [HVM]
FDR10	N/A	980-9I145-00T030	MC2206310-030	NVIDIA active fiber cable, IB QDR/FDR10, 40Gb/s, QSFP, 30m	EOL [HVM]
FDR10	N/A	980-9I147-00T050	MC2206310-050	NVIDIA active fiber cable, IB QDR/FDR10, 40Gb/s, QSFP, 50m	EOL [HVM]
FDR10	N/A	980-9I148-00T100	MC2206310-100	NVIDIA active fiber cable, IB QDR/FDR10, 40Gb/s, QSFP, 100m	EOL [HVM]
N/A	40GE	980-9I666-00B004	MC2210126-004	NVIDIA passive copper cable, ETH 40GbE, 40Gb/s, QSFP, 4m	EOL [HVM]
N/A	40GE	980-9I667-00B005	MC2210126-005	NVIDIA passive copper cable, ETH 40GbE, 40Gb/s, QSFP, 5m	EOL [HVM]
N/A	40GE	980-9I668-00B003	MC2210128-003	NVIDIA passive copper cable, ETH 40GbE, 40Gb/s, QSFP, 3m	EOL [HVM]
N/A	40GE	980-9I66A-00B001	MC2210130-001	NVIDIA passive copper cable, ETH 40GbE, 40Gb/s, QSFP, 1m	EOL [HVM]
N/A	40GE	980-9I66C-00B002	MC2210130-002	NVIDIA passive copper cable, ETH 40GbE, 40Gb/s, QSFP, 2m	EOL [HVM]
N/A	40GE	980-9I14D-00B003	MC2210310-003	NVIDIA active fiber cable, ETH 40GbE, 40Gb/s, QSFP, 3m	EOL [MP]
N/A	40GE	980-9I14E-00B005	MC2210310-005	NVIDIA active fiber cable, ETH 40GbE, 40Gb/s, QSFP, 5m	EOL [MP]
N/A	40GE	980-9I14F-00B010	MC2210310-010	NVIDIA active fiber cable, ETH 40GbE, 40Gb/s, QSFP, 10m	EOL [MP]
N/A	40GE	980-9I14G-00B015	MC2210310-015	NVIDIA active fiber cable, ETH 40GbE, 40Gb/s, QSFP, 15m	EOL [MP]

IB Data Rate	Eth Data Rate	NVIDIA P/N	Legacy OPN	Description	LifeCycle Phase
N/A	40GE	980-9I14H-00B020	MC2210310-020	NVIDIA active fiber cable, ETH 40GbE, 40Gb/s, QSFP, 20m	EOL [MP]
N/A	40GE	980-9I14I-00B030	MC2210310-030	NVIDIA active fiber cable, ETH 40GbE, 40Gb/s, QSFP, 30m	EOL [MP]
N/A	40GE	980-9I14J-00B050	MC2210310-050	NVIDIA active fiber cable, ETH 40GbE, 40Gb/s, QSFP, 50m	EOL [MP]
N/A	40GE	980-9I14K-00B100	MC2210310-100	NVIDIA active fiber cable, ETH 40GbE, 40Gb/s, QSFP, 100m	EOL [MP]
FDR10	40GE	980-9I170-00B M00	MC2210411-SR4E	NVIDIA optical module, 40Gb/s, QSFP, MPO, 850nm, up to 300m	EOL [HVM]
FDR10	N/A	980-9I210-00T R00	MC2210511-LR4	NVIDIA optical module, 40Gb/s, QSFP, LC-LC, 1310nm, LR4 up to 10km	EOL [MP]
N/A	40GE	980-9I64V-00B005	MC2609125-005	NVIDIA passive copper hybrid cable, ETH 40GbE to 4x10GbE, QSFP to 4xSFP+, 5m	EOL [P-Rel]
N/A	40GE	980-9I64W-00B001	MC2609130-001	NVIDIA passive copper hybrid cable, ETH 40GbE to 4x10GbE, QSFP to 4xSFP+, 1m	EOL [HVM]
N/A	40GE	980-9I64Y-00B003	MC2609130-003	NVIDIA passive copper hybrid cable, ETH 40GbE to 4x10GbE, QSFP to 4xSFP+, 3m	EOL [HVM]
N/A	40GE	980-9I72J-00B005	MC6709309-005	NVIDIA passive fiber hybrid cable, MPO to 8xLC, 5m	EOL [HVM]
N/A	40GE	980-9I72K-00B010	MC6709309-010	NVIDIA passive fiber hybrid cable, MPO to 8xLC, 10m	EOL [HVM]
N/A	40GE	980-9I72L-00B020	MC6709309-020	NVIDIA passive fiber hybrid cable, MPO to 8xLC, 20m	EOL [HVM]
N/A	40GE	980-9I72M-00B030	MC6709309-030	NVIDIA passive fiber hybrid cable, MPO to 8xLC, 30m	EOL [HVM]
N/A	40GE	980-9I66U-00B001	MCP1700-B001E	NVIDIA passive copper cable, ETH 40GbE, 40Gb/s, QSFP, 1m, Black Pulltab	EOL [HVM]
N/A	40GE	980-9I66V-00B002	MCP1700-B002E	NVIDIA passive copper cable, ETH 40GbE, 40Gb/s, QSFP, 2m, Black Pulltab	EOL [HVM]
N/A	40GE	980-9I66W-00B003	MCP1700-B003E	NVIDIA passive copper cable, ETH 40GbE, 40Gb/s, QSFP, 3m, Black Pulltab	EOL [HVM]

IB Data Rate	Eth Data Rate	NVIDIA P/N	Legacy OPN	Description	LifeCycle Phase
N/A	40GE	980-9I66X-00B01A	MCP1700-B01AE	NVIDIA passive copper cable, ETH 40GbE, 40Gb/s, QSFP, 1.5m, Black Pulltab	EOL [MP]
N/A	40GE	980-9I66Y-00B02A	MCP1700-B02AE	NVIDIA passive copper cable, ETH 40GbE, 40Gb/s, QSFP, 2.5m, Black Pulltab	EOL [MP]
N/A	40GE	980-9I426-00B M00	MMA1B00-B150D	NVIDIA transceiver, 40GbE, QSFP+, MPO, 850nm, SR4, up to 150m, DDMI	EOL [HVM]
N/A	40GE	980-9I64X-00B01A	MCP7900-X01AA	NVIDIA passive copper hybrid cable, ETH 40GbE to 4x10GbE, QSFP to 4xSFP+, 1.5m, Blue Pulltab, customized label	EOL [P-Rel] [HIBERNATE]
N/A	40GE	980-9I640-00B002	MCP7904-X002A	NVIDIA passive copper hybrid cable, ETH 40GbE to 4x10GbE, QSFP to 4xSFP+, 2m, Black Pulltab, customized label	EOL [HVM]
N/A	40GE	980-9I641-00B003	MCP7904-X003A	NVIDIA passive copper hybrid cable, ETH 40GbE to 4x10GbE, QSFP to 4xSFP+, 3m, Black Pulltab, customized label	EOL [HVM] [HIBERNATE]
N/A	40GE	980-9I642-00B01A	MCP7904-X01AA	NVIDIA passive copper hybrid cable, ETH 40GbE to 4x10GbE, QSFP to 4xSFP+, 1.5m, Black Pulltab, customized label	EOL [HVM]
N/A	40GE	980-9I643-00B02A	MCP7904-X02AA	NVIDIA passive copper hybrid cable, ETH 40GbE to 4x10GbE, QSFP to 4xSFP+, 2.5m, Black Pulltab, customized label	EOL [P-Rel] [HIBERNATE]

8.1.11 25GbE Cables

IB Data Rate	Eth Data Rate	NVIDIA P/N	Legacy OPN	Description	LifeCycle Phase
N/A	25GE	980-9I78I-00A000	MAM1Q00A-QSA28	NVIDIA cable module, ETH 25GbE, 100Gb/s to 25Gb/s, QSFP28 to SFP28	HVM
N/A	25GE	980-9I63J-00A001	MCP2M00-A001	NVIDIA Passive Copper cable, ETH, up to 25Gb/s, SFP28, 1m, 30AWG	EOL [HVM]
N/A	25GE	980-9I63L-00A001	MCP2M00-A001E30N	NVIDIA Passive Copper cable, ETH, up to 25Gb/s, SFP28, 1m, Black, 30AWG, CA-N	LTB [HVM]

IB Data Rate	Eth Data Rate	NVIDIA P/N	Legacy OPN	Description	LifeCycle Phase
N/A	25GE	980-9I63M-00A002	MCP2M00-A002	NVIDIA Passive Copper cable, ETH, up to 25Gb/s, SFP28, 2m, 30AWG	EOL [HVM]
N/A	25GE	980-9I63N-00A002	MCP2M00-A002E26N	NVIDIA® Passive Copper cable, ETH, up to 25Gb/s, SFP28, 2m, Black, 26AWG, CA-N	Preliminary
N/A	25GE	980-9I63O-00A002	MCP2M00-A002E30N	NVIDIA Passive Copper cable, ETH, up to 25Gb/s, SFP28, 2m, Black, 30AWG, CA-N	LTB [HVM]
N/A	25GE	980-9I63R-00A003	MCP2M00-A003E26N	NVIDIA Passive Copper cable, ETH, up to 25Gb/s, SFP28, 3m, Black, 26AWG, CA-N	EOL [HVM]
N/A	25GE	980-9I63S-00A003	MCP2M00-A003E30L	NVIDIA Passive Copper cable, ETH, up to 25Gb/s, SFP28, 3m, Black, 30AWG, CA-L	LTB [HVM]
N/A	25GE	980-9I63T-00A004	MCP2M00-A004E26L	NVIDIA Passive Copper cable, ETH, up to 25Gb/s, SFP28, 4m, Black, 26AWG, CA-L	EOL [HVM]
N/A	25GE	980-9I63V-00A005	MCP2M00-A005E26L	NVIDIA Passive Copper cable, ETH, up to 25Gb/s, SFP28, 5m, Black, 26AWG, CA-L	LTB [HVM]
N/A	25GE	980-9I63W-00A00A	MCP2M00-A00A	NVIDIA Passive Copper cable, ETH, up to 25Gb/s, SFP28, 0.5m, 30AWG	EOL [HVM]
N/A	25GE	980-9I63X-00A00A	MCP2M00-A00AE30N	NVIDIA Passive Copper cable, ETH, up to 25Gb/s, SFP28, 0.5m, Black, 30AWG, CA-N	EOL [HVM]
N/A	25GE	980-9I63Z-00A01A	MCP2M00-A01AE30N	NVIDIA Passive Copper cable, ETH, up to 25Gb/s, SFP28, 1.5m, Black, 30AWG, CA-N	LTB [HVM]
N/A	25GE	980-9I631-00A02A	MCP2M00-A02AE26N	NVIDIA Passive Copper cable, ETH, up to 25Gb/s, SFP28, 2.5m, Black, 26AWG, CA-N	EOL [HVM]
N/A	25GE	980-9I632-00A02A	MCP2M00-A02AE30L	NVIDIA Passive Copper cable, ETH, up to 25Gb/s, SFP28, 2.5m, Black, 30AWG, CA-L	LTB [HVM]
N/A	25GE	980-9IA1T-00A003	MFA2P10-A003	NVIDIA active optical cable 25GbE, SFP28, 3m	EOL [HVM]
N/A	25GE	980-9I53W-00A005	MFA2P10-A005	NVIDIA active optical cable 25GbE, SFP28, 5m	EOL [HVM]

IB Data Rate	Eth Data Rate	NVIDIA P/N	Legacy OPN	Description	LifeCycle Phase
N/A	25GE	980-9I53Z-00A007	MFA2P10-A007	NVIDIA active optical cable 25GbE, SFP28, 7m	EOL [HVM]
N/A	25GE	980-9I532-00A010	MFA2P10-A010	NVIDIA active optical cable 25GbE, SFP28, 10m	EOL [HVM]
N/A	25GE	980-9I535-00A015	MFA2P10-A015	NVIDIA active optical cable 25GbE, SFP28, 15m	EOL [HVM]
N/A	25GE	980-9I536-00A020	MFA2P10-A020	NVIDIA active optical cable 25GbE, SFP28, 20m	EOL [HVM]
N/A	25GE	980-9I539-00A030	MFA2P10-A030	NVIDIA active optical cable 25GbE, SFP28, 30m	EOL [HVM]
N/A	25GE	980-9I53A-00A050	MFA2P10-A050	NVIDIA active optical cable 25GbE, SFP28, 50m	EOL [HVM]
N/A	25GE	980-9I094-00AR00	MMA2L20-AR	NVIDIA optical transceiver, 25GbE, 25Gb/s, SFP28, LC-LC, 1310nm, LR up to 10km	MP
N/A	25GE	980-9I595-00AM00	MMA2P00-AS	NVIDIA transceiver, 25GbE, SFP28, LC-LC, 850nm, SR	HVM
N/A	25GE	980-9I34B-00AS00	MMA2P00-AS-SP	NVIDIA transceiver, 25GbE, SFP28, LC-LC, 850nm, SR, up to 100m, single package	EOL [HVM]
N/A	25GE	980-9I34D-00AS00	MMA2P00-AS_FF	NVIDIA transceiver, 25GbE, SFP28, LC-LC, 850nm, SR, up to 100m	EOL [HVM]

8.1.12 10GbE Cables

IB Data Rate	Eth Data Rate	NVIDIA P/N	Legacy OPN	Description	LifeCycle Phase
N/A	10GE	980-9I71G-00J000	MAM1Q00A-QSA	NVIDIA cable module, ETH 10GbE, 40Gb/s to 10Gb/s, QSFP to SFP+	HVM
N/A	10GE	980-9I65P-00J005	MC2309124-005	NVIDIA passive copper hybrid cable, ETH 10GbE, 10Gb/s, QSFP to SFP+, 5m	EOL [P-Rel]
N/A	10GE	980-9I65Q-00J007	MC2309124-007	NVIDIA passive copper hybrid cable, ETH 10GbE, 10Gb/s, QSFP to SFP+, 7m	EOL [P-Rel]
N/A	10GE	980-9I65R-00J001	MC2309130-001	NVIDIA passive copper hybrid cable, ETH 10GbE, 10Gb/s, QSFP to SFP+, 1m	EOL [HVM]

IB Data Rate	Eth Data Rate	NVIDIA P/N	Legacy OPN	Description	LifeCycle Phase
N/A	10GE	980-9165S-00J002	MC2309130-002	NVIDIA passive copper hybrid cable, ETH 10GbE, 10Gb/s, QSFP to SFP+, 2m	EOL [HVM]
N/A	10GE	980-9165T-00J003	MC2309130-003	NVIDIA passive copper hybrid cable, ETH 10GbE, 10Gb/s, QSFP to SFP+, 3m	EOL [HVM]
N/A	10GE	980-9165U-00J00A	MC2309130-00A	NVIDIA passive copper hybrid cable, ETH 10GbE, 10Gb/s, QSFP to SFP+, 0.5m	EOL [HVM] [HIBERN/ATE]
N/A	10GE	980-91682-00J004	MC3309124-004	NVIDIA passive copper cable, ETH 10GbE, 10Gb/s, SFP+, 4m	EOL [HVM]
N/A	10GE	980-91683-00J005	MC3309124-005	NVIDIA passive copper cable, ETH 10GbE, 10Gb/s, SFP+, 5m	EOL [HVM]
N/A	10GE	980-91684-00J006	MC3309124-006	NVIDIA passive copper cable, ETH 10GbE, 10Gb/s, SFP+, 6m	EOL [HVM]
N/A	10GE	980-91685-00J007	MC3309124-007	NVIDIA passive copper cable, ETH 10GbE, 10Gb/s, SFP+, 7m	EOL [HVM]
N/A	10GE	980-91686-00J001	MC3309130-001	NVIDIA passive copper cable, ETH 10GbE, 10Gb/s, SFP+, 1m	EOL [HVM]
N/A	10GE	980-91688-00J002	MC3309130-002	NVIDIA passive copper cable, ETH 10GbE, 10Gb/s, SFP+, 2m	EOL [HVM]
N/A	10GE	980-9168B-00J003	MC3309130-003	NVIDIA passive copper cable, ETH 10GbE, 10Gb/s, SFP+, 3m	EOL [HVM]
N/A	10GE	980-9168F-00J00A	MC3309130-00A	NVIDIA passive copper cable, ETH 10GbE, 10Gb/s, SFP+, 0.5m	EOL [HVM]
N/A	10GE	980-9168G-00J001A	MC3309130-00A1	NVIDIA passive copper cable, ETH 10GbE, 10Gb/s, SFP+, 1.5m	EOL [HVM]
N/A	10GE	980-9168H-00J002A	MC3309130-00A2	NVIDIA passive copper cable, ETH 10GbE, 10Gb/s, SFP+, 2.5m	EOL [HVM]
N/A	10GE	980-9168A-00J001	MCP2100-X001B	NVIDIA passive copper cable, ETH 10GbE, 10Gb/s, SFP+, 1m, Blue Pulltab, Connector Label	EOL [HVM] [HIBERN/ATE]

IB Data Rate	Eth Data Rate	NVIDIA P/N	Legacy OPN	Description	LifeCycle Phase
N/A	10GE	980-9168B-00J002	MCP2100-X002B	NVIDIA passive copper cable, ETH 10GbE, 10Gb/s, SFP+, 2m, Blue Pulltab, Connector Label	EOL [HVM] [HIBERN/ATE]
N/A	10GE	980-9168C-00J003	MCP2100-X003B	NVIDIA passive copper cable, ETH 10GbE, 10Gb/s, SFP+, 3m, Blue Pulltab, Connector Label	EOL [HVM]
N/A	10GE	980-9168E-00J001	MCP2104-X001B	NVIDIA passive copper cable, ETH 10GbE, 10Gb/s, SFP+, 1m, Black Pulltab, Connector Label	EOL [HVM] [HIBERN/ATE]
N/A	10GE	980-9168F-00J002	MCP2104-X002B	NVIDIA passive copper cable, ETH 10GbE, 10Gb/s, SFP+, 2m, Black Pulltab, Connector Label	EOL [HVM]
N/A	10GE	980-9168G-00J003	MCP2104-X003B	NVIDIA passive copper cable, ETH 10GbE, 10Gb/s, SFP+, 3m, Black Pulltab, Connector Label	EOL [HVM]
N/A	10GE	980-9168H-00J01A	MCP2104-X01AB	NVIDIA passive copper cable, ETH 10GbE, 10Gb/s, SFP+, 1.5m, Black Pulltab, Connector Label	EOL [HVM]
N/A	10GE	980-9168I-00J02A	MCP2104-X02AB	NVIDIA passive copper cable, ETH 10GbE, 10Gb/s, SFP+, 2.5m, Black Pulltab, Connector Label	EOL [HVM]
N/A	10GE	930-90000-0000-343	MFM1T02A-LR	NVIDIA SFP+ optical module for 10GBASE-LR	HVM
N/A	10GE	MFM1T02A-LR-F	MFM1T02A-LR-F	NVIDIA optical module, ETH 10GbE, 10Gb/s, SFP+, LC-LC, 1310nm, LR up to 10km	HVM
N/A	10GE	930-90000-0000-409	MFM1T02A-SR	NVIDIA SFP+ optical module for 10GBASE-SR	HVM
N/A	10GE	MFM1T02A-SR-F	MFM1T02A-SR-F	NVIDIA optical module, ETH 10GbE, 10Gb/s, SFP+, LC-LC, 850nm, SR up to 300m	HVM
N/A	10GE	MFM1T02A-SR-P	MFM1T02A-SR-P	NVIDIA optical module, ETH 10GbE, 10Gb/s, SFP+, LC-LC, 850nm, SR up to 300m	HVM

8.1.13 1GbE Cables

IB Data Rate	Eth Data Rate	NVIDIA P/N	Legacy OPN	Description	LifeCycle Phase
N/A	1GE	980-9I270-00IM00	MC3208011-SX	NVIDIA Optical module, ETH 1GbE, 1Gb/s, SFP, LC-LC, SX 850nm, up to 500m	EOL [P-Rel]
N/A	1GE	980-9I251-00ISO0	MC3208411-T	NVIDIA module, ETH 1GbE, 1Gb/s, SFP, Base-T, up to 100m	HVM

8.1.14 Supported 3rd Party Cables and Modules

Speed	Cable OPN	Description
10GbE	FTLX8571D3BCL-ME	10gb SFP 850nm Optic Transceiver
10GbE	SP7051-HP	HP-MethodeElec. 10GbE AOM
40GbE	2231254-2	Cisco 3m 40GbE copper
40GbE	AFBR-7QER15Z-CS1	Cisco 40GbE 15m AOC
40GbE	BN-QS-SP-CBL-5M	PASSIVE COPPER SPLITTER CABLE ETH 40GBE TO 4X10GBE 5M
40GbE	NDCCGJ-C402	15m (49ft) Avago AFBR-7QER15Z Compatible 40G QSFP+ Active Optical Cable
40GbE	QSFP-40G-SR-BD	Cisco 40GBASE-SR-BiDi, duplex MMF
100GbE	1AT-3Q4M01XX-12A	O-NET QSFP28 100G Active cable/module
100GbE	AQPMANQ4EDMA0784	QSFP28 100G SMF 500m Transceiver
100GbE	CAB-Q-Q-100G-3M	Passive 3 meter, QSFP+ to QSFP+ QSFP100 TWINAX 103.125Gbps-CR4
100GbE	CAB-Q-Q-100GbE-3M	Passive 3 meter , QSFP+ to QSFP+ QSFP100 TWINAX 103.125Gbps-CR4
100GbE	FCBN425QE1C30-C1	100GbE Quadwire® QSFP28 Active Optical Cable 30M
100GbE	FTLC1151RDPL	TRANSCIEVER 100GBE QSFP LR4
100GbE	FTLC9152RGPL	100G 100M QSFP28 SWDM4 OPT TRANS
100GbE	FTLC9555REPM3-E6	100m Parallel MMF 100QSFP28Optical Transceiver
100GbE	NDAAFJ-C102	SF-NDAAFJ100G-005M
100GbE	QSFP-100G-AOC30M	30m (98ft) Cisco QSFP-100G-AOC30M Compatible 100G QSFP28 Active Optical Cable
100GbE	QSFP28-LR4-AJ	CISCO-PRE 100GbE LR4 QSFP28 Transceiver Module
100GbE	SFBR-89BDDZ-CS2	CISCO-PRE 100G AOM BiDi
100GbE	SQF1002L4LNC101P	Cisco-SUMITOMO 100GbE AOM

8.2 Tested Switches

8.2.1 HDR / 200Gb/s Switches

Speed	Switch Silicon	OPN # / Name	Description	Vendor
HDR	Quantum	MQM8700-xxx	40-port Managed Non-blocking HDR 200Gb/s InfiniBand Smart Switch	NVIDIA
HDR	Quantum	MQM8790-xxx	40-port Unmanaged, Non-blocking HDR 200Gb/s InfiniBand Smart Switch	NVIDIA

8.2.2 EDR / 100Gb/s Switches

Speed	Switch Silicon	OPN # / Name	Description	Vendor
EDR	Switch-IB	MSB7790-XXX	36-port Unmanaged EDR 100Gb/s InfiniBand Switch Systems	NVIDIA
EDR	Switch-IB	MSB7700-XXX	36-port Managed EDR 100Gb/s InfiniBand Switch Systems	NVIDIA
EDR	Switch-IB 2	MSB7800-XXX	36-port Managed EDR 100Gb/s InfiniBand Switch Systems	NVIDIA

8.2.3 200GbE Switches

Speed	Switch Silicon	OPN # / Name	Description	Vendor
200GbE	Spectrum-3	MSN4600V-XXXX	64 QSFP56 ports, 200GbE 2U Open Ethernet Switch with Onyx	NVIDIA
200GbE	Spectrum-2	MSN3700-XXXX	32 QSFP56 ports, 200GbE Open Ethernet Switch System	NVIDIA

8.2.4 100GbE Switches

Speed	Switch Silicon	OPN # / Name	Description	Vendor
100GbE	Spectrum-3	MSN4600-XXXX	64-port Non-blocking 100GbE Open Ethernet Switch System	NVIDIA
100GbE	Spectrum-2	MSN3700C-XXXX	32-port Non-blocking 100GbE Open Ethernet Switch System	NVIDIA
100GbE	Spectrum-2	MSN3420-XXXX	48 SFP + 12 QSFP ports Non-blocking 100GbE Open Ethernet Switch System	NVIDIA

Speed	Switch Silicon	OPN # / Name	Description	Vendor
100GbE	Spectrum	MSN2410-XXXX	48-port 25GbE + 8-port 100GbE Open Ethernet Switch System	NVIDIA
100GbE	Spectrum	MSN2700-XXXX	32-port Non-blocking 100GbE Open Ethernet Switch System	NVIDIA
100GbE	N/A	QFX5200-32C-32	32-port 100GbE Ethernet Switch System	Juniper
100GbE	N/A	S6820-56HF	48 SFP+ + 8 QSFP Ports 100GbE Switch Ethernet	H3C
100GbE	N/A	CE6860-1-48S8CQ-EI	Huawei 100GbE Ethernet switch	Huawei
100GbE	N/A	7060CX-32S	32-port 100GbE Ethernet Switch System	Arista
100GbE	N/A	3232C	32-port 100GbE Ethernet Switch System	Cisco
100GbE	N/A	N9K-C9236C	36-port 100GbE Ethernet Switch System	Cisco
100GbE	N/A	93180YC-EX	48-port 25GbE + 6-port 100GbE Ethernet Switch System	Cisco
100GbE	N/A	T7032-IX7	32-port 100GbE Ethernet Switch System	Quanta

8.2.5 10/40GbE Switches

Speed	Switch Silicon	OPN # / Name	Description	Vendor
10GbE	N/A	5548UP	32x 10GbE SFP+ Switch System	Cisco
10/40GbE	N/A	7050Q	16 x 40GbE QSFP+ Switch System	Arista
10/40GbE	N/A	7050S	48x 10GbE SFP+ and 4 x 40GbE QSFP+ Switch System	Arista
10/40GbE	N/A	G8264	48x 10GbE SFP+ and 4 x 40GbE QSFP+ Switch System	Lenovo
10/40GbE	N/A	QFX3500	48x 10GbE SFP+ and 4 x 40GbE QSFP+ Switch System	Juniper
10/40GbE	N/A	S4810P-AC	48x 10GbE SFP+ and 4 x 40GbE QSFP+ Switch System	Force10
10/40GbE	N/A	3064	48x 10GbE SFP+ and 4 x 40GbE QSFP+ Switch System	Cisco
10/40GbE	N/A	8164F	48x 10GbE SFP+ and 2 x 40GbE QSFP+ Switch System	Dell
10/40GbE	N/A	S5000	48x 10GbE SFP+ and 4 x 40GbE QSFP+ Switch System	Dell
10/40GbE	N/A	3132Q	4x 10GbE SFP+ and 32 x 40GbE QSFP+ Switch System	Cisco
40GbE	N/A	7050QX	32x 40GbE QSFP+ Switch System	Arista

Speed	Switch Silicon	OPN # / Name	Description	Vendor
40GbE	N/A	G8316	16x 40GbE QSFP+ Switch System	Lenovo
40GbE	N/A	S6000	32x 40GbE QSFP+ Switch System	Dell

8.3 PRM Revision Compatibility

This firmware version complies with the following Programmer's Reference Manual:

- Adapters Programmer's Reference Manual (PRM), Rev 0.53 or later, which has Command Interface Revision 0x5. The command interface revision can be retrieved by means of the QUERY_FW command and is indicated by the field cmd_interface_rev.

9 Supported Non-Volatile Configurations


Configuration	mlxconfig Parameter Name	Class	TLV ID
NV_MEMIC_CONF	MEMIC_BAR_SIZE	GLOBAL (0)	0x6
	MEMIC_SIZE_LIMIT		
NV_HOST_CHAINING_CONF	HOST_CHAINING_MODE		0x8
	HOST_CHAINING_DESCRIPTOR		
	HOST_CHAINING_TOTAL_BUFFER_SIZE		
NV_FLEX_PARS_CONF	FLEX_PARSER_PROFILE_ENABLE		0xe
	FLEX_IPV4_OVER_VXLAN_PORT		
NV_ROCE_1_5_CONF	ROCE_NEXT_PROTOCOL		0x10
NV_INTERNAL_RESOURCE_CONF	ESWITCH_HAIRPIN_DESCRIPTOR		0x13
	ESWITCH_HAIRPIN_TOT_BUFFER_SIZE		
NV_GLOBAL_PCI_CONF	NON_PREFETCHABLE_PF_BAR	0x80	
	NUM_OF_VFS		
	SRIOV_EN		
	PF_LOG_BAR_SIZE		
	VF_LOG_BAR_SIZE		
	NUM_PF_MSIX		
	NUM_VF_MSIX		
NV_TPT_CONF	INT_LOG_MAX_PAYLOAD_SIZE	0x82	
NV_POWER_CONF	SW_RECOVERY_ON_ERRORS	0x88	
	RESET_WITH_HOST_ON_ERRORS		
	ADVANCED_POWER_SETTINGS		
NV_GLOBAL_MASK	ece_disable_mask	0x116	
NV_SW_OFFLOAD_CONFIG	CQE_COMPRESSION	0x10a	
	IP_OVER_VXLAN_EN		
	PCI_ATOMIC_MODE		
	LRO_LOG_TIMEOUT0		
	LRO_LOG_TIMEOUT1		
	LRO_LOG_TIMEOUT2		
	LRO_LOG_TIMEOUT3		
	log_max_outstandng_wqe		
	NV_config.sr_enable (ConnectX-6 Dx and above)		
NV_IB_DC_CONF	LOG_DCR_HASH_TABLE_SIZE	0x190	

Configuration	mlxconfig Parameter Name	Class	TLV ID
	DCR_LIFO_SIZE		
NV_VPI_LINK_TYPE	LINK_TYPE	PHYSICAL_PORT (2)	0x12
NV_ROCE_CC	ROCE_CC_PRIO_MASK		0x107
	ROCE_CC_ALGORITHM		
NV_ROCE_CC_ECN	CLAMP_TGT_RATE_AFTER_TIME_INC		0x108
	CLAMP_TGT_RATE		
	RPG_TIME_RESET		
	RPG_BYTE_RESET		
	RPG_THRESHOLD		
	RPG_MAX_RATE		
	RPG_AI_RATE		
	RPG_HAI_RATE		
	RPG_GD		
	RPG_MIN_DEC_FAC		
	RPG_MIN_RATE		
	RATE_TO_SET_ON_FIRST_CNP		
	DCE_TCP_G		
	DCE_TCP_RTT		
	RATE_REDUCE_MONITOR_PERIOD		
INITIAL_ALPHA_VALUE			
MIN_TIME_BETWEEN_CNPS			
CNP_802P_PRIO			
CNP_DSCP			
NV_LLDP_NB_CONF	LLDP_NB_DCBX	0x10a	
	LLDP_NB_RX_MODE		
	LLDP_NB_TX_MODE		
NV_LLDP_NB_DCBX	DCBX_IEEE	0x18e	
	DCBX_CEE		
	DCBX_WILLING		
NV_KEEP_LINK_UP	KEEP_ETH_LINK_UP	0x190	
	KEEP_IB_LINK_UP		
	KEEP_LINK_UP_ON_BOOT		
	KEEP_LINK_UP_ON_STANDBY		
NV_QOS_CONF	NUM_OF_VL	0x192	

Configuration	mlxconfig Parameter Name	Class	TLV ID
	NUM_OF_TC		
	NUM_OF_PFC		
NV_MPFS_CONF	DUP_MAC_ACTION		0x196
	SRIOV_IB_ROUTING_MODE		
	IB_ROUTING_MODE		
NV_HCA_CONF	PCI_WR_ORDERING	HOST-FUNCTION (3)	0x112
	MULTI_PORT_VHCA_EN		
NV_EXTERNAL_PORT_CTRL	PORT_OWNER		0x192
	ALLOW_RD_COUNTERS		
	RENEG_ON_CHANGE		
	TRACER_ENABLE		
NV_ROM_BOOT_CONF2	IP_VER		0x195
	BOOT_UNDI_NETWORK_WAIT		
NV_ROM_UEFI_CONF	UEFI_HII_EN		0x196
NV_ROM_UEFI_DEBUG_LEVEL	BOOT_DBG_LOG		0x206
	UEFI_LOGS		
NV_ROM_BOOT_CONF1	BOOT_VLAN		0x221
	LEGACY_BOOT_PROTOCOL		
	BOOT_RETRY_CNT		
	BOOT_LACP_DIS		
	BOOT_VLAN_EN		
NV_ROM_IB_BOOT_CONF	BOOT_PKEY		0x222
NV_PCI_CONF	ADVANCED_PCI_SETTINGS	HOST (7)	0x80
SAFE_MODE_CONF	SAFE_MODE_THRESHOLD		0x82
	SAFE_MODE_ENABLE		

10 Release Notes History

10.1 Changes and New Feature History

 This section includes history of changes and new feature of 3 major releases back. For older releases history, please refer to the relevant firmware versions.

Feature/Change	Description
20.39.1002	
MCTP over PCIe	Enabled Management Component Transport Protocol (MCTP) over PCIe.
Expansion ROM	Added a caching mechanism to improved expansion ROM performance and to avoid any slow boot occurrences when loading the expansion ROM driver.
Reserved mkey	Added new support for reserved mkey index range. When enabled, a range of mkey indexes is reserved for mkey by name use.
Bug Fixes	See <i>Bug Fixes in this Firmware Version</i> section.


Feature/Change	Description
20.38.1900	
QKEY Mitigation in the Kernel	<p>QKEY creation with the MSB set is available now for non-privileged users as well.</p> <p>To allow non-privileged users to create QKEY with MSB set, the below new module parameter was added to <code>ib_uverbs</code> module:</p> <ul style="list-style-type: none">• Module Parameter: <code>enforce_qkey_check</code>• Description: Force QKEY MSB check for non-privileged user on UD QP creation• Default: 0 (disabled) <p>Note: In this release, this module parameter is disabled by default to ensure backward compatibility and give customers the opportunity to update their applications accordingly. In the upcoming release, it will be enabled by default, and later on deprecated.</p>

Feature/Change	Description
20.38.1002	
INT Packets	Added support for forwarding INT packets to the user application for monitoring purposes by matching the BTH acknowledge request bit (<code>bth_a</code>).
QKEY Mitigation in the Kernel	Non-privileged users are now blocked by default from setting controlled/privileged QKEYs (QKEY with MSB set).
Bug Fixes	See <i>Bug Fixes in this Firmware Version</i> section.

Feature/Change	Description
20.37.1014	
Monitoring Cloud Guest RoCE Statistics on Cloud Provider	This new capability enables the VM to track and limit its Vport's activity. This is done using the new q_counters counter which enables aggregation of other Vport's from PF GVMI.
Bug Fixes	See Bug Fixes in this Firmware Version section.

Feature/Change	Description
20.36.1010	
NVconfig	Enabled provisioning of the OEM public key that is used for OEM NVconfig file signature verification.
Bug Fixes	See Bug Fixes in this Firmware Version section.

10.2 Bug Fixes History

 This section includes history of bug fixes of 3 major releases back. For older releases history, please refer to the relevant firmware versions Release Notes in <https://docs.mellanox.com/category/adapterfw>.

Internal Ref.	Issue
3605363	Description: Get Temperature OEM command now always returns a unified temperature.
	Keywords: Temperature
	Discovered in Version: 20.38.1002
	Fixed in Release: 20.39.1002

Internal Ref.	Issue
3365411	Description: Fixed a link failure that occurred due to a wrong 'is_inphi_cable' indication.
	Keywords: Link failure
	Discovered in Version: 20.37.1014
	Fixed in Release: 20.38.1002
3331179	Description: Improved token calculation.
	Keywords: Token calculation
	Discovered in Version: 20.37.1014
	Fixed in Release: 20.38.1002

Internal Ref.	Issue
3491841	Description: Fixed a firmware assert that occurred when tried to verify if the module supported "swap".
	Keywords: Firmware assert
	Discovered in Version: 20.37.1014
	Fixed in Release: 20.38.1002

Internal Ref.	Issue
3233061	Description: Updated the link maintenance flow to avoid high uncorrectable error rate.
	Keywords: Error rate
	Discovered in Version: 20.31.2354
	Fixed in Release: 20.37.1014

Internal Ref.	Issue
3239340	Description: Aligned RDE behavior to DSP0266 v1.15.0 table 23.
	Keywords: PTP, PPS offset
	Discovered in Version: 20.35.1012
	Fixed in Release: 20.36.1010
3225504	Description: Enabled constant clock offset (visible using PPS out) when synchronizing the device using PTP in 25G or 10G port link speed.
	Keywords: PTP, PPS offset
	Discovered in Version: 20.35.1012
	Fixed in Release: 20.36.1010

11 Legal Notices and 3rd Party Licenses

The following are the drivers' software, tools and HCA firmware legal notices and 3rd party licenses.

Product	Version	Legal Notices and 3rd Party Licenses
Firmware	xx.39.2048	<ul style="list-style-type: none">• HCA Firmware EULA• 3rd Party Notice
MLNX_OFED	23.10-1.1.9.0	<ul style="list-style-type: none">• License• 3rd Part Notice
MFT FreeBSD	4.26.1	<ul style="list-style-type: none">• 3rd Party Notice• License
MFT Linux		<ul style="list-style-type: none">• 3rd Party Notice• License
MFT VMware		<ul style="list-style-type: none">• 3rd Party Notice• License
MFT Windows		<ul style="list-style-type: none">• 3rd Party Notice• License
msflint	4.26.1	<ul style="list-style-type: none">• 3rd Party Notice• License

Notice

This document is provided for information purposes only and shall not be regarded as a warranty of a certain functionality, condition, or quality of a product. Neither NVIDIA Corporation nor any of its direct or indirect subsidiaries and affiliates (collectively: "NVIDIA") make any representations or warranties, expressed or implied, as to the accuracy or completeness of the information contained in this document and assumes no responsibility for any errors contained herein. NVIDIA shall have no liability for the consequences or use of such information or for any infringement of patents or other rights of third parties that may result from its use. This document is not a commitment to develop, release, or deliver any Material (defined below), code, or functionality.

NVIDIA reserves the right to make corrections, modifications, enhancements, improvements, and any other changes to this document, at any time without notice.

Customer should obtain the latest relevant information before placing orders and should verify that such information is current and complete.

NVIDIA products are sold subject to the NVIDIA standard terms and conditions of sale supplied at the time of order acknowledgement, unless otherwise agreed in an individual sales agreement signed by authorized representatives of NVIDIA and customer ("Terms of Sale"). NVIDIA hereby expressly objects to applying any customer general terms and conditions with regards to the purchase of the NVIDIA product referenced in this document. No contractual obligations are formed either directly or indirectly by this document.

NVIDIA products are not designed, authorized, or warranted to be suitable for use in medical, military, aircraft, space, or life support equipment, nor in applications where failure or malfunction of the NVIDIA product can reasonably be expected to result in personal injury, death, or property or environmental damage. NVIDIA accepts no liability for inclusion and/or use of NVIDIA products in such equipment or applications and therefore such inclusion and/or use is at customer's own risk.

NVIDIA makes no representation or warranty that products based on this document will be suitable for any specified use. Testing of all parameters of each product is not necessarily performed by NVIDIA. It is customer's sole responsibility to evaluate and determine the applicability of any information contained in this document, ensure the product is suitable and fit for the application planned by customer, and perform the necessary testing for the application in order to avoid a default of the application or the product. Weaknesses in customer's product designs may affect the quality and reliability of the NVIDIA product and may result in additional or different conditions and/or requirements beyond those contained in this document. NVIDIA accepts no liability related to any default, damage, costs, or problem which may be based on or attributable to: (i) the use of the NVIDIA product in any manner that is contrary to this document or (ii) customer product designs.

No license, either expressed or implied, is granted under any NVIDIA patent right, copyright, or other NVIDIA intellectual property right under this document. Information published by NVIDIA regarding third-party products or services does not constitute a license from NVIDIA to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property rights of the third party, or a license from NVIDIA under the patents or other intellectual property rights of NVIDIA.

Reproduction of information in this document is permissible only if approved in advance by NVIDIA in writing, reproduced without alteration and in full compliance with all applicable export laws and regulations, and accompanied by all associated conditions, limitations, and notices.

THIS DOCUMENT AND ALL NVIDIA DESIGN SPECIFICATIONS, REFERENCE BOARDS, FILES, DRAWINGS, DIAGNOSTICS, LISTS, AND OTHER DOCUMENTS (TOGETHER AND SEPARATELY, "MATERIALS") ARE BEING PROVIDED "AS IS." NVIDIA MAKES NO WARRANTIES, EXPRESSED, IMPLIED, STATUTORY, OR OTHERWISE WITH RESPECT TO THE MATERIALS, AND EXPRESSLY DISCLAIMS ALL IMPLIED WARRANTIES OF NONINFRINGEMENT, MERCHANTABILITY, AND FITNESS FOR A PARTICULAR PURPOSE. TO THE EXTENT NOT PROHIBITED BY LAW, IN NO EVENT WILL NVIDIA BE LIABLE FOR ANY DAMAGES, INCLUDING WITHOUT LIMITATION ANY DIRECT, INDIRECT, SPECIAL, INCIDENTAL, PUNITIVE, OR CONSEQUENTIAL DAMAGES, HOWEVER CAUSED AND REGARDLESS OF THE THEORY OF LIABILITY, ARISING OUT OF ANY USE OF THIS DOCUMENT, EVEN IF NVIDIA HAS BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES. Notwithstanding any damages that customer might incur for any reason



whatsoever, NVIDIA's aggregate and cumulative liability towards customer for the products described herein shall be limited in accordance with the Terms of Sale for the product.

Trademarks

NVIDIA, the NVIDIA logo, and Mellanox are trademarks and/or registered trademarks of NVIDIA Corporation and/or Mellanox Technologies Ltd. in the U.S. and in other countries. Other company and product names may be trademarks of the respective companies with which they are associated.

Copyright

© 2023 NVIDIA Corporation & affiliates. All Rights Reserved.

