



NVIDIA DOCA Telemetry Service

Guide

Table of Contents

Chapter 1. Introduction.....	1
Chapter 2. Service Deployment.....	2
2.1. DOCA Service on NGC.....	2
2.2. Default Deployment – BlueField BSP.....	2
Chapter 3. Configuration.....	3
3.1. Init Scripts.....	3
3.2. Enabling Fluent Bit Forwarding.....	3
3.3. Generating Configuration.....	3
3.4. Resetting Configuration.....	4
3.5. Enabling Providers.....	4
3.6. Enabling Data Write.....	4
Chapter 4. Description.....	5
4.1. Providers.....	5
4.1.1. Sysfs Counters List.....	5
4.1.2. Ethtool Counters.....	7
4.1.3. Traffic Control Info.....	7
4.1.4. Fluent Aggregator.....	8
4.1.5. Prometheus Aggregator.....	8
4.2. Data Outputs.....	8
4.2.1. Data Writer.....	8
4.2.2. Prometheus.....	9
4.2.3. Configuration Details.....	9
4.2.4. Prometheus Aggregator Exporter.....	10
4.2.5. Fluent Bit.....	10
4.2.5.1. Export File Configuration Details.....	11
4.2.5.2. Msgpack Data Layout.....	11
4.2.5.3. Cset/Fset Filtering.....	12
4.2.6. NetFlow Exporter.....	13
Chapter 5. DOCA Privileged Executer.....	14
5.1. DPE Usage.....	14
5.2. DPE Configuration File.....	14
Chapter 6. Troubleshooting.....	16

Chapter 1. Introduction

DOCA Telemetry Service (DTS) collects data from built-in providers and from external telemetry applications. The following providers are available:

- ▶ Data providers:
 - ▶ sysfs
 - ▶ ethtool
 - ▶ tc (traffic control)
- ▶ Aggregation providers
 - ▶ fluent_aggr
 - ▶ prometheus_aggr



Note: Sysfs provider is enabled by default.

DTS stores collected data into binary files under the `/opt/mellanox/doca/services/telemetry/data` directory. Data write is disabled by default due to BlueField storage restrictions.

DTS can export the data via Prometheus Endpoint (pull) or Fluent Bit (push).

DTS allows exporting NetFlow packets when data is collected from the DOCA Telemetry NetFlow API client application. NetFlow exporter is enabled from `dto_config.ini` by setting NetFlow collector IP/address and port.

Chapter 2. Service Deployment

For more information about the deployment of DOCA containers on top of the BlueField DPU, refer to [NVIDIA DOCA Container Deployment Guide](#).

2.1. DOCA Service on NGC

DTS is available on NGC, NVIDIA's container catalog. Service-specific configuration steps and deployment instructions can be found under the service's [container page](#).

2.2. Default Deployment – BlueField BSP

DTS service starts automatically on BlueField boot according to the `.yaml` file located at `/etc/kubelet.d/doca_telemetry_standalone.yaml`. Removing the `.yaml` file from this path stops the automatic DTS boot.

DTS files can be found under the directory `/opt/mellanox/doca/services/telemetry/`.

- ▶ Container folder mounts:
 - ▶ `config`
 - ▶ `data`
 - ▶ `ipc_sockets`
- ▶ Backup files:
 - ▶ `doca_telemetry_service_${version}_arm64.tar.gz` – DTS image
 - ▶ `doca_telemetry_standalone.yaml` – copy of the default boot `.yaml` file

Chapter 3. Configuration

The configuration of DTS is placed under `/opt/mellanox/doca/services/telemetry/config` by DTS during initialization. The user can interact with the `dto_config.ini` file and `fluent_bit_configs` folder. `dto_config.ini` contains the main configuration for the service and must be used to enable/disable providers, exporters, data writing. More details are provided in the corresponding sections. For every update in this file, DST must be restarted. Interaction with `fluent_bit_configs` folder is described in section [Fluent Bit](#).

3.1. Init Scripts

The `InitContainers` section of the `.yaml` file has 2 scripts for config initialization:

- ▶ `/usr/bin/telemetry-init.sh` – generates the default configuration files if, and only if, the `/opt/mellanox/doca/services/telemetry/config` folder is empty.
- ▶ `/usr/bin/enable-fluent-forward.sh` – configures the destination host and port for Fluent Bit forwarding. The script requires that both the host and port are present, and only in this case it would start. The script overwrites the `/opt/mellanox/doca/services/telemetry/config/fluent_bit_configs` folder and configures the `forward.exp` file.

3.2. Enabling Fluent Bit Forwarding

To enable Fluent Bit forward, add the destination host and port to the command line found in the `initContainers` section of the `.yaml` file:

```
command: ["/bin/bash", "-c", "/usr/bin/telemetry-init.sh && /usr/bin/enable-fluent-forward.sh -i=127.0.0.1 -p=24224"]
```



Note: The host and port shown above are just an example. See section [Fluent Bit](#) to learn about manual configuration.

3.3. Generating Configuration

The configuration folder `/opt/mellanox/doca/services/telemetry/config` starts empty by default. Once the service starts, the initial scripts run as a part of the initial container and create configuration as described in section [Enabling Fluent Bit Forwarding](#).

3.4. Resetting Configuration

Resetting the configuration can be done by deleting the content found in the configuration folder and restarting the service to generate the default configuration.

3.5. Enabling Providers

Providers are enabled from the `dts_config.ini` configuration file. Uncomment the `enable-provider=$provider-name` line to allow data collection for this provider. For example, uncommenting the following line enables the `ethtool` provider:

```
#enable-provider=ethtool
```



Note: More information about telemetry providers can be found under the [Providers](#) section.

3.6. Enabling Data Write

Uncomment the following line in `dts_config.ini`:

```
#output=/data
```



Note: Changes in `dts_config.ini` force the main DTS process to restart in 60 seconds to apply the new settings.

Chapter 4. Description

4.1. Providers

DTS supports on-board data collection from sysfs, ethtool, and tc providers.

Fluent and Prometheus aggregator providers can collect the data from other applications.

4.1.1. Sysfs Counters List

The sysfs provider has several components: `ib_port`, `hw_port`, `mr_cache`, `eth`, and `hwmon`. By default, all the components are enabled when the provider is enabled:

```
#disable-provider=sysfs
```

The components can be disabled separately. For instance, to disable `eth`:

```
enable-provider=sysfs
disable-provider=sysfs.eth
```



Note: `ib_port` and `ib_hvw` are state counters which are collected per port. These counters are only collected for ports whose state is active.

► `ib_port` counters:

```
{hca_name}:{port_num}:ib_port_state
{hca_name}:{port_num}:VLI5_dropped
{hca_name}:{port_num}:excessive_buffer_overrun_errors
{hca_name}:{port_num}:link_downed
{hca_name}:{port_num}:link_error_recovery
{hca_name}:{port_num}:local_link_integrity_errors
{hca_name}:{port_num}:multicast_rcv_packets
{hca_name}:{port_num}:multicast_xmit_packets
{hca_name}:{port_num}:port_rcv_constraint_errors
{hca_name}:{port_num}:port_rcv_data
{hca_name}:{port_num}:port_rcv_errors
{hca_name}:{port_num}:port_rcv_packets
{hca_name}:{port_num}:port_rcv_remote_physical_errors
{hca_name}:{port_num}:port_rcv_switch_relay_errors
{hca_name}:{port_num}:port_xmit_constraint_errors
{hca_name}:{port_num}:port_xmit_data
{hca_name}:{port_num}:port_xmit_discards
{hca_name}:{port_num}:port_xmit_packets
{hca_name}:{port_num}:port_xmit_wait
{hca_name}:{port_num}:symbol_error
{hca_name}:{port_num}:unicast_rcv_packets
{hca_name}:{port_num}:unicast_xmit_packets
```

► **ib_hw counters:**

```
{hca_name}:{port_num}:hw_state
{hca_name}:{port_num}:hw_duplicate_request
{hca_name}:{port_num}:hw_implied_nak_seq_err
{hca_name}:{port_num}:hw_lifespan
{hca_name}:{port_num}:hw_local_ack_timeout_err
{hca_name}:{port_num}:hw_out_of_buffer
{hca_name}:{port_num}:hw_out_of_sequence
{hca_name}:{port_num}:hw_packet_seq_err
{hca_name}:{port_num}:hw_req_cqe_error
{hca_name}:{port_num}:hw_req_cqe_flush_error
{hca_name}:{port_num}:hw_req_remote_access_errors
{hca_name}:{port_num}:hw_req_remote_invalid_request
{hca_name}:{port_num}:hw_resp_cqe_error
{hca_name}:{port_num}:hw_resp_cqe_flush_error
{hca_name}:{port_num}:hw_resp_local_length_error
{hca_name}:{port_num}:hw_resp_remote_access_errors
{hca_name}:{port_num}:hw_rnr_nak_retry_err
{hca_name}:{port_num}:hw_rx_atomic_requests
{hca_name}:{port_num}:hw_rx_dct_connect
{hca_name}:{port_num}:hw_rx_icrc_encapsulated
{hca_name}:{port_num}:hw_rx_read_requests
{hca_name}:{port_num}:hw_rx_write_requests
```

► **ib_mr_cache counters:**



Note: n ranges from 0 to 24.

```
{hca_name}:mr_cache:size_{n}:cur
{hca_name}:mr_cache:size_{n}:limit
{hca_name}:mr_cache:size_{n}:miss
mlx5_0:mr_cache:size_{n}:size
```

► **eth counters:**

```
{hca_name}:{device_name}:eth_collisions
{hca_name}:{device_name}:eth_multicast
{hca_name}:{device_name}:eth_rx_bytes
{hca_name}:{device_name}:eth_rx_compressed
{hca_name}:{device_name}:eth_rx_crc_errors
{hca_name}:{device_name}:eth_rx_dropped
{hca_name}:{device_name}:eth_rx_errors
{hca_name}:{device_name}:eth_rx_fifo_errors
{hca_name}:{device_name}:eth_rx_frame_errors
{hca_name}:{device_name}:eth_rx_length_errors
{hca_name}:{device_name}:eth_rx_missed_errors
{hca_name}:{device_name}:eth_rx_nohandler
{hca_name}:{device_name}:eth_rx_over_errors
{hca_name}:{device_name}:eth_rx_packets
{hca_name}:{device_name}:eth_tx_aborted_errors
{hca_name}:{device_name}:eth_tx_bytes
{hca_name}:{device_name}:eth_tx_carrier_errors
{hca_name}:{device_name}:eth_tx_compressed
{hca_name}:{device_name}:eth_tx_dropped
{hca_name}:{device_name}:eth_tx_errors
{hca_name}:{device_name}:eth_tx_fifo_errors
{hca_name}:{device_name}:eth_tx_heartbeat_errors
{hca_name}:{device_name}:eth_tx_packets
{hca_name}:{device_name}:eth_tx_window_errors
```

► **hwmon counters:**

```
{hwmon_name}:{l3cache}:CYCLES
{hwmon_name}:{l3cache}:HITS_BANK0
{hwmon_name}:{l3cache}:HITS_BANK1
{hwmon_name}:{l3cache}:MISSES_BANK0
{hwmon_name}:{l3cache}:MISSES_BANK1
{hwmon_name}:{pcie}:IN_C_BYTE_CNT
```



```

{hwmon_name}:{pcie}:IN_C_PKT_CNT
{hwmon_name}:{pcie}:IN_NP_BYTE_CNT
{hwmon_name}:{pcie}:IN_NP_PKT_CNT
{hwmon_name}:{pcie}:IN_P_BYTE_CNT
{hwmon_name}:{pcie}:IN_P_PKT_CNT
{hwmon_name}:{pcie}:OUT_C_BYTE_CNT
{hwmon_name}:{pcie}:OUT_C_PKT_CNT
{hwmon_name}:{pcie}:OUT_NP_BYTE_CNT
{hwmon_name}:{pcie}:OUT_NP_PKT_CNT
{hwmon_name}:{pcie}:OUT_P_PKT_CNT
{hwmon_name}:{tile}:MEMORY_READS
{hwmon_name}:{tile}:MEMORY_WRITES
{hwmon_name}:{tile}:MSS_NO_CREDIT
{hwmon_name}:{tile}:VICTIM_WRITE
{hwmon_name}:{tilenet}:CDN_DIAG_C_OUT_OF_CRED
{hwmon_name}:{tilenet}:CDN_REQ
{hwmon_name}:{tilenet}:DDN_REQ
{hwmon_name}:{tilenet}:NDN_REQ
{hwmon_name}:{trio}:TDMA_DATA_BEAT
{hwmon_name}:{trio}:TDMA_PBUF_MAC_AF
{hwmon_name}:{trio}:TDMA_RT_AF
{hwmon_name}:{trio}:TPIO_DATA_BEAT
{hwmon_name}:{triogen}:TX_DAT_AF
{hwmon_name}:{triogen}:TX_DAT_AF

```

4.1.2. Ethtool Counters

Ethtool counters is the generated list of counters which corresponds to [Ethtool utility](#). Counters are generated on a per-device basis. See [this community post](#) for more information on mlx5 ethtool counters.

4.1.3. Traffic Control Info

The following TC objects are supported and reported regarding the ingress filters:

- ▶ Filters
 - ▶ [flower](#)
- ▶ Actions
 - ▶ [mirred](#)
 - ▶ [tunnel_key](#)

The info is provided as one of the following events:

- ▶ Basic filter event
- ▶ flower/ipv4 filter event
- ▶ flower/ipv6 filter event
- ▶ Basic action event
- ▶ mirred action event
- ▶ tunnel_key/ipv4 action event
- ▶ tunnel_key/ipv6 action event

General notes:

- ▶ Actions always belong to a filter, so action events share the filter event's ID via the `event_id` data member
- ▶ Basic filter event only contains textual *kind* (so users can see which real life objects' support they are lacking)
- ▶ Basic action event only contains textual *kind* and some basic common statistics if available

4.1.4. Fluent Aggregator

`fluent_aggr` listens on a port for [Fluent Bit Forward protocol](#) input connections. Received data can be streamed via a [Fluent Bit](#) exporter.

The default port is 42442. This can be changed by updating the following option:

```
fluent-aggr-port=42442
```

4.1.5. Prometheus Aggregator

`prometheus_aggr` polls data from a list of Prometheus endpoints.

Each endpoint is listed in the following format:

```
prometheus_aggr_endpoint.{N}={host_name},{host_port_url},{poll_interval_msec}
```

Where N starts from 0.

Aggregated data can be exported via a [Prometheus aggregator exporter](#) endpoint.

4.2. Data Outputs

DTS can send the collected data to the following outputs:

- ▶ Data writer (saves binary data to disk)
- ▶ Fluent Bit (push-model streaming)
- ▶ Prometheus endpoint (keeps the most recent data to be pulled).

4.2.1. Data Writer

The data writer is disabled by default to save space on BlueField. Steps for activating data write during debug can be found under section [Enabling Data Write](#).

The schema folder contains JSON-formatted metadata files which allow reading the binary files containing the actual data. The binary files are written according to the naming convention shown in the following example (`apt install tree`):

```
tree /opt/mellanox/doca/services/telemetry/data/
/opt/mellanox/doca/services/telemetry/data/
├── {year}
│   └── {mmd}
│       └── {hash}
│           ├── {source_id}
│           │   └── {source_tag}{timestamp}.bin
│           └── {another_source_id}
│               └── {another_source_tag}{timestamp}.bin
└── schema
    └── schema_{MD5_digest}.json
```

New binary files appear when the service starts or when binary file age/size restriction is reached. If no schema or no data folders are present, refer to the [Troubleshooting](#) section.



Note: `source_id` is usually set to the machine hostname. `source_tag` is a line describing the collected counters, and it is often set as the provider's name or name of user-counters.

Reading the binary data can be done from within the DTS container using the following command:

```
crictl exec -it <Container ID> /opt/mellanox/collectx/bin/clx_read -s /data/schema /data/path/to/datafile.bin
```



Note: The path to the data file must be an absolute path.

Example output:

```
{
  "timestamp": 1634815738799728,
  "event_number": 0,
  "iter_num": 0,
  "string_number": 0,
  "example_string": "example_str_1"
}
{
  "timestamp": 1634815738799768,
  "event_number": 1,
  "iter_num": 0,
  "string_number": 1,
  "example_string": "example_str_2"
}
...
```

4.2.2. Prometheus

The Prometheus endpoint keeps the most recent data to be pulled by the Prometheus server and is enabled by default.

To check that data is available, run the following command on BlueField:

```
curl -s http://0.0.0.0:9100/metrics
```

The command dumps every counter in the following format:

```
counter_name {list of label fields} counter_value timestamp
```



Note: The default port for Prometheus can be changed in `dts_config.ini`.

4.2.3. Configuration Details

Prometheus is configured as a part of `dts_config.ini`.

By default, the Prometheus HTTP endpoint is set to port 9100. Comment this line out to disable Prometheus export.

```
prometheus=http://0.0.0.0:9100
```

Prometheus can use the data field as an index to keep several data records with different index values. Index fields are added to Prometheus labels.

```
# Comma-separated counter set description for Prometheus indexing:
#prometheus-indexes=idx1,idx2
```

```
# Comma-separated fieldset description for prometheus indexing
#prometheus-fset-indexes=idx1,idx2
```

The default `fset` index is `device_name`. It allows Prometheus to keep ethtool data up for both the `p0` and `p1` devices.

```
prometheus-fset-indexes=device_name
```

If the `fset` index is not set, the data from `p1` overwrites `p0`'s data.

For quick name filtering, the Prometheus exporter supports being provided with a comma-separated list of counter names to be ignored:

```
#prometheus-ignore-names=counter_name1,counter_name_2
```

For quick filtering of data by tag, the Prometheus exporter supports being provided with a comma-separated list of data source tags to be ignored.

Users should add tags for all streaming data since the Prometheus exporter cannot be used for streaming. By default, `FI_metrics` are disabled.

```
prometheus-ignore-tags=FI_metrics
```

4.2.4. Prometheus Aggregator Exporter

Prometheus aggregator exporter is an endpoint that keeps the latest aggregated data using `prometheus_aggr`. This exporter labels data according to its source. To enable this provider, users must set 2 parameters in `dts_config.ini`:

```
prometheus-aggr-exporter-host=0.0.0.0
prometheus-aggr-exporter-port=33333
```

4.2.5. Fluent Bit

Fluent Bit allows streaming to multiple destinations. Destinations are configured in `.exp` files that are documented in-place and can be found under:

```
/opt/mellanox/doca/services/telemetry/config/fluent_bit_configs
```

Fluent Bit allows exporting data via "Forward" protocol which connects to the Fluent Bit/FluentD instance on customer side.

Export can be enabled manually:

1. Uncomment the line with `fluent_bit_configs=` in `dts_config.ini`.
2. Set `enable=1` in required `.exp` files for the desired plugins.
3. Additional configurations can be set according to instructions in the `.exp` file if needed.
4. Restart the DTS.
5. Set up receiving instance of Fluent Bit/FluentD if needed.
6. See the data on the receiving side.

Export file destinations are set by configuring `.exp` files or creating new ones. It is recommended to start by going over documented example files. Documented examples exist for the following supported plugins:

- ▶ forward
- ▶ file

- ▶ stdout
- ▶ kafka
- ▶ es (elastic search)
- ▶ influx



Note: All `.exp` files are disabled by default if not configured by `initContainer` entry point through `.yaml` file.



Note: To forward the data to several destinations, create several `forward_{num}.exp` files. Each of these files must have their own destination host and port.

4.2.5.1. Export File Configuration Details

Each export destination has the following fields:

- ▶ `name` – configuration name
- ▶ `plugin_name` – Fluent Bit plugin name
- ▶ `enable` – 1 or 0 values to enable/disable this destination
- ▶ `host` – the host for Fluent Bit plugin
- ▶ `port` – port for Fluent Bit plugin
- ▶ `msgpack_data_layout` – the msgpacked data format. Default is `flb_std`. The other option is `custom`. See section [Msgpack Data Layout](#) for details.
- ▶ `plugin_key=val` – key-value pairs of Fluent Bit plugin parameter (optional)
- ▶ `counterset/fieldset` – file paths (optional). See details in section [Cset/Fset Filtering](#).
- ▶ `source_tag=source_tag1,source_tag2` – comma separated list of data page source tags for filtering. The rest tags will be filtered out during export.



Note: Use `#` to comment a configuration line.

4.2.5.2. Msgpack Data Layout

Data layout can be configured using `.exp` files by setting `msgpack_data_layout=layout`. There are two available layouts: Standard and Custom.

The standard `flb_std` data layout is an array of 2 fields:

- ▶ timestamp double value
- ▶ a plain dictionary (key-value pairs)

The standard layout is appropriate for all Fluent Bit plugins. For example:

```
[timestamp_val, {"timestamp"->ts_val, type=>"counters/
events", "source"=>"source_val", "key_1"=>val_1, "key_2"=>val_2,...}]
```

The custom data layout is a dictionary of meta-fields and counter fields. Values are placed into a separate plain dictionary. Custom data format can be dumped with `stdout_raw` output plugin of Fluent-Bit installed, or can be forwarded with `forward` output plugin.

Counters example:

```
{"timestamp"=>timestamp_val, "type"=>"counters", "source"=>"source_val", "values"=>
{"key_1"=>val_1, "key_2"=>val_2,...}}
```

Events example

```
{"timestamp"=>timestamp_val, "type"=>"events", "type_name"=>"type_name_val", "source"=>"
source_val", "values"=>{"key_1"=>val_1, "key_2"=>val_2,...}}
```

4.2.5.3. Cset/Fset Filtering

Each export file can optionally use one cset and one fset file to filter UFM telemetry counters and events data.

- ▶ Cset file contains tokens per line to filter data with `"type"="counters"`.
- ▶ Fset contains several blocks started with the header line `[event_type_name]` and tokens under that header. An Fset file is used to filter data with `"type"="events"`.



Note: Event type names could be prefixed to apply the same tokens to all fitting types. For example, to filter all ethtool events, use `[ethtool_event_*]`.

If several tokens must be matched simultaneously, use `<tok1>+<tok2>+<tok3>`. Exclusive tokens are available as well. For example, the line `<tok1>+<tok2>-<tok3>-<tok4>` filters names that match both tok1 and tok2 and do not match tok3 or tok4.

The following are the details of writing cset files:

```
# Put tokens on separate lines
# Tokens are the actual name 'fragments' to be matched
# port$ # match names ending with token "port"
# ^port # match names starting with token "port"
# ^port$ # include name that is exact token "port"
# port+xmit # match names that contain both tokens "port" and "xmit"
# port-support # match names that contain the token "port" and do not match the "-"
# token "support"
#
# Tip: To disable counter export put a single token line that fits nothing
```

The following are the details of writing fset files:

```
# Put your events here
# Usage:
#
# [type_name_1]
# tokens
# [type_name_2]
# tokens
# [type_name_3]
# tokens
# ...
# Tokens are the actual name 'fragments' to be matched
# port$ # match names ending with token "port"
# ^port # match names starting with token "port"
# ^port$ # include name that is exact token "port"
# port+xmit # match names that contain both tokens "port" and "xmit"
# port-support # match names that contain the token "port" and do not match the "-"
# token "support"
```

```

# The next example will export all the "tc" events and all events with type prefix
# "ethhtool_" "ethhtool" are filtered with token "port":
# [tc]
#
# [ethhtool_*]
# packet

# To know which event type names are available check export and find field
# "type_name"=>"ethhtool_event_p0"
# ...
# Corner cases:
# 1. Empty fset file will export all events.
# 2. Tokens written above/without [event_type] will be ignored.
# 3. If cannot open fset file, warning will be printed, all event types will be
# exported.

```

4.2.6. NetFlow Exporter

NetFlow exporter must be used when data is collected as NetFlow packets from the telemetry client applications. In this case, DOCA Telemetry NetFlow API sends NetFlow data packages to DTS via IPC. DTS uses NetFlow exporter to send data to the NetFlow collector (3rd party service).

To enable NetFlow exporter, set `netflow-collector-ip` and `netflow-collector-port` in `dts_config.ini`. `netflow-collector-ip` could be set either to IP or an address.

For additional information, refer to the `dts_config.ini` file.

Chapter 5. DOCA Privileged Executer

DOCA Privileged Executer (DPE) is a daemon that allows specific DOCA services (DTS included) to access BlueField information that is otherwise inaccessible from a container due to technology limitations or permission granularity issues.

When enabled, DPE enriches the information collected by DTS. However, DTS can still be used if DPE is disabled (default).

5.1. DPE Usage

DPE is controlled by systemd, and can be used as follows:

- ▶ To check DPE status:

```
sudo systemctl status dpe
```
- ▶ To start DPE:

```
sudo systemctl start dpe
```
- ▶ To stop DPE:

```
sudo systemctl stop dpe
```

DPE logs can be found in `/var/log/doca/telemetry/dpe.log`.

5.2. DPE Configuration File

DPE can be configured by the user. This section covers the syntax and implications of its configuration file.



Note: The DPU telemetry collected by DTS does not require for this configuration file to be used.

The DPE configuration file allows users to define the set of commands that DPE should support. This may be done by passing the `-f` option in the following line of `/etc/systemd/system/dpe.service`:

```
ExecStart=/opt/mellanox/doca/services/telemetry/dpe/bin/dpeserver -vvv
```

To use the configuration file:

```
ExecStart=/opt/mellanox/doca/services/telemetry/dpe/bin/dpeserver -vvv -f /path/to/dpe_config.ini
```

The configuration file supports the following sections:

- ▶ [server] - list of key=value lines for general server configuration. Allowed keys: socket.
- ▶ [commands] - list of bash command lines that are not using custom RegEx
- ▶ [commands_regex] - list of bash command lines that are using custom RegEx
- ▶ [regex_macros] - custom RegEx definitions used in the commands_regex section

Consider the following example configuration file:

```
[server]
socket=/tmp/dpe.sock

[commands]
hostname
cat /etc/os-release

[commands_regex]
crictrl inspect $HEXA      # resolved as "crictrl inspect [a-f0-9]+"
lspci $BDF                 # resolved as "lspci ([0-9a-f]{4}\:|)[0-9a-f]{2}\:[0-9a-f]{2}\.[0-9a-f]"

[regex_macros]
HEXA=[a-f0-9]+
BDF=([0-9a-f]{4}\:|)[0-9a-f]{2}\:[0-9a-f]{2}\.[0-9a-f]
```



Note: DPE is shipped with a preconfigured file that matches the commands used by the standalone DTS version included in the same DOCA installation. The file is located in `/opt/mellanox/doca/services/telemetry/dpe/etc/dpe_config.ini`.



Note: Using a DPE configuration file allows for a fine-grained control over the interface exposed by it to the rest of the DOCA services. However, even when using the pre-supplied configuration file mentioned above, one should remember that it has been configured to match a fixed DTS version. That is, replacing the standalone DTS version with a new one downloaded from NGC means that the used configuration file might not cover additional features added in the new DTS version.

Chapter 6. Troubleshooting

On top of the troubleshooting section found in the [NVIDIA DOCA Container Deployment Guide](#), here are additional troubleshooting tips for DTS:

- ▶ For general troubleshooting, refer to the [NVIDIA DOCA Troubleshooting Guide](#)
- ▶ If the pod's state fails to be marked as Ready, refer to the log `/var/log/syslog`.
- ▶ Check if the service is configured to write data to the disk, as this may cause the system to run out of disk space.
- ▶ If a PIC bus error occurs, configure the following files inside the container:

```
crictl exec -it <Container ID> /bin/bash
# Add to /config/clx.env the following line:
"
export UCX_TLS=tcp
"
```

Notice

This document is provided for information purposes only and shall not be regarded as a warranty of a certain functionality, condition, or quality of a product. NVIDIA Corporation nor any of its direct or indirect subsidiaries and affiliates (collectively: "NVIDIA") make no representations or warranties, expressed or implied, as to the accuracy or completeness of the information contained in this document and assume no responsibility for any errors contained herein. NVIDIA shall have no liability for the consequences or use of such information or for any infringement of patents or other rights of third parties that may result from its use. This document is not a commitment to develop, release, or deliver any Material (defined below), code, or functionality.

NVIDIA reserves the right to make corrections, modifications, enhancements, improvements, and any other changes to this document, at any time without notice.

Customer should obtain the latest relevant information before placing orders and should verify that such information is current and complete.

NVIDIA products are sold subject to the NVIDIA standard terms and conditions of sale supplied at the time of order acknowledgement, unless otherwise agreed in an individual sales agreement signed by authorized representatives of NVIDIA and customer ("Terms of Sale"). NVIDIA hereby expressly objects to applying any customer general terms and conditions with regards to the purchase of the NVIDIA product referenced in this document. No contractual obligations are formed either directly or indirectly by this document.

NVIDIA products are not designed, authorized, or warranted to be suitable for use in medical, military, aircraft, space, or life support equipment, nor in applications where failure or malfunction of the NVIDIA product can reasonably be expected to result in personal injury, death, or property or environmental damage. NVIDIA accepts no liability for inclusion and/or use of NVIDIA products in such equipment or applications and therefore such inclusion and/or use is at customer's own risk.

NVIDIA makes no representation or warranty that products based on this document will be suitable for any specified use. Testing of all parameters of each product is not necessarily performed by NVIDIA. It is customer's sole responsibility to evaluate and determine the applicability of any information contained in this document, ensure the product is suitable and fit for the application planned by customer, and perform the necessary testing for the application in order to avoid a default of the application or the product. Weaknesses in customer's product designs may affect the quality and reliability of the NVIDIA product and may result in additional or different conditions and/or requirements beyond those contained in this document. NVIDIA accepts no liability related to any default, damage, costs, or problem which may be based on or attributable to: (i) the use of the NVIDIA product in any manner that is contrary to this document or (ii) customer product designs.

No license, either expressed or implied, is granted under any NVIDIA patent right, copyright, or other NVIDIA intellectual property right under this document. Information published by NVIDIA regarding third-party products or services does not constitute a license from NVIDIA to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property rights of the third party, or a license from NVIDIA under the patents or other intellectual property rights of NVIDIA.

Reproduction of information in this document is permissible only if approved in advance by NVIDIA in writing, reproduced without alteration and in full compliance with all applicable export laws and regulations, and accompanied by all associated conditions, limitations, and notices.

THIS DOCUMENT AND ALL NVIDIA DESIGN SPECIFICATIONS, REFERENCE BOARDS, FILES, DRAWINGS, DIAGNOSTICS, LISTS, AND OTHER DOCUMENTS (TOGETHER AND SEPARATELY, "MATERIALS") ARE BEING PROVIDED "AS IS." NVIDIA MAKES NO WARRANTIES, EXPRESSED, IMPLIED, STATUTORY, OR OTHERWISE WITH RESPECT TO THE MATERIALS, AND EXPRESSLY DISCLAIMS ALL IMPLIED WARRANTIES OF NON-INFRINGEMENT, MERCHANTABILITY, AND FITNESS FOR A PARTICULAR PURPOSE. TO THE EXTENT NOT PROHIBITED BY LAW, IN NO EVENT WILL NVIDIA BE LIABLE FOR ANY DAMAGES, INCLUDING WITHOUT LIMITATION ANY DIRECT, INDIRECT, SPECIAL, INCIDENTAL, PUNITIVE, OR CONSEQUENTIAL DAMAGES, HOWEVER CAUSED AND REGARDLESS OF THE THEORY OF LIABILITY, ARISING OUT OF ANY USE OF THIS DOCUMENT, EVEN IF NVIDIA HAS BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES. Notwithstanding any damages that customer might incur for any reason whatsoever, NVIDIA's aggregate and cumulative liability towards customer for the products described herein shall be limited in accordance with the Terms of Sale for the product.

Trademarks

NVIDIA, the NVIDIA logo, and Mellanox are trademarks and/or registered trademarks of Mellanox Technologies Ltd. and/or NVIDIA Corporation in the U.S. and in other countries. The registered trademark Linux® is used pursuant to a sublicense from the Linux Foundation, the exclusive licensee of Linus Torvalds, owner of the mark on a world-wide basis. Other company and product names may be trademarks of the respective companies with which they are associated.

Copyright

© 2023 NVIDIA Corporation & affiliates. All rights reserved.